

## MPE Calculations

Systems operating under the provision of 47 CFR 1.1307(b)(1) shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the FCC guidelines.

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user or nearby persons and can therefore be considered a mobile transmitter per 47 CFR 2.1091(b). The MPE calculation for this exposure is shown below.

### **Using the Ethertronics Antennas @ 5 GHz Range with highest output power:**

The peak radiated output power (EIRP) is calculated as follows:

$$\text{EIRP} = P + G$$

$$\text{EIRP} = 23.20 \text{ dBm} + 5.00 \text{ dBi}$$

$$\text{EIRP} = 28.20 \text{ dBm} (660.69 \text{ mW})$$

Where

P = Power input to the antenna (mW).

G = Power gain of the antenna (dBi)

Power density at the specific separation:

$$S = PG/(4R^2\delta)$$

$$S = (208.93 \times 3.162) / (4 \times 20^2 \times \delta)$$

$$S = 0.131 \text{ mW/cm}^2$$

Where

S = Maximum power density (mW/cm<sup>2</sup>)

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)

The maximum permissible exposure (MPE) for the general population is 1mW/cm<sup>2</sup>.

The power density at 20cm does not exceed the 1mW/cm<sup>2</sup> limit. Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

$$R = \sqrt{PG/4\delta}$$

$$R = \sqrt{(208.93 \times 3.162) / 4\delta}$$

$$R = 7.25 \text{ cm}$$

Where

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = The safe estimated separation that the user must maintain from the antenna (cm)

The numeric gain (G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain}/10)$$

$$G = \text{Log}^{-1} (5.00 \text{ dBi}/10)$$

$$G = 3.162$$

**Using the Ethertronics Antennas @ 2.4 GHz Range with highest output power:**

The peak radiated output power (EIRP) is calculated as follows:

$$\text{EIRP} = P + G$$

$$\text{EIRP} = 23.90 \text{ dBm} + 3.00 \text{ dBi}$$

$$\text{EIRP} = 26.90 \text{ dBm (489.78 mW)}$$

Where

P = Power input to the antenna (mW).

G = Power gain of the antenna (dBi)

Power density at the specific separation:

$$S = PG/(4R^2\delta)$$

$$S = (245.47 \times 1.995) / (4 \times 20^2 \times \delta)$$

$$S = 0.097 \text{ mW/cm}^2$$

Where

S = Maximum power density (mW/cm<sup>2</sup>)

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)

The maximum permissible exposure (MPE) for the general population is 1mW/cm<sup>2</sup>.

The power density at 20cm does not exceed the 1mW/cm<sup>2</sup> limit. Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

$$R = \sqrt{PG/4\delta}$$

$$R = \sqrt{(245.47 \times 1.995) / 4\delta}$$

$$R = 6.24 \text{ cm}$$

Where

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = The safe estimated separation that the user must maintain from the antenna (cm)

The numeric gain (G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain}/10)$$

$$G = \text{Log}^{-1} (3.00 \text{ dBi}/10)$$

$$G = 1.995$$