Go to www.vtechphones.com to register your product for enhanced

warranty support and the latest VTech product news.



vtech

DM221

(BC)

DM221-2

Digital Audio Monitor

User's manual

CONGRATULATIONS

on purchasing your new VTech product Before using this product, please read Important safety instructions

This manual has all the feature operations and troubleshooting necessary to install and operate your new VTech product. Please review this manual thoroughly to ensure proper installation and operation of this innovative and feature-rich VTech product.

For support, shopping, and everything new at VTech, visit our website at www.vtechphones.com.

🖅 What's in the box



Specifications are subject to change without notice. © 2022 VTech Communications, inc. MII rights reserved: II./22. DM221-X_CI8_V12	
₩ N N N N N N N N N N N N N N N N N N N	



IECHNICAL SPECIFICATIONS

ТИЭМЭЭАИАМ ЭЛВАЭ



IMPORTANT SAFETY INSTRUCTIONS

Inextracted to assist you in supervising your baby. Do not use this product near water. For example, do not use it next to a bath tub, wash bowl, kitchen sink, laundry tub or swimming pool, or in a wet basement or shower.

 Ise only the adapters included with this product. Incorrect adapter polarity or voltage can seriously damage the

7 Use only adaptors and batteries listed below

Use only adoption Output: 6V Dc 400mA VTECH TELECOMMUNICATIONS LTD. Model: VT05UUS06040

Model: Ni-MH AAA750*2

2.4V 750mAh Ni-MH battery YIYANG CORUN BATTERY CO LTD.

Model: NI-MH AAA/SU² The power adapters are intended to be correctly oriented in a vertical or floor mount position. The prongs are not designed to hold the pubgin place if it is plugged into a ceiling, under-the-table or cabinet outlet. For pluggable equipment, the socket-outlet shall be installed near the equipment and shall be easily accessible.

Unplug this product from the wall outlet before cleaning. Do not use liquid or aerosol cleaners. Use a damp cloth for

The applied nameplate is located in the battery compartment of To protect them from overheating, these openings must no be blocked by placing the product on a soft surface such as a bed, sofa or rug. This product should never be placed nea The applies hair epine's located in the bank's comparison of the back and parent units. When using your equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and injury, including the following: 1 - Follow all warnings and instructions marked on the product. or over a radiator or heat registe Never push objects of any kind into this product through

the slots because they may touch dangerous voltage points or create a short circuit. Never spill liquid of any kind on the product Adult setup is required. CAUTION: Do not install the baby unit at a height above 2 10 To reduce the risk of electric shock, do not disassemble this meters. 4. This product is not a substitute for adult supervision of the infant. Supervising the infant is the parent's or caregiver's responsibility. This product could cease operating, and therefore you should not assume it will continue working properly for any given period of time. Further, this is not a medical device and should not be used as such. This product

To reduce the risk or electric shock, do not alssemble this product, but take in to an authorized service facility. Opening or removing parts of the product other than specified access doors may expose you to dangerous voltages or other risks. Incorrect reassembling can cause electric shock when the product is subsequently used.

product is subsequently used. 20. You should be the sourch reception every time you turn on 21. Periodically examine all components for damage. 22. Periodically examine all components for damage. 23. Denote a very leve inits of phose Jobs when using certain helphones, etc. To protect your physics, make sure the product has nevel been used before purchase, teet the baby the units, and power of the baby monitor if you will not use if for some time.

In nost to a bath tub, wath bowk, lishchen sink, learndry tub or 4. CAUTION Learn with tub metal provided. There may be a risk of explosion if a worng type of bathery is used for the parent unit. The batheries cannot be subjected to high a risk metal tub batheries and bash and the subjected to high a risk and the batheries and bash and the subjected to high a risk the first or batheries and bash are pressure at high altitude into first or a hot subjected to high tub batheries in an externed high temperature as unrounding environment of gas. Batheries subjected to externely low at pressure may result in an explosion or the leakage of flammable liquid or gas. Dispose of used bathery according to the information of the batheries included with this product horsoner. 23 Children should be supervised to ensure that they do not play with the product. 24. The product is not intended for use by persons (including

The product is nor intended to use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety. SAVE THESE INSTRUCTIONS Cautions Use and store the product at a temperature between 32°F

and 104°F and 104%. Do not expose the product to extreme cold, heat or direct sunlight. Do not put the product close to a heating source. Batteries should not be exposed to excessive heat such as bright sunshine or fire.

A way that a start of the start

as a towel or a blanket. Other electronic products may cause interference with your baby monitor. Try installing your baby monitor as far away from these electronic devices as possible: wireless routers, radios, cellular telephones, intercoms, room monitors, relevisions, personal computers, kitchen appliances and

cordless telephones

corotess treepnones. Precautions for users of implanted cardiac pacemakers Cardiac pacemakers (applies only to digital cordiess devices): Wriekess Technology Research, LLC (WTR), an independent research entity, led a multidisciplinary evaluation of the interference between portable wriekes devices and implanted cardiac pacemakers. Supported by the U.S. Food and Drug Administration, WTR recommends to physicians that: Pacemaker patients

cleaning. 11. Unplug the power cords before replacing batteries. 12. Do not cut off the power adapters to replace them with other plugs, as this causes a hazardous situation. 13. Do not allow anything to rest on the power cords. Do not install this product where the cords may be walked on or the cords. Should keep wireless devices at least six inches from the

Install Int Drouble where the control of the hyper of power source indicated on the marking label. If you are not size of the type of power supply in your home, consult your dealer or local power company. IS Do not oversized will outlet or use an extension cord. 16. Do not place this product on an unsable table, shell, shad 19. Do not place this product on an unsable table, shell, she r nod ON


Electromagnetic fields (EMF) This VTech product complies with all standards regarding electromagnetic fields (EMF). This product should not be placed in any area where proper ventilation is not provided. Slots and openings in the back or bottom of this product are provided for ventilation. ccording to the instructions in this user's manual, the product is afe to be used based on scientific evidence available today.

BEFORE USE (CONT'D)


Positioning the baby monitor

() CAUTION · Keep the baby units out of the reach of your baby. Never place or mount the baby units inside the baby's crib or playpen.

1. Place the baby units more than 3 feet (1 meter) away from your baby



2. Place the parent unit more than 3 feet (1 meter) away from the baby unit to avoid





The default volume of your parent unit is level 3. If you experience high-pitched screeching noise from your baby monitor while positioning: Make sure your baby unit and parent unit are more than 3 feet (1 meter) apart, OF

Turn down the volume of your parent unit.

Operating range

The operating range of the baby monitor is up to 1,000 feet (300 meters) outdoors or 160 feet (50 meters) indoors. The actual operating range may vary depending on the environmental conditions, and other interferences such as walls, doors, and other obstructions.

CONNECT AND CHARGE THE BATTERY

Install the parent unit battery

The parent unit runs on rechargeable battery or AC power. To continuously monitor your baby, make sure you use both battery and AC power at the same time. With the battery alone, the parent unit can cordlessly run for a short time only.

Use only the battery supplied with this product

If the parent unit will not be used for a long time, disconnect and remove the battery to prevent possible leakage




Replace the battery

To replace the battery, unplug the battery connector from the socket, and then pull the battery out of the battery compartment. Follow the steps above to install the battery.

Connect the baby monitor

■NOTES

- Use only the power adapters supplied with this product.
- Make sure the baby monitor is not connected to an electric outlet that is controlled by a switch. The power adapters' prongs are not designed to hold the weight of your baby monitor. Make sure
- you connect the adapters to wall outlets that are in vertical or floor mount position. Do not connect them to undermount and ceiling outlets. Otherwise, your baby monitor would fall out of the outlets
- Make sure the parent unit, the baby unit and the power adapter cords are out of reach of children



USING THE BABY MONITOR

Power on or off the baby unit

 Press () to power on the baby unit. The power light turns on. DRC Press and hold U to power off the baby unit. The power light turns off.

Power on or off the parent unit

- Press (b) to power on the parent unit. The screen turns on. Press and hold & again to power off the parent unit. The
- screen turns off. NOTE 1

The parent unit powers on automatically once it is connected to power socket or battery installed. The baby unit also powers on automatically once connected to power socket.

Adjust the speaker volume for baby unit

🖹 Note The speaker of baby unit cannot be muted.

Adjust the speaker volume for parent unit

You can adjust the speaker volume from VOLUME 1 to VOLUME 5, or turn it off. The speaker

- volume is preset to VOLUME 3. Press VOLUME A when the parent unit is not in use
- When the speaker volume is set to **VOLUME OFF**, the screen displays **Q**.

Adjust the sound sensitivity of the baby unit

You can choose to hear sounds from the baby unit all the time, or to hear sounds that exceed a certain level. You can use the parent unit to adjust the microphone sensitivity of your baby unit. The higher the sensitivity level, the more sensitivity level the more sensitivity level the more sensitivity level is preset to HIGHEST.

VOX Sensitivity level	HIGHEST	нібн	MEDIUM	LOW	LOWEST
Description	The parent unit speaker is constantly on, and you will hear all sounds (including background noises) from your baby's room.	The parent unit speaker turns on for soft babbling and louder sounds from your baby. It remains quiet when your baby sleeps soundly.	The parent unit speaker turns on for loud babbling and louder sounds from your baby. It remains quiet when your baby makes soft sounds.	The parent unit speaker turns on for crying and louder sounds from your baby. It remains quiet when your baby makes soft sounds.	The parent unit speaker turns on for loud crying or screeching sounds from your baby. It remains quiet when your baby makes soft sounds.

Charge the parent unit battery

When you have connected the parent unit and installed its battery for the first time or after power outage, the parent unit powers on automatically. The battery icon indicates the battery status (see the following table)

NOTES

- The parent unit battery is fully charged after 11 hours of continuous charging.
 It takes longer to charge the battery when the parent unit is turned on. To shorten the charging time, turn the parent unit off while charging.
- The standby time varies depending on the sensitivity level you set, your actual use and the age of the battery.

The battery icon is off.	No battery is installed but operates using AC power.	Install the parent unit battery. Charge without interruption (at least 30 minutes).
The screen displays LOW BATTERY and The Ight flashes.	The battery has very little charge and may be used for only a short time.	Charge without interruption (about 30 minutes).
The battery icon becomes solid (118 .	The battery is fully charged.	To keep the battery charged, connect it to AC power when not in use.

2 BEFORE USE

Test your baby monitor

You may test the baby monitor before initial use, and at regular times thereafter

1. Make sure your baby unit and parent unit are on. 2. Speak towards the microphone of the baby unit. 612 1. You will hear the sound at the parent unit, and see the visual sound indicators light up. CAUTION For hearing protection, make sure the parent unit is more

than 3 feet (1 meter) away from the baby unit. If you hear any high-pitched noise, move the parent unit further until the noise stops. You can also press 🔻 VOLUME on the parent unit to lower or mute the noise

NOTE

This baby monitor is intended as an aid. It is not a substitute for proper adult supervision, and should not be used as such.

When the parent unit displays **NOT LINKED** and \overline{T} flashes, move the parent unit closer to the baby unit (observe the minimum distance of 3 feet/1 meter). You can also check if the baby monitor is connected to a live nower socket and switched on

-1'- TIP

- Increase the speaker volume of the parent unit if you cannot hear the sounds transmitted from the baby unit
- 1. Press MENU when the parent unit is not in use.
- Press SELECT to select VOX LEVEL

1 Press MENU when the parent unit is not in use

The sound alert setting on each parent unit is independent.

2. Press ▲ or ▼ to choose VIBE ALERT, then press SELECT.

The vibration alert setting on each parent unit is independent

Turn on/off the nightlight using the baby unit:

Turn on/off the nightlight using the parent unit:

1. Press MENU when the parent unit is not in use

2. Press - o- again to turn off the nightlight

1. Press - o- to turn on the nightlight

1. Press MENU when the parent unit is not in use

Press ▲ or ▼ to choose ON or OFF.

sounds. This feature is preset to OFF.

3. Press ▲ or ▼ to choose ON or OFF.

confirmation tone

confirmation tone. NOTES

Nightlight

Vibration alert

🖹 Note

- Press ▲ or ▼ to choose the desired sensitivity level
- 4. Press SELECT to confirm your selection. The screen displays SAVED and you hear a

Press ▲ or ▼ to choose SOUND ALERT, then press SELECT.



Ċ

🖹 Note

To enter the VOX LEVEL menu of the parent unit, the baby unit must be turned on

Sound alert

If you want the parent unit alerts you with sound, especially when the baby unit detects loud sounds, you can turn on the sound alert feature. This feature is preset to OFF. Once this feature is on, () is shown on LCD display. When the visual sound indicator hits the red light range, i.e. the baby unit detects loud sounds, your parent unit beeps and () flashes

4. Press SELECT to confirm your selection. The screen displays SAVED and you hear a

You can set your parent unit to vibrate and alert you, whenever the baby unit detects loud

light range, i.e. the baby unit detects loud sounds, your parent unit vibrates and R flashes.

4. Press SELECT to confirm your selection. The screen displays SAVED and you hear a

Each time you set the vibration alert to ON, the parent unit vibrates briefly after you press SELECT.

Both your parent unit(s) and baby unit allow you to turn on or off the nighlight on the baby unit.

Once this feature is on, 🛱 is shown on LCD display. When the visual sound indicator hits the red

USING THE BABY MONITOR (CON'T)

- 2. Press ▲ or ▼ to choose NIGHTLIGHT, then press SELECT.
- 3 Press A or T to choose ON or OFF
- 4. Press SELECT to confirm your selection. The screen displays SAVED and you hear
- a confirmation tone 🖹 Notes
- When the nightlight is turned on, the parent unit displays ¥.
- The nightlight on baby unit operates even when the parent unit battery is out of charge or has been turned
- If the parent unit lost link, the nightlight icon on its LCD display will disappear, regardless of the nightlight

Language

You can select a language (English, Spanish or French) to be used in all screen displays. The language is preset to English

- 1. Press MENU when the parent unit is not in use
- 2. Press ▲ or ▼ to choose LANGUAGE, then press SELECT.
- 3. Press ▲ or ▼ to choose ENGLISH, ESPANOL, or FRANCAIS.
- 4. Press SELECT to confirm your selection. The screen displays SAVED and you hear a confirmation tone

🖹 NOTE The language setting on each parent unit is independent.

Set default

Use this feature to restore to the default settings. Restoring the default settings on one parent unit will also reset the shared settings for VOX sensitivity level of the other parent

- 1. Press MENU when the parent unit is not in use.
- 2. Press ▲ or ▼ to choose SET DEFAULT, then press SELECT.
- 3 Press A or T to choose YFS or NO
- 4. When you choose YES, press SELECT to confirm your selection. The screen displays SAVED and you hear a confirmation tone

-OR

When you choose NO, press SELECT to confirm your selection. The screen displays the previous menu.

Talk to the baby unit

You can broadcast messages from a parent unit to the baby unit and the other parent unit. If you have two parent units, you can use both of them at the same time to talk to the baby

- 1. Press and hold TALK on the side of the parent unit. The screen displays TALK when the
- voice connection to the baby unit is made 2. Speak towards the MIC on the parent unit. Your voice is broadcast to the baby unit and the other parent unit.
 - NOTES Paging rings all parent units even if the speaker volume of parent unit is set to VOLUME OFF. The baby unit cannot page any parent unit that is turned off, out of range, or talking to the baby unit

FCC Part 15

level after the talk finished

Find/page the parent unit

^Q_{*}, Frequently asked questions

Below are the questions most frequently asked about the baby monitor. If you cannot find the answer to your question, visit our website at www.vtechphones.com or call 1 (800) 595-9511 for customer service. Why does the baby monitor not Try the following (in the order listed) for common cure:

respond normally?	 Disconnect the power to the baby unit and the parent unit. 			
	Remove the batteries in the parent unit. Then, install the batteries again.			
	3. Wait a few minutes before connecting power back to the baby unit and the			
	parent unit.			
	Turn on the baby unit and the parent unit.			
	Wait for the parent unit to synchronize with the baby unit. Allow up to one minute for this to take place.			
Why doesn't the screen of the parent unit go on when I switch on the unit?	Perhaps the rechargeable battery of the parent unit is empty and the parent unit is not connected to the power. Insert the appliance plug into the parent unit and put the adapter in a wall socket.			
Why doesn't the POWER light of the baby unit go on when I switch on the unit?	Perhaps the baby unit is not connected to the power. Connect the baby unit to the power.			
Why does the baby monitor produce a high-pitched noise?	The units may be too close to each other. Make sure the parent unit and the baby unit are more than 3 feet (1 meter) away from each other.			
Why does the parent unit react too quickly to other sounds?	The baby unit also detects other sounds than those of your baby. Adjust the VOX sensitivity level to a lower level or adjust the speaker volume on the parent unit.			
Why don't I hear a sound/Why can't I hear my baby cry?	The volume of the parent unit may have set too low. Press ${\rm VOLUME} \blacktriangle$ to increase the volume level.			
	You may have set a low VOX sensitivity level. See Adjust the sound sensitivity of the baby unit to change the setting.			
Why does the parent unit beep?	If the sound alert feature is on, there is sound detected from the baby unit.			
	The baby unit may be out of range. Move the parent unit closer to the baby unit (but not less than 3 feet).			
	If the parent unit is powered by the provided battery, it may not have enough charge for the parent unit to perform normally. Charge the battery in the parent unit for up to 11 hours.			
Why can't I establish a connection? Why is the	The baby unit may be out of range. Move the parent unit closer to the baby unit (but not less than 3 feet).			

connection lost every now and Other electronic products may cause interference with your baby monitor. then? Why are there sound Try installing your baby monitor as far away from these electronic devices as interruptions? possible. Why doesn't the battery icon The battery may not be working. Contact our customer service to purchase a shown on LCD display even new battery I have properly installed the

Seneral product care

- To keep this product working well and looking good, follow these guidelines: Avoid putting it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps).
 DD NDT expose it to direct sunlight or moisture.
- Avoid dropping the product or treating it roughly
- Clean with a soft cloth.

battery?

- DO NOT immerse the parent unit and the baby unit in water and do not clean them under the tap.
- DO NOT use cleaning spray or liquid cleaners. Make sure the baby unit and parent unit are dry before you connect them to the mains again.

FCC AND IC REGULATIONS

Use this feature to locate misplaced parent units.

BABY UNIT OVERVIEW

(2)

(3)

(4)

manually.

manually.

POWER light

4 ▼ VOLUME ▲

1 Night light

2

·ö-

vtech

-0

300

 \bigcirc

On when night light is turned on

Off when night light is turned off

On when the baby unit is turned on.

· Press to turn the night light on or off.

Press to adjust the speaker volume

(5)

(6)

(8)

(9)

5 也(On/off)

6 PAGE

8 Speaker

If you have two parent units, and you use one of them to talk to you have your yoice will breadcast to

sound will transmit from the baby unit to any parent unit during broadcasting

1. Press PAGE on the baby unit. All idle parent units ring and display PAGING.

2. To end paging, press any key on the parent unit, or press PAGE on the baby unit.

both the baby unit and the other parent unit. The other parent unit displays TALKBACK. However, no

If speaker volume of the parent unit has been turned off before the talk, it will change to default volume

9 Power jack

unit.

Microphone

light turns on

Press to power on, and the power

Press and hold to power off, and

· Press to start or stop paging parent

interference. (2) This device must accept any interference, including interference that may cause undesired operation of the device.

The term "IC." before the certification/registration number on signifies that the Industry Canada technical specifications were

mer. This product meets the applicable Innovation, Science and

The device has been tested and complies with FCC and IC SAR

To ensure safety of users, the ECC has established criteria for the to ensure sately of users, the FCC has established criteria tof the amount of racido frequency energy that can be safety absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC criteria. The baby unit shall be installed and used such that parts of all persons' body are maintained at a distance

For body worn operation, this parent unit has been tested and

meets the FCC RF exposure guidelines when used with the accessories supplied or designed for this product. Use of other accessories may not ensure compliance with FCC RF exposure

of approximately 20 cm (8 inches) or more

the power light turns off.

Industry Canada This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) This device may not cause

This equipment has been tested and found to comply with the requirements for a Class B digital device under Part IS of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This against harmful interference in a residential installation. This equipment generates, uses and can adulte radio frequency equipment generates, uses and can adulte radio frequency the instructions, may cause harmful interference for radio communications. Theowere, three is no guarantee that interference will not occur in a particular installation. If this interference will not occur in a particular installation. If the levision neception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct in interference by one or more of the following measures: Reorient or relocate the receiving antenna.
 Increase the separation between the equipment and

Economic Development Canada technical specifications. This equipment complies with Industry Canada RSS-102 with respect to Canada's Health Code 6 for Exposure of Humans t RF Fields. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician RF radiation exposure statement

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complex with Part 15 of the FCE reles, Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause This Class B digital apparatus complies with Canadian

requirement: CAN ICES-3 (B)/NMB-3(B)

THE RBRC SEAL

The RBRC seal on the NI-MH battery indicates that VTech Communications, Inc. is voluntarily participating in an industry program to collect and recycle these batteries at the end of their useful lives, when taken out of service within the United States and Canada.

quidelines

The program provides a convenient alternative to placing used Ni-MH batteries into the trash or municipal waste, which may be illegal in your area.

vesses, mixed, mixed and provide and a set of the spent battery at local retailers participating in the program or at subtrated Volume 1 and a subtrated V for a procedure on the set in each of the spent battery at local retailers participating in the program or at subtrated V for a product service entries, these call 1 (200) 5 BATTERY for information on N-MH battery protecting our environment and conserving natural resources. The RBRC Seal and 1 (800) 8 BATTERY® are registered trademarks of Call2recycle, Inc

CALIFORNIA ENERGY COMMISSION BATTERY CHARGING TESTING MODE

This bady monitor meets the california Energy Commission (ECE) regulations for anergy consumption. You bady monitor is so up to comply with the energy-conserving standards rights of of the box Follow the instructions to install and charge the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to bady units, the CEC battery charging itesting mode is activated while to powered of an of charging.

DISCLAIMER AND LIMITATION OF LIABILITY

VTech Communications, Inc. and its suppliers assume no responsibility for any damage or loss resulting from the use of this user's manual. VTech Communications, Inc. and its suppliers assume no responsibility for any loss or claims by third parties that may arise through the use of this product. Company: VTech Communications Inc.

- Address: 9020 SW Washington Square Road Ste 555 Tigard, OR 97223, United States
- Phone: 1 (800) 595-9511 in the U.S. or 1 (800) 267-7377 in Canada

PARENT UNIT OVERVIEW

functions. One is to show the sound

level detected by the baby unit. The

during speaker volume setting

other one is to show the volume level

Sound level detected by the baby unit

One to three green lights

lights indicate a higher sound level

One to three green lights

indicate Level 1 to Level 3 of the

lights indicate Level 4 to Level 5 of

speaker volume setting

O O O O O Additional red

the speaker volume setting.

· Press to power on, the screen turns

· Press and hold again to power off

detected by the baby unit (e.g. baby

indicate a moderate sound level

detected by the baby unit.

crying loudly).


LCD display

3 Microphone

4 ()(On/off)

Speaker volume level

O O O O O Additional red



· Press to adjust the speaker volume. · While in a menu, press to scroll up or down

-(12)

- SELECT 6 · While in a menu, press to choose an
 - item, or save a setting. Battery LED
 - Light on when the battery is being charged.
 - Light flashes when the battery is low and needs charging.
 - Light off when the parent unit is running on AC power without
 - battery installed, or the parent unit is running on battery only
 - MENU/BACK Press to enter the menu
 - While in a menu press to return to the previous menu.
 - Speake

n'empêchez pas l'aération adéquate de l'appareil en le plaçant su un lit, divan, tapis ou toute autre surface similaire. De méme. ne le

ou d'un calorifère. De plus, ne placez pas l'appareil dans un endre avant de vous assurer qu'il y ait une bonne circulation d'air.

Avent de vous assurer qui ly an dire bonne circulation d'air. N'enfoncez jamais d'objets à travers les ouvertures de cet appareil, car ils pourraient entrer en contact avec des points d tension dangereux ou causer des courts-circuits aui peuvent

tension dangereux ou causer des cours-circuits qui peuvent dégénérer en incendies ou en risques d'électrocution. Ne renversez jamais de liquide dans ce produit. Afin de réchuire les risques d'électrocution, ne démontez pas ce

Afin de réduire les risques d'électrocution, ne démonter pas cet appareil, mais apporter-le dans un centre de service autorisé. Jouverture du boîtiler ou le retrait de toutes pièces que contient et appareil, à l'exception de l'accès autorisé à certaines portes yo uvertures, fuque de vous cesorer à des points de tension fangereux ou d'autres dangers. Un remontage incorrect peut par suite présenter des ricques d'électrocution.

la suite presenter des risques d'electrocution. Vous devriez tester la réception chaque fois que vous mettez l'appareil en fonction. Examinez les composantes afin de vérifier si celles-ci ne sont pas

certains appared perre de confidentialité avec certains appareis électroniques (autre écoute-bébé, kiéphones sans fils ec). Pour l'évire, rássurer que le produit na jamais été utilisé avan l'hoshr, réinitister l'unité de façon périodique, éteindre l'écoute-bébé quand il n'est pas en cours d'utilisation. Les enfants devaineit ner supervisés afin de vous assurer qu'ils ne jouent pas avec l'appareil.

jouent pas avec l'appareil. Le produit nest pas concu pour être utilisé par des personnes (incluant des enfants) aux capacités physiques, sensorielles ou mentales réduites ou qui manquent d'expérience et de connaissances, à moins qu'on leur ait donné suffisamment de supervision ou d'instructions relativement à ruitilisation de

appareil par une personne responsable de leur sécurité

CONSERVEZ CES INSTRUCTIONS Mises en garde 1. Utilisies et entreposota le produit à une température entre 0°C (22 F) et el d°C (Clui F), 2. airel organis la lumière directe du solet. Ne l'installez pas près d'une source de chauffage. 3. Le blio-pillez ne doit pas être exposé à la chalsure excessive telle que à lumière du solet lou feu.

enquette. Ne jamais placer le moniteur à l'intérieur du berceau ou du parc de bébé. Ne jamais couvrir le moniteur ou l'unité (s) portative avec un article tel une serviette ou une couverture.

avec un article tet une serviette ou une couvernure. O. D'autres équipements électroniques peuvent produire des interférences sur votre moniteur vidéo et audio. Tentez d'installer votre moniteur vidéo una dudi o l'écart de sapareils électroniques tété que des routeurs sans fil, radios, téléphones cabilaites, interphones, moniteurs, i éléphones, ordinaleurs

cenuaires, interprones, monieurs, teeprones, or personnels, électroménagers et téléphones sans fil Stimulateurs cardiaques implantés dans l'organisme Les simulateurs cardiaques (ne s'applique qu'aux dispos numériques sans fil-

cardiaques implantés dans l'organisme. Appuyée par l'Adm des aliments et drogues (FDA) des États-Unis, la firme WTR

recommande aux medecins: Avis aux detentients de stimulateurs cardiaques Avis aux detentient de stimulateurs cardiaques I sin ed obvers de stimulateurs and avis aux sin sin avis I sin ed obvers I AS placer le tréliphone sans fil directement sur le stimulateur cardiaque, tel que dans une poche de chemise, lorsque celui- ci est en marche.

lorsque celui-ci est en marche. L'étude effectuée par l'organisme WRS n'a pas identifié de risque pour les détenteurs de simulateurs cardiaques causés par les gens qui utilisent dispositifs sans fil à proximité de ceux-ci.

ande aux n

E

Avertissement - Risque de strangulation - Les enfants se sont ETRANOLES dans des cordons. Gardez ce cordon hors de portée des enfants (à plus de 0,9 m). N'enlevez pas cette éfiquette.

endommagées. Il existe un très faible risque de perte de confidentialité avec l'autres écoute-bébés, télépi

nez pas à proximité ni au-dessus d'une source de ch

- 10 TALK
- Press and hold to talk to the baby
- 11 Power iack
- the screen turns off 12 Belt clin While in a menu, press to return to 13 Battery compartment cover idle screen.

8

9

20

21

74

FOR CETL COMPLIANCE ONLY

Mesures de sécurité importantes resultes or section e implicit experimentes of the product signal deficience of the product signal deficience appliquede se trouve dans le compartiment à lies des unités bébé et parents. songe vous utiliser voite appeard, vous devriez toujours suivre certaines resultes de précaution de base afin de récluire les tridiques d'internelle, décincoution et de bisseurs corponelles, dont ceux qui suivent : Observez toutes les instructions et misses en garde inscrites sur l'appareit.

l'appareil. L'installation par un adulte est requise. MISE EN GARDE: N'installez pas l'unité du bébé à une hauteur

suppleters 2 interface. Ce produit ne remplece pais la unellance sublita du locaritoso La supervisión du nourrisson et la responsabilité du la nourrisson de la personne qui do conte side refanta. La conda la puest présume qu'il continuers de fonctionner la conda la puest présume qu'il continuers de fonctionner correctmente pendar une periodo de les not devant pas des utilités contextes. Tables par est especial pas de la culta de la conda de la conda insorment materiale a not devant pas des utilités contextes. Nuitilises par est especial parte de la cent a de loca autor source chumidade, par esemple prés de l'ena la conda de locate autor source chumidade, par esemple prés de l'ena la conda pas des utilités contextes. Tables par est especial prés de l'ena la conda de locate autor source chumidade, par esemple prés de l'ena la conda pas des utilités contextes. Tables par est especial prés de l'ena la conda de locate autors source chumidade, par esemple prés de l'ena la conda pas des utilités contextes autors de la culta de la culta de la culta de la conda de la conda de locate autors source de la culta de la culta de la culta de la conda de la conda de la conda de la culta de la conda de la culta de la culta de la conda de la conda de la conda de la conda de la culta de la conda de la conda

evier de cusane, dans un sous-soi numide ni pres d'une pace dans un soussoi humide ou une douche. MISE EN GARDE: N'utilisez que la pile fournie. Il peut y avoir un risque d'explosion si un mauvais type de pile est utilisé pour le dispositif apaisant. La pile ne peut pas être soumise a des températures extrêmes élevées ou basses et a une faible ~ Des temperatures extremes elevees ou basses et a une table pression atmosphérique a haute altitude pendant son utilisati son entreposage ou son transport. Le fait de jeter la pile dans au feu ou dans un four chaud, ou d'écraser ou de couper

au reu ou dans un rour chaud, ou d'ecraser ou de couper mécaniquement la pile peut entrainer une explosion. Le fait de laisser la pile dans un environnement a température extrêmemes élevée peut entrainer une explosion ou une fuite de liquide elevee peur enmaner une explosion ou une tuite de iquide ou de gas inflammable. Une plie soumise a une pression ou une fuite extrêmement basse peur provoquer une explosion ou une fuite de liquide ou de gas inflammable. Mettes au rebut la plie usagée conformément aux informations figurant dans la section Le sceau paper

N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur dont la polarité ou la tension serait inadéquate risque d'endommager sérieusement le produit et mettre Informations sur les adaptateurs électriques

Sortie : 6 V CC 400mA. VTech Telecommunicati ons Ltd. T05EUS06040

2.4V 750mAh Ni-MH batter 2.4V 750mAh Ni-MH battery YIYANG CORUN BATTERY CO LTD. Model: NI-MHAAA750'2

Threader-ULXIII A AAT STD Loogardii soot threader a service de courant, les adaptateurs secteur ont été conso puro été e crientes consertements, rela la verrolate ou a particul. Es torches n'ont consertements, rela la verrolate ou particul. Es torches n'ont de la matterier et places à celuid cel branché dais sue parte au platfond, sous une taleo dans un medito. Es torches de la matterier et places à celuid cel branché dais sue parte au platfond, sous une taleo dans un medito. Debranches ce produit de la pitre de courant avent de proceder a nethorges. Vultate pas de nethores de medito. El taleo norden Debranche les contos d'alimentation avent de remplacer le bloch place.

10. 11

L'organisme "Wireless Technology Research, LLC (WTR), une firme de recherche independante, a mee une évaluation pluridisciplinaire des interfirences entre les téléphones sans fil portatifs et les etime. 12

bioc pipeles de concesso a d'alimentation para de transparse la No couper pas les concions d'alimentation pour remplacer les frènes, care ci peut présente nu d'angre potentia. les laisse auxun d'ale préparent in appure su le cardon d'alimentation, les réalises para et appareil d'aux un estadou l'ito d'alimentation, aux et appareil d'auxun estadou l'ito he faite fonctionne et appareil qu'auxun et les para d'alimentation que alimentation que aux possedéra à varier les per alimentation indiquée aux l'étiquette. Si vous ne consisser pas le type d' d'alimentation que vous possédera à varier dencinée, consulte et auxun possédera à varier dencinée, constante ne sucharger pas las prises de courant muraties ni les nationges électriques. 13 14

16

17.

utilisent dispositifs sans fil à proximité de ceux-ci. Champs décromagnétiques (EMF) Ce produit de VTech est conforme à toutes les normes se rapportant aux champs déctromagnétiques (EMF) standard. Si vous le manipulez concetement en auvaint les naturcitons de ce guide, son utilization sera sécuritaire pendant de nombreuses années, selon les mélieures évidences scientifiques dont nous disposons aujourd'hui. électriques. Ne placez pas cet appareil sur un chariot, meuble, trépied, support de montage ni table chancelants. Les trous et ouvertures du bolher, situés à l'arrière de l'appareil ou sous celui-ci, servent à aérer l'appareil. Pour l'empécher de surchauffer, ne bloquez sous aucun préference ces ouvertures et

PARENT UNIT ICONS

Status icons Connection status

- Ϋ́I displays when strong signal strength is detected between the baby unit and the parent unit.
 - Ti displays when moderate signal strength is detected between the baby unit and the parent unit.
 - T displays when the weak signal strength is detected between the baby unit and the parent unit
 - T flashes when the link between the baby unit and the parent unit is lost
 - Niaht liaht On when the night light is turned on.

Parent unit display screen messages

((•)) Sound alert

Ÿ

m

I INKED

POGTNG

SAVED

TO K

Canada.

pproximately 30 days

How long is the limited warranty period?

NOT LINKED

SEARCHING

LIMITED WARRANTY

The manufacturer of this VTech Product warrants to the

package ("Product") are free from defects in materia

holder of a valid proof of purchase ("Consumer" or "you") that the Product and all accessories provided in the sales

and workmanship, pursuant to the following terms and conditions, when installed and used normally and in

accordance with the Product operating instructions. This

What will VTech do if the Product is not free from defect

in materials and workmanship during the limited warranty period ("Materially Defective Product")?

During the limited warranty period, VTech's authorized service representative will replace at VTech's option, without charge, a Materially Defective Product. If we choose to replace

a Matenally Defective Product. If we choose to replace the Product, we may replace it with a new or refurbished Product of the same or similar design. We will retain defective parts, modules, or equipment. Replacement of the Product, at VTech's option, is your exclusive remedy. VTech will return the replacement Products to you in working condition. You should expect the replacement to take

How long is the limited warranty period? The limited warranty period for the Moulze stends for ONE (1) YEAR from the date of purchase (V0 days on products and the standard of the stendard of the stendard of the polisis to the reglement Product for a period of either (a) V0 days from the date the replacement Product is shipped to you or (b) the inter remaining on the original one-year warranty (V0-day limited warranty on products that are purchased as Refutibility of the viter is longer.

*Refurbished products purchased from our online store carry a 90-day replacement warranty.

Product that has been subjected to misuse, accident, shipping or other physical damage, improper installat abnormal operation or handling, neglect, inundation, fire, water or other liquid intrusion; or

Product that has been damaged due to repair, alteration or modification by anyone other than an authorized

Product to the extent that the problem experienced is caused by signal conditions, network reliability, or cable or

Product to the extent that the problem is caused by use with non-VTech accessories; or

Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada. or

used for commercial or institutional purposes (including

but not limited to Products used for rental purposes); o

Product returned without a valid proof of purchase (see item 2 below); or

Charges for installation or set up, adjustment of custome controls, and installation or repair of systems outside the

Product to the extent that the problem is caused by us with non-VTech accessories; or
 Product whose warranty/quality stickers, product serial number plates or electronic serial numbers have been removed, altered or rendered illegible; or

What is not covered by this limited warranty

This limited warranty does not cover:

service representative of VTech: or

antenna systems; or

unit

limited warranty extends only to the Consumer for Products purchased and used in the United States of America and

What does this limited warranty cover?

Displays when the sound alert of the parent unit is turned on. Flashes when there are loud sounds detected from the baby unit. Vibration alert

Þ.

· Displays when the vibration alert of the parent unit is turned on. Flashes when there are loud sounds detected from the baby unit.

Battery status

Volume off Q · Displays when the patient unit speaker volume is turned off.

m displays solid when the battery is fully charged.

needs to be recharged

No battery icon displays when there is no battery installed

• C flashes when the battery is in low level and needs charging.

1.01.1 BOTTERV • The parent unit uses only the rechargeable battery pack and it

continuously for over 10 seconds.

Your selection has been saved.

out of nower

(For DM221-2 only)

· The link between the parent unit and the baby unit is established.

· The parent unit is out of range of the baby unit, or the baby unit is

Someone is using the other parent unit to talk to the baby, and

the voice is also broadcasting to your parent unit. No sound will transmit from the baby unit to any parent unit during broadcasting.

How do you get warranty service

save you a service call.

transit

service?

Other limitation

of purchase

nent of the

To obtain warranty service in the USA, please visit out

website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or call 1 (800) 267-7377.

NOTE: Before calling for service, please review the user's manual - a check of the Product's controls and features may

save you a service call. Except as provided by applicable law, you assume the risk of loss or damage during transit and transportation and are responsible for delivery or handling charges incurred in the transport of the Product(s) to the service location. Viech will return replaced Product under this limited warranty. Transportation, delivery or handling charges are prepaid. Viech assumes no risk for damage or loss of the Product in

What must you return with the Product to get warranty

Include a "valid proof of purchase" (sales receipt)

Provide your name, complete and correct mailing address, and telephone number.

This warranty is the complete and exclusive agreement

between you and VTech. It supersedes all other written or oral communications related to this Product. VTech provid

no other warranties for this Product. The warranty exclusively describes all of VTech's responsibilities regarding the Product. There are no other express warranties. No one is

Product. Ihere are no other express warranties. No one is authorized to make modifications to this limited warranty and you should not rely on any such modification. State/Provincial Law Rights: This warranty gives you specific legal rights, and you may also have other rights, which vary from state to state or province to province.

Limitations: Implied warranties, including those of fitness for a particular purpose and merchantability (an unwritten warranty that the Product is fit for ordinary use) are limited

provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you

In no event shall VTech be liable for any indirect, specia

incidental, consequential, or similar damages (including but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of

do not allow the exclusion or limitation of incidental or

consequential damages, so the above limitation or ex may not apply to you.

substitute equipment, and claims by third parties) resulting from the use of this Product. Some states/provinces

Please retain your original sales receipt as proof

to one year from the date of purchase. Some states.

Return the entire original package and contents including the Product to the VTech service location along with a description of the malfunction or difficulty; and

identifying the Product purchased (Product model) and the date of purchase or receipt; and

· The link between the parent unit and the baby unit is lost

· Both idle parent units are being paged by the baby unit.

You are using the parent unit to talk to your baby.