

Report No.: KSCR241100241501 Page: 1 of 28

TEST REPORT

Application No.:	KSCR2411002415AT		
FCC ID:	WBKR232UB		
Applicant:	BTI Wireless		
Address of Applicant:	11205 Knott Avenue-Suite A, Cypress, CA 90630, United States		
Manufacturer:	BTI Wireless		
Address of Manufacturer:	11205 Knott Avenue-Suite A, Cypress, CA 90630, United States		
Equipment Under Test (EUT	Г):		
EUT Name:	Remote Unit		
Model No.:	PS-R232		
Trade mark:	(BTI WIRELESS		
Standard(s) :	FCC Part 2		
	FCC Part 20		
	FCC Part 90		
Date of Receipt:	2024-12-09		
Date of Test:	2025-02-05 to 2025-02-09		
Date of Issue:	2025-02-17		
Test Result:	Pass*		

* In the configuration tested, the EUT complied with the standards specified above.

This document is issued by the Company subject to its General Conditions of Service printed overleaf, available on request or accessible at http://www.sgs.com/en/Terms-and-Conditions and, for electronic format documents, subject to Terms and Conditions for Electronic Documents at http://www.sgs.com/en/Terms-and-Conditions for electronic format documents, subject to Terms and Conditions for Electronic Documents at http://www.sgs.com/en/Terms-and-Conditions/Terms-e-Document. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein.

Any holder of this document is advised that information contained hereon reflects the Company's findings at the time of its intervention only and within the limits of Client's instructions, if any. The Company's sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

Unless otherwise stated the results shown in this test report refer only to the sample(s) tested and such sample(s) are retained for 30 days only.

Compliance Certification Services (Kunshan) Inc. 程智电子科技(昆山)有限公司 中

No.10 Weiye Road, Development Zone, Kunshan, Jiangsu, China t (86-512)57355888 www.sgsgroup.com.cn 中国・江苏省昆山开发区伟业路 10 号 215301 f (86-512)57370818 sgs.china@sgs.com



Report No.: KSCR241100241501 Page: 2 of 28

Revision Record			
Version	Description	Date	Remark
00	Original	2025-02-17	

Authorized for issue by:		
Tested By	Kass Gao /Project Engineer	
Approved By	Terry Hou /Reviewer	



Report No.: KSCR241100241501 Page: 3 of 28

2 Test Summary

2.1 452MHz-512MHz for Part 90

Test Item	Reference	Result
Input/output power and amplifier/booster gain	§2.1046 §90.219 KDB 935210 D05	Pass
Conducted Spurious Emissions	§2.1051 §90.219 KDB 935210 D05	Pass
Out-of-band/out-of-block (including intermodulation) Emissions	§2.1051 §90.219 ANSI C63.26 KDB 935210 D05 KDB 935210 D02	Pass
Radiated Spurious Emissions	§2.1053 §90.219 KDB 935210 D05	Pass
Occupied Bandwidth and Input- versus-output signal comparison	§2.1049 §90.209 §90.219 KDB 935210 D05	Pass
Out of Band Rejection	KDB 935210 D05	Pass
Frequency Stability	§2.1055 §90.213	Pass
Emission Mask	§2.1055 §90.210	Pass
Noise	§90.219 KDB 935210 D05	Pass

Remark:

EUT: In this whole report EUT means Equipment Under Test.

Tx: In this whole report Tx (or tx) means Transmitter.

Rx: In this whole report Rx (or rx) means Receiver.

The EUT supports AC 100-240V 50/60Hz or DC 48V or DC 24V, all modes have been tested and only record the worst test result.

Test method standard:

ANSI C63.26-2015

KDB 935210 D05 Indus Booster Basic Meas v01r04

KDB 935210 D02 Signal Booster Certification v04r02



Report No.:	KSCR241100241501
Page:	4 of 28

3 Contents

		Pa	је
1	COV	ER PAGE	.1
2	Test	Summary	.3
	2.1	452MHz-512MHz for Part 90	.3
3	Con	tents	.4
Ŭ	0011		•••
4	Gen	eral Information	.5
	4.1	Details of E.U.T.	.5
	4.2	Description of Support Units	.5
	4.3	Measurement Uncertainty	.6
	4.4	Test Location	.7
	4.5	Test Facility	.7
	4.6	Deviation from Standards	.7
	4.7	Abnormalities from Standard Conditions	.7
5	Equi	pment List	.8
6	Test	Results	.9
	6.1	Test conditions	.9
	6.2	Test Procedure & Measurement Data	11
7	Pho	ographs - Test Setup	28
8	EUT	Constructional Details (EUT Photos)	28



Report No.: KSCR241100241501 Page: 5 of 28

4 General Information

4.1 Details of E.U.T.

Product Name:	Remote Unit
Device type	Booster
Model No.:	PS-R232
Antenna Type:	External Antenna
Antenna Gain:	0 dBi for 452MHz to 512MHz (Provided by manufacturer)
Power Supply:	AC 100-240V 50/60Hz or DC 48V or DC 24V
Type of Modulation	CQPSK/12.5kHz FM/TETRA
Frequency Band:	452MHz to 512MHz
Power Control Method:	ALC
Antenna Delivery:	SISO
Nominal Output Power:	37±1dBm
Nominal gain:	47dB

4.2 Description of Support Units

Description	Manufacture	Model No.	S/N
Note Book	Acer	ZQT	NXM0QCN01031403EE876
AU	CROSSFIRE	N/A	/



Report No.: KSCR241100241501 Page: 6 of 28

7.0				
No.	Item	Measurement Uncertainty		
1	Radio Frequency	8.4 x 10 ⁻⁸		
2	Timeout	2s		
3	Duty Cycle	0.37%		
4	Occupied Bandwidth	3%		
5	RF Conducted Power	0.6dB		
6	RF Power Density	2.9dB		
7	Conducted Spurious Emissions	0.75dB		
8	DE Dadiatad Dawar	5.2dB (Below 1GHz)		
	RF Radiated Power	5.9dB (Above 1GHz)		
		4.2dB (Below 30MHz)		
0		4.5dB (30MHz-1GHz)		
9	Radiated Spurious Emission Test	5.1dB (1GHz-18GHz)		
		5.4dB (Above 18GHz)		
10	Temperature Test	1°C		
11	Humidity Test	3%		
12	Supply Voltages	1.5%		
13	Time	3%		

4.3 Measurement Uncertainty

Note: The measurement uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.



Report No.: KSCR241100241501 Page: 7 of 28

4.4 Test Location

All tests were performed at:

Compliance Certification Services (Kunshan) Inc.

No.10 Weiye Rd, Innovation park, Eco&Tec, Development Zone, Kunshan City, Jiangsu, China.

Tel: +86 512 5735 5888 Fax: +86 512 5737 0818

No tests were sub-contracted.

Note:

1.SGS is not responsible for wrong test results due to incorrect information (e.g., max. internal working frequency, antenna gain, cable loss, etc) is provided by the applicant. (If applicable).

2.SGS is not responsible for the authenticity, integrity and the validity of the conclusion based on results of the data provided by applicant. (If applicable).

3. Sample source: sent by customer.

4.5 Test Facility

The test facility is recognized, certified, or accredited by the following organizations:

• A2LA

Compliance Certification Services (Kunshan) Inc. is accredited by the American Association for Laboratory Accreditation (A2LA). Certificate No. 2541.01.

• FCC

Compliance Certification Services (Kunshan) Inc. has been recognized as an accredited testing laboratory. Designation Number: CN1172.

• ISED

Compliance Certification Services (Kunshan) Inc. has been recognized by Innovation, Science and Economic Development Canada (ISED) as an accredited testing laboratory.

Company Number: 2324E

• VCCI

The 3m and 10m Semi-anechoic chamber and Shielded Room of Compliance Certification Services (Kunshan) Inc. has been registered in accordance with the Regulations for Voluntary Control Measures with Registration No.: R-20134, R-11600, C-11707, T-11499, G-10216 respectively.

4.6 Deviation from Standards

None

4.7 Abnormalities from Standard Conditions

None



Report No.: KSCR241100241501 Page: 8 of 28

5 Equipment List

Item	Equipment	Manufacturer	Model	Inventory No	Cal Date	Cal. Due Date
RF Cor	RF Conducted Test					
1	Spectrum Analyzer	Keysight	N9020A	KUS1911E004-2	08/01/2024	07/31/2025
2	Spectrum Analyzer	Keysight	N9020A	KUS2001M001-2	08/01/2024	07/31/2025
3	Spectrum Analyzer	Keysight	N9030B	KSEM021-1	01/15/2025	01/14/2026
4	Signal Generator	R&S	SMBV100B	KSEM032	03/19/2024	03/18/2025
5	Signal Generator	R&S	SMW200A	KSEM020-1	08/02/2024	08/01/2025
6	Signal Generator	Agilent	N5182A	KUS2001M001-1	08/01/2024	07/31/2025
7	Radio Communication Test Station	Anritsu	MT8000A	KSEM001-1	08/01/2024	07/31/2025
8	Radio Communication Analyzer	Anritsu	MT8821C	KSEM002-1	03/19/2024	03/18/2025
9	Universal Radio Communication Tester	R&S	CMW500	KUS1911E004-1	08/13/2024	08/12/2025
10	Switcher	CCSRF	FY562	KUS2001M001-3	08/02/2024	08/01/2025
11	AC Power Source	EXTECH	6605	KS301178	N.C.R	N.C.R
12	DC Power Supply	Aglient	E3632A	KS301180	N.C.R	N.C.R
13	Conducted Test Cable	Thermax	RF01-RF04	CZ301111-CZ301120	01/14/2025	01/13/2026
14	Temp. / Humidity Chamber	TERCHY	MHK-120AK	KS301190	08/26/2024	08/25/2025
15	Temperature & Humidity Recorder	Renke Control	RS-WS-N01-6J	KSEM024-5	03/21/2024	03/20/2025
16	Software	BST	TST-PASS	/	N/A	N/A
RF Radiated Test						
1	Spectrum Analyzer	R&S	FSV40	KUS1806E003	08/05/2024	08/04/2025
2	Universal Radio Communication Tester	R&S	CMW500	KSEM009-1	03/19/2024	03/18/2025
3	Signal Generator	Agilent	E8257C	KS301066	08/05/2024	08/04/2025
4	Loop Antenna	COM-POWER	AL-130R	KUS1806E001	03/18/2023	03/17/2025
5	Bilog Antenna	TESEQ	CBL 6112D	KUS1806E005	06/29/2023	06/28/2025
6	Horn-antenna(1- 18GHz)	Schwarzbeck	BBHA9120D	KS301079	03/23/2024	03/22/2025
7	Horn Antenna(18- 40GHz)	Schwarzbeck	BBHA9170	CZ301058	01/07/2024	01/06/2026
8	Amplifier(30MHz~18GH z)	PANSHAN TECHNOLOGY	LNA:1~18G	KSEM010-1	01/15/2025	01/14/2026
9	Amplifier(18~40GHz)	TST	LNA180400G40	KSEM038	08/12/2024	08/11/2025
10	RE Test Cable	REBES MICROWAVE	/	CZ301097	11/10/2024	11/09/2025
11	Temperature & Humidity Recorder	Renke Control	RS-WS-N01-6J	KSEM024-4	03/21/2024	03/20/2025
12	Software	Faratronic	EZ_EMC-v 3A1	/	N/A	N/A



Report No.: KSCR241100241501 Page: 9 of 28

6 Test Results

6.1 Test conditions

Input voltage:	AC 100-240V 50/60Hz or DC 48V or DC 24V		
Test voltage	Normal	AC 120V	
	Extreme	AC 102V-AC 138V	
Operating Environment:			
Test Temperature:	Normal	22°C~26°C	
	Extreme	-40~55°C	
Humidity:	46%~56% RH		
Atmospheric Pressure:	990~1005mbar		
Test Requirement:	The RF output power of the EUT was measured at the antenna port, by adjusting the input power of signal generator to drive the EUT to get to maximum output power point and keep the EUT at maximum gain setting for all tests. The device should be tested on downlink.		
	For detail test Modulation and Frequency, please refer to 7.2.		

Remark:

FIBER-OPTIC AND OTHER SIMILAR RF DISTRIBUTION SYSTEMS

Fiber-optic distribution systems are a type of in-building radiation system that receives RF signals from an antenna, distributes the signal over fiber-optic cable, and then retransmits at another location for example within a building or tunnel. Most fiber-optic systems are signal boosters; however, some may be boosters. These systems generally have two enclosures typically called host (or local or donor unit) and remote. Some systems may also have an optional expander box for fan-out to multiple remotes. The system transmits downlink signals from the remote unit to handsets, portables, or clients, and transmits uplink signals via from the host unit. Usually but not always the uplink goes through an intermediate amplifier to a "donor" antenna. Therefore both uplink and downlink must be tested, unless filing effectively documents how connection of uplink to donor antenna with or without an intermediate amplifier will be prevented, such as for always only a cabled connection to a base station. Fiber-optic systems are not amplifiers (AMP equipment class) – they are equipment class TNB or PCB. The same approval procedures also apply for multiple-enclosure systems connected by coax cable.

Synonyms and related terms: in-building radiation system, coverage enhancer, distributed antenna system, fiber-optic distribution system, converter, donor antenna

Typical in-building or distributed antenna systems can consist of five different components (enclosures), not counting antennas:

1) host unit

a) transmits uplink to base station via antenna thru coax, *passive interface unit*, or *active interface unit* (amplifier)

- b) sends base-station downlink via fiber-optic or coax to *remote*
- c) receives handset uplink via fiber-optic or coax from *remote*
- d) optional connection to expansion unit via fiber-optic

f) non-transmitting host unit

i) connects directly to a base station via coax cable but does not connect to antenna or amplifier

2) remote unit



Report No.: KSCR241100241501 Page: 10 of 28

a) receives base-station downlink via fiber-optic or coax from host, transmits via antenna to handsets

b) returns handset uplink via fiber-optic or coax to host

3) fiber-optic expansion unit

- a) fiber-optic or coax from host
- b) fiber-optic or coax fan-out to **remote(s)**

4) RF expansion unit

- a) internal or external device used to add band(s) and/or transmit mode(s) to a remote
- b) operates only when connected to a *remote unit* as part of a booster system
- c) contains signal-processing functions to convert baseband signal into modulated RF signal

5) passive interface unit

a) contains attenuators, splitters, combiners

b) coax cable connection between *host* and base-station

6) active interface unit

- a) amplifies uplink signal from *host unit* for transmit by donor antenna
- b) attenuates downlink from donor antenna
- c) coax cable connection between *host* and *active interface unit*



Report No.: KSCR241100241501 Page: 11 of 28

6.2 Test Procedure & Measurement Data

6.2.1 Input/output power and amplifier/booster gain

Test Requirement:	§2.1046; §90.219
Test Method:	KDB 935210 D05 Indus Booster Basic Meas v01r04
EUT Operation:	
Status:	Drive the EUT to maximum output power.
Conditions:	Normal conditions
Application:	Cellular Band RF output ports
Test Configuration:	





Report No.: KSCR241100241501 Page: 12 of 28

Test Procedure:	 RF output power test procedure: a) Connect a signal generator to the input of the EUT. b) Configure to generate the CW signal. c) The frequency of the signal generator shall be set to the frequency f0 as determined from 3.3. d) Connect a spectrum analyzer or power meter to the output of the EUT using appropriate attenuation as necessary. e) Set the signal generator output power to a level that produces an EUT output level that is just below the AGC threshold (see 3.2), but not more than 0.5 dB below. f) Measure and record the output power of the EUT; use 3.5.3 or 3.5.4 for power measurement. g) Remove the EUT from the measurement setup. Using the same signal generator settings, repeat the power measurement at the signal generator port.
	 which was used as the input signal to the EUT, and record as the input power. EUT gain may be calculated as described in 3.5.5. h) Repeat steps f) and g) with input signal amplitude set to 3 dB above the AGC threshold level. i) Repeat steps e) to h) with the narrowband test signal. j) Repeat steps e) to i) for all frequency bands authorized for use by the EUT.
	Amplifier gain test procedure: After the mean input and output power levels have been measured as described in the preceding subclauses, the mean gain of the EUT can be determined from: Gain (dB) = output power (dBm) - input power (dBm).
Remark:	Peak to Average Ratio: Please according to KDB 971168 D01 clause 5.7. The system continuously monitors the input power.

6.2.1.1 Measurement Record:

Please refer to Appendix A for Input output power and amplifier booster gain



Report No.: KSCR241100241501 Page: 13 of 28

6.2.2 Conducted Spurious Emissions

Test Requirement:	§2.1051; §90.219
Test Method:	KDB 935210 D05 Indus Booster Basic Meas v01r04
EUT Operation:	
Status:	Drive the EUT to maximum output power.
Conditions:	Normal conditions
Application:	Cellular Band RF output ports
Test Configuration:	





Report No.: KSCR241100241501 Page: 14 of 28

Conducted Emissions test procedure: Test Procedure: a) Connect a signal generator to the input of the EUT. b) Configure the signal generator to produce a CW signal. c) Set the frequency of the CW signal to the center channel of the EUT passband. d) Set the output power level so that the resultant signal is just below the AGC threshold (see 4.2). e) Connect a spectrum analyzer to the output of the EUT, using appropriate attenuation as necessary. f) Set the RBW = 100 kHz. (i.e., for 30 MHz to 1 GHz PLMRS and/or PSRS booster devices) g) Set the VBW = $3 \times RBW$. h) Set the Sweep time = auto-couple. i) Set the detector to PEAK. j) Set the spectrum analyzer start frequency to 30 MHz (or the lowest radio frequency signal generated in the EUT, without going below 9 kHz if the EUT has additional internal clock frequencies), and the stop frequency to 10 × the highest allowable frequency of the EUT passband. k) Select MAX HOLD, and use the marker peak function to find the highest emission(s) outside the passband. (This could be either at a frequency lesser or greater than the passband frequencies.) I) Capture a plot for inclusion in the test report. m) Repeat steps c) to I) for each authorized frequency band/block of operation.

6.2.2.1 Measurement Record:

Please refer to Appendix B for Conducted Spurious Emissions



Report No.: KSCR241100241501 Page: 15 of 28

6.2.3 Out-of-band/out-of-block emissions

Test Requirement:§2.1051; §90.219Test Method:KDB 935210 D05 Indus Booster Basic Meas v01r04EUT Operation:Drive the EUT to maximum output power.Status:Drive the EUT to maximum output power.Conditions:Normal conditionsApplication:Cellular Band RF output portsTest Configuration:Cellular Band RF output ports



Test Procedure:

Out-of-band/out-of-block emissions test procedure:

a) Connect a signal generator to the input of the EUT. If the signal generator is not capable of producing two independent modulated carriers simultaneously, then two discrete signal generators can be connected, with an appropriate combining network to support the two-signal test.

b) Configure the two signal generators to produce CW on frequencies spaced consistent with 4.7.1, with amplitude levels set to just below the AGC threshold (see 4.2). Set the signal generator amplitudes so that the power from each into the EUT is equivalent.

c) Connect a spectrum analyzer to the EUT output.

d) Set the span to 100 kHz.

e) Set RBW = 300 Hz with VBW \ge 3 × RBW.

f) Set the detector to power averaging (rms).

g) Place a marker on highest intermodulation product amplitude.

h) Capture the plot for inclusion in the test report.

i) Repeat steps c) to h) with the composite input power level set to 3 dB above the AGC threshold.

j) Repeat steps b) to i) for all operational bands.



Report No.: KSCR241100241501 Page: 16 of 28

6.2.3.1 Measurement Record:

Please refer to Appendix C for Out-of-band out-of-block emissions (including intermodulation)



Report No.: KSCR241100241501 Page: 17 of 28

6.2.4 Radiated Spurious Emissions

Test Requirement:	§2.1053; §90.219
Test Method:	KDB 935210 D05 Indus Booster Basic Meas v01r04
EUT Operation:	
Status:	Drive the EUT to maximum output power.
Conditions:	Normal conditions
Application:	Enclosure

Test Configuration:

30MHz to 1GHz emissions:





Report No.: KSCR241100241501 Page: 18 of 28



1GHz to 40GHz emissions:

Test Procedure:

1. Test the background noise level with all the test facilities;

2. Keep one transmitting path, all other connectors shall be connected by normal power or RF leads;

3. Select the suitable RF notch filter to avoid the test receiver or spectrum analyzer produce unwanted spurious emissions;

4. Keep the EUT continuously transmitting in max power;

5. Read the radiated emissions of the EUT enclosure.

Radiated Emissions Test Procedure:





Report No.: KSCR241100241501 Page: 19 of 28

- a) Connect the equipment as illustrated.
- b) Adjust the spectrum analyzer for the following settings:
 - 1) Resolution Bandwidth = 100 kHz for spurious emissions below 1 GHz, and 1 MHz for spurious emissions above 1GHz.
 - 2) Video Bandwidth = 300 kHz for spurious emissions below 1 GHz, and 3 MHz for spurious emissions above 1 GHz.
 - 3) Sweep Speed slow enough to maintain measurement calibration.
 - 4) Detector Mode = Positive Peak.
- c) Place the transmitter to be tested on the turntable in the standard test site. The transmitter is transmitting into a no radiating load that is placed on the turntable. The RF cable to this load should be of minimum length.
- d) Measurements shall be made from30MHz to 10 times of fundamental carrier, except for the region close to the carrier equal to ± the carrier bandwidth.
- e) Key the transmitter without modulation or normal modulation base the standard.
- f) For each spurious frequency, raise and lower the test antenna from 1 m to 4 m to obtain a maximum reading on the spectrum analyzer with the test antenna at horizontal polarity. Then the turntable should be rotated 360° to determine the maximum reading. Repeat this procedure to obtain the highest possible reading. Record this maximum reading.
- g) Repeat step f) for each spurious frequency with the test antenna polarized vertically.





Report No.: KSCR241100241501 Page: 20 of 28

- h) Reconnect the equipment as illustrated.
- i) Keep the spectrum analyzer adjusted as in step b).
- j) Remove the transmitter and replace it with a substitution antenna (the antenna should be half-wavelength for each frequency involved). The center of the substitution antenna should be approximately at the same location as the center of the transmitter. At the lower frequencies, where the substitution antenna is very long, this will be impossible to achieve when the antenna is polarized vertically. In such case the lower end of the antenna should be 0.3 m above the ground.
- k) Feed the substitution antenna at the transmitter end with a signal generator connected to the antenna by means of a no radiating cable. With the antennas at both ends horizontally polarized, and with the signal generator tuned to a particular spurious frequency, raise and lower the test antenna to obtain a maximum reading at the spectrum analyzer. Adjust the level of the signal generator output until the previously recorded maximum reading for this set of conditions is obtained. This should be done carefully repeating the adjustment of the test antenna and generator output.
- I) Repeat step k) with both antennas vertically polarized for each spurious frequency.
- m) Calculate power in dBm into a reference ideal half-wave dipole antenna by reducing the readings obtained in steps k) and l) by the power loss in the cable between the generator and the antenna, and further corrected for the gain of the substitution antenna used relative to an ideal half-wave dipole antenna by the following formula:

Pd(dBm) = Pg(dBm) - cable loss (dB) + antenna gain (dB)

where:

Pd is the dipole equivalent power and

Pg is the generator output power into the substitution antenna.

NOTE:

1) It is permissible to use other antennas provided they can be referenced to a dipole.

2) For below 1GHz signal, the *antenna gain* (dB) is dBd, and for above 1GHz signal, the *antenna gain* (dB) is dBi

3) Effective radiated power (e.r.p) refers to the radiation of a half wave tuned dipole instead of an isotropic antenna. There is a constant difference of 2.15 dB between e.i.r.p. and e.r.p.

e.r.p (dBm) = e.i.r.p. (dBm) - 2.15

4) For this test, the AU and EU are put outside of the chamber; connect to the RU through the optical fiber

6.2.4.1 Measurement Record:

Please refer to Appendix D for Radiated Spurious Emissions



Report No.: KSCR241100241501 Page: 21 of 28

6.2.5 Occupied bandwidth and Input-versus-output signal comparison

Test Requirement:§2.1049; §90.209; §90.219; KDB 935210 D05 Indus Booster Basic
Meas v01r04
The spectral shape of the output should look similar to input for all
modulations.EUT Operation:Drive the EUT to maximum output power. .Status:Drive the EUT to maximum output power. .Conditions:Normal conditionsApplication:Cellular Band RF output portsTest Configuration:Cellular Band RF output ports



Test Procedure:

a) Connect a signal generator to the input of the EUT.

b) Configure the signal generator to transmit the appropriate test signal associated with the public safety emission designation (see Table 1).

c) Configure the signal level to be just below the AGC threshold (see results from 4.2).

d) Connect a spectrum analyzer to the output of the EUT using appropriate attenuation as necessary.

e) Set the spectrum analyzer center frequency to the nominal EUT channel center frequency. The span range for the spectrum analyzer shall be between $2 \times to 5 \times the EBW$ (or OBW).

f) The nominal RBW shall be 300 Hz for 16K0F3E, and 100 Hz for all other emissions types.

g) Set the reference level of the spectrum analyzer to accommodate the maximum input amplitude level, i.e., the level at f0 per 4.3.

h) Set spectrum analyzer detection mode to peak, and trace mode to max hold.



Report No.: KSCR241100241501 Page: 22 of 28

i) Allow the trace to fully stabilize.

j) Confirm that the signal is contained within the appropriate emissions mask.

k) Use the marker function to determine the maximum emission level and record the associated frequency.

I) Capture the emissions mask plot for inclusion in the test report (output signal spectra).

m) Measure the EUT input signal power (signal generator output signal) directly from the signal generator using power measurement guidance provided in KDB Publication 971168 [R8] (input signal spectra).

n) Compare the spectral plot of the output signal (determined in step k), to the input signal (determined in step I) to affirm they are similar (in passband and rolloff characteristic features and relative spectral locations).

o) Repeat steps d) to n) with the input signal amplitude set 3 dB above the AGC threshold.

p) Repeat steps b) to o) for all authorized operational bands and emissions types (see applicable regulatory specifications, e.g., Section 90.210).

q) Include all accumulated spectral plots depicting EUT input signal and EUT output signal in the test report, and note any observed dissimilarities.

6.2.5.1 Measurement Record:

Please refer to Appendix E for Input-versus-output signal comparison



Report No.: KSCR241100241501 Page: 23 of 28

6.2.6 Out of Band Rejection

Test Requirement:	KDB 935210 D05 Indus Booster Basic Meas v01r04		
	Test for rejection of out of band signals. Filter freq. response plots are acceptable.		
Test Method:	KDB 935210 D05 Indus Booster Basic Meas v01r04		
EUT Operation:			
Status:	Drive the EUT to maximum output power		
Conditions:	Normal conditions		
Application:	Cellular Band RF output ports		
Test Configuration:			



Test Procedure:

a) Connect a signal generator to the input of the EUT.

b) Configure a swept CW signal with the following parameters: 1) Frequency range = ± 250 % of the manufacturer's specified pass band. 2) The CW amplitude shall be 3 dB below the AGC threshold (see 4.2), and shall not activate the AGC threshold throughout the test. 3) Dwell time = approximately 10 ms. 4) Frequency step = 50 kHz.

c) Connect a spectrum analyzer to the output of the EUT using appropriate attenuation.

d) Set the RBW of the spectrum analyzer to between 1 % and 5 % of the manufacturer's rated passband, and VBW = $3 \times RBW$.

e) Set the detector to Peak and the trace to Max-Hold.

f) After the trace is completely filled, place a marker at the peak amplitude, which is designated as f0, and with two additional markers (use the markerdelta method) at the 20 dB bandwidth (i.e., at the points where the level has fallen by 20 dB).

g) Capture the frequency response plot for inclusion in the test report.



Report No.: KSCR241100241501 Page: 24 of 28

6.2.6.1 Measurement Record:

Please refer to Appendix F for Out of Band Rejection



Report No.: KSCR241100241501 Page: 25 of 28

6.2.7 Frequency Stability

	Test Requirement:		§2.1055; §90.213			
		Th em	e fre lissio	quency stability shall be sufficient to ensure that the fundamental ns stay within the authorized bands of operation.		
	EUT Operation:					
	Status:	Dri	ve th	e EUT to maximum output power.		
	Conditions:	Те	mper	ature conditions, voltage conditions		
	Application:	Ce	llular	Band RF output ports		
	Test Procedure:	1.	Ten	nperature conditions:		
			a)	The RF output port of the EUT was connected to Frequency Meter;		
			b)	Set the working Frequency in the middle channel;		
			c)	record the 20°C and norminal voltage frequency value as reference point;		
			d)	vary the temperature from -40°C to 55°C with step 10°C		
			e)	when reach a temperature point, keep the temperature banlance at least 1 hour to make the product working in this status;		
			f)	read the frequency at the relative temperature.		
		2.	Volt	age conditions:		
			a)	record the 20°C and norminal voltage frequency value as reference point;		
			b)	vary the voltage from -15% norminal voltage to +15% voltage;		
			c)	read the frequency at the relative voltage.		

6.2.7.1 Measurement Record:

Please refer to Appendix G for Frequency Stability



Report No.: KSCR241100241501 Page: 26 of 28



Test Procedure: Please refer to §90.210(b); §90.210(d); §90.210(e).

6.2.8.1 Measurement Record:

Please refer to Appendix H for Emission Mask



Report No.: KSCR241100241501 Page: 27 of 28

6.2.9 Noise

Test Requirement:

Test Method: EUT Operation: Status:

Conditions:

Application:

Test Configuration:

§90.219 KDB 935210 D05 Indus Booster Basic Meas v01r04 Clause 4.6 Drive the EUT to maximum output power. Normal conditions Cellular Band RF output ports



Test Procedure: Several widely recognized methods for performing noise figure measurements are available. Some require the use of specialized equipment, such as a noise figure analyzer and/or an excess noise ratio (ENR) calibrated noise source, while others involve the use of conventional measurement instrumentation such as a spectrum analyzer. Methods that require use of a noise figure analyzer are generally accepted as producing the most accurate results and are considered to be the reference method within this document, while others are considered to be acceptable alternative methods.

Consult the relevant instrumentation application notes for detailed guidance regarding the selection and application of an appropriate methodology for performing noise figure measurements. Note also that noise figure measurements require that any AGC circuitry be disabled over the duration of the measurement.

6.2.9.1 Measurement Record:

Please refer to Appendix I for Noise



Report No.: KSCR241100241501 Page: 28 of 28

7 Photographs - Test Setup

Refer to Appendix - Test Setup Photo for KSCR2411002415AT

8 EUT Constructional Details (EUT Photos)

Refer to Appendix - Photographs of EUT Constructional Details for KSCR2411002415AT

--The End of Report--