

Transmitter SK2015

Procedure	Parameter	Test point	min. Value	max. Value	Unit	Adjuster	Remarks
RF board							
Adjust	PLL Voltage@ mid frequency	TP3	2,5	2,9	V	C114	Set to 2,7V +0,2 V Offset Offset without chassis cover
Adjust	RF power level, fs=fm		2	20	mW	C220, R226 or R326 if available	Depending on version and range
Adjust	RF power level, fs=fu		2	20	mW	C220, R226 or R326 if available	Depending on version and range
Adjust	RF power level, fs=fo		2	20	mW	C220, R226 or R326 if available	Depending on version and range
Adjust	FM Deviation , fs=fm		23,5	24,5	kHz	R8	Input TP21 1kHz/370mV

Version	Änderungsnr./EC No.	Datum/Date	Name		Datum/ Date	Name	Bezeichnung/Specification Alignment Procedure SK2015	
				Bearbeiter/ Originator	15.05.04	Hag		
				Geprüft/ Checked by				
				Gesehen/ 2 nd check			Nr. des zugeh. Teils/ Related Ident. No.	Zeichnungsnr./ Drawing No.
 SENNHEISER Für dieses Dokument behalten wir uns die Rechte vor. All rights reserved. Sennheiser electronic GmbH & Co. KG, D-30900 Wedemark								Seite/Page 1 von/of 1