

Loc	Parts code	Parts name	Parts description
01	PVACPSN731	ACCESSROY AS	DC-B8CB1N-PS(N619,AAA)
DP01	97P95600N0	MANUAL OWERNS	NTSC 미주향 MODEL
DP02	97P880RN15	CABLE RF	NTSC 1.5M
DP03	97P0424100	COVER ACCESSORY	LD-PE T0.05
DP04	486A716202	BATTERY	AAA 1.5V(SUPERGARD)
DP08	97P880P815	CABLE RCA	3P-3P WEL-WHT-RED 1.5M
02	PVPKCPN730	PACKING AS	DF-L71D1N-BJ(YW)
CP01	97P4933300	PAD F/B	EPS
CP02	97P4809400	POLY BAG FOR SET	900*900*T0.5 PE-FOAM
CP03	97P5058120	BOX CARTON	541X453X175 SW-4 COLOR
CP04	47P4502205	LABEL SERIAL A	PAPER (42X12X1EA)
CP05	6520010020	STAPPLE	M20
03	PVMCASN744	CHASSIS MAIN AS	DF-L72B1N-BJ
A001	97P0613410	CHASSIS MAIN	HIPS(VO)
A0011	97P0800602	LEG	PLASTOMER
A0013	97P0804401	LEG-B	HI-PS(HB, SPRAY)
A002	97P93617N0	LABEL SPEC	PE FILM(131*47)
A006	97P0996000	EARTH BACK	SUS 304 CSP T=0.2
A013	97P0995301	PLATE A/V BACK	PVC T0.3
A040	97P0482110	COVER TOP	SECC T0.6+PAINT
A040A	97P4219500	CUSHION TOP	EVA 20X14
A040B	97P4219700	CUSHION TOP PLATE	EVA(SOFT) T=1 175*8
A041	7173300812	SCREW TAPTITE	TT2 BIN 3X8 BK
A042	7173300812	SCREW TAPTITE	TT2 BIN 3X8 BK
A051	7174300811	SCREW TAPPTITE	TT2 RND 3X8 MFZN
A052	97P4220200	CUSHION LEG	EVA T4.0
A060	97P04822A6	COVER BOTTOM	SECC T0.8, PHONE
AJ01A	7173300812	SCREW TAPTITE	TT2 BIN 3X8 BK
AP01A	7174300811	SCREW TAPPTITE	TT2 RND 3X8 MFZN
AT01A	7274300412	SCREW TAPPTITE	TT3 RND 3X4 MFZN BK
AZ01A	7174300811	SCREW TAPPTITE	TT2 RND 3X8 MFZN
AZ04A	7174300811	SCREW TAPPTITE	TT2 RND 3X8 MFZN
AZ04B	7174300811	SCREW TAPPTITE	TT2 RND 3X8 MFZN
D100	97P1R2KFA0	REMOCON HANDSET AS	VR-F2KFA0 GY503A(AAA)

M01	97PP342013	PANEL FRONT AS	DF-L72B1N-BJ
Z03A	7173300811	SCREW TAPPTITE	TT2 RND 3*8 MFZN
M011	7174301011	SCREW TAPPTITE	TT2 RND 3X10 MFZN
M021	7173401211	SCREW TAPPTITE	TT2 BIN 4X12 MFZN
M022	7174301211	SCREW TAPPTITE	TT2 RND 3X12 MFZN
M100	97QD021300	TOTAL DVD	BDR-L04P
M1000	PVDKARNB66	DECK VCR AS(T50,F/L)	DRN-B610R NON,F/L
A0100	97SA332200	MAIN BASE AS	T4.5-MECHA
A0101	97S3102000	SCREW TAPPTITE	TT2 BIN-P 2.6X7 MFZN
A011	97P93B2102	LABEL CD(DECK)	PAPER(13X56) ALL MODEL
A0200	97SA316500	S SLANT POLE AS	T-MECHA
A0300	97SA316600	T SLANT POLE AS	T-MECHA
A0400	97S8104200	MOTOR CAPSTAN	F2QVB37K
A0600	97SA320500	AC HEAD AS	T-MECHA
B0610	97SA326800	HEAD A/C	HVMXA1101A(ALPS)
A0601	7003300511	SCREW MACHINE	BIN 3X5 MFZN
A1000	97SA316800	L LOADING AS	T-MECHA
A1100	97SA316900	R LOADING AS	T-MECHA
A1200	97S2709510	RACK LOADING	SECC T1.2
A1201	7008301911	SCREW MACHINE	WAS M3*19 MFZN
A1400	97S0904310	PLATE CONNECT-H	SECC T1.0
A1500	97SA319410	REEL BRKT TOTAL AS	T2-MECHA
A1501	7273300511	SCREW TAPPTITE	TT3 BIN 3X5 MFZN
A1700	97S5500400	BELT REEL	CR68
A1800	97S2623200	LEVER RELAY	SECC T1.2
A1900	97S2709600	RACK FL	PBT(DY4410GF) NATURAL
A2000	97S2708200	GEAR CAM	DERLIN 100
A2100	97SA317150	PINCH LEVER TOT AS	T-MECHA
B1910	97SA481050	PINCH ROLLER AS	D15(DAEJIN D2.6*D7*T4.5)
A2200	97SA318050	LC BRKT AS	T5-MECHA
B2040	97P885X146	CONN AS	A/C HEAD(6P) SHIELD
A2201	7273300611	SCREW TAPPTITE	TT3 BIN 3X6 MFZN
A2400	97SA317310	IDLER PLATE TOT AS	T2-MECHA
A2401	97S3108200	POLYWASHER	D2.6XD6.0XT0.5
A2600	97S2909400	TABLE REEL	POM(F20-03) BLACK

A2700	97SA317200	TENSION LVR TOT AS	T-MECHA
A2800	97SA317400	S BRAKE AS	T-MECHA
A2900	97SA317510	T BRAKE AS	T2-MECHA
A3000	97S8023700	HEAD FE	HVFHP0042A
A3001	7174301011	SCREW TAPPTITE	TT2 RND 3X10 MFZN
AD001	97PA296001	DRUM PRICE AS	CYN-T610R
AD002	7003300511	SCREW MACHINE	BIN 3X5 MFZN
AF001	97SA261070	F/L AS	TCE-COMBO
AF002	7273300511	SCREW TAPPTITE	TT3 BIN 3X5 MFZN
AN002	2291131304	GREASE	DELUXE 5221G(NAM-YOUNG)
M200A	7174301211	SCREW TAPPTITE	TT2 RND 3X12 MFZN
P602A	97P88F1M10	CABLE FFC	1.25 R 21P 100MM
PW01	97P69BY910	CORD POWER	USA LP-11W YH396 1.7M
Z001	PVMPMSN730	PCB MAIN MANUAL AS	DF-L71D1N-BJ
AM01	2193100801	SOLDER WIRE	SN:PB=63:37 3PI(NO FLUX)
AM02	2193011100	SOLDER WIRE	60 SNA 1.2D
AM03	2291050305	FLUX LIQUID	RF-800KN
AM04	2291050306	FLUX THINNER	RF-800ADD
AM05	2291140501	WAX COVER	
AM06	97P93B2101	LABEL CD(PCB)	PAPER(13X25) ALL MODEL
IC603	14SEK24D08	IC EEPROM	S-24C08ADP-01(8K DIP)
JK101	97P6318210	JACK PIN	DPAM-0274
JK103	97Q6316200	JACK DIN	DUAЕ-9619
P201	97P62Y1318	CONN WAFER	DVW250 PLUG 2.5MM 8P
P202	97P62T14B2	CONN HOUSING	TMC-EX-B1 RECEP 2.0MM 2P
P301	97P62G06DA	CONN FFC	GF120-10S-TS 10P ST
P301A	97P0478200	CASE SHI PREAMP	ET T0.4
P601	97P62G06DM	CONN FFC	GF120-21S-TS 21P ST
P603	97P62J012C	CONN B/B	JE612 PLUG 2.0 12P
PJ601	97P885X195	CONN AS	13H-13S 100MM
PT01	97P6269000	CONN WAFER	00-8283-0612-00000
RF101	97P7621300	TUNER 3 IN 1	LGTMI-US6
S603	97P0S02500	SENSOR REEL	RPI-303N
S604	97P0S02500	SENSOR REEL	RPI-303N
SW601	5SD0101100	SW DETE	MXS00921MPC0

SW651	5S10104200	SW MODE	MMS01010ZMB0
T201	560202L692	COIL OSC	DEO-006
X101	5XJ18R4LAE	CRYSTAL QUARTZ	HC-49/S 18.43200MHZ 30PP
Z0011	PVMPJ1N730	MAIN CHIP MOUNT A AS	DF-L71D1N-BJ
C101	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C103	HCBK562KBA	C CHIP CERA	X7R 50V 5600PF K 1608
C104	HCBK562KBA	C CHIP CERA	X7R 50V 5600PF K 1608
C109	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C110	HCQK240JBA	C CHIP CERA	50V CH 24PF J 1608
C111	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C112	HCQK209CBA	C CHIP CERA	50V CH 2PF C 1608
C113	HCQK209CBA	C CHIP CERA	50V CH 2PF C 1608
C114	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C116	HCBK332KBA	C CHIP CERA	50V X7R 3300PF K 1608
C117	HCBK332KBA	C CHIP CERA	50V X7R 3300PF K 1608
C120	HCBK223KBA	C CHIP CERA	50V X7R 0.022MF K 1608
C121	HCQK809DBA	C CHIP CERA	50V CH 8PF D 1608
C125	HCBK223KBA	C CHIP CERA	50V X7R 0.022MF K 1608
C128	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C131	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C146	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C148	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C150	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C168	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C171	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C201	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C203	HCBK272KBA	C CHIP CERA	50V X7R 2700PF K 1608
C204	HCBK821KBA	C CHIP CERA	50V X7R 820PF K 1608
C205	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C207	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C209	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C211	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C213	HCQK100JBA	C CHIP CERA	50V CH 10PF J 1608
C214	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C216	HCQK821JBA	C CHIP CERA	50V CH 820PF J 1608

C217	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C251	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C252	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C253	HCFH474ZBA	C CHIP CERA	25V Y5V 0.47MF Z 1608
C254	HCFH474ZBA	C CHIP CERA	25V Y5V 0.47MF Z 1608
C255	HCFH474ZBA	C CHIP CERA	25V Y5V 0.47MF Z 1608
C256	HCFH474ZBA	C CHIP CERA	25V Y5V 0.47MF Z 1608
C257	HCFH474ZBA	C CHIP CERA	25V Y5V 0.47MF Z 1608
C258	HCFH474ZBA	C CHIP CERA	25V Y5V 0.47MF Z 1608
C268	HCBK682KBA	C CHIP CERA	50V X7R 6800PF K 1608
C274	HCBK682KBA	C CHIP CERA	50V X7R 6800PF K 1608
C278	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C279	HCBK122KBA	C CHIP CERA	50V X7R 1200PF K 1608
C281	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C285	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C294	HCBK223KBA	C CHIP CERA	50V X7R 0.022MF K 1608
C300	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C302	HCBK391KBA	C CHIP CERA	50V X7R 390PF K 1608
C303	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C304	HCQK181JBA	C CHIP CERA	50V CH 180PF J 1608
C311	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C318	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C325	HCBK223KBA	C CHIP CERA	50V X7R 0.022MF K 1608
C328	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C329	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C330	HCBK473KBA	C CHIP CERA	50V X7R 0.047MF K 1608
C331	HCBK473KBA	C CHIP CERA	50V X7R 0.047MF K 1608
C335	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C336	HCQK180JBA	C CHIP CERA	50V CH 18PF J 1608
C342	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C343	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C405	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C408	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608
C411	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C417	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608

C603	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C604	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C608	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C609	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C610	HCQK101JBA	C CHIP CERA	50V CH 100PF J 1608
C611	HCQK101JBA	C CHIP CERA	50V CH 100PF J 1608
C612	HCBK471KBA	C CHIP CERA	50V X7R 470PF K 1608
C614	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C616	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C617	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
C618	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608
C619	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608
C621	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608
C622	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608
C624	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C626	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C628	HCQK130JBA	C CHIP CERA	50V CH 13PF J 1608
C651	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608
C652	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
C653	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C655	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
C656	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C658	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C659	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
C660	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
C662	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C902	HCQK221JBA	C CHIP CERA	50V CH 220PF J 1608
C903	HCQK471JBA	C CHIP CERA	50V CH 470PF J 1608
C904	HCQK471JBA	C CHIP CERA	50V CH 470PF J 1608
C905	HCQK471JBA	C CHIP CERA	50V CH 470PF J 1608
C906	HCQK471JBA	C CHIP CERA	50V CH 470PF J 1608
C907	HCQK221JBA	C CHIP CERA	50V CH 220PF J 1608
C909	HCBK182KBA	C CHIP CERA	X7R 50V 1800PF K 1608
C911	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
C912	HCQK221JBA	C CHIP CERA	50V CH 220PF J 1608

C913	HCBK182KBA	C CHIP CERA	X7R 50V 1800PF K 1608
C914	HCQK221JBA	C CHIP CERA	50V CH 220PF J 1608
C923	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C926	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C927	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C930	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CS11	HCQK221JBA	C CHIP CERA	50V CH 220PF J 1608
CS5	HCQK471JBA	C CHIP CERA	50V CH 470PF J 1608
CS6	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CS7	HCQK471JBA	C CHIP CERA	50V CH 470PF J 1608
CS8	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
IC101	1MSP3425G-	IC MTS	MSP3425G-08
IC102	1LA73054-E	IC CHIP VIDEO DRIVER	LA73054 6 CHANNEL Y/C-MAX 7/14MHZ LPF 36PIN
IC201	1SN74HCU0D	IC CHIP HEX INVERTER	SN74HCU04DR(SO14) 14 PIN
IC251	1TDA9605H-	IC HI-FI	TDA9605H
IC253	1CD4052BMD	IC CHIP LOGIC	CD4052BM SOIC 16 REEL
IC301	1LA71207M-	IC A/V	LA71207M QFP 80PIN
IC401	1CD4053BMD	IC CHIP LOGIC	CD4053BM SOIC 16 REEL
IC402	1CD4051BMD	IC CHIP LOGIC	CD4051BM SOIC 16 REEL
IC601	168K37760H	IC MICOM	M37760EFHGP
IC901	1PCM1754DD	IC CHIP DAC	PCM1754DBQ 16PIN SSOP REEL
		IC CHIP AUDIO A/D	
IC902	1PCM1802DD	CONVERTER	PCM1802DBR SSOP 20PIN REEL
IC903	1NJM4580MC	IC CHIP AMP	NJM4580M
Q301	T2SA1037KB	TR CHIP	2SA1037AKT146-R
Q302	T2SC2412KB	TR CHIP	2SC2412K-T146-BR
Q304	T2SC2412KB	TR CHIP	2SC2412K-T146-BR
Q401	T2SA1037KB	TR CHIP	2SA1037AKT146-R
R107	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
R108	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
R112	HRFS750JBA	R CHIP	1/16 75 OHM J 1608
R113	HRFS750JBA	R CHIP	1/16 75 OHM J 1608
R117	HRFS562JBA	R CHIP	1/16 5.6K OHM J 1608
R118	HRFS750JBA	R CHIP	1/16 75 OHM J 1608
R121	HRFS750JBA	R CHIP	1/16 75 OHM J 1608

R124	HRFS562JBA	R CHIP	1/16	5.6K OHM J 1608
R139	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R140	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R142	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R151	HRFS102JBA	R CHIP	1/16	1K OHM J 1608
R152	HRFS243JBA	R CHIP	1/16	24K OHM J 1608
R153	HRFS303JBA	R CHIP	1/16	30K OHM J 1608
R158	HRFS151JBA	R CHIP	1/16	150 OHM J 1608
R159	HRFS151JBA	R CHIP	1/16	150 OHM J 1608
R160	HRFS151JBA	R CHIP	1/16	150 OHM J 1608
R161	HRFS151JBA	R CHIP	1/16	150 OHM J 1608
R162	HRFS151JBA	R CHIP	1/16	150 OHM J 1608
R163	HRFS151JBA	R CHIP	1/16	150 OHM J 1608
R201	HRFS912JBA	R CHIP	1/16	9.1K OHM J 1608
R202	HRFS912JBA	R CHIP	1/16	9.1K OHM J 1608
R203	HRFS334JBA	R CHIP	1/16	330K OHM J 1608
R204	HRFS181JBA	R CHIP	1/16	180 OHM J 1608
R205	HRFS273JBA	R CHIP	1/16	27K OHM J 1608
R206	HRFS821JBA	R CHIP	1/16	820 OHM J 1608
R207	HRFS333JBA	R CHIP	1/16	33K OHM J 1608
R208	HRFS622JBA	R CHIP	1/16W	6.2K OHM J 1608
R210	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R212	HRFS751JBA	R CHIP	1/16	750 OHM J 1608
R214	HRFS391JBA	R CHIP	1/16	390 OHM J 1608
R215	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R221	HRFS103JBA	R CHIP	1/16	10K OHM J 1608
R248	HRFS512JBA	R CHIP	1/16	5.1K OHM J 1608
R249	HRFS512JBA	R CHIP	1/16	5.1K OHM J 1608
R250	HRFS225JBA	R CHIP	1/16	2.2M OHM J 1608
R251	HRFS225JBA	R CHIP	1/16	2.2M OHM J 1608
R252	HRFS333JBA	R CHIP	1/16	33K OHM J 1608
R253	HRFS272JBA	R CHIP	1/16	2.7K OHM J 1608
R254	HRFS393JBA	R CHIP	1/16	39K OHM J 1608
R255	HRFS272JBA	R CHIP	1/16	2.7K OHM J 1608
R256	HRFS333JBA	R CHIP	1/16	33K OHM J 1608

R257	HRFS470JBA	R CHIP	1/16 47 OHM J 1608
R258	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R261	HRFS242JBA	R CHIP	1/16 2.4K OHM J 1608
R262	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608
R263	HRFS242JBA	R CHIP	1/16 2.4K OHM J 1608
R264	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608
R281	HRFS153JBA	R CHIP	1/16 15K OHM J 1608
R282	HRFS153JBA	R CHIP	1/16 15K OHM J 1608
R283	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
R284	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
R285	HRFS203JBA	R CHIP	1/16 20K OHM J 1608
R286	HRFS203JBA	R CHIP	1/16 20K OHM J 1608
R296	HRFS153JBA	R CHIP	1/16 15K OHM J 1608
R297	HRFS153JBA	R CHIP	1/16 15K OHM J 1608
R301	HRFS363JBA	R CHIP	1/16 36K OHM J 1608
R302	HRFS202JBA	R CHIP	1/16 2K OHM J 1608
R303	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608
R305	HRFS124JBA	R CHIP	1/16 120K OHM J 1608
R306	HRFS104JBA	R CHIP	1/16 100K OHM J 1608
R308	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608
R309	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608
R310	HRFS684JBA	R CHIP	1/16 680K OHM J 1608
R311	HRFS122JBA	R CHIP	1/16 1.2K OHM J 1608
R312	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608
R313	HRFS822JBA	R CHIP	1/16 8.2K OHM J 1608
R319	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R322	HRFS132JBA	R CHIP	1/16 1.3K OHM J 1608
R324	HRFS473JBA	R CHIP	1/16 47K OHM J 1608
R331	HRFS363JBA	R CHIP	1/16 36K OHM J 1608
R332	HRFS132JBA	R CHIP	1/16 1.3K OHM J 1608
R335	HRFS104JBA	R CHIP	1/16 100K OHM J 1608
R336	HRFS473JBA	R CHIP	1/16 47K OHM J 1608
R337	HRFS473JBA	R CHIP	1/16 47K OHM J 1608
R350	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R351	HRFS103JBA	R CHIP	1/16 10K OHM J 1608

R352	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R353	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R354	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R355	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R356	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R357	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R358	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R359	HRFS474JBA	R CHIP	1/16	470K OHM J 1608
R360	HRFS102JBA	R CHIP	1/16	1K OHM J 1608
R361	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R402	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R403	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R404	HRFS203JBA	R CHIP	1/16	20K OHM J 1608
R406	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R407	HRFS101JBA	R CHIP	1/16	100 OHM J 1608
R408	HRFS751JBA	R CHIP	1/16	750 OHM J 1608
R438	HRFS229JBA	R CHIP	1/16	2.2 OHM J 1608
R439	HRFS229JBA	R CHIP	1/16	2.2 OHM J 1608
R441	HRFS182JBA	R CHIP	1/16	1.8K OHM J 1608
R442	HRFS470JBA	R CHIP	1/16	47 OHM J 1608
R444	HRFS103JBA	R CHIP	1/16	10K OHM J 1608
R445	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R446	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R447	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R450	HRFS102JBA	R CHIP	1/16	1K OHM J 1608
R451	HRFS203JBA	R CHIP	1/16	20K OHM J 1608
R452	HRFS203JBA	R CHIP	1/16	20K OHM J 1608
R454	HRFS102JBA	R CHIP	1/16	1K OHM J 1608
R455	HRFS242JBA	R CHIP	1/16	2.4K OHM J 1608
R609	HRFS122JBA	R CHIP	1/16	1.2K OHM J 1608
R610	HRFS102JBA	R CHIP	1/16	1K OHM J 1608
R611	HRFS102JBA	R CHIP	1/16	1K OHM J 1608
R614	HRFS201JBA	R CHIP	1/16	200 OHM J 1608
R615	HRFS273JBA	R CHIP	1/16	27K OHM J 1608
R629	HRFS103JBA	R CHIP	1/16	10K OHM J 1608

R630	HRFS133JBA	R CHIP	1/16 13K OHM J 1608
R632	HRFS000-BA	R CHIP	1/16 0 OHM 1608
R651	HRFS332JBA	R CHIP	1/16 3.3K OHM J 1608
R652	HRFS131JBA	R CHIP	1/16 130 OHM J 1608
R653	HRFS131JBA	R CHIP	1/16 130 OHM J 1608
R901	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
R904	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R905	HRFS303JBA	R CHIP	1/16 30K OHM J 1608
R906	HRFS104JBA	R CHIP	1/16 100K OHM J 1608
R907	HRFS104JBA	R CHIP	1/16 100K OHM J 1608
R908	HRFS303JBA	R CHIP	1/16 30K OHM J 1608
R909	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R911	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
R917	HRFS302JBA	R CHIP	1/16 3K OHM J 1608
R919	HRFS302JBA	R CHIP	1/16 3K OHM J 1608
R921	HRFS223JBA	R CHIP	1/16 22K OHM J 1608
R923	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R924	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R930	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R931	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R932	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R934	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R940	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R942	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
R943	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
RC02	HRFS209JBA	R CHIP	1/16 2 OHM J 1608
RC04	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
RC05	HRFS209JBA	R CHIP	1/16 2 OHM J 1608
RJ019	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RJ18	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RS4	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
Z0012	PVMPJRN730	PCB MAIN RADIAL AS	DF-L71D1N-BJ
C102	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C107	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C108	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7

C115	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C118	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C119	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C122	CEXF1A471V	C ELECTRO	10V RSS 470MF (8X11.5) TP
C123	CEXF1A471V	C ELECTRO	10V RSS 470MF (8X11.5) TP
C124	CEXF1A101V	C ELECTRO	10V RSS 100MF
C127	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C129	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C130	CEXF1H339A	C ELECTRO	50V RSM 3.3MF 4X7
C132	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C138	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C142	CEXF1A471V	C ELECTRO	10V RSS 470MF (8X11.5) TP
C145	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C154	CEXF1H220V	C ELECTRO	50V RSS 22MF (5X11) TP
C158	CEXF1A101V	C ELECTRO	10V RSS 100MF
C169	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C170	CEXF1A101V	C ELECTRO	10V RSS 100MF
C172	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C202	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C206	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C208	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C210	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C212	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7
C215	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C218	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C219	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C223	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7
C224	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C225	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C227	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C228	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C245	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C248	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C249	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C250	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7

C259	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C263	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C264	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C265	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C266	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C267	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C269	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C270	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C271	CEXF1H229A	C ELECTRO	50V RSM 2.2MF (4X7) TP
C272	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C273	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C275	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C277	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C280	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C290	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C301	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C305	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C306	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C307	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C308	CEXF1H100A	C ELECTRO	50V RSM 10MF (5X7) TP
C309	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C312	CEXF1H100A	C ELECTRO	50V RSM 10MF (5X7) TP
C313	CEXF1H100A	C ELECTRO	50V RSM 10MF (5X7) TP
C314	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C315	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C316	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C322	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C323	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C324	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C326	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
C327	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C334	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C338	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7
C340	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C404	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP

C406	CEXF1H100A	C ELECTRO	50V RSM 10MF (5X7) TP
C409	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C412	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C414	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C415	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C416	CMXM2A243J	C MYLAR	100V 0.024MF J (TP)
C419	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C422	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C601	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C615	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C625	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C654	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C657	CEXF1C101A	C ELECTRO	16V RSM 100MF (6.3X7) TP
C663	CEXF1E470A	C ELECTRO	25V RSM 47MF 6.3*7
C666	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C667	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C669	CEXF1E470A	C ELECTRO	25V RSM 47MF 6.3*7
C670	CEXF1E470A	C ELECTRO	25V RSM 47MF 6.3*7
C671	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C672	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C673	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C675	CEXF1H470V	C ELECTRO	50V RSS 47MF (6.3X11) TP
C901	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C908	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C910	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C915	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C916	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C918	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C919	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)
C920	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C921	CEXF1C100A	C ELECTRO	16V RSM 10MF 5X7
C922	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C924	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C925	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
C928	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP

CS10	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP
CS9	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP
L100	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L101	5CPX688K2T	COIL PEAKING	0.68UH(BLU-SILV)
L103	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L104	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L105	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L111	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L201	5CPX101J2T	COIL PEAKING	100UH(BRN-BRN)
L222	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L250	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L251	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L256	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L259	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L301	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L304	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L305	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L306	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L307	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L401	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L402	5CPX680J2T	COIL PEAKING	68UH(BLU-BLK)
L403	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L601	5CPX120J--	COIL PEAKING	12UH J (RADIAL)
L901	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L902	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L903	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
L904	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
LS2	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)
Q201	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)
Q206	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q251	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q252	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q256	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q305	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)
Q403	TZTC3202Y-	TR	KTC3202Y (AUTO)(1959Y)

Q404	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q405	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q406	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)
Q601	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q602	TZTC3205Y-	TR	KTC3205Y (2236Y)
Q603	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q604	TZTC3205Y-	TR	KTC3205Y (2236Y)
Q605	TZTC3205Y-	TR	KTC3205Y (2236Y)
Q606	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q901	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q902	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
Q903	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)
Q904	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
QC01	TZTC3198Y-	TRANSISTOR	KTC3198Y-(1815Y) (AUTO)
QC02	TZTC3205Y-	TR	KTC3205Y (2236Y)
X301	5XE3R579TB	CRYSTAL QUARTZ	HC-49/U 3.579545MHZ 15PPM
Z0013	PVMPJAN730	PCB MAIN AXIAL AS	DF-L71D1N-BJ
C152	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C153	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C159	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C160	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C161	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C162	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C163	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C164	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C167	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C317	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C332	CCZF1H473Z	C CERA	50V F 0.047MF Z
C333	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C337	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C339	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C341	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C613	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL
C627	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C661	CCZF1H104Z	C CERA	HIKF 50V 0.1MF Z AXIAL

C664	CBZF1E223Z	C CERA SEMI	25V Y5V 0.022MF Z
C665	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M (AXIAL)
C668	CBZR1C272M	C CERA SEMI	16V Y5R 2700PF M AXIAL
D101	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D102	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D103	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D104	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D105	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D106	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D107	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D108	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D109	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D110	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D111	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D112	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D113	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D114	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D115	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D116	DZN4148---	DIODE	1N4148 AUTO 52MM
D117	DZN4148---	DIODE	1N4148 AUTO 52MM
D119	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D120	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D121	DZN4148---	DIODE	1N4148 AUTO 52MM
D122	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D123	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D124	DZN4148---	DIODE	1N4148 AUTO 52MM
D125	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D126	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D253	DZUZ13BSB-	DIODE ZENER	UZ-13BSB(12.59-13.16V)
D602	DZN4004---	DIODE	1N4004(AUTO)
D603	85801060TA	WIRE COPPER	0.6X52MM TAPING
D609	DZN4004---	DIODE	1N4004(AUTO)
D610	DZN4004---	DIODE	1N4004(AUTO)
D611	DZN4004---	DIODE	1N4004(AUTO)
D612	DZUZ13BSB-	DIODE ZENER	UZ-13BSB(12.59-13.16V)

D613	DZN4004---	DIODE	1N4004(AUTO)
D614	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)
D615	DZN4148---	DIODE	1N4148 AUTO 52MM
D616	DZUZ3R9BSA	DIODE ZENER	UZ-3.9BSA(3.77-3.98V)
D617	DZUZ33BSB-	DIODE ZENER	UZ-33BSB(30.32-31.38V)
DC01	DZN4148---	DIODE	1N4148 AUTO 52MM
R101	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R102	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R106	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R114	RD-AZ750J-	R CARBON FILM	1/6 75 OHM J
R125	RD-AZ750J-	R CARBON FILM	1/6 75 OHM J
R128	RD-AZ750J-	R CARBON FILM	1/6 75 OHM J
R130	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R131	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R143	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R147	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R148	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R156	RD-AZ332J-	R CARBON FILM	1/6 3.3K OHM J
R157	RD-AZ332J-	R CARBON FILM	1/6 3.3K OHM J
R209	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R213	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R220	RD-AZ223J-	R CARBON FILM	1/6 22K OHM J
R222	85801060TA	WIRE COPPER	0.6X52MM TAPING
R243	RD-AZ301J-	R CARBON FILM	1/6 300 OHM J
R244	RD-AZ512J-	R CARBON FILM	1/6 5.1K OHM J
R245	RD-AZ512J-	R CARBON FILM	1/6 5.1K OHM J
R246	RD-AZ512J-	R CARBON FILM	1/6 5.1K OHM J
R247	RD-AZ512J-	R CARBON FILM	1/6 5.1K OHM J
R259	RD-AZ183J-	R CARBON FILM	1/6 18K OHM J
R260	RD-AZ473J-	R CARBON FILM	1/6 47K OHM J
R265	RD-AZ153J-	R CARBON FILM	1/6 15K OHM J
R266	RD-AZ153J-	R CARBON FILM	1/6 15K OHM J
R267	RD-AZ153J-	R CARBON FILM	1/6 15K OHM J
R268	RD-AZ153J-	R CARBON FILM	1/6 15K OHM J
R269	RD-AZ822J-	R CARBON FILM	1/6 8.2K OHM J

R270	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R277	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R278	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R292	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R293	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
R294	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R295	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R298	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R299	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R307	RD-AZ222J-	R CARBON FILM	1/6 2.2K OHM J
R314	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R315	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R316	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R317	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R318	RD-AZ183J-	R CARBON FILM	1/6 18K OHM J
R320	RD-AZ203J-	R CARBON FILM	1/6 20K OHM J
R325	RD-AZ393J-	R CARBON FILM	1/6 39K OHM J
R326	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R329	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R330	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R333	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R362	RD-AZ151J-	R CARBON FILM	1/6 150 OHM J
R363	RD-AZ151J-	R CARBON FILM	1/6 150 OHM J
R401	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R405	RD-AZ242J-	R CARBON FILM	1/6 2.4K OHM J
R413	RD-AZ242J-	R CARBON FILM	1/6 2.4K OHM J
R414	RD-AZ242J-	R CARBON FILM	1/6 2.4K OHM J
R415	RD-AZ242J-	R CARBON FILM	1/6 2.4K OHM J
R416	RD-AZ242J-	R CARBON FILM	1/6 2.4K OHM J
R418	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R440	RD-AZ561J-	R CARBON FILM	1/6 560 OHM J
R443	RD-AZ223J-	R CARBON FILM	1/6 22K OHM J
R448	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R449	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R453	RD-AZ202J-	R CARBON FILM	1/6 2K OHM J

R601	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R602	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R607	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R608	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R612	RD-AZ105J-	R CARBON FILM	1/6 1M OHM J
R613	RD-AZ201J-	R CARBON FILM	1/6 200 OHM J
R616	RD-AZ201J-	R CARBON FILM	1/6 200 OHM J
R617	RD-AZ273J-	R CARBON FILM	1/6 27K OHM J
R618	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R619	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R621	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J
R622	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J
R623	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J
R624	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J
R626	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R631	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R634	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R635	RD-AZ474J-	R CARBON FILM	1/6 470K OHM J
R637	RD-AZ202J-	R CARBON FILM	1/6 2K OHM J
R639	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R640	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R642	85801060TA	WIRE COPPER	0.6X52MM TAPING
R654	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R655	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R656	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R657	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R658	RD-AZ473J-	R CARBON FILM	1/6 47K OHM J
R659	RD-AZ122J-	R CARBON FILM	1/6 1.2K OHM J
R660	RD-AZ203J-	R CARBON FILM	1/6 20K OHM J
R661	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R662	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R663	RD-AZ431J-	R CARBON FILM	1/6 430 OHM J
R664	RN-AZ103F-	R METAL FILM	1/6 10K OHM F
R665	RN-AZ103F-	R METAL FILM	1/6 10K OHM F
R666	RD-AZ912J-	R CARBON FILM	1/6 9.1K OHM J

R667	RD-AZ473J-	R CARBON FILM	1/6 47K OHM J
R668	RD-4Z123J-	R CARBON FILM	1/4 12K OHM J
R669	RD-4Z123J-	R CARBON FILM	1/4 12K OHM J
R670	RD-AZ201J-	R CARBON FILM	1/6 200 OHM J
R671	RD-AZ303J-	R CARBON FILM	1/6 30K OHM J
R672	RD-AZ272J-	R CARBON FILM	1/6 2.7K OHM J
R673	RD-AZ511J-	R CARBON FILM	1/6 510 OHM J
R674	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R902	RD-AZ122J-	R CARBON FILM	1/6 1.2K OHM J
R910	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R912	RD-AZ122J-	R CARBON FILM	1/6 1.2K OHM J
R913	RD-AZ301J-	R CARBON FILM	1/6 300 OHM J
R914	RD-AZ223J-	R CARBON FILM	1/6 22K OHM J
R915	RD-AZ471J-	R CARBON FILM	1/6 470 OHM J
R916	RD-AZ221J-	R CARBON FILM	1/6 220 OHM J
R918	RD-AZ471J-	R CARBON FILM	1/6 470 OHM J
R920	RD-AZ221J-	R CARBON FILM	1/6 220 OHM J
R922	RD-AZ301J-	R CARBON FILM	1/6 300 OHM J
R925	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R926	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R927	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R928	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J
R933	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R935	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R936	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R937	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R938	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R939	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R945	85801060TA	WIRE COPPER	0.6X52MM TAPING
R946	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R947	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R948	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R949	RD-AZ220J-	R CARBON FILM	1/6 22 OHM J
R950	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R952	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J

RC01	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
RC03	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J
RS6	RD-AZ222J-	R CARBON FILM	1/6 2.2K OHM J
U001	97P65443MA	PCB MAIN	330X246 D1B
Z0014	PVMPJVN730	PCB MAIN JUMP ONLY AS	DF-L71D1N-BJ
JP001	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP002	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP003	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP004	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP005	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP006	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP007	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP008	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP009	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP010	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP011	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP012	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP013	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP014	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP015	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP016	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP017	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP018	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP019	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP020	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP021	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP022	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP023	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP024	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP025	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP026	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP027	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP028	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP029	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP030	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP031	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP032	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP033	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP034	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP035	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP036	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP037	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP038	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP039	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP040	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP041	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP042	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP043	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP044	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP045	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP046	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP047	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP048	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP049	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP050	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP051	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP052	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP053	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP054	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP055	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP056	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP057	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP058	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP059	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP060	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP061	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP062	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP063	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP064	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP065	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP066	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP067	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP068	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP069	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP070	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP071	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP072	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP073	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP074	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP075	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP076	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP077	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP078	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP079	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP080	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP081	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP082	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP083	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP084	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP085	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP086	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP087	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP088	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP089	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP090	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP091	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP092	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP093	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP094	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP095	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP096	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP097	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP098	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP099	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP100	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP101	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP102	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP103	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP104	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP105	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP106	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP107	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP108	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP109	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP110	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP111	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP112	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP113	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP114	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP115	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP116	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP117	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP118	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP119	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP120	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP121	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP122	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP123	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP124	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP125	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP126	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP127	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP128	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP129	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP130	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP131	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP132	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP133	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP134	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP135	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP136	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP137	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP138	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP139	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP140	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP141	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP142	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP143	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP144	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP145	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP146	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP147	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP148	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP149	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP150	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP151	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP152	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP153	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP154	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP155	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP156	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP157	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP158	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP159	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP160	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP161	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP162	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP163	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP164	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP165	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP166	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP167	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP168	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP169	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP170	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP171	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP172	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP173	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP174	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP175	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP176	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP177	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP178	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP179	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP180	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP181	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP182	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP183	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP184	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP185	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP186	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP188	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP189	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP190	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP191	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP192	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP193	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP194	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP195	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP196	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP197	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP198	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP199	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP201	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP202	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP203	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP204	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP205	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP206	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP207	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP208	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP209	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP210	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP211	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP212	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP213	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP214	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP215	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP216	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP218	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP219	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP220	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP221	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP222	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP223	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP224	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP225	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP226	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP227	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP228	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP229	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP230	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP231	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP232	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP233	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP234	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP235	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP236	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP237	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP238	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP239	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP240	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP241	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP242	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP243	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP244	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP245	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP246	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP247	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP248	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP249	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP250	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP251	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP252	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP253	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP254	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP255	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP256	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP257	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP258	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP259	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP260	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP261	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP262	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP263	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP264	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP265	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP266	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP267	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP268	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP269	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP271	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP500	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP600	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
R604	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
Z003	PVLAMSN730	PCB LOGIC MANUAL AS	DF-L71D1N-BJ
AL01	2193100801	SOLDER WIRE	SN:PB=63:37 3PI(NO FLUX)
AL02	2193011100	SOLDER WIRE	60 SNA 1.2D
AL03	2291050305	FLUX LIQUID	RF-800KN
AL04	2291050306	FLUX THINNER	RF-800ADD

AL05	2291140501	WAX COVER	
AL06	97P4220200	CUSHION LEG	EVA T4.0
E701	97P0991600	PLATE EARTH A/V	C5210(PBS) T0.2
G701	DZ201209F-	DIGITRON	VFD20-1209F
G701A	97P2348100	HOLDER DIGITRON	PP
H701	10RC356HF6	IC UNIT R/RECEIVER	ORC-356HF6
JK701	97P6316800	JACK PIN	DPSE-9966
P701	97P62M13DM	CONN WAFER	52492-2120 21P RA 1.25
P702	97P62G08E9	CONN FFC	GF102-09S-TS 09P ST
P703	97P62G08E9	CONN FFC	GF102-09S-TS 09P ST
P704	97P62A10A6	CONN WAFER	440053-6 PLUG 6P 2.5
Z0031	PVLAJ1N730	PCB LOGIC CHIP AS	DF-L71D1N-BJ
C701	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C702	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C704	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C705	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C706	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C707	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C708	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
C709	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
IC701	1PT6315--Q	IC VFD DRIVER	PT6315 44PIN LQFP
R701	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R702	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
R703	HRFS301JBA	R CHIP	1/16 300 OHM J 1608
R707	HRFS301JBA	R CHIP	1/16 300 OHM J 1608
Z0032	PVLAJRN730	PCB LOGIC RADIAL AS	DF-L71D1N-BJ
C703	CEXF1E470A	C ELECTRO	25V RSM 47MF 6.3*7
SW701	5S50101Z90	SW TACT	THVV502GDA
SW702	5S50101Z90	SW TACT	THVV502GDA
SW703	5S50101Z90	SW TACT	THVV502GDA
SW704	5S50101Z90	SW TACT	THVV502GDA
SW705	5S50101Z90	SW TACT	THVV502GDA
SW706	5S50101Z90	SW TACT	THVV502GDA
SW707	5S50101Z90	SW TACT	THVV502GDA
SW708	5S50101Z90	SW TACT	THVV502GDA

SW709	5S50101Z90	SW TACT	THVV502GDA
SW710	5S50101Z90	SW TACT	THVV502GDA
SW711	5S50101Z90	SW TACT	THVV502GDA
SW712	5S50101Z90	SW TACT	THVV502GDA
SW713	5S50101Z90	SW TACT	THVV502GDA
Z0033	PVLAJAN730	PCB LOGIC AXIAL AS	DF-L71D1N-BJ
AL31	2TM14006LB	TAPE MASKING	3M #232 6.0X2000M
AL31A	2TM110620R	TAPE MASKING	SI-600N RED
AL31B	2TM1106200	TAPE MASKING	SI-600N
C710	CCZB1H221K	C CERA	50V B 220PF K (AXIAL)
C711	CCZB1H221K	C CERA	50V B 220PF K (AXIAL)
C712	CCZB1H221K	C CERA	50V B 220PF K (AXIAL)
C713	CCZB1H221K	C CERA	50V B 220PF K (AXIAL)
D701	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D702	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)
D703	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)
D705	DZN4148---	DIODE	1N4148 AUTO 52MM
D706	DZN4148---	DIODE	1N4148 AUTO 52MM
D707	DZN4148---	DIODE	1N4148 AUTO 52MM
D708	DZN4148---	DIODE	1N4148 AUTO 52MM
D709	DZN4148---	DIODE	1N4148 AUTO 52MM
D710	DZN4148---	DIODE	1N4148 AUTO 52MM
D711	DZN4148---	DIODE	1N4148 AUTO 52MM
D712	DZN4148---	DIODE	1N4148 AUTO 52MM
D713	DZN4148---	DIODE	1N4148 AUTO 52MM
D715	DZUZ5R6BSB	DIODE ZENER	UZ-5.6BSB(5.46-5.70V)
D716	DZN4148---	DIODE	1N4148 AUTO 52MM
JP001	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP002	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP003	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP004	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP005	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP006	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP007	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP008	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP009	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP010	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP011	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP012	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP013	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP015	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP016	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP017	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP018	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP019	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP020	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP021	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP022	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP023	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP024	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP025	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP026	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP029	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
L701	5CPZ229K02	COIL PEAKING	2.2UH K(AXIAL 3.5MM)
L702	5CPZ229K02	COIL PEAKING	2.2UH K(AXIAL 3.5MM)
R704	RD-AZ823J-	R CARBON FILM	1/6 82K OHM J
R705	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R706	RD-AZ750J-	R CARBON FILM	1/6 75 OHM J
UL01	97P65447UA	PCB UNION	330X246 D1B
Z004	PVMGMSN730	PCB MPEG MANUAL AS	DF-L71D1N-BJ
PC05	97P62A0539	CONN WAFER	2-440091-5 2.54MM 39PIM
Z0051	PVMGJ1N730	PCB MPEG CHIP AS	DF-L71D1N-BJ
AMA1	2193220007	SOLDER CLEAM	RMA9154 63SN/37PB,#325
CC02	HCEMF470MD	C CHIP ELECTRO	MV 16V 47MF D6.3XH5.2
CC04	HCQK220JBA	C CHIP CERA	50V CH 22PF J 1608
CC05	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CC08	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CC09	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CC11	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CC13	HCEPF331ME	C CHIP ELECTRO	MVG 16V 330MF M D8XH10

CC15	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CC16	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC17	HCEPF331ME	C CHIP ELECTRO	MVG 16V 330MF M D8XH10
CC19	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CC24	HCEMF470MD	C CHIP ELECTRO	MV 16V 47MF D6.3XH5.2
CC26	HCEMF470MD	C CHIP ELECTRO	MV 16V 47MF D6.3XH5.2
CD01	HCQK560JBA	C CHIP CERA	50V CH 56PF J 1608
CD02	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD06	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD07	HCQK200JBA	C CHIP CERA	50V CH 20PF J 1608
CD08	HCQK220JBA	C CHIP CERA	50V CH 22PF J 1608
CD09	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CD13	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD19	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD20	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM28	HCQK102JBA	C CHIP CERA	50V CH 1000PF J 1608
CM29	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM38	HCQK102JBA	C CHIP CERA	50V CH 1000PF J 1608
CM39	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM46	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CM52	HCEJD221MD	C CHIP ELECTRO	MVG 10V 220MF M D8XH6.3
CM56	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM63	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM73	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM92	HCQK102JBA	C CHIP CERA	50V CH 1000PF J 1608
CN05	HCEEF101MD	C CHIP ELECTRO	MV 16V 100MF M 6.3DX5.7H
CN09	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CN10	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN27	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN33	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN55	HCEMF470MD	C CHIP ELECTRO	MV 16V 47MF D6.3XH5.2
CN58	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CV08	HCBK473KBA	C CHIP CERA	50V X7R 0.047MF K 1608
CV13	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV14	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608

CV22	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV23	HCEEF101MD	C CHIP ELECTRO	MV 16V 100MF M 6.3DX5.7H
CV29	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
ICC02	1AP1184ADE	IC CHIP REGULATOR	AP1184K5A ADJ VOLT 4A T0263-5L REEL
ICC03	1AP1184ADE	IC CHIP REGULATOR	AP1184K5A ADJ VOLT 4A T0263-5L REEL
ICD01	1TSB41AB1E	IC CHIP 1EEE1394	TSB41AB1PHPR 48PIN PQFP TYPE REEL
ICM01	1G2995F1UC	IC CHIP DDR REGUATOR	G2995F1U AV1N=PV1N=2.5V SOP-8L
ICM02	1HYB25D25E	IC CHIP DDRSDRAM	HYB25D256160CE-6 256MB(16MX6) 333MHZ 66PIN TSOP-11
ICM03	1HYB25D25E	IC CHIP DDRSDRAM	HYB25D256160CE-6 256MB(16MX6) 333MHZ 66PIN TSOP-11
ICM05	1LVC16373E	IC CHIP TRANSPARENT	SN74LVC16373ADGGR 48PIN TSSOP-DGGR
ICM06	1160ATTC7Q	IC CHIP FLASH ROM	MX29LV160ATTC-70 48PIN TSOP
ICN01	1DMN8602-Q	IC CHIP CODEC	DMN-8602 SINGLE DRIVE DVD REC PROCESSOR BGA 308PIN
ICV03	1SAA7115HQ	IC CHIP VIDEO DECODER	SAA7115 LQFP 100PIN TRAY
LC03	HRF8000-EA	R CHIP	1/8 0 OHM 3216
LC05	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC07	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC08	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC09	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC10	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC12	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC13	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC14	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC15	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC33	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC34	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC35	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC36	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC37	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC38	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC39	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC40	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC58	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC59	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC60	HRF8000-EA	R CHIP	1/8 0 OHM 3216
LC61	HRF8000-EA	R CHIP	1/8 0 OHM 3216

LC62	HRF8000-EA	R CHIP	1/8 0 OHM 3216
LC64	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LC65	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LC66	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LC67	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LD01	HFEACM321B	F CHIP EMI	80 OHM ACM 3225
LD02	HFEACM321B	F CHIP EMI	80 OHM ACM 3225
LD04	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LD05	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LV16	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LV17	HRF8000-EA	R CHIP	1/8 0 OHM 3216
PC02	97P62Y33BC	CONN WAFER SMD	20022WS-12A00 ST 2.0MM SMD
RC01	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RC04	HRFS332JBA	R CHIP	1/16 3.3K OHM J 1608
RC05	HRFS332JBA	R CHIP	1/16 3.3K OHM J 1608
RC09	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC10	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RC11	HRFS820JBA	R CHIP	1/16 82 OHM J 1608
RC12	HRFS820JBA	R CHIP	1/16 82 OHM J 1608
RC13	HRFS820JBA	R CHIP	1/16 82 OHM J 1608
RC14	HRFS681JBA	R CHIP	1/16 680 OHM J 1608
RC15	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
RC29	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC37	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC38	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RC46	HRFS331JBA	R CHIP	1/16 330 OHM J 1608
RC49	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RC50	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RD01	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RD03	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RD04	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
RD06	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RD10	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RD11	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RD13	HRFS102JBA	R CHIP	1/16 1K OHM J 1608

RD14	HRFS560JBA	R CHIP	1/16 56 OHM J 1608
RD16	HRFS560JBA	R CHIP	1/16 56 OHM J 1608
RD17	HRFS560JBA	R CHIP	1/16 56 OHM J 1608
RD18	HRFS560JBA	R CHIP	1/16 56 OHM J 1608
RD21	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RD22	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RD23	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RD24	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RD25	HRFS153JBA	R CHIP	1/16 15K OHM J 1608
RD26	HRFS153JBA	R CHIP	1/16 15K OHM J 1608
RM03	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM04	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM05	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM07	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM10	HRTS8E220J	R CHIP ARRAY	1/16 8P 22 OHM J 3216
RM12	HRTS8E220J	R CHIP ARRAY	1/16 8P 22 OHM J 3216
RM18	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RM19	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RM20	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RM21	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RM22	HRTS8E220J	R CHIP ARRAY	1/16 8P 22 OHM J 3216
RM23	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RM24	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM25	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM26	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM27	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM28	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM29	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM30	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM31	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM36	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM38	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM39	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM40	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM42	HRFS510JBA	R CHIP	1/16 51 OHM J 1608

RM43	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM45	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM47	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM51	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RN01	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN05	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN07	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN08	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN09	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN11	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN12	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN13	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN14	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN15	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN23	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN30	HRFS122JBA	R CHIP	1/16 1.2K OHM J 1608
RN38	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN40	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN42	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN49	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN50	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN52	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RN53	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
RV18	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RV19	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RV25	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RV26	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
UM01	97P65443MB	PCB MPEG	126.5X145(253X145/2)
XD01	5XJ24R57SE	CRYSTAL QUARTZ	HC-49/S 24.576000MHZ 30PP (SMD)
XV01	5XJ24R57SE	CRYSTAL QUARTZ	HC-49/S 24.576000MHZ 30PP (SMD)
Z0052	PVMGJ2N730	PCB MPEG CHIP B AS	DF-L71D1N-BJ
AMB1	2193220007	SOLDER CLEAM	RMA9154 63SN/37PB,#325
CC01	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC03	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC06	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608

CC07	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC10	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC12	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC14	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC18	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC20	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC21	HCQK180JBA	C CHIP CERA	50V CH 18PF J 1608
CC22	HCQK180JBA	C CHIP CERA	50V CH 18PF J 1608
CC23	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC25	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CC27	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CC28	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD03	HCQK221JBA	C CHIP CERA	50V CH 220PF J 1608
CD04	HCBF224KBA	C CHIP CERA	16V X7R 0.22MF K 1608
CD05	HCEKK109MC	C CHIP ELECTRO	MV 50V 1MF D4.0XH5.2
CD10	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CD11	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD12	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CD14	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CD15	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD16	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD17	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CD18	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM01	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM02	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM03	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM04	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM05	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM06	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM07	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM08	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM09	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM10	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM11	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM12	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608

CM13	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM14	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM15	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM16	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM17	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM18	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM19	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM20	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM21	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM22	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM23	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM24	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM25	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM26	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM27	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM30	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM31	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM32	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM33	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CM34	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM35	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM36	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM37	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM40	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM41	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM42	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM43	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM44	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM45	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM47	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM48	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM49	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM50	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM51	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM53	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608

CM54	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM55	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM57	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM58	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM59	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM60	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM61	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM62	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM64	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM65	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM66	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM67	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM68	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM69	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM70	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM71	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM72	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM74	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM75	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM76	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM77	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM78	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM79	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CM80	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM81	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM82	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM83	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM84	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM85	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM86	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM87	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM88	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CM89	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM91	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM93	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2

CM94	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM95	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CM96	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN01	HCQK150JBA	C CHIP CERA	50V CH 15PF J 1608
CN02	HCQK150JBA	C CHIP CERA	50V CH 15PF J 1608
CN03	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN04	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN06	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN07	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN08	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN11	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN12	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN13	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN14	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN15	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN16	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN17	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN18	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN19	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN20	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN21	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CN22	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CN23	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN24	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN25	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN26	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN28	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN29	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN30	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN31	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN32	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN34	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CN35	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CN36	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN37	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608

CN38	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN39	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN40	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN41	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN42	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN43	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN44	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608
CN45	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608
CN46	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN48	HCEMF470MD	C CHIP ELECTRO	MV 16V 47MF D6.3XH5.2
CN49	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN50	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN51	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN52	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN53	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN54	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN56	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CN57	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV01	HCBK473KBA	C CHIP CERA	50V X7R 0.047MF K 1608
CV02	HCBK473KBA	C CHIP CERA	50V X7R 0.047MF K 1608
CV09	HCQK200JBA	C CHIP CERA	50V CH 20PF J 1608
CV10	HCQK200JBA	C CHIP CERA	50V CH 20PF J 1608
CV11	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV12	HCEKF100MC	C CHIP ELECTRO	MV 16V 10MF D4.0XH5.2
CV15	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV16	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV17	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV18	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV19	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV20	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV21	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV24	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV25	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
CV26	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608
DC02	DRLS4148-B	DIODE CHIP	RLS4148TE-11 3415

DN01	DRLS4148-B	DIODE CHIP	RLS4148TE-11 3415
DN02	DRLS4148-B	DIODE CHIP	RLS4148TE-11 3415
LC01	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LC02	HRF8000-EA	R CHIP	1/8 0 OHM 3216
LC16	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC17	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC18	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC19	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC20	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC21	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC22	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC32	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC41	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC42	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC43	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC44	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC45	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC46	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC47	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC48	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC49	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC50	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC51	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC52	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC53	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC54	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC55	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC56	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC57	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC63	HRF8000-EA	R CHIP	1/8 0 OHM 3216
LC68	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC69	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC70	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC71	HRFS000-BA	R CHIP	1/16 0 OHM 1608
LC73	HRFT000-CA	R CHIP	1/10 0 OHM 2012

LD03	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LM03	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LN01	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LN02	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LN03	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LN04	HRFT000-CA	R CHIP	1/10 0 OHM 2012
LN05	HRFT000-CA	R CHIP	1/10 0 OHM 2012
RC08	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608
RC16	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RC17	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RC18	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RC19	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RC20	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RC21	HRTS8E330J	R CHIP ARRAY	1/16 8P 33 OHM 3216
RC23	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC30	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC32	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC33	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC34	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC35	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC36	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RC41	HRFS271JBA	R CHIP	1/16 270 OHM J 1608
RC42	HRFS121JBA	R CHIP	1/16 120 OHM J 1608
RC43	HRFS121JBA	R CHIP	1/16 120 OHM J 1608
RC44	HRFS121JBA	R CHIP	1/16 120 OHM J 1608
RC45	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RC47	HRFS221JBA	R CHIP	1/16 220 OHM J 1608
RC48	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RD02	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RD07	HRFS681JBA	R CHIP	1/16 680 OHM J 1608
RD08	HRFS681JBA	R CHIP	1/16 680 OHM J 1608
RD09	HRFS681JBA	R CHIP	1/16 680 OHM J 1608
RD12	HRFS102JBA	R CHIP	1/16 1K OHM J 1608
RD15	HRFS512JBA	R CHIP	1/16 5.1K OHM J 1608
RD19	HRFS913FBA	R CHIP	1/16 91K OHM F 1608

RD20	HRFS682FBA	R CHIP	1/16 6.8K OHM F 1608
RM01	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM02	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM06	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM08	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM09	HRTS8E220J	R CHIP ARRAY	1/16 8P 22 OHM J 3216
RM11	HRTS8E220J	R CHIP ARRAY	1/16 8P 22 OHM J 3216
RM13	HRTS8E220J	R CHIP ARRAY	1/16 8P 22 OHM J 3216
RM14	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM15	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM16	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM17	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM32	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM33	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM34	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM35	HRTS8E510J	R CHIP ARRAY	1/16 8P 51 OHM J 3216
RM37	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM41	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM44	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM46	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM48	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM49	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM50	HRFS510JBA	R CHIP	1/16 51 OHM J 1608
RM56	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RM57	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RM58	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RM62	HRFS000-BA	R CHIP	1/16 0 OHM 1608
RN02	HRFS471JBA	R CHIP	1/16 470 OHM J 1608
RN06	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN10	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN16	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN17	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN18	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN19	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN21	HRFS103JBA	R CHIP	1/16 10K OHM J 1608

RN22	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN31	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN32	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN33	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN34	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN35	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
RN36	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN37	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN39	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN43	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN44	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN46	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN48	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RN54	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RV17	HRFS101JBA	R CHIP	1/16 100 OHM J 1608
RV22	HRFS103JBA	R CHIP	1/16 10K OHM J 1608
RV23	HRFS220JBA	R CHIP	1/16W 22 OHM J 1608
Z800	PVPWMSN730	PCB POWER MANUAL AS	DF-L71D1N-BJ
AP01	2193100801	SOLDER WIRE	SN:PB=63:37 3PI(NO FLUX)
AP02	2193011100	SOLDER WIRE	60 SNA 1.2D
AP03	2291050305	FLUX LIQUID	RF-800KN
AP04	2291050306	FLUX THINNER	RF-800ADD
AP05	2291140501	WAX COVER	
AP06	97P93B2101	LABEL CD(PCB)	PAPER(13X25) ALL MODEL
C801	CL2EE3104M	C LINE ACROSS	AC 275V 0.1MF M PCX2 335M
C802	CH1TFE222M	C CERA AC	4.0KV 2200PF M AD AC250V
C804	CH1TFE332M	C CERA AC	4.0KV 3300PF M AD AC250V
C805	CH1TFE222M	C CERA AC	4.0KV 2200PF M AD AC250V
C806	CEXF2E680V	C ELECTRO	250V RSS 68MF 16X25(SG)
C821	CEXK1C102L	C ELECTRO	16V 1000UF KXL (10X20)
C822	CEXK1C102L	C ELECTRO	16V 1000UF KXL (10X20)
C823	CEXK1C102L	C ELECTRO	16V 1000UF KXL (10X20)
C824	CEXK1E681L	C ELECTRO	25V 680UF KXL
C825	CEXK1E681L	C ELECTRO	25V 680UF KXL
D801	DS1WBA60--	DIODE BRIDGE	S1WBA60

D821	DD3S4M----	DIODE SCHOTTKY	D3S4M
D822	DD3S4M----	DIODE SCHOTTKY	D3S4M
D823	DD3S4M----	DIODE SCHOTTKY	D3S4M
D824	DS2L20U--F	DIODE	S2L20U 4004 P15
D825	DS2L20U--F	DIODE	S2L20U 4004 P15
D832	DS2L20U--F	DIODE	S2L20U 4004 P15
D834	DD3S4M----	DIODE SCHOTTKY	D3S4M
IC801	1LTV817MDW	IC PHOTO COUPLER	LVT-817M-DW
IC802	1FSDM0565P	IC POWER SWITCH	FSDM0565RYDTU 70KHZ TO-220F-6L(F/M)
IC807	1KA78R05TU	IC REGULATOR	KA78R05TU 5.0V 1.0A TO-220F
IC808	1K1A78R12A	IC REGULATOR	K1A78R12AP1 12.0V 1.0A TO-220
L801	5PLFSF212A	FILTER LINE	SF-2120A
L802	5PLFBLF216	FILTER LINE	BLF-2116
L821	56C339K705	COIL CHOKE	3R3K(3.3UH)
P801	97P62Y04X4	CONN WAFER	YW396 4P NC
P821	97P62A09A4	CONN WAFER	440052-4 PLUG 4P 2.5
P823	97P62A09AD	CONN WAFER	1-440052-3 PLUG 13P 2.5
Q821	TFQP20N06-	FET	FQP20N06
R802	RW02B229J-	R WIRE WOUND	2W 2.2 OHM J
R806	RS02F473JS	R M-OXIDE FILM	2W 47K OHM J SMALL
T801	57M8282316	TRANS SMPS	TSW-C9AD1D(MAIN)
VA801	D1NR10D471	VARISTOR	1NR10D471
VA802	D1NR10D471	VARISTOR	1NR10D471
Z0081	PVPWJRN730	PCB POWER RADIAL AS	DF-L71D1N-BJ
C807	CMXL2G333K	C MYLAR	400V MEU 0.033MF K
C808	CEXF1H220V	C ELECTRO	50V RSS 22MF (5X11) TP
C809	CMXM2A223J	C MYLAR	100V 0.022MF J TP
C810	CBXB3A101K	C CERA SEMI	1KV RR 100PF K
C826	CEXK1H470L	C ELECTRO	50V 47MF KXL
C827	CEXK1H470L	C ELECTRO	50V 47MF KXL
C828	CEXK1H470L	C ELECTRO	50V 47MF KXL
C829	CEXF1A471V	C ELECTRO	10V RSS 470MF (8X11.5) TP
C830	CEXF1E221V	C ELECTRO	25V RSS 220MF (8X11.5) TP
C831	CEXF1E221V	C ELECTRO	25V RSS 220MF (8X11.5) TP
C832	CEXF1E221V	C ELECTRO	25V RSS 220MF (8X11.5) TP

C833	CEXF1E221V	C ELECTRO	25V RSS 220MF (8X11.5) TP
C834	CMXL1J104K	C MYLAR	MEU 63V 0.1MF K
C836	CEXK1H470L	C ELECTRO	50V 47MF KXL
F801	5FWPS2022L	FUSE	WIDE TL 250V 2A CASE
IC803	1KA431AZ--	IC REGULATOR	KA431AZ 1% TO-92
L822	56C220K695	COIL CHOKE(CAP TYPE)	22UH K 9X11.1 (CAP TYPE)
L823	56C220K695	COIL CHOKE(CAP TYPE)	22UH K 9X11.1 (CAP TYPE)
L824	56C220K695	COIL CHOKE(CAP TYPE)	22UH K 9X11.1 (CAP TYPE)
Z0082	PVPWJAN730	POWER AXIAL AUTO AS	DF-L71D1N-BJ
AP31	2TM14006LB	TAPE MASKING	3M #232 6.0X2000M
AP31A	2TM110620R	TAPE MASKING	SI-600N RED
AP31B	2TM1106200	TAPE MASKING	SI-600N
D802	DZEG01C---	DIODE	EG01C
D803	DZN4148---	DIODE	1N4148 AUTO 52MM
D804	DZUZ6R8BSC	DIODE ZENER	UZ-6.8BSC(6.70-6.97)
D805	DUZ22BM---	DIODE ZENER	UZ-22BM
D826	DZ1F3E----	DIODE FR	1F3E
D827	DZ1F3E----	DIODE FR	1F3E
D828	DZ1F3E----	DIODE FR	1F3E
D830	DZUZ3R9BSB	DIODE ZENER	UZ-3.9BSB(3.92-4.14)
D833	DZN4003---	DIODE	IN4003
JP801	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP802	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP803	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP821	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP822	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP823	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP824	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP825	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP826	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP827	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP828	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP829	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP830	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP831	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING

JP832	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP833	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP834	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP835	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP836	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP837	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP838	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP839	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP840	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
JP841	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING
R801	RC-2Z335KP	R CARBON COMP	1/2 3.3M OHM K
R803	RD-4Z333J-	R CARBON FILM	1/4 33K OHM J
R804	RD-4Z473J-	R CARBON FILM	1/4 47K OHM J
R805	RD-AZ820J-	R CARBON FILM	1/6 82 OHM J
R821	RD-AZ221J-	R CARBON FILM	1/6 220 OHM J
R822	RD-AZ272J-	R CARBON FILM	1/6 2.7K OHM J
R823	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J
R824	RN-AZ182F-	R METAL FILM	1/6 1.8K OHM F
R825	RN-AZ132F-	R METAL FILM	1/6 1.3K OHM F
R826	RD-AZ223J-	R CARBON FILM	1/6 22K OHM J
R827	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R830	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J
R832	RD-AZ301J-	R CARBON FILM	1/6 300 OHM J
UP01	97P65443PA	PCB POWER	330X246 D1B