











FRONT SIDE

<div><h1>SOLO+</h1><p>WIRELESS EARBUD</p><h2>INSTRUCTION MANUAL</h2><p>Thank you for purchasing the Solo+ Wireless Earbud. This manual provides more information about the wireless earbud, please read the instructions before using.</p></div>	<div><h3>Product Overview</h3><div><div><p>Earbud</p><p>1. Power Indicator 2. On/Off Button/Play/ Pause Music/Answer/End Call</p></div><div><p>Charging Case Front</p><p>3. LED Indicator 4. Micro USB Charging Port</p></div><div><p>Instruction Manual</p></div><div><p>Micro USB Charging Cable</p><p>USB Plug Micro USB Plug</p></div></div></div> <div><h3>Power On/Off</h3><p>Power On Press and hold down the On/Off Button of earbud for 3 seconds and the LED will flash.</p><p>Power Off Press and hold down the On/Off Button of earbud for 4 seconds and the LED will turn off.</p></div> <div><h3>Pair the wireless earbud with your mobile device</h3><ol style="list-style-type: none">1. Keep the distance between the earbud and mobile device within 32.8 feet.2. De-activate the Bluetooth function on your mobile device.3. Power on the earbud by pressing the On/Off button for 3 seconds. The earbud has indicator blinking alternatively in Red and Blue.4. Activate the Bluetooth function on your mobile device and select "BT SOLO+ EARBUD" from the list shown.5. After pairing is successful, the earbud will start blinking slowly in blue.</div> <div><h3>Package Contents</h3><table><tr><td>Solo+ Plus Wireless Earbud x 1 Portable Charging Case x 1</td><td>Micro USB Charging Cable x 1 Instruction Manual x 1</td></tr></table></div> <div><h3>Specifications</h3><table><tr><td>Driver Diameter: 10 mm Impedance: 16 Ohms Frequency Response: 20 Hz – 20K Hz Sensitivity: 100 dB +/- 3 dB Power Supply: Li-ion Battery 3.7V 45 mAh Li-ion Battery 3.7V 200 mAh (Charging Case) Total Talk Time: 6 Hours Charging Time: 2 Hours</td><td>Bluetooth Range: 32.8 Feet Micro USB Charging cable included Magnetic Charging Case</td></tr></table></div> <div><h3>Reconnect the wireless earbuds to your mobile device</h3><p>When powered on, the wireless earbud will automatically connect with the last successfully paired device.</p></div> <div><h3>Disconnect the wireless earbuds from your mobile device</h3><p>Power off the wireless earbud; or Switch off the Bluetooth on your mobile phone; or Leave the earbud 60ft away from your mobile phone or further.</p></div>	Solo+ Plus Wireless Earbud x 1 Portable Charging Case x 1	Micro USB Charging Cable x 1 Instruction Manual x 1	Driver Diameter: 10 mm Impedance: 16 Ohms Frequency Response: 20 Hz – 20K Hz Sensitivity: 100 dB +/- 3 dB Power Supply: Li-ion Battery 3.7V 45 mAh Li-ion Battery 3.7V 200 mAh (Charging Case) Total Talk Time: 6 Hours Charging Time: 2 Hours	Bluetooth Range: 32.8 Feet Micro USB Charging cable included Magnetic Charging Case
Solo+ Plus Wireless Earbud x 1 Portable Charging Case x 1	Micro USB Charging Cable x 1 Instruction Manual x 1				
Driver Diameter: 10 mm Impedance: 16 Ohms Frequency Response: 20 Hz – 20K Hz Sensitivity: 100 dB +/- 3 dB Power Supply: Li-ion Battery 3.7V 45 mAh Li-ion Battery 3.7V 200 mAh (Charging Case) Total Talk Time: 6 Hours Charging Time: 2 Hours	Bluetooth Range: 32.8 Feet Micro USB Charging cable included Magnetic Charging Case				

BACK SIDE

<div><h3>Answer / Reject a call</h3><p>When receive a call, press the On/Off Button once to accept the call, or answer the call normally via your mobile phone. Press and hold 2 seconds to reject it.</p></div> <div><h3>End a call</h3><p>To end the call, just press On/Off button on the earbud with Beep sound to end it.</p></div> <div><h3>Charging your Earbud with Charging case</h3><ol style="list-style-type: none">1. Put earbud to charging case and press the charging On/Off button to start charging.2. Earbud LED indicator light turns red when charging your earbud.4. Earbud LED indicator light turns off when your earbud is fully charged.</div> <div><h3>Recharge Charging Case</h3><p>⚠ For your safety, please always use appropriate 5V input charger/Adapter to charge the product. DO NOT USE Quick Charging USB Adapter to charge the product, as it might damage the product.</p><ol style="list-style-type: none">1. Use the Micro USB charging cable provided with the packaging.2. Connect the Micro USB plug to Micro USB charging port on the charging case, then connect the USB plug to a USB port on a computer or wall adapter to begin charging.3. The Red LED on the charging case will be flashing during charge.4. Once fully charged, the Red LED will be on and stop flashing.<p>NOTE:</p><ul style="list-style-type: none">• You must select a qualified charger from a regular manufacturer.• You must charge the charging case and earbuds if it has been not used for more than 6 months.<div></div></div>		<div><h3>FAQ</h3><p>If the wireless earbud cannot be paired with your device, please try the following: Ensure that your earbud is in pairing mode or reconnection mode Ensure that Bluetooth search function of your mobile device is activated.</p><p>If the wireless earbud will not turn on: Make sure the earbud is fully charged.</p><p>Can I change the battery for the charging case and earbud? The charging case and earbud use a built-in non-detachable battery which cannot be removed.</p><p>If the charging case cannot be recharged: If you use a power outlet, ensure that the power supply is connected securely and the outlet works. If you use a computer, ensure that it is connected and the USB port is powered.</p><p>⚠ Safety instructions for the lithium battery and charging the product</p><ul style="list-style-type: none">-The input voltage to the product is 5V 1A.-In order to charge the product in safe manner and reliable conditions, please only adopt certified appropriate charger/ adapter for charging the product.-Only charge the product at ambient temperatures between 10 deg °C/ 50 deg °F and 40 deg °C/104 deg °F.- Do not heat above 70 deg °C/158 deg °F, eg. Do not expose to sunlight or throw into fire.-Switch off the product after use.-Please note that we won't take any responsibility for any wrong operation (eg. Voltage higher than 5V) as this may result in severe injury or loss of property, and we cannot control the operating process during the time the user using this product.-In extreme cases, abuse or misuse of Lithium battery pack can lead to explosion, heat generation, fire development or smoke development.</div> <div><h3>FCC STATEMENT</h3><p>1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation.</p><p>2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p><p>NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p><ul style="list-style-type: none">- Reorient or relocate the receiving antenna.- Increase the separation between the equipment and receiver.- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.- Consult the dealer or an experienced radio/TV technician for help.<p>RF warning statement: The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.</p><div><p>FCC ID: 2ADM5-EP-0663 ITEM# EP-0663</p></div><div><p>⚠ WARNING: This product can expose you to chemicals including Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information, go to www.P65Warnings.ca.gov.</p></div><p>Keep all relevant information for future reference</p></div>
---	--	--