Go to www.vtechphones.com to register your product for enhanced warranty support and the latest VTech



vtech Quick start quide



on purchasing your new VTech product.

Before using this baby monitor, please read the Important safety instructions

VTach 5" Smart Wi-Ei 1080n Video Monitor allows you to stay close to your haby when you viecn 5' Smart Wri-11 Libeup video Monitor allows you to stay close to your baby white are on the move or away. This monitor is Wi-Fi enabled, using your home wireless ne to stream live video and audio through the 1080p baby unit and 5-inch colour screen parent unit. It allows you to maintain a constant connection to your baby.

You can also monitor from your smartphone or mobile tablet.

Vlech 5' Smart Wi-Fi 1080p Video Monitor use: MyVTech Bay Pro app to let you instantly see and hear what 'happening with your baby from anywhere in the world. The app can be downloaded from the App Store or the Google Play<sup>34'</sup> Store.

## IMPORTANT SAFETY INSTRUCTIONS

RM5756HD

RM5756HD-2

- Video Monitor

  - Description of the Color of the Rechargeable bath
  - Zhuhai Great Power Energy Co., Ltd.
  - o most we play in place if it is plaggied into a ceiling, under-the-shaber or ceiling when the ceiling and the ceiling. Under-the-shaber or ceiling when the ceiling and the ceiling and ceiling and the ceiling and the ceiling and the ceiling and ceiling.

    10. Unplug this product from the wall outlet before classing, and ceiling and ceiling and ceiling and ceiling and ceiling and cleaning.

    10. Do not cell the power adoption to replace them with other plags, as the course is therection states, which can need the ceiling and plags, as the ceiling as the ceiling and ceiling and ceiling and install the product afters the credit may be walled on or crispost.

CABLE MANAGEMENT

- - SAVE THESE INSTRUCTIONS
    - store the product at a temperature between 0°C and

## WHAT'S IN THE BOX

itor package contains the following items. Save your sales receipt and original







# After installing the mobile app, follow the instructions in the mobile app and parent unit to set up and pair your baby unit. In your mobile device:

We recommend that you use common webmail services, such as Google Gmail for registration of your user account. Check your email (and Spam folder), and activate your new camera account via the email link, then sign in to your account.



Download the free MyVTech Baby Pro mobile app and install it to a

- 1 Press MENU/SELECT when the parent unit is idle
- 2 Go to O > Connect Mobile Phone

DOWNLOAD APP FOR MOBILE ACCESS

 Scan the QR code in the parent unit to download the app into your mobile device if you have not installed the app yet. Follow the instructions in the mobile app to set up and pair your baby

### Install MyVTech Raby Pro mobile app

unit to the mobile ann

- Rrowse the App Store or the Google Play store
- 2. Search for the mobile app with the keyword "myvtech baby pro".

  3. Download and install the MyVTech Baby Pro mobile app to your mobile device.

回数回 双数数 回数数

# **P** Note

Make sure your mobile device meets the minimum requirement for the mobile app. Minimum requirement

### The mobile app is compatible with: Android™ 6.0 or later: and

· iOS 12 or late

- Tap [iii] to run the mobile app in your mobile device, and then create a user account.
- Follow the instructions in the mobile app to pair the camera. Tap .... then Add Camera in the mobile app to get started.





Allow you to see clearly in a dark ·Ö- Night Light Control Key Go to Night Light section to learn more

Camera lens

Infrared LEDs

Power it on or off.



- LED indicator

  Red is steady on when the baby unit is connecting to the parent until in direct mode. Green is steady on when the baby unit is connected in Wi-Fi router mode. Red flathes dowly during video streaming in circle timed lowly during video streaming in Mi-Fi router mode.

  Wi-Fi router mode.
- Speaker
- Temperature sensor
- Press and hold for three seconds to enter
  - Reset the baby unit to factory default Press and hold PAIR key until you hear a
  - beep sound.

    Release the PAIR key, and then press the PAIR key again five times until you hear another beep sound.
- The baby unit will sound another beep when the reset completes. Then, the baby unit will reboot. 12 Power jack
- 13 Wall mount slots

TALK / TO

MENU | SELECT

Press to enter the main menu.

While in a menu, press to che item, or save a setting.

Parent unit overview



<|∧|>|∨ Arrow keys

Press to navigate left, right, up and down within the main and sub-men. Flashes when the link to the baby unit is lost.

(2)—

⊕-

- LED light On when the parent unit is connected to AC power, and the battery is charging.
- Flashes when the parent unit battery is low and needs to be charged. VOL - | VOL +
- 3- level sound indicator light Green: low sound level is detected by the baby unit.
  - Press to zoom in/out.

    While in a sub-menu, press to view thelo menu
- Green and amber: moderate sound level is detected by the baby unit. Green, amber and red: high sound level is detected by the baby unit. 10 (b) Power | LCD ON/OFF
- 11 Antenna Press and hold to talk to the baby unit.
   While in a sub-menu, press to exit.
  - 12 Speaker
  - 12 Powerisch



Address: 9020 SW Washington Square Road - Ste 555 Tigard, OR 97223, United States Phones I (800) 595-9511 in the U.S. or I (800) 267-7377 in Canada

DISCLAIMER AND LIMITATION OF LIABILITY

TECHNICAL SPECIFICATIONS

Parent unit battery: s./V sudumAn, talawn Limium-ion battery

Actual operating range may vary according to enviror at the time of use.





Vision, cases about your privacy and peace of mined. That's why wo've put together a list of industry-recommended been practices to help keep your wireless connection private and your devices protect when online. We recommend you cantafully view and consider complying with the following stor. Frature your wireless connection is secure.

- Before installing a device, areasize your router's wireless signal is encrypted by selecting the "WPI FSK with AES" satting in your router's wireless security menu.

- Biocus in Australian (proport router's wireless security inserus. STA with Ad-Stating in your router's wireless security inserus. Change your wireless router's default wireless network name (SSID) to something Change default passwords to unique, strong passwords. A strong password: Is at least 10 characters long.

- Deminds acoustly patible from menuflicance as soon as they become available. This will ensure you always have the last earthing validate acousting containing the menuflicance of the service of the service acoustic patients of their extraors as washing, enable arounds copiants for those relatives.

  This factor is washing, enable arounds copiant for those acoustic patients are contained as the contraction of the service of t
- www.fcc.gov/consumers/guides/how-protect-yourself-online.

  2. U.S. Department of Homeland Security: Before You Connect a New Computer to the Internet
- U.S. Logariment of Homosanda Saccinity, Bettole You Connect a New Communic and Englishman Mississippin Services (TES 202)
   Fedderal Trade Commission: Using IP Cameras Safely Affect Pressure Consument Re-particles (7382 vislo-10--comment-safely, MISSISSIPPIN SERVICES)
   Will-Filliance: Discover Will-Fi Security
   Mississippin Services (Security Connection Security Connection Security


# CONNECT, CHARGE AND POWER ON THE BABY MONITOR


### Connect the baby monitor

For mobile access:

MvVTech Baby Pro mobile ac

- The rechargeable battery in the parent unit is built-in.
- Use only the power adapters supplied with this product.
  Make sure the parent unit and the baby unit are not conn
- Connect the power adapters in a vertical or floor mount position only. The adapter prongs are not designed to hold the weight of the parent unit and the bably unit, so do not connect them to any cunder-the-table, or cabinet outlets. Otherwise, the adapter may not properly connect to the outlets.









## Charge the parent unit battery before use

■ Notes Before using the baby monitor for the first time, charge the parent unit battery for 12 hours. When the parent unit battery is fully charged, the battery icon becomes solid [17].

The standby time varies depending on your actual use.



The battery icon indicates the battery status (see the following table

The screen displays III and III The battery has very little charge and may be used interruption (about 30 minutes). The battery icon becomes solid The battery is fully charged.



## PARENT UNIT ICONS

So Al

Menu Options Monitoring mode (\* For RM\$756HD-2 only) View baby units in Single mode.
 View baby units in Patrol mode.

View baby units in Split screen.

 Turn on or turn off night light.
 Select a night light color. Adjust night light brightness.
 Set a night light timer. and soothing sounds

 Select play all melodies, or play one of the five melodies and five soothing sounds. You can also set the timer to stop playing after 15, 30 or 60 minutes, or playing non-stop.

Alerts - Sound, motion and temperature Select the sound and motion sensitivity level.

Parent unit settings

**é**j Turn on/off sound and motion detection alerts.

 Select maximum and minimum temperature for alert range.
 Turn on/off temperature alert. Turn on/off Auto Wake Up
function

 Adjust parent unit screen brightness.
 Adjust Low Battery Alert Tone. Adjust No Link Alert Tone.
 Turn on/off Dim mode.

Baby unit settings Turn on/off Night Vision.
Turn on/off baby unit Status LED.
Adjust baby unit speaker volume.

Options 0 - Configure Wi-Fi

 Change Wi-Fi Network
 Selection Connection N Connection Status
 Connect mobile phone

Reset Settings to factory default
 Software Update.

Status icons 101 201

Wi-Fi Router mode Parent unit, baby unit 1 and baby unit 2 ("For RM5756HD-2 only) are connected to home Wi-Fi network.  $\nabla$ 

Baby unit 1 and 2 are being viewed Patrol mode ("For RM5756HD-2 only). Baby unit 1 and 2 are being viewed in Split mode ("For RM5756HD-2 only). Night vision is turned on

Motion detection alert is turned on Sound detection alert is turned on Melodies and soothing sounds are playing.

Battery indicator.

Night light is turned on. Auto night light brightness is activated Temperature alert is turned on.

70°F °F Temperature is lower than 68°F. # Adjust night light brightness Temperature is within 68°F and 75°F

Temperature is higher than 75°F.

# AUTO SOFTWARE AND FIRMWARE UPDATE

To ensure that your baby monitor is always at its best performance, the parent unit will prompt you to update its software and the baby unit firmware when there are new vers available.

 Follow the instructions on the parent unit screen to update your baby monitor, the updates, the parent unit and baby unit will be updated automatically when unit is powered off, and then powered on again. To check if your device is running on the latest software or to update your device software, go t

> Software Update

# Connect your baby monitor to Wi-Fi

You must connect your video monitor to your secured home Wi-Fi network in order to receive the latest software and firmware updates. To set it up, go to: > Configure Wi-Fi

NIGHT LIGHT

You can control the night light remotely on the parent unit or directly on the baby unit. On the parent unit: On the baby unit:

menu, then press MENU or 🗸 to enter. 3. Press ≺or > to choose below options:

Turn on/off night light Ohange night light color

- O- Night Light Control Key Single Tap: Turn on/off





# BASIC OPERATION

After powering up your baby monitor, the parent unit streams live video in direct mode. We recommend you follow the instructions on-screen to set up home Wi-F network with your monitor for functionality enhancements and mobile access. See Auto software and firmware update and Download app for mobile access in this Quick Start Guide.

## Hee the menu

Press MENU on the parent unit to enter the main menu, choose a menu item, or save a Press MENU on the parent unit to enter the main menu, choose a menu item, or save a setting. You can use the parent unit menu for advanced settings or operations, such as to play or stop the baby unit fullaby, or adjust the baby unit sound sensitivity.

- Press < | A | > | V to scroll through the
- Press SELECT to select an item.
- Press TALK to return to the live video Press 🗓 to go to the **Help & info** page.

# Press VOL - | VOL + to adjust the parent unit



Press (1) to zoom in or out in a fixed zoom sequence. indicates the image is magnified 3 times.



### Talk to your baby via the baby unit

### Press and hold the TALK key.

- 2. When the icon displays on Your voice is transmitted to the baby unit.
- Turn on/off baby unit's status LED





## Turn on/off the parent unit screen

You can turn on or turn off the parent unit screen without powering off the unit. You will still hear sounds from the baby unit. Press () LCD ON/OFF on the parent unit

to turn off the screen. Press any key on the parent unit to turn



You can reset the parent unit by pressing the RESET key at the back of the unit. Insert a pin into the RESET hole on the back of the parent unit, and then gently press the butto incide.



(CS CRICEY

1


⊣()

## TEST THE SOUND LEVEL AND POSITION THE BABY MONITOR

### Testing the sound level of the baby monitor

### **₽** Note

(CAUTION



### Positioning the baby monitor

(1) CAUTION

Keep the baby unit out of the reach of your baby. Never place or mount the baby unit inside the born playnen.

L. Place the baby unit more than 3 feet away 2. Adjust the angle of the baby unit to aim from your baby.





# 3. To avoid causing high-pitched screeching noise from your baby monitor

## TEST THE LOCATION FOR THE BABY UNIT

If you plan to install your baby unit in a designated location, and use your home Wi-Fi network to connect your video mentior, you need to test which of your selected monitoring seas within the which of your selected monitoring areas within the when yoursed only your parent unit, by you can use your parent unit Wi-Fi signal strength indicator to saist in checking. Once you have identified the suitable location, you can install your baby unit.



## MOUNT THE BABY UNIT (OPTIONAL)

Check for reception strength and camera angle of the baby unit bet drilling the holes.

The types of screws and plugs vo

Align the wall mount bracket and screws with the holes in the wall as shown. Tighten the screw in the middle hole first, so that the wall mount bracket position is fixed. You can fighten the other screw in the top hole.

Place the baby unit on the wall mount bracks and then slide it forward until it locks into pla Connect the power adapter to the baby unit

Place the wall mount bracket on a wall and then use a pencil to mark two holes in parallel. Remove the wall mount bracket and drill two holes in the wall (5.5mm drill bit).



- 2. If you drill the holes into a stud, go
- If you drill the holes into an object other than a stud, insert the wall plugs into the holes. Tap gently on the ends with a hammer until the wall plugs are flush with the wall.

b. Place the baby unit on the wall mount bracket, and then slide it forward until if locks into place. Align the holes on the wall mount bracket with the screws on the wall, and slide the wall mount bracket down until it locks into place.







# For RM5756HD-2 ONLY

## Monitorina Modes

When more than one baby unit is paired to the parent unit, you can choose to view different baby units in three monitoring modes. Learn more about each below:



Single Mode 
The screen displays images only from the selected baby unit in full screen.



Split Mode The screen displays images from all paired baby units at the same time in split view. The screen displays a single cam view that transitions to a different baby unit every 10 seconds.

## NEED HELP?

Oriven by system updates, the software, online help topics, and online FAQs will be

to your smartnhone or mobile rieuine to access our online bein use your smarpnone or mobile device to access our online help.

for in https://help.vicehphones.com/HBJ756HD-2; OR Scan the GR code on the https://help.vicehphones.com/HBJ756HD-2; OR Scan the GR code on the right. Launch the camera app or GR code scannier app on your smartphone or table. I held the device's camera up to the GR code and frame it. Tap the nonliferant in linger the redirection of the oritine head.

If the QR code is not clearly displayed, adjust your camera's focus by moving your device closer or further away until it is clear.

If you would like to contact us, visit https://help.vtechphones.com/cs or scan the GR code You can also call our Customer Support at 1-844-848-8324 (1-844-84-VTECH) [in US] or 1-888-211-2005 [in Canada]



# How the system works

The parent unit and the baby unit of your video monitor connect to each others in Direct mode by default, which allows you to stream live video right out of the box. **Direct mode** connection lets you stream live video from the parent unit only.



## Wi-Fi Router mode

To stream live video with better connection, you can also set up you monitor in **Router mode** connection

monitor in Router mode connection.

Router mode uses your home Wi-Fi
network to connect the video monitor.

It supports streaming live video through
the parent unit and MyVTech Baby Pro

Pro mobile app to stream remotely. W the mobile app, your Wi-Fi router (not included) serves as a communicating channel between your baby unit and mobile device, allowing you to monits and control your baby unit wherever v

are. For details, see Download app for mobile access section in this quick start quide.

With **Auto mode** connection, the parent unit will automatically select the most reliable connection mode (**Direct or Wi-Fi**) when connecting to the baby unit(s). Mobile app accent not be interrupted in **Auto mode**.

When both parent unit and app are viewing the camera simultaneously, the video quality will be optimised to deliver the best possible viewing result.

## GENERAL PRODUCT CARE

To keep this product working well and looking good, follow these guidelines

- To keep this product working well and boking good, follow these guideline:

  A work placing in read healing applicance and devices that generate electrical noise (for example, motors or fluorescent lamps).

  O NOVI (exposit to device suringly) or micrature.

  A world dropping the product or treating it roughly,
  Colass with a soft damp dom.

  I A DO NOVI (sure south groups or groups) or the south groups or g

## STORAGE

# 

Below are the questions most frequently asked about the video monitor.

Can I turn the parent unit of parent questions and display areas of the parent unit to turn off the screen. The parent unit display areas and some time to turn off the screen in the parent unit display areas unit display and be made and unitarity and the being inactive for some time. In both unitarity and the parent unit to turn off the screen is the parent unit display and the parent unit display areas to the parent unit display and the parent unit display areas to the parent unit display and the parent unit display areas to the parent display are the parent display areas to th unit? Why is the baby Try the following (in the order listed) for a common cure

2. Wait a few minutes before connecting power back to the baby unit.

3. Reboot the parent unit. unit not responding normally?

The baby unit has a light sensor that measures ambient light. When the ambient light is dim, such as during night time or in a dark room, the baby unit activates its infrared LEDs, and displays the camera images in black and white night vision.

Why does my baby unit The baby unit may have lost connection to the Wi-Fi router. Check you show offline? Why is the network and router settings.

now and then? installing your baby unit as far away from these electronic devices as possible. The parent unit speaker volume may be too low. Press VOL + on the parent unit You may have set a low sound sensitivity level. Set the sound sensitivity to a higher level. For details, go to www.vtechphones.com for online help topics.

## THE RBRC SEAL

## FCC AND IC REGULATIONS

FCC Part 15

This Class B digital apparatus CAN ICES, 3 (BUNAR), 9(8)

# CALIFORNIA ENERGY COMMISSION BATTERY

# CHARGING TESTING MODE

Industry Canada

## FOR CFTL COMPLIANCE ONLY

médical.

N'utilisez pas cet appareil près de l'eau ni de toute autre source d'humidré, par essemple, près d'une balgnobre, curve à lessive, de l'eau ni partie de l'eau n'est d'une de l'essive.

risque d'endommager sécurité en péril.

ine prise au plafond, sous une table ou dans un meuble. four les appareis raccordés, la prise de courant (de l'adaptat acteur doit être instalée près de l'équipement et doit être siement accessible. Ibranchez ce produit de la prixe de courant avant de océder au nettoyage. N'utiliser pas de nettoyants en aérosols

Ne laissez aucun objet reposer ni appuyer sur le cordon d'alimentation. N'installez pus cet appareil dans un enclorit où l'on risque d'écraser le cordon d'alimentation ou de le pietiner. Ne faites fonctionner cet appareil qu'avec le type d'alimentatio indiqué sur l'étiquette. Si vous ne connaissez pais le type d'alimentation que vous possèdez à votre domicile, consultez

le placez pas cet appareil sur un chariot, meuble, trépied, apport de montage ni table chancelants. support de montage et table chancelaris. Les trous et ouvertures du boîtier, situés à l'arrière de l'appareil ou pous cetai-ci, servent à airer l'appareil. Pour l'empêcher de surchauffer, ne bloquez sous aucun préféde ces ouvertures et n'empéchez pas l'aération adéquate de l'appareil en le plaçant

. You can maximize your baby unit viewing angles by filting the wall mount bracket. Hold the baby unit, and then rotate the knob in an anticlockwise direction. This will loosen the joint of the wall mount bracket Titl your baby unit up or down to adjust to your preferred angle. Then, rotate the knob in a clockwise direction to righten the joint and secure the angle.

or territorios jumais d'objets à travers les ouvertures de cet spapareil, car la poursaient entrer en contact avec des points de infrasion dangerisux ou causer des courts-crouts qui peuvent réformèrer en incerndies, ou en risques d'éjectrocution. Ne

2. Il directiva piece de confidentiales en la maior de parte de confidentiales en la maior un maior de parte de confidentiales en la maior de la maior del maior de la maior de la maior de la maior de la maior del maior de la maior del maior del

une en garos

Unities et entreposez le produit à une température entre 0° C

(32° F) et 40° C (304° F).

(32 F) et 40 C (30 6 F).

Risque de brûser, risque d'incendie, risque d'explosion associé à une mauveste manipulation de la battete.

N'exposer pas cet appareit à des froids ou des chaleurs extrétines, airei qu'à la lurrière directe du solieil. Ne l'installier pas près d'une source de chardinge. pris d'une source un de la strangulation -Les enfants se sont ETRANCLES dans des condons.

Levi V.V. Nerthere par citire éficaréte.

Je jimas place le moniteur à l'etietur du berceau ou du parc de biblis. Ne jermis courie le monteur ou l'unété (li) portière de biblis. Ne jermis courie le monteur ou l'unété (li) portière de biblis. Ne jermis courie le monte de l'active de l'active produit des l'actives produit des l'actives des l'actives des l'actives des l'actives des l'actives de l'actives au serif à réclut i highibities qu'alité les l'actives de l'actives

Its ne doivent PAS placer le téléphone sans fil directement sur le stimulateur cardiaque, tel que dans une poche de chemise, loronus ratificir et en marche. l'orique ceux-ci est en marche.
L'étude effectuée par l'organisme WIS n'a pas identifié de risque pour les détenteurs de sinhulateurs cardiaques causés par les gens qui utilisent dispositifs sans fil à proximité de ceux-ci.

## LIMITED WARRANTY

The limited warranty period?
The limited warranty period?
The limited warranty period for the Product extends for (1) YEAR from the date of purchase (90 days on produs purchased as Refurbished). This limited warranty also

How do you get warranty service? To obtain warranty service in the U website at www.vtechphones.com In Canada, go to www.vtechcanac 1 (800) 267-7377.

