

FCC REPORT

(Bluetooth)

Applicant: Swagtek

Address of Applicant: 10205 NW 19th St. Suite 101, Miami, FL, 33172

Equipment Under Test (EUT)

Product Name: 7 inch Wi-Fi Tablet

Model No.: T7W, STREAM 7W, UT7W

Trade mark: LOGIC, iSWAG, UNONU

FCC ID: O55702720

Applicable standards: FCC CFR Title 47 Part 15 Subpart C Section 15.247

Date of sample receipt: 24 Aug., 2020

Date of Test: 24 Aug., to 24 Sep., 2020

Date of report issued: 25 Sep., 2020

Test Result: PASS *

* In the configuration tested, the EUT complied with the standards specified above.

Authorized Signature:



Bruce Zhang
Laboratory Manager

This report details the results of the testing carried out on one sample. The results contained in this test report do not relate to other samples of the same product and does not permit the use of the CCIS product certification mark. The manufacturer should ensure that all products in series production are in conformity with the product sample detailed in this report.

This report may only be reproduced and distributed in full. If the product in this report is used in any configuration other than that detailed in the report, the manufacturer must ensure the new system complies with all relevant standards.

This document cannot be reproduced except in full, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law. Unless otherwise stated the results shown in this test report refer only to the sample(s) tested and such sample(s) are retained for 90 days only.

2 Version

Version No.	Date	Description
00	25 Sep., 2020	Original

Tested by:**Test Engineer****Date:**

25 Sep., 2020

Reviewed by:**Project Engineer****Date:**

25 Sep., 2020

3 Contents

	Page
1 COVER PAGE.....	1
2 VERSION.....	2
3 CONTENTS.....	3
4 TEST SUMMARY.....	4
5 GENERAL INFORMATION.....	5
5.1 CLIENT INFORMATION.....	5
5.2 GENERAL DESCRIPTION OF E.U.T.....	5
5.3 TEST ENVIRONMENT AND MODE	6
5.4 DESCRIPTION OF SUPPORT UNITS	6
5.5 MEASUREMENT UNCERTAINTY.....	6
5.6 ADDITIONS TO, DEVIATIONS, OR EXCLUSIONS FROM THE METHOD	6
5.7 LABORATORY FACILITY.....	6
5.8 LABORATORY LOCATION.....	6
5.9 TEST INSTRUMENTS LIST	7
6 TEST RESULTS AND MEASUREMENT DATA.....	8
6.1 ANTENNA REQUIREMENT	8
6.2 CONDUCTED EMISSIONS	9
6.3 CONDUCTED OUTPUT POWER	12
6.4 20DB OCCUPY BANDWIDTH.....	13
6.5 CARRIER FREQUENCIES SEPARATION	14
6.6 HOPPING CHANNEL NUMBER	15
6.7 DWELL TIME	16
6.8 PSEUDORANDOM FREQUENCY HOPPING SEQUENCE.....	17
6.9 BAND EDGE	18
6.9.1 Conducted Emission Method	18
6.9.2 Radiated Emission Method	19
6.10 SPURIOUS EMISSION.....	32
6.10.1 Conducted Emission Method.....	32
6.10.2 Radiated Emission Method.....	33
7 TEST SETUP PHOTO	38
8 EUT CONSTRUCTIONAL DETAILS	39
APPENDIX A – BT	40

4 Test Summary

Test Items	Section in CFR 47	Result
Antenna Requirement	15.203 & 15.247 (b)	Pass
AC Power Line Conducted Emission	15.207	Pass
Conducted Peak Output Power	15.247 (b)(1)	Pass
20dB Occupied Bandwidth	15.247 (a)(1)	Pass
Carrier Frequencies Separation	15.247 (a)(1)	Pass
Hopping Channel Number	15.247 (a)(1)	Pass
Dwell Time	15.247 (a)(1)	Pass
Spurious Emission	15.205 & 15.209	Pass
Band Edge	15.247(d)	Pass
Remark:		
1. Pass: The EUT complies with the essential requirements in the standard.		
2. N/A: Not Applicable.		
3. The cable insertion loss used by "RF Output Power" and other conduction measurement items is 0.5dB (provided by the customer).		
Test Method:	ANSI C63.10-2013 KDB 558074 D01 15.247 Meas Guidance v05r02	

5 General Information

5.1 Client Information

Applicant:	Swagtek
Address:	10205 NW 19th St. Suite 101, Miami, FL, 33172
Manufacturer/ Factory:	Swagtek
Address:	10205 NW 19th St. Suite 101, Miami, FL, 33172

5.2 General Description of E.U.T.

Product Name:	7 inch Wi-Fi Tablet
Model No.:	T7W, STREAM 7W, UT7W
Operation Frequency:	2402MHz~2480MHz
Transfer rate:	1/2/3 Mbits/s
Number of channel:	79
Modulation type:	GFSK, $\pi/4$ -DQPSK, 8DPSK
Modulation technology:	FHSS
Antenna Type:	Internal Antenna
Antenna gain:	-1.5 dBi
Power supply:	Rechargeable Li-ion Battery DC3.8V, 2500mAh
AC adapter:	Model: MKC-0501500SU Input: AC100-220V, 50/60Hz, 0.4A Output: DC 5V, 1.5A
Remark:	The Model No.: T7W, STREAM 7W, UT7W were identical inside, the electrical circuit design, layout, components used and internal wiring, The only difference between them is as follows: The trademark LOGIC correspond model T7W; The trademark iSWAG correspond model STREAM 7W; The trademark UNONU correspond model UT7W.
Test Sample Condition:	The test samples were provided in good working order with no visible defects.

Operation Frequency each of channel for GFSK, $\pi/4$ -DQPSK, 8DPSK							
Channel	Frequency	Channel	Frequency	Channel	Frequency	Channel	Frequency
0	2402MHz	20	2422MHz	40	2442MHz	60	2462MHz
1	2403MHz	21	2423MHz	41	2443MHz	61	2463MHz
2	2404MHz	22	2424MHz	42	2444MHz	62	2464MHz
3	2405MHz	23	2425MHz	43	2445MHz	63	2465MHz
4	2406MHz	24	2426MHz	44	2446MHz	64	2466MHz
5	2407MHz	25	2427MHz	45	2447MHz	65	2467MHz
...
15	2417MHz	35	2437MHz	55	2457MHz	75	2477MHz
16	2418MHz	36	2438MHz	56	2458MHz	76	2478MHz
17	2419MHz	37	2439MHz	57	2459MHz	77	2479MHz
18	2420MHz	38	2440MHz	58	2460MHz	78	2480MHz
19	2421MHz	39	2441MHz	59	2461MHz		

Remark: Channel 0, 39 &78 selected for GFSK, $\pi/4$ -DQPSK and 8DPSK.

5.3 Test environment and mode

Operating Environment:	
Temperature:	24.0 °C
Humidity:	54 % RH
Atmospheric Pressure:	1010 mbar
Test Modes:	
Non-hopping mode:	Keep the EUT in continuous transmitting mode with worst case data rate.
Hopping mode:	Keep the EUT in hopping mode.
Remark	GFSK (1 Mbps) is the worst case mode.
Radiated Emission: The sample was placed 0.8m (below 1GHz)/1.5m (above 1GHz) above the ground plane of 3m chamber*. Measurements in both horizontal and vertical polarities were performed. During the test, each emission was maximized by: having the EUT continuously working, investigated all operating modes, rotated about all 3 axis (X, Y & Z) and considered typical configuration to obtain worst position, manipulating interconnecting cables, rotating the turntable, varying antenna height from 1m to 4m in both horizontal and vertical polarizations. The emissions worst-case are shown in Test Results of the following pages.	

5.4 Description of Support Units

The EUT has been tested as an independent unit.

5.5 Measurement Uncertainty

Parameters	Expanded Uncertainty
Conducted Emission (9kHz ~ 30MHz)	±1.60 dB (k=2)
Radiated Emission (9kHz ~ 30MHz)	±3.12 dB (k=2)
Radiated Emission (30MHz ~ 1000MHz)	±4.32 dB (k=2)
Radiated Emission (1GHz ~ 18GHz)	±5.16 dB (k=2)
Radiated Emission (18GHz ~ 40GHz)	±3.20 dB (k=2)

5.6 Additions to, deviations, or exclusions from the method

No

5.7 Laboratory Facility

The test facility is recognized, certified, or accredited by the following organizations:

- **FCC - Designation No.: CN1211**

Shenzhen Zhongjian Nanfang Testing Co., Ltd. has been accredited as a testing laboratory by FCC(Federal Communications Commission). The test firm Registration No. is 727551.

- **ISED – CAB identifier.: CN0021**

The 3m Semi-anechoic chamber of Shenzhen Zhongjian Nanfang Testing Co., Ltd. has been Registered by Certification and Engineering Bureau of Industry Canada for radio equipment testing with Registration No.: 10106A-1.

- **A2LA - Registration No.: 4346.01**

This laboratory is accredited in accordance with the recognized International Standard ISO/IEC 17025:2005 General requirements for the competence of testing and calibration laboratories. The test scope can be found as below link: <https://portal.a2la.org/scopepdf/4346-01.pdf>

5.8 Laboratory Location

Shenzhen Zhongjian Nanfang Testing Co., Ltd.
 Address: No.110~116, Building B, Jinyuan Business Building, Xixiang Road,
 Bao'an District, Shenzhen, Guangdong, China
 Tel: +86-755-23118282, Fax: +86-755-23116366
 Email: info@ccis-cb.com, Website: <http://www.ccis-cb.com>

5.9 Test Instruments list

Radiated Emission:					
Test Equipment	Manufacturer	Model No.	Serial No.	Cal. Date (mm-dd-yy)	Cal. Due date (mm-dd-yy)
3m SAC	SAEMC	9m*6m*6m	966	07-21-2020	07-20-2021
Loop Antenna	SCHWARZBECK	FMZB1519B	044	03-07-2020	03-06-2021
BiConiLog Antenna	SCHWARZBECK	VULB9163	497	03-07-2020	03-06-2021
Horn Antenna	SCHWARZBECK	BBHA9120D	916	03-07-2020	03-06-2021
Horn Antenna	SCHWARZBECK	BBHA9120D	1805	06-20-2020	06-19-2021
Horn Antenna	SCHWARZBECK	BBHA 9170	BBHA9170582	11-18-2019	11-17-2020
EMI Test Software	AUDIX	E3	Version: 6.110919b		
Pre-amplifier	HP	8447D	2944A09358	03-07-2020	03-06-2021
Pre-amplifier	CD	PAP-1G18	11804	03-07-2020	03-06-2021
Spectrum analyzer	Rohde & Schwarz	FSP30	101454	03-05-2020	03-04-2021
Spectrum analyzer	Rohde & Schwarz	FSP40	100363	11-18-2019	11-17-2020
EMI Test Receiver	Rohde & Schwarz	ESRP7	101070	03-05-2020	03-04-2021
Cable	ZDECL	Z108-NJ-NJ-81	1608458	03-07-2020	03-06-2021
Cable	MICRO-COAX	MFR64639	K10742-5	03-07-2020	03-06-2021
Cable	SUHNER	SUCOFLEX100	58193/4PE	03-07-2020	03-06-2021
RF Switch Unit	MWRFTEST	MW200	N/A	N/A	N/A
Test Software	MWRFTEST	MTS8200	Version: 2.0.0.0		

Conducted Emission:					
Test Equipment	Manufacturer	Model No.	Serial No.	Cal. Date (mm-dd-yy)	Cal. Due date (mm-dd-yy)
EMI Test Receiver	Rohde & Schwarz	ESCI	101189	03-05-2020	03-04-2021
Pulse Limiter	SCHWARZBECK	OSRAM 2306	9731	03-05-2020	03-04-2021
LISN	CHASE	MN2050D	1447	03-05-2020	03-04-2021
LISN	Rohde & Schwarz	ESH3-Z5	8438621/010	06-18-2020	07-17-2021
Cable	HP	10503A	N/A	03-05-2020	03-04-2021
EMI Test Software	AUDIX	E3	Version: 6.110919b		

6 Test results and measurement data

6.1 Antenna Requirement


Standard requirement:	FCC Part 15 C Section 15.203 & 247(b)
15.203 requirement: An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.	
15.247(b) (4) requirement: (4) The conducted output power limit specified in paragraph (b) of this section is based on the use of antennas with directional gains that do not exceed 6 dBi. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b)(1), (b)(2), and (b)(3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.	
E.U.T Antenna:	The Bluetooth antenna is an Internal antenna which permanently attached, and the best case gain of the antenna is -1.5 dBi.

6.2 Conducted Emissions

Test Requirement:	FCC Part 15 C Section 15.207		
Test Frequency Range:	150 kHz to 30 MHz		
Class / Severity:	Class B		
Receiver setup:	RBW=9 kHz, VBW=30 kHz, Sweep time=auto		
Limit:	Frequency range (MHz)		Limit (dBuV)
			Quasi-peak Average
	0.15-0.5	66 to 56*	56 to 46*
	0.5-5	56	46
	5-30	60	50
* Decreases with the logarithm of the frequency.			
Test setup:	<p>Remark: E.U.T: Equipment Under Test LISN: Line Impedance Stabilization Network Test table height=0.8m</p>		
Test procedure:	<ol style="list-style-type: none"> The E.U.T and simulators are connected to the main power through a line impedance stabilization network (L.I.S.N.). This provides a 50ohm/50uH coupling impedance for the measuring equipment. The peripheral devices are also connected to the main power through a LISN that provides a 50ohm/50uH coupling impedance with 50ohm termination. (Please refer to the block diagram of the test setup and photographs). Both sides of A.C. line are checked for maximum conducted interference. In order to find the maximum emission, the relative positions of equipment and all of the interface cables must be changed according to ANSI C63.10(latest version) on conducted measurement. 		
Test Instruments:	Refer to section 5.9 for details		
Test mode:	Hopping mode		
Test results:	Pass		

Measurement Data:

Product name:	7 inch Wi-Fi Tablet	Product model:	T7W
Test by:	Carey	Test mode:	BT Tx mode
Test frequency:	150 kHz ~ 30 MHz	Phase:	Line
Test voltage:	AC 120 V/60 Hz	Environment:	Temp: 22.5°C Huni: 55%




Freq MHz	Read Level dBuV	LISN Factor dB	Cable Loss dB	Aux Factor dB	Limit Line dBuV	Over Line dB	Over Limit Remark
	Freq MHz	Read Level dBuV	LISN Factor dB	Cable Loss dB			
1	0.162	45.59	-0.58	10.77	-0.08	55.70	65.34 -9.64 QP
2	0.166	25.99	-0.58	10.77	-0.09	36.09	55.16 -19.07 Average
3	0.186	40.70	-0.59	10.76	-0.13	50.74	64.20 -13.46 QP
4	0.198	22.59	-0.59	10.76	-0.16	32.60	53.71 -21.11 Average
5	0.222	39.61	-0.58	10.76	-0.19	49.60	62.74 -13.14 QP
6	0.226	22.52	-0.58	10.75	-0.19	32.50	52.61 -20.11 Average
7	0.286	37.56	-0.55	10.74	-0.25	47.50	60.63 -13.13 QP
8	0.527	24.34	-0.45	10.76	-0.36	34.29	46.00 -11.71 Average
9	0.541	35.17	-0.45	10.76	-0.36	45.12	56.00 -10.88 QP
10	0.582	23.39	-0.48	10.76	-0.37	33.30	46.00 -12.70 Average
11	11.257	31.74	-0.72	10.93	2.41	44.36	60.00 -15.64 QP
12	12.318	15.27	-0.71	10.92	2.78	28.26	50.00 -21.74 Average

Notes:

1. An initial pre-scan was performed on the line and neutral lines with peak detector.
2. Quasi-Peak and Average measurement were performed at the frequencies with maximized peak emission.
3. Final Level = Receiver Read level + LISN Factor + Aux Factor + Cable Loss.

Product name:	7 inch Wi-Fi Tablet	Product model:	T7W
Test by:	Carey	Test mode:	BT Tx mode
Test frequency:	150 kHz ~ 30 MHz	Phase:	Neutral
Test voltage:	AC 120 V/60 Hz	Environment:	Temp: 22.5°C Huni: 55%




Freq MHz	Read Level dBuV	LISN Factor	Cable Loss dB	Aux Factor	Level dBuV	Limit Line dBuV	Over Limit dB	Over Limit Remark
1	0.162	45.12	-0.68	10.77	0.01	55.22	65.34	-10.12 QP
2	0.170	44.17	-0.68	10.77	0.01	54.27	64.94	-10.67 QP
3	0.170	25.14	-0.68	10.77	0.01	35.24	54.94	-19.70 Average
4	0.194	40.92	-0.67	10.76	0.00	51.01	63.84	-12.83 QP
5	0.194	24.16	-0.67	10.76	0.00	34.25	53.84	-19.59 Average
6	0.219	38.81	-0.67	10.76	0.00	48.90	62.88	-13.98 QP
7	0.219	20.40	-0.67	10.76	0.00	30.49	52.88	-22.39 Average
8	0.242	37.49	-0.67	10.75	0.00	47.57	62.04	-14.47 QP
9	0.527	19.76	-0.65	10.76	0.03	29.90	46.00	-16.10 Average
10	0.549	33.05	-0.65	10.76	0.03	43.19	56.00	-12.81 QP
11	0.582	18.03	-0.65	10.76	0.03	28.17	46.00	-17.83 Average
12	13.479	14.67	-0.80	10.91	2.64	27.42	50.00	-22.58 Average

Notes:


1. An initial pre-scan was performed on the line and neutral lines with peak detector.
2. Quasi-Peak and Average measurement were performed at the frequencies with maximized peak emission.
3. Final Level =Receiver Read level + LISN Factor + Aux Factor + Cable Loss.

6.3 Conducted Output Power

Test Requirement:	FCC Part 15 C Section 15.247 (b)(1)
Receiver setup:	RBW=1MHz, VBW=3MHz, Detector=Peak (If 20dB BW ≤1 MHz) RBW=2MHz, VBW=6MHz, Detector=Peak (If 20dB BW > 1 MHz and < 3MHz)
Limit:	For frequency hopping systems operating in the 2400-2483.5 MHz band employing at least 75 non-overlapping hopping channels: 1 watt. For all other frequency hopping systems in the 2400-2483.5 MHz band: 0.125 watts.
Test setup:	
Test Instruments:	Refer to section 5.9 for details
Test mode:	Non-hopping mode
Test results:	Pass


Measurement Data: Refer to Appendix A - BT

6.4 20dB Occupy Bandwidth

Test Requirement:	FCC Part 15 C Section 15.247 (a)(1)
Receiver setup:	DH1: RBW=15 kHz, VBW=47 kHz, detector=Peak 2DH1&3DH: RBW=20 kHz, VBW=62 kHz, detector=Peak
Limit:	N/A
Test setup:	
Test Instruments:	Refer to section 5.9 for details
Test mode:	Non-hopping mode
Test results:	Pass


Measurement Data: Refer to Appendix A - BT

6.5 Carrier Frequencies Separation

Test Requirement:	FCC Part 15 C Section 15.247 (a)(1)
Receiver setup:	RBW=300 kHz, VBW=1 MHz, detector=Peak
Limit:	a) 0.025MHz or the 20dB bandwidth (whichever is greater) b) 0.025MHz or two-thirds of the 20dB bandwidth (whichever is greater)
Test setup:	
Test Instruments:	Refer to section 5.9 for details
Test mode:	Hopping mode
Test results:	Pass


Measurement Data: Refer to Appendix A - BT

6.6 Hopping Channel Number

Test Requirement:	FCC Part 15 C Section 15.247 (a)(1)
Receiver setup:	RBW=100 kHz, VBW=300 kHz, Center Frequency=2441MHz, Span= 100MHz, Detector=Peak
Limit:	15 channels
Test setup:	
Test Instruments:	Refer to section 5.9 for details
Test mode:	Hopping mode
Test results:	Pass

Measurement Data: Refer to Appendix A - BT

6.7 Dwell Time

Test Requirement:	FCC Part 15 C Section 15.247 (a)(1)
Receiver setup:	RBW=1 MHz, VBW=1 MHz, Span=0 Hz, Detector=Peak
Limit:	0.4 Second
Test setup:	
Test Instruments:	Refer to section 5.9 for details
Test mode:	Hopping mode
Test results:	Pass

Measurement Data: Refer to Appendix A - BT

6.8 Pseudorandom Frequency Hopping Sequence

Test Requirement:

FCC Part 15 C Section 15.247 (a)(1) requirement:


Frequency hopping systems shall have hopping channel carrier frequencies separated by a minimum of 25 kHz or the 20 dB bandwidth of the hopping channel, whichever is greater.

Alternatively. Frequency hopping systems operating in the 2400-2483.5 MHz band may have hopping channel carrier frequencies that are separated by 25 kHz or two-thirds of the 20 dB bandwidth of the hopping channel, whichever is greater, provided the systems operate with an output power no greater than 125 mW. The system shall hop to channel frequencies that are selected at the system hopping rate from a Pseudorandom ordered list of hopping frequencies. Each frequency must be used equally on the average by each transmitter. The system receivers shall have input bandwidths that match the hopping channel bandwidths of their corresponding transmitters and shall shift frequencies in synchronization with the transmitted signals.

EUT Pseudorandom Frequency Hopping Sequence


The pseudorandom sequence may be generated in a nine-stage shift register whose 5th and 9th stage outputs are added in a modulo-two addition stage. And the result is fed back to the input of the first stage. The sequence begins with the first ONE of 9 consecutive ONEs; i.e. the shift register is initialized with nine ones.

- Number of shift register stages: 9
- Length of pseudo-random sequence: $2^9 - 1 = 511$ bits
- Longest sequence of zeros: 8 (non-inverted signal)



Linear Feedback Shift Register for Generation of the PRBS sequence

An example of Pseudorandom Frequency Hopping Sequence as follow:




Each frequency used equally on the average by each transmitter.

The system receivers have input bandwidths that match the hopping channel bandwidths of their corresponding transmitters and shift frequencies in synchronization with the transmitted signals.

6.9 Band Edge

6.9.1 Conducted Emission Method

Test Requirement:	FCC Part 15 C Section 15.247 (d)
Receiver setup:	RBW=100 kHz, VBW=300 kHz, Detector=Peak
Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement.
Test setup:	 <p>The diagram illustrates the test setup for conducted emission testing. A Spectrum Analyzer is connected to the E.U.T (Equipment Under Test) via a coaxial cable. The E.U.T is placed on a Non-Conducted Table, which sits above a Ground Reference Plane.</p>
Test Instruments:	Refer to section 5.9 for details
Test mode:	Non-hopping mode and hopping mode
Test results:	Pass


Measurement Data: Refer to Appendix A - BT

6.9.2 Radiated Emission Method

Test Requirement:	FCC Part 15 C Section 15.209 and 15.205								
Test Frequency Range:	2310 MHz to 2390 MHz and 2483.5 MHz to 2500 MHz								
Test Distance:	3m								
Receiver setup:	Frequency	Detector	RBW	VBW	Remark				
	Above 1GHz	Peak	1MHz	3MHz	Peak Value				
		RMS	1MHz	3MHz	Average Value				
Limit:	Frequency	Limit (dBuV/m @3m)		Remark					
	Above 1GHz	54.00		Average Value					
		74.00		Peak Value					
Test setup:									
Test Procedure:	<ol style="list-style-type: none"> The EUT was placed on the top of a rotating table 1.5 meters above the ground at a 3 meter camber. The table was rotated 360 degrees to determine the position of the highest radiation. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rota table was turned from 0 degrees to 360 degrees to find the maximum reading. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet. 								
Test Instruments:	Refer to section 5.9 for details								
Test mode:	Non-hopping mode								
Test results:	Passed								

GFSK Mode:

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	DH1 Tx mode
Test Channel:	Lowest channel	Polarization:	Vertical
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read	Antenna	Cable	Aux	Preamp	Limit Line dB	Over Limit dB	Remark
	Level	Factor	Loss	Factor	Factor			
	dBuV	dB/m	dB	dB	dB	dBuV/m	dBuV/m	
1	2390.000	20.88	27.03	4.28	1.68	0.00	53.87	74.00 -20.13 Peak
2	2390.000	10.86	27.03	4.28	1.68	0.00	43.85	54.00 -10.15 Average

Remark:

- Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	DH1 Tx mode
Test Channel:	Lowest channel	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read	Antenna	Cable	Aux	Preamp	Limit Line dBuV/m	Over Line Limit dB	Remark
	Level dBuV	Factor dB/m	Loss dB	Factor dB	Level dB			
1 2390.000	20.48	27.03	4.28	1.68	0.00	53.47	74.00	-20.53 Peak
2 2390.000	10.08	27.03	4.28	1.68	0.00	43.07	54.00	-10.93 Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	DH1 Tx mode
Test Channel:	Highest channel	Polarization:	Vertical
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read Antenna Level Factor		Cable Loss	Aux Factor	Preamp Factor	Limit Level dBuV/m	Over Line dBuV/m	Over Line dB	Remark
	MHz	dBuV	dB/m	dB	dB				
1 2483.500	21.89	27.27	4.38	1.70	0.00	55.24	74.00	-18.76	Peak
2 2483.500	11.51	27.27	4.38	1.70	0.00	44.86	54.00	-9.14	Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	DH1 Tx mode
Test Channel:	Highest channel	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read Level dBuV	Antenna Factor dB/m	Cable Loss dB	Aux Factor dB	Preamp Factor dB	Limit Line dBuV/m	Over Line dBuV/m	Over Line dB	Remark
1 2483.500	22.20	27.27	4.38	1.70	0.00	55.55	74.00	-18.45	Peak
2 2483.500	11.50	27.27	4.38	1.70	0.00	44.85	54.00	-9.15	Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

$\pi/4$ -DQPSK mode

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	2DH1 Tx mode
Test Channel:	Lowest channel	Polarization:	Vertical
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq	ReadAntenna Level	Antenna Factor	Cable Loss	Aux Factor	Preamp Factor	Line Level	Limit Line	Over Limit	Remark
MHz	dBuV	dB/m	dB	dB	dB	dBuV/m	dBuV/m	dB	
1	2390.000	20.24	27.03	4.28	1.68	0.00	53.23	74.00	-20.77 Peak
2	2390.000	10.58	27.03	4.28	1.68	0.00	43.57	54.00	-10.43 Average

Remark:

- Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	2DH1 Tx mode
Test Channel:	Lowest channel	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read	Antenna	Cable	Aux	Preamp	Limit	Over	Remark
	Level dBuV	Factor	Cable Loss dB	Aux Factor	Preamp Level dB	dBuV/m	Line dBuV/m	
1 2390.000	19.50	27.03	4.28	1.68	0.00	52.49	74.00	-21.51 Peak
2 2390.000	10.24	27.03	4.28	1.68	0.00	43.23	54.00	-10.77 Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	2DH1 Tx mode
Test Channel:	Highest channel	Polarization:	Vertical
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq	ReadAntenna Level	Antenna Factor	Cable Loss	Aux Factor	Preamp Factor	Limit Level	Line Limit	Over Line Limit	Remark
MHz	dBuV	dB/m	dB	dB	dB	dBuV/m	dBuV/m	dB	
1	2483.500	20.48	27.27	4.38	1.70	0.00	53.83	74.00	-20.17 Peak
2	2483.500	10.14	27.27	4.38	1.70	0.00	43.49	54.00	-10.51 Average

Remark:

- Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	2DH1 Tx mode
Test Channel:	Highest channel	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	ReadAntenna Level Factor		Cable Loss	Aux Factor	Preampl Factor	Limit dBuV/m	Over Line dB	Over Limit dB	Remark
	MHz	dBuV	dB/m	dB	dB				
1 2483.500	21.27	27.27	4.38	1.70	0.00	54.62	74.00	-19.38	Peak
2 2483.500	11.55	27.27	4.38	1.70	0.00	44.90	54.00	-9.10	Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

8DPSK mode

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	3DH1 Tx mode
Test Channel:	Lowest channel	Polarization:	Vertical
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read	Antenna	Cable	Aux	Preamp	Limit Line dBuV/m	Over Line dB	Over Limit dB	Remark
	Freq	Level	Factor	Loss	Factor				
	MHz	dBuV	dB/m	dB	dB	dBuV/m			
1	2390.000	19.70	27.03	4.28	1.68	0.00	52.69	74.00	-21.31 Peak
2	2390.000	10.61	27.03	4.28	1.68	0.00	43.60	54.00	-10.40 Average

Remark:

- Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	3DH1 Tx mode
Test Channel:	Lowest channel	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read	Antenna	Cable	Aux	Preamp	Limit Line dBuV/m	Over Line dB	Remark
	Level	Factor	Loss	Factor	Level			
1 2390.000	19.20	27.03	4.28	1.68	0.00	52.19	74.00	-21.81 Peak
2 2390.000	10.26	27.03	4.28	1.68	0.00	43.25	54.00	-10.75 Average

Remark:

- Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	3DH1 Tx mode
Test Channel:	Highest channel	Polarization:	Vertical
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq MHz	Read Level dBuV	Antenna Factor dB/m	Cable Loss dB	Aux Factor dB	Preamp Factor dB	Level dB dBuV/m	Limit Line dB dBuV/m	Over Limit dB	Remark
1 2483.500	21.92	27.27	4.38	1.70	0.00	55.27	74.00	-18.73	Peak
2 2483.500	11.18	27.27	4.38	1.70	0.00	44.53	54.00	-9.47	Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	3DH1 Tx mode
Test Channel:	Highest channel	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%




Freq	ReadAntenna Level	Antenna Factor	Cable Loss	Aux Factor	Preamp Factor	Level	Limit Line	Over Limit	Remark
MHz	dBuV	dB/m	dB	dB	dB	dBuV/m	dBuV/m	dB	
1	2483.500	21.67	27.27	4.38	1.70	0.00	55.02	74.00	-18.98 Peak
2	2483.500	11.74	27.27	4.38	1.70	0.00	45.09	54.00	-8.91 Average

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

6.10 Spurious Emission

6.10.1 Conducted Emission Method

Test Requirement:	FCC Part 15 C Section 15.247 (d)
Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement.
Test setup:	
Test Instruments:	Refer to section 5.9 for details
Test mode:	Non-hopping mode
Test results:	Pass

Measurement Data: Refer to Appendix A - BT


6.10.2 Radiated Emission Method

Test Requirement:	FCC Part 15 C Section 15.209								
Test Frequency Range:	9 kHz to 25 GHz								
Test Distance:	3m								
Receiver setup:	Frequency	Detector	RBW	VBW	Remark				
Receiver setup:	30MHz-1GHz	Quasi-peak	120kHz	300kHz	Quasi-peak Value				
	Above 1GHz	Peak	1MHz	3MHz	Peak Value				
		RMS	1MHz	3MHz	Average Value				
Limit:	Frequency	Limit (dBuV/m @3m)		Remark					
Limit:	30MHz-88MHz	40.0		Quasi-peak Value					
	88MHz-216MHz	43.5		Quasi-peak Value					
	216MHz-960MHz	46.0		Quasi-peak Value					
	960MHz-1GHz	54.0		Quasi-peak Value					
	Above 1GHz	54.0		Average Value					
		74.0		Peak Value					
Test setup:	Below 1GHz								
Test setup:									
Test Procedure:	<ol style="list-style-type: none"> The EUT was placed on the top of a rotating table 0.8m(below 1GHz) /1.5m(above 1GHz) above the ground at a 3 meter chamber. The table was rotated 360 degrees to determine the position of the highest radiation. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna 								

	<p>tower.</p> <ol style="list-style-type: none">3. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.4. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rota table was turned from 0 degrees to 360 degrees to find the maximum reading.5. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.6. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.
Test Instruments:	Refer to section 5.9 for details
Test mode:	Non-hopping mode
Test results:	Pass
Remark:	<ol style="list-style-type: none">1. Pre-scan all kind of the place mode (X-axis, Y-axis, Z-axis), and found the Y-axis is the worst case.2. 9 kHz to 30 MHz is noise floor and lower than the limit 20dB, so only shows the data of above 30MHz in this report.

Measurement Data (worst case):**Below 1GHz:**

Product Name:	7 inch Wi-Fi Tablet		Product Model:	T7W
Test By:	Carey		Test mode:	BT Tx mode
Test Frequency:	30 MHz ~ 1 GHz		Polarization:	Vertical
Test Voltage:	AC 120/60Hz		Environment:	Temp: 24°C Huni: 57%




Freq	ReadAntenna Level	Antenna Factor	Cable Loss	Aux Factor	Preamp Factor	Limit Level	Line Limit	Over Limit	Remark
MHz	dBuV	dB/m	dB	dB	dB	dBuV/m	dBuV/m	dB	
1	71.330	47.25	10.47	0.45	0.00	29.71	28.46	40.00	-11.54 QP
2	78.965	46.50	12.53	0.47	0.00	29.65	29.85	40.00	-10.15 QP
3	111.738	45.95	10.00	0.55	0.00	29.44	27.06	43.50	-16.44 QP
4	162.611	42.58	15.56	0.64	0.00	29.11	29.67	43.50	-13.83 QP
5	186.441	44.58	17.26	0.69	0.00	28.93	33.60	43.50	-9.90 QP
6	196.510	43.39	17.94	0.71	0.00	28.85	33.19	43.50	-10.31 QP

Remark:

- Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.
- The Aux Factor is a notch filter switch box loss, this item is not used.

Product Name:	7 inch Wi-Fi Tablet	Product Model:	T7W
Test By:	Carey	Test mode:	BT Tx mode
Test Frequency:	30 MHz ~ 1 GHz	Polarization:	Horizontal
Test Voltage:	AC 120/60Hz	Environment:	Temp: 24°C Huni: 57%



Freq MHz	ReadAntenna Level	Antenna Factor	Cable Loss	Aux Factor	Preamp Factor	Limit Level	Over Line	Over Limit	Remark
	dBuV	dB/m	dB	dB	dB	dBuV/m	dBuV/m	dB	
1 110.957	52.69	9.95	0.55	0.00	29.45	33.74	43.50	-9.76	QP
2 185.788	46.64	17.23	0.69	0.00	28.93	35.63	43.50	-7.87	QP
3 191.745	46.36	17.55	0.70	0.00	28.89	35.72	43.50	-7.78	QP
4 215.268	45.93	18.37	0.74	0.00	28.73	36.31	43.50	-7.19	QP
5 230.099	43.20	18.42	0.75	0.00	28.65	33.72	46.00	-12.28	QP
6 321.061	40.79	18.74	0.89	0.00	28.50	31.92	46.00	-14.08	QP

Remark:

1. Final Level = Receiver Read level + Antenna Factor + Cable Loss – Preamplifier Factor.
2. The emission levels of other frequencies are lower than the limit 20dB and not show in test report.
3. The Aux Factor is a notch filter switch box loss, this item is not used.

Above 1GHz:

Test channel: Lowest channel									
Detector: Peak Value									
Frequency (MHz)	Read Level (dBuV)	Antenna Factor (dB/m)	Cable Loss (dB)	Aux Factor (dB)	Preamp Factor (dB)	Level (dBuV/m)	Limit Line (dBuV/m)	Over Limit (dB)	Polarization
4804.00	48.43	30.78	6.80	2.44	41.81	46.64	74.00	-27.36	Vertical
4804.00	48.23	30.78	6.80	2.44	41.81	46.44	74.00	-27.56	Horizontal
Detector: Average Value									
Frequency (MHz)	Read Level (dBuV)	Antenna Factor (dB/m)	Cable Loss (dB)	Aux Factor (dB)	Preamp Factor (dB)	Level (dBuV/m)	Limit Line (dBuV/m)	Over Limit (dB)	Polarization
4804.00	41.67	30.78	6.80	2.44	41.81	39.88	54.00	-14.12	Vertical
4804.00	41.47	30.78	6.80	2.44	41.81	39.68	54.00	-14.32	Horizontal
Test channel: Middle channel									
Detector: Peak Value									
Frequency (MHz)	Read Level (dBuV)	Antenna Factor (dB/m)	Cable Loss (dB)	Aux Factor (dB)	Preamp Factor (dB)	Level (dBuV/m)	Limit Line (dBuV/m)	Over Limit (dB)	Polarization
4882.00	48.51	30.96	6.86	2.47	41.84	46.96	74.00	-27.04	Vertical
4882.00	48.79	30.96	6.86	2.47	41.84	47.24	74.00	-26.76	Horizontal
Detector: Average Value									
Frequency (MHz)	Read Level (dBuV)	Antenna Factor (dB/m)	Cable Loss (dB)	Aux Factor (dB)	Preamp Factor (dB)	Level (dBuV/m)	Limit Line (dBuV/m)	Over Limit (dB)	Polarization
4882.00	41.15	30.96	6.86	2.47	41.84	39.60	54.00	-14.40	Vertical
4882.00	41.24	30.96	6.86	2.47	41.84	39.69	54.00	-14.31	Horizontal
Test channel: Highest channel									
Detector: Peak Value									
Frequency (MHz)	Read Level (dBuV)	Antenna Factor (dB/m)	Cable Loss (dB)	Aux Factor (dB)	Preamp Factor (dB)	Level (dBuV/m)	Limit Line (dBuV/m)	Over Limit (dB)	Polarization
4960.00	48.97	31.11	6.91	2.49	41.87	47.61	74.00	-26.39	Vertical
4960.00	48.25	31.11	6.91	2.49	41.87	46.89	74.00	-27.11	Horizontal
Detector: Average Value									
Frequency (MHz)	Read Level (dBuV)	Antenna Factor (dB/m)	Cable Loss (dB)	Aux Factor (dB)	Preamp Factor (dB)	Level (dBuV/m)	Limit Line (dBuV/m)	Over Limit (dB)	Polarization
4960.00	41.95	31.11	6.91	2.49	41.87	40.59	54.00	-13.41	Vertical
4960.00	41.38	31.11	6.91	2.49	41.87	40.02	54.00	-13.98	Horizontal

Remark:


- Final Level = Receiver Read level + Antenna Factor + Cable Loss + Aux Factor – Preamplifier Factor.
- The emission levels of other frequencies are lower than the limit 20dB and not show in test report.

Appendix A – BT


Maximum Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	1-DH1	2402	Ant1	5.874	0	5.874	21	Pass
NVNT	1-DH1	2441	Ant1	5.256	0	5.256	21	Pass
NVNT	1-DH1	2480	Ant1	4.421	0	4.421	21	Pass
NVNT	2-DH1	2402	Ant1	6.371	0	6.371	21	Pass
NVNT	2-DH1	2441	Ant1	5.702	0	5.702	21	Pass
NVNT	2-DH1	2480	Ant1	4.755	0	4.755	21	Pass
NVNT	3-DH1	2402	Ant1	6.769	0	6.769	21	Pass
NVNT	3-DH1	2441	Ant1	6.161	0	6.161	21	Pass
NVNT	3-DH1	2480	Ant1	5.233	0	5.233	21	Pass


Power NVNT 1-DH1 2402MHz Ant1




Power NVNT 1-DH1 2441MHz Ant1




Power NVNT 1-DH1 2480MHz Ant1




Power NVNT 2-DH1 2402MHz Ant1




Power NVNT 2-DH1 2441MHz Ant1




Power NVNT 2-DH1 2480MHz Ant1




Power NVNT 3-DH1 2402MHz Ant1



Power NVNT 3-DH1 2441MHz Ant1



Power NVNT 3-DH1 2480MHz Ant1



-20dB Bandwidth

Condition	Mode	Frequency (MHz)	Antenna	-20 dB Bandwidth (MHz)	Limit -20 dB Bandwidth (MHz)	Verdict
NVNT	1-DH1	2402	Ant1	0.825	0	Pass
NVNT	1-DH1	2441	Ant1	0.828	0	Pass
NVNT	1-DH1	2480	Ant1	0.828	0	Pass
NVNT	2-DH1	2402	Ant1	1.25	0	Pass
NVNT	2-DH1	2441	Ant1	1.255	0	Pass
NVNT	2-DH1	2480	Ant1	1.253	0	Pass
NVNT	3-DH1	2402	Ant1	1.213	0	Pass
NVNT	3-DH1	2441	Ant1	1.211	0	Pass
NVNT	3-DH1	2480	Ant1	1.219	0	Pass

-20dB Bandwidth NVNT 1-DH1 2402MHz Ant1

-20dB Bandwidth NVNT 1-DH1 2441MHz Ant1**-20dB Bandwidth NVNT 1-DH1 2480MHz Ant1**

-20dB Bandwidth NVNT 2-DH1 2402MHz Ant1**-20dB Bandwidth NVNT 2-DH1 2441MHz Ant1**


-20dB Bandwidth NVNT 2-DH1 2480MHz Ant1**-20dB Bandwidth NVNT 3-DH1 2402MHz Ant1**

-20dB Bandwidth NVNT 3-DH1 2441MHz Ant1**-20dB Bandwidth NVNT 3-DH1 2480MHz Ant1**


Carrier Frequencies Separation

Condition	Mode	Antenna	Hopping Freq1 (MHz)	Hopping Freq2 (MHz)	HFS (MHz)	Limit (MHz)	Verdict
NVNT	1-DH1	Ant1	2401.854	2402.852	0.998	0.827	Pass
NVNT	1-DH1	Ant1	2440.850	2441.840	0.990	0.828	Pass
NVNT	1-DH1	Ant1	2478.848	2479.842	0.994	0.828	Pass
NVNT	2-DH1	Ant1	2401.842	2402.844	1.002	0.833	Pass
NVNT	2-DH1	Ant1	2441.164	2442.160	0.996	0.837	Pass
NVNT	2-DH1	Ant1	2478.844	2479.850	1.006	0.835	Pass
NVNT	3-DH1	Ant1	2401.858	2402.848	0.990	0.809	Pass
NVNT	3-DH1	Ant1	2440.846	2441.848	1.002	0.807	Pass
NVNT	3-DH1	Ant1	2478.844	2479.844	1.000	0.813	Pass


CFS NVNT 1-DH1 2402MHz Ant1




CFS NVNT 1-DH1 2441MHz Ant1




CFS NVNT 1-DH1 2480MHz Ant1




CFS NVNT 2-DH1 2402MHz Ant1




CFS NVNT 2-DH1 2441MHz Ant1




CFS NVNT 2-DH1 2480MHz Ant1




CFS NVNT 3-DH1 2402MHz Ant1



CFS NVNT 3-DH1 2441MHz Ant1




CFS NVNT 3-DH1 2480MHz Ant1




Band Edge

Condition	Mode	Frequency (MHz)	Antenna	Hopping Mode	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	1-DH1	2402	Ant1	No-Hopping	-55.44	-20	Pass
NVNT	1-DH1	2480	Ant1	No-Hopping	-53.80	-20	Pass
NVNT	2-DH1	2402	Ant1	No-Hopping	-54.97	-20	Pass
NVNT	2-DH1	2480	Ant1	No-Hopping	-52.54	-20	Pass
NVNT	3-DH1	2402	Ant1	No-Hopping	-53.77	-20	Pass
NVNT	3-DH1	2480	Ant1	No-Hopping	-52.04	-20	Pass


Band Edge NVNT 1-DH1 2402MHz Ant1 No-Hopping Ref




Band Edge NVNT 1-DH1 2402MHz Ant1 No-Hopping Emission



Band Edge NVNT 1-DH1 2480MHz Ant1 No-Hopping Ref




Band Edge NVNT 1-DH1 2480MHz Ant1 No-Hopping Emission



Band Edge NVNT 2-DH1 2402MHz Ant1 No-Hopping Ref




Band Edge NVNT 2-DH1 2402MHz Ant1 No-Hopping Emission



Band Edge NVNT 2-DH1 2480MHz Ant1 No-Hopping Ref




Band Edge NVNT 2-DH1 2480MHz Ant1 No-Hopping Emission



Band Edge NVNT 3-DH1 2402MHz Ant1 No-Hopping Ref




Band Edge NVNT 3-DH1 2402MHz Ant1 No-Hopping Emission



Band Edge NVNT 3-DH1 2480MHz Ant1 No-Hopping Ref



Band Edge NVNT 3-DH1 2480MHz Ant1 No-Hopping Emission




Band Edge(Hopping)

Condition	Mode	Frequency (MHz)	Antenna	Hopping Mode	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	1-DH1	2402	Ant1	Hopping	-55.33	-20	Pass
NVNT	1-DH1	2480	Ant1	Hopping	-53.93	-20	Pass
NVNT	2-DH1	2402	Ant1	Hopping	-53.59	-20	Pass
NVNT	2-DH1	2480	Ant1	Hopping	-51.70	-20	Pass
NVNT	3-DH1	2402	Ant1	Hopping	-54.01	-20	Pass
NVNT	3-DH1	2480	Ant1	Hopping	-51.90	-20	Pass

Band Edge(Hopping) NVNT 1-DH1 2402MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 1-DH1 2402MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 1-DH1 2480MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 1-DH1 2480MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 2-DH1 2402MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 2-DH1 2402MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 2-DH1 2480MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 2-DH1 2480MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 3-DH1 2402MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 3-DH1 2402MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 3-DH1 2480MHz Ant1 Hopping Ref



Band Edge(Hopping) NVNT 3-DH1 2480MHz Ant1 Hopping Emission




Conducted RF Spurious Emission

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	1-DH1	2402	Ant1	-52.6	-20	Pass
NVNT	1-DH1	2441	Ant1	-52.07	-20	Pass
NVNT	1-DH1	2480	Ant1	-50.74	-20	Pass
NVNT	2-DH1	2402	Ant1	-51.42	-20	Pass
NVNT	2-DH1	2441	Ant1	-49.17	-20	Pass
NVNT	2-DH1	2480	Ant1	-49.32	-20	Pass
NVNT	3-DH1	2402	Ant1	-51.19	-20	Pass
NVNT	3-DH1	2441	Ant1	-50.8	-20	Pass
NVNT	3-DH1	2480	Ant1	-49.63	-20	Pass

Tx. Spurious NVNT 1-DH1 2402MHz Ant1 Ref




Tx. Spurious NVNT 1-DH1 2402MHz Ant1 Emission



Tx. Spurious NVNT 1-DH1 2441MHz Ant1 Ref




Tx. Spurious NVNT 1-DH1 2441MHz Ant1 Emission



Tx. Spurious NVNT 1-DH1 2480MHz Ant1 Ref




Tx. Spurious NVNT 1-DH1 2480MHz Ant1 Emission



Tx. Spurious NVNT 2-DH1 2402MHz Ant1 Ref




Tx. Spurious NVNT 2-DH1 2402MHz Ant1 Emission



Tx. Spurious NVNT 2-DH1 2441MHz Ant1 Ref




Tx. Spurious NVNT 2-DH1 2441MHz Ant1 Emission



Tx. Spurious NVNT 2-DH1 2480MHz Ant1 Ref




Tx. Spurious NVNT 2-DH1 2480MHz Ant1 Emission



Tx. Spurious NVNT 3-DH1 2402MHz Ant1 Ref




Tx. Spurious NVNT 3-DH1 2402MHz Ant1 Emission



Tx. Spurious NVNT 3-DH1 2441MHz Ant1 Ref




Tx. Spurious NVNT 3-DH1 2441MHz Ant1 Emission



Tx. Spurious NVNT 3-DH1 2480MHz Ant1 Ref




Tx. Spurious NVNT 3-DH1 2480MHz Ant1 Emission




Number of Hopping Channel

Condition	Mode	Antenna	Hopping Number	Limit	Verdict
NVNT	1-DH1	Ant1	79	15	Pass
NVNT	2-DH1	Ant1	79	15	Pass
NVNT	3-DH1	Ant1	79	15	Pass


Hopping No. NVNT 1-DH1 2441MHz Ant1



Hopping No. NVNT 2-DH1 2441MHz Ant1




Hopping No. NVNT 3-DH1 2441MHz Ant1




Dwell Time

Condition	Mode	Frequency (MHz)	Antenna	Pulse Time (ms)	Total Dwell Time (ms)	Period Time (ms)	Limit (ms)	Verdict
NVNT	1-DH1	2441	Ant1	0.392	125.44	31600	400	Pass
NVNT	1-DH3	2441	Ant1	1.648	263.68	31600	400	Pass
NVNT	1-DH5	2441	Ant1	2.896	308.907	31600	400	Pass
NVNT	2-DH1	2441	Ant1	0.385	123.2	31600	400	Pass
NVNT	2-DH3	2441	Ant1	1.637	261.92	31600	400	Pass
NVNT	2-DH5	2441	Ant1	2.884	307.627	31600	400	Pass
NVNT	3-DH1	2441	Ant1	0.382	122.24	31600	400	Pass
NVNT	3-DH3	2441	Ant1	1.633	261.28	31600	400	Pass
NVNT	3-DH5	2441	Ant1	2.884	307.627	31600	400	Pass


Dwell NVNT 1-DH1 2441MHz Ant1




Dwell NVNT 1-DH3 2441MHz Ant1




Dwell NVNT 1-DH5 2441MHz Ant1




Dwell NVNT 2-DH1 2441MHz Ant1




Dwell NVNT 2-DH3 2441MHz Ant1




Dwell NVNT 2-DH5 2441MHz Ant1




Dwell NVNT 3-DH1 2441MHz Ant1



Dwell NVNT 3-DH3 2441MHz Ant1



Dwell NVNT 3-DH5 2441MHz Ant1



-----End of report-----