

Antenna Sample Confirmation From

Vendor Name	ShenZhen Aihui Technology Co. , Ltd				
Customer Name	Get together				
Sample Name	F108FL				
Part Number					
Specification					
Inspection Item	Performance	Total Appearance	structure	Others	Inspection Result
Remark					
QA Audit		Engineer Audit		Sales Confirm	
The following are filled by Customer					
Customer Evaluation					
Signation/ Chapter by Customer	date:				

Antenna Test Report

Test by: ShenZhen Aihui Technology Co. , Ltd			
Material	FPC coaxial line		
Antenna Type	MonopoleType	Polarization mode	Linear
Application			
Band	GSM/WCDMA/LTE/2. 4G/5 GWIFI/GPS/BT	VSWR	≤2
Power	Max: 2W	Impedance	50 Ω
dBi	≥1dBi		
Test Equipment	HPE5071C、Shielding Room、3D automatic turntable		
Antenna Description: 1. Grounding processing and picture description: no 2. Need to change the motherboard to match: no ● Test voltage: 3.6V, check the antenna contact is good before testing. ● The RF cable of the integrated tester is kept in a natural state and can not be curled. Specification:test the specified power level, all indicators must conform to the specifications.			

Shenzhen Aihui Technology Co. , Ltd.

1. Project Picture

2. Test fixture

3. Antenna matching circuit

4. S11 test 4.0S11 test method illustration

4.1S11 parameter picture

5. Darkroom test apparatus and data

5.0 test apparatus

5.1 active test data Passive efficiency data

6. Antenna assembly schematic diagram

7. Antenna Environment Treatment

8. Antenna mass production index

9. Structure drawing


Address: Building C, Juxin Science and Technology Industry Park, 58 Gushu Nanchang Road, Xixiang, Baoan District, Shenzhen Tel: 0755-23203435fax: 0755-23203435

Shenzhen Aihui Technology Co. , Ltd.


1. Project picture explanation:

the customer finally verifies the antenna performance prototype to keep in our company at least one year time, is convenient to analyze and solve the antenna mass production abnormal situation, ensure the antenna shipment quality

2, test system objective: to test the antenna passive parameters as accurately as possible. Making Method: the handset is made of a 50 ohm coaxial cable, one end of which is connected to the test point of the back end of the matching circuit of the handset motherboard (front end of the RF test hole) , and the other end is connected to the SMA joint. The diagram is as follows:



3、Antenna matching circuit



Modify

E01	E02	E03
No	No	No

Note: The match is unmodified.

Four. S11 test

4.0S11 test method description of test equipment: Network Analyzer (E5071C) test method: export from the instrument test port using a 50 ohm CABLE, after calibration, the SMA Joint of the handset is connected to record the return loss and standing wave ratio corresponding to the relevant frequency points. The test schematic is as follows:

Test schematic

Shenzhen Aihui Technology Co. , Ltd.


5.ANECHOIC chamber test equipment and data

5.0 test equipment test system: SHIELDED ANECHOIC chamber test environment:

temperature $22^{\circ}\text{C} \pm 3^{\circ}\text{C}$, humidity $50\% \pm 15\%$ test equipment: Test passive data,

when testing active data with the Network analyzer AGILENT E5071C, use the omnibus

CMW500



Address: Building C, Juxin Science and Technology Industry Park, 58 Gushu Nanchang Road, Xixiang, Baoan District, Shenzhen Tel: 0755-23203435 fax: 0755-23203435


5.1 Active antenna test data

Frequency Band	GSM850			900		
channel	L	M	H	L	M	H
TRP	26.12	27.08	26.13	25.89	25.91	25.99
TIS			-102.82			-102.5
Frequency Band	1800			1900		
channel	L	M	H	L	M	H
TRP	25.41	25.57	25.28	25.74	25.94	25.33
TIS			-104.15			-103.95
Frequency Band	W2			W4		
channel	L	M	H	L	M	H
TRP	18.17	18.75	18.8	18.69	18.73	19.3
TIS			-103.57			-104.01
Frequency Band	W5					
channel	L	M	H			
TRP	16.01	16.1	16.14			
TIS			-102.47			

Frequency Band	B4			B5		
channel	L	M	H	L	M	H
TRP	18.69	18.19	18.24	16.56	16.47	17.68
TIS			-90.1			-89.57
Frequency Band	B12					
channel	L	M	H			
TRP	15.54	15.58	15.15			
			-88.59			

Passive efficiency data of main antenna

Shenzhen Aihui Technology Co. , Ltd.




Address: Building C, Juxin Science and Technology Industry Park, 58 Gushu Nanchang Road, Xixiang, Baoan District, Shenzhen Tel: 0755-23203435fax: 0755-23203435


Three-in-one antenna passive efficiency data


Gain&Efficiency			
frequency (Hz)	gain (dB)	efficiency (dB)	efficiency
2400M	0.91	-3.96	32.47%
2410M	0.96	-3.88	30.16%
2420M	1.02	-3.93	31.11%
2430M	0.86	-3.97	33.21%
2440M	1.12	-3.85	34.03%
2450M	1.96	-3.84	34.41%
2460M	1.14	-3.96	35.74%
2470M	1.2	-3.92	32.38%
2480M	1.03	-3.91	33.37%
2490M	0.95	-3.86	32.28%
2500M	0.97	-3.98	33.66%

Gain&Efficiency			
frequency (Hz)	gain (dB)	efficiency (dB)	efficiency
1560M	0.91	-4.12	33.47%
1565M	0.96	-4.45	31.16%
1570M	1.02	-4.06	33.11%
1575M	0.86	-4.01	34.25%
1580M	1.12	-3.98	34.14%




Gain&Efficiency			
frequency (Hz)	gain (dB)	efficiency (dB)	efficiency
5050M	1.26	-3.47	45.54%
5100M	1.34	-3.43	47.15%
5150M	1.14	-3.86	48.25%
5200M	1.97	-3.17	45.38%
5250M	1.24	-2.97	46.23%
5300M	1.26	-3.13	49.66%
5350M	1.34	-3.55	48.73%
5400M	1.31	-3.02	49.62%
5450M	1.36	-3.34	46.38%
5500M	1.25	-3.43	47.83%
5550M	1.14	-3.24	48.52%
5600M	1.26	-3.61	46.71%
5650M	1.37	-3.88	49.10%
5700M	1.14	-3.79	49.83%
5750M	1.34	-4.1	48.19%
5800M	1.44	-4.22	46.24%
5850M	1.36	-4.31	44.28%






5. 2 WIFI/GPS measurements




Distance from the
hot spot 10M
signal full grid,
internet normal





Test site for our
windowsill, more
than 40 2-3.
Location Time 60S

6. Schematic diagram of antenna assembly



7. Antenna environment handling

Shenzhen Aihui Technology Co. , Ltd.



Address: Building C, Juxin Science and Technology Industry Park, 58 Gushu Nanchang Road, Xixiang, Baoan District, Shenzhen Tel: 0755-23203435fax: 0755-23203435