












正面

反面

<div>HAVIT</div> <div></div> <div>I98 BILATERAL TRUE WIRELESS STEREO EARBUDS</div> <div>PRODUCT MANUAL</div> <div>FCC ID:2AIG-I98</div>	<div>Product and accessories</div> <div> Earbuds *2</div> <div> charging case *1</div> <div> 2 pairs of ear cap (L/S size, M equipped)</div> <div> Charging cable *1</div> <div> User manual *1</div> <div> Certificate of quality x1</div> <div>1</div>	<div>Description of product structure</div> <div> 1  2</div> <div> 1.Power LED indicator 2.MFB (Touch panel) 3.Indicator light 4.Charging port</div> <div>3</div> <div>Wearing method</div> <div>Gently cram the earbuds into the cochlea then adjust the appropriate angle</div> <div> 2</div> <div>5</div>	<div>Basic function</div> <div>01 Power on,Bluetooth connection</div> <div>—Follow the steps (Please confirm that your phone is built-in Bluetooth function)</div> <div>1. Power on Method 1: Remove earbuds from the charging case. Method 2: If earbuds are power off outside the case, touch and hold MFB button for 2 seconds on both sides to turn them on.</div> <div>When one earbud indicator starts flashing alternately with white and orange and the other earbud indicator is turn off.And the product is ready for use.</div> <div>2. Turn on Bluetooth on your device and select “HAVIT I98” referring to your phone instructions.</div> <div>3. Pairing mode can just last 180 seconds. if you miss the pairing time, you need to restart the device and operate follow the procedural steps mentioned above.</div> <div>6</div>	<div>*Note:</div> <div>a). HAVIT I98 remembers previously connected devices. When turned on, earbuds attempts to reconnect to previously connected devices.</div> <div>b). HAVIT I98 will lose the connection when deviate the working range of Bluetooth. The earbuds will reconnect automatically if you come back to the range in 3 minutes.</div> <div>02 Power off</div> <div>Method 1: Put the earbuds into the charging box, they will automatically shut off.</div> <div>Method 2: Touch and hold MFB for 5 seconds, the white light flashes three times, and the earbuds are turned off.</div> <div>03 Answering incoming calls</div> <div>1.Short press left or right MFB to answer incoming calls.</div> <div>2.One phone is answering a call,while another has a call retained: A.Short press left/right MFB once to keep the current phone call and answer incoming calls;</div> <div>4</div>	<div>B.Long press left/right MFB 2s to refuse the incoming call; C.In the three-way call, long press left or right MFB to realize two mobile phone calls switch over. D.One current call, another phone call maintenance: a. Long press left/right MFB 1s to maintain the current call and connect to the maintained call. b. Short press left/right MFB once, hang up the current call and connect the maintained call.</div> <div>04 End the call</div> <div>Short press the MFB once to end the current call.</div> <div>05 Refuse incoming calls</div> <div>Long press the MFB for 2s to reject a call.</div> <div>06 One key for Siri</div> <div>Dual press the left/right MFB to activate voice assistant.</div> <div>5</div>
<div>07 Music playing</div> <div>1. Play/Pause: short press the left/right MFB once; 2. Long press the left MFB for 1s to switch to the previous song 3. Long press the right MFB for 1s to switch to the next song *When single side earbuds works, it has only the next function.</div> <div>08 Mono mode (take out any earbuds as a unilateral bluetooth earbud)</div> <div>(note: single channel mode only needs to remove one of earbuds from the charging box; If two earbuds are removed before connection, the earbud will be used in TWS mode by default, and the TWS connection will be automatically realized.) 1.Take out a earbud from charging case,the earbud automatically turn on and reconnect to previously connected devices. 2.Switch from one earbud to the other when playing music, taking out the other earbud from</div> <div>6</div>	<div>the charging case and these two earbuds will connected automatically. Both earbuds will play music automatically and then put the earbud which do not need anymore into the charging case and the switching process completes. (note:Call mode is applicable) 3.Please refer to the TWS mode for more functions.</div> <div>09 Restore factory settings</div> <div>If the earbuds cannot pair or disconnect frequently, please restore the factory settings. Click the both earbuds' MFB button twice, when one earbud indicator starts flashing alternately with white and orange and the other earbud indicator is turn off, the reset completed.</div> <div>10 Charging</div> <div>-Case Charge the case using the Type-C cable connected to a computer or wall charger. The indicator at the front of the charging case flashes white when charging and turns to be steady</div> <div>7</div>	<div>white when fully charged. Charging time is approximately 2 hours.</div> <div>-Earbuds</div> <div>1.When the power of the earbuds is lower than 3.45v, the orange light flashes 2 times every 3 minutes and a sound prompt is heard. 2.Put the earbuds back into the charging case for charging. While charging, the indicator flashes white slowly. After full charge, the white light goes out.</div> <div>Specification</div> <div>IPX5 sweat proof Bluetooth Version: V5.1 Earbud Battery: 50mAh*(Fully charged in 1.5H) Charging case battery: 420mAh Charging case dimension: 80*32*31mm Earbud dimensions: 26*21*18.4mm*2 Net weight: 4.5g*2(Earbuds)/41g(Charging case) Wireless working range: 10M (without obstacles) Speaker: Φ6MM diaphragm Speaker sensitivity: 98±3dB 1kHz/1mW</div> <div>8</div>	<div>Profiles supported: HSP, HFP, A2DP, AVRCP Impedance: 16Ω±15% 1kHz Speaker frequency: 20Hz~20KHz Input voltage / current: DC 5V/1A Play time: 6H (in medium vol.) Talk time: 6H (in medium vol.) Standby time: 280H Charging time: about 2H Battery display indicator</div> <div>Warnings</div> <div>1. Please follow the instruction to operate. 2. Please charge the earbuds with input power below 5V/1A, in order to protect the battery, 3. Please store or use the earbuds in a normal temperature environment. 4. Please do not use this product near the water. Do not immerse this product in any liquid or splash any liquid on this product. 5. Please keep the earbuds from heat source, such as radiators, hot air regulators, stoves, or other heat generating instruments. As it is not anti high temperature.</div> <div>9</div>	<div>6. Don't jam the ports of the earbuds, such as charger port, LED port and microphone etc.. 7. In order to protect your hearing and extend the speaker service life, it is not recommended to adjust the volume to the maximum level for a long time. 8. Whatever reasons damage the earbuds, please feel free to contact our after-sales staff in time rather than repair by yourself. Otherwise, you will accept without after-sales service.</div> <div>10</div>	<div>FCC Caution:</div> <div>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</div> <div>Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</div> <div>Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: -Reorient or relocate the receiving antenna. -Increase the separation between the equipment and receiver. -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -Consult the dealer or an experienced radio/TV technician for help.</div> <div>The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.</div> <div>11</div>