

Page 1 of 135 JQA File No. : KL80130675S Issue Date : April 11, 2014

TEST REPORT

Applicant	:	Sharp Corporation, Communication Systems Division
Address	:	2-13-1, Iida Hachihonmatsu, Higashi-Hiroshima City, Hiroshima, 739-0192, JAPAN
Products	:	Cellular Phone
Model No.	:	304SH
SERIAL NO.	:	004401/11/507683/4
		004401/11/507702/2
		004401/11/495699/4
FCC ID	:	APYHRO00205
Test Standard	:	CFR 47 FCC Rules and Regulations Part 15
Test Results	:	Passad
I COU INCOULIO	•	1 abbeu
Date of Test	:	March 6 ~14, 2014



Kousei Shibata Manager Japan Quality Assurance Organization KITA-KANSAI Testing Center SAITO EMC Branch 7-3-10, Saito-asagi, Ibaraki-shi, Osaka 567-0085, Japan

- The measurement values stated in Test Report was made with traceable to National Institute of Advanced Industrial Science and Technology (AIST) of Japan and National Institute of Information and Communications Technology (NICT) of Japan.
- The applicable standard, testing condition and testing method which were used for the tests are based on the request of the applicant.
- The test results presented in this report relate only to the offered test sample.
- The contents of this test report cannot be used for the purposes, such as advertisement for consumers.
- This test report shall not be reproduced except in full without the written approval of JQA.
- VLAC does not approve, certify or warrant the product by this test report.



Page 2 of 135

TABLE OF CONTENTS

Page

1	Description of the Equipment Under Test	3
2	Summary of Test Results	4
3	Test Procedure	5
4	Test Location	5
5	Recognition of Test Laboratory	5
6	Details of the Equipment Under Test	6
7	Details of the Test Item	10

DEFINITIONS FOR ABBREVIATION AND SYMBOLS USED IN THIS TEST REPORT

EUT	: Equipment Under Test	E
AE	: Associated Equipment	E

N/A : Not Applicable

N/T : Not Tested

- EMC: Electromagnetic CompatibilityEMI: Electromagnetic InterferenceEMC: Electromagnetic Interference
- **EMS** : Electromagnetic Susceptibility
- \boxtimes indicates that the listed condition, standard or equipment is applicable for this report.
- \Box indicates that the listed condition, standard or equipment is not applicable for this report.



Page 3 of 135

1 Description of the Equipment Under Test

1. Manufacturer : Sharp Corporation, Communication Systems Division 2-13-1, Iida Hachihonmatsu, Higashi-Hiroshima City, Hiroshima, 739-0192, JAPAN Products Cellular Phone 2. : Model No. : 304SH3. Serial No. • 4. 004401/11/507683/4 004401/11/507702/2 004401/11/495699/4 Product Type Pre-production 5. : 6. Date of Manufacture : January, 2014 : 4.0VDC (Lithium-ion Battery UBATIA243AFN1 2600mAh) 7. Power Rating 8. EUT Grounding : None 5180.0 MHz(36CH) -5700.0MHz(140CH): IEEE802.11a/n/ac(20MHz) 9. **Operating Frequency** : 5190.0 MHz(38CH) -5670.0MHz(134CH): IEEE802.11n/ac(40MHz) 5210.0 MHz(42CH) -5530.0MHz(106CH): IEEE802.11n/ac(80MHz) 10. Modulation : OFDM 11. Antenna type Inverted-L Type Antenna : 12. Category : Spread Spectrum Transmitter(OFDM)/UNII* 13. EUT Authorization : Certification 14. Received Date of EUT : March 4, 2014

*The EUT does not apply any emission testing as specified in FCC KDB 644545 (D02 and D01), Because it has no function shown in the(KDB) guidance.



Page 4 of 135

2 Summary of Test Results

Applied Standard : CFR 47 FCC Rules and Regulations Part 15 – Radio Frequency Devices Subpart E – Unlicensed National Information Infrastructure Devices

The EUT described in clause 1 was tested according to the applied standard shown above. Details of the test configuration is shown in clause 6.

The conclusion for the test items of which are required by the applied standard is indicated under the test result.

 \boxtimes - The test result was **passed** for the test requirements of the applied standard.

 \Box - The test result was **failed** for the test requirements of the applied standard.

□ - The test result was **not judged** the test requirements of the applied standard.

In the approval of test results,

- Determining compliance with the limits in this report was based on the results of the compliance measurement, not taking into account measurement instrumentation uncertainty.
- No deviations were employed from the applied standard.
- No modifications were conducted by JQA to achieve compliance to the limitations.

Reviewed by:

Shigeru Kinoshita Deputy Manager JQA KITA-KANSAI Testing Center SAITO EMC Branch

Tested by:

gery asawa

Shigeru Osawa Deputy Manager JQA KITA-KANSAI Testing Center SAITO EMC Branch



Page 5 of 135

3 Test Procedure

The tests documented in this report were performed in accordance with CFR 47 FCC Rules and Regulations Part 15 Subpart E – Unlicensed National Information Infrastructure Devices

ANSI C63.10–2009 Testing unlicensed wireless devices.

KDB 789033 D01 General UNII Test Procedures v01r03: April 8, 2013

FCC 06-96 Compliance measurement procedures for Unlicensed National Information Infrastructure Devices

4 Test Location

Japan Quality Assurance Organization (JQA) KITA-KANSAI Testing Center 7-7, Ishimaru, 1-chome, Minoh-shi, Osaka, 562-0027, Japan SAITO EMC Branch 7-3-10, Saito-asagi, Ibaraki-shi, Osaka 567-0085, Japan

5 Recognition of Test Laboratory

JQA KITA-KANSAI Testing Center SAITO EMC Branch is accredited under ISO/IEC 17025 by following accreditation bodies and the test facility is registered by the following bodies.

VLAC Accreditation No.	:	VLAC-001-2 (Expiry date : March 30, 2014)
VCCI Registration No.	:	A-0002 (Expiry date : March 30, 2014)
BSMI Registration No.	:	SL2-IS-E-6006, SL2-IN-E-6006, SL2-R1/R2-E-6006, SL2-A1-E-6006
		(Expiry date : September 14, 2016)
IC Registration No.	:	2079E-3, 2079E-4 (Expiry date : July 20, 2014)

Accredited as conformity assessment body for Japan electrical appliances and material law by METI. (Expiry date : February 22, 2016)



Page 6 of 135

6 Details of the Equipment Under Test

:

6.1 Operating Condition

Test Voltage : 4.0VDC (Internal Lithium-ion Battery UBATIA243AFN1 2600mAh)

Operation Mode

The EUT is set with the test mode, the specification of the test mode is as followings.

Transmitting frequency	: 5180.0 MHz (36CH) $-5700.0 \rm MHz$ (140CH): IEEE802.11a/n/ac (20MHz)
	: 5190.0 MHz(38CH) –5670.0MHz(134CH): IEEE802.11n/ac(40MHz)
	: 5210.0 MHz(42CH) –5530.0MHz(106CH): IEEE802.11ac(80MHz)
Receiver frequency	: 5180.0 MHz(36CH) – 5700.0 MHz(140CH)

Modulation Type 1. 802.11a : OFDM 2. 802.11n/ac(20MHz) : OFDM 3. 802.11n/ac(40MHz) : OFDM 3. 802.11ac(80MHz) : OFDM

Other Clock Frequency 32.768 kHz, 19.2 MHz, 24 MHz, 27 MHz, 27.12 MHz, 48 MHz

The EUT was rotated through three orthogonal axis (X, Y and Z axis) in radiated measurement. The EUT with temporary antenna port was used in conducted measurement.



Page 7 of 135

6.2 Test Configuration

The equipment under	test (EUT) consists of	of:
---------------------	------------------------	-----

	Item	Manufacturer	Model No.	Serial No.	FCC ID
А	Cellular Phone	Sharp	304SH	004401/11/507683/4*1) 004401/11/507702/2*2) 004401/11/495699/4*3)	APYHRO00205
В	AC Adapter	Sharp	SHCEJ1		N/A
С	Earphone	Softbank Mobile	ZTCAA1		N/A

*1) Used for AC Powerline Conducted Emission and Field Strength of Spurious Emission

*2) Used for Antenna Conducted Emission

*3) Used for DFS Measurement

The auxiliary equipment used for testing :

None

Type of Cable:

No	Description	Identification	Connector	Cable	Ferrite	Length
INO.	Description	(Manu. etc.)	Shielded	Shielded	Core	(m)
1	DC Power Cord			NO	NO	1.5
2	Earphone Cable			NO	NO	0.5



6.3 Test Arrangement (Drawings)

Page 8 of 135





b) AC Adapter used



c) Earphone used





Page 9 of 135

6.4 Maximum Output Power

The preliminary maximum peak conducted output power measurements were performed each TX rate and maximum value are listed as followings.

802.11a

Channel	36	44	48	52	56	64	100	116	140
Frequency(MHz)	5180	5220	5240	5260	5280	5320	5500	5580	5700
Power(dBm)	11.03	10.83	11.14	11.09	10.95	11.46	10.67	11.05	11.21

The TX rate 6Mbps was maximum case.(MCS0)

802.11n (20MHz BW)

Channel	36	44	48	52	56	64	100	116	140
Frequency(MHz)	5180	5220	5240	5260	5280	5320	5500	5580	5700
Power(dBm)	11.18	10.58	10.71	11.09	11.12	11.60	10.34	11.06	10.79
	·				1			I	

The TX rate 6.5Mbps was maximum case.(MCS0)

802.11n (40MHz BW)

Channel	38	46	54	62	102	134
Frequency(MHz)	5190	5230	5270	5310	5510	5670
Power(dBm)	11.00	10.59	11.20	11.79	10.41	10.83

The TX rate 13.5Mbps was maximum case.(MCS0)

802.11ac(80MHz BW)

Channel	42	58	106
Frequency(MHz)	5210	5290	5530
Power(dBm)	10.96	11.68	10.64

The TX rate 29.3Mbps was maximum case.(MCS0)

All test cases were performed to the highest RF output power data rate listed above.



Page 10 of 135

7 Details of the Test Item

7.0 Summary of the Test Results

Test Item	FCC Specification	Reference of the	Results	Remarks
		Test Report		
26dB Bandwidth	Section 15.407(a)(1)(2)(3)	Section 7.1	-	-
Maximum Conducted	Section 15.407(a)(1)(2)(3)	Section 7.2	Passed	-
Output Power				
Peak Power	Section 15.407(a)(1)(2)(3)	Section 7.3	Passed	-
Spectral Density				
Peak Excursion	Section 15.407(a)(6)	Section 7.4	Passed	-
AC Powerline Conducted	Section 15.407(b)(6)	Section 7.5	Passed	-
Emission	Section 15.207			
Unwanted Radiated	Section 15.407(b)	Section 7.6	Passed	-
Emission	Section 15.205			
	Section 15.209			
Dynamic Frequency	Section 15.407(h)(2)	Section 7.7	Passed	-
Selection				

7.1 26dB Bandwidth

For the requirements,	⊠ -	Applicable	$[\square$	- Tested.	- Not tested by applicant request.]
	-	Not Applica	ble		

For the limits,	🗌 - Passed	🗌 - Failed	🛛 - Not judged
-----------------	------------	------------	----------------

7.1.1 Worst Point and Measurement Uncertainty

Reporting Purpose (No limitation applied)

Uncertainty of Measurement Results

+/- 0.9 %

Remarks :

7.1.2 Test Site and Instruments

7.1.2.1 Test Site

KITA-KANSAI Testing Center

Test site : SAITO

- Anechoic chamber (A1)
- Measurement room (M2)
- \Box Shielded room (S1)
- □ Shielded room (S3)
- Measurement room (M1)
- Measurement room (M3)
- □ Shielded room (S2)
- \square Shielded room (S4)



Page 11 of 135

7.1.2.2 Test Instruments

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
RF Cable	SUCOFLEX102	SUHNER	C-52	2013/7	1 Year
Spectrum Analyzer	E4446A	Agilent	A-39	2013/9	1 Year
Attenuator	54A-10	Weinschel	D-28	2013/9	1 Year

7.1.3 Test Method and Test Setup (Diagrammatic illustration)

The occupied bandwidth measurements were carried out connecting to the spectrum analyzer. The spectrum analyzer was set in accordance with KDB 789033 D01 as follows;. The RBW was set approximately 1% of the emission bandwidth. Set the VBW > RBW., Detector = Peak, and Trace mode = max hold. The bandwidth function in the analyzer was used.

(referred documentation is No. G70364M)





Page 12 of 135

7.1.4 Test Data

7.1.5.1 802.11a 26dB/ 99% OBW

<u>Test Date : March 8, 2014</u> <u>Temp.: 21°C, Humi: 25%</u>

Mode of EUT: TX 802.11a Test Port: Temporary antenna connector

Channel	Frequency	26dB OBW	99% OBW
	(MHz)	(MHz)	(MHz)
36	5180	21.776	16.689
44	5220	21.390	16.715
48	5240	21.335	16.681
52	5260	21.607	16.721
56	5280	21.199	16.720
64	5320	21.329	16.725
100	5500	21.615	16.723
116	5580	21.508	16.710
140	5700	21.580	16.682

802.11a 36ch (5180 MHz)



Transmit Freq Error	67.608 kHz
Occupied Bandwidth	21.776 MHz



Page 13 of 135

802.11a 44ch (5220 MHz)



Transmit	Freq Error	56.353 kHz
Occupied	Bandwidth	21.390 MHz

802.11a 48ch (5240 MHz)



Transmit	Freq Error	44.512 kHz
Occupied	Bandwidth	21.335 MHz



Page 14 of 135

802.11a 52ch (5260 MHz)



Transmit F	req Error	45.095 kHz
Occupied	Bandwidth	21.607 MHz

802.11a 56ch (5280 MHz)



Transmit F	req Error	55.859 kHz
Occupied E	Bandwidth	21.199 MHz



Page 15 of 135

802.11a 64ch (5320 MHz)



Transmit F	req Error	37.769 kHz
Occupied	Bandwidth	21.329 MHz





Transmit Freq Error	45.948 kHz
Occupied Bandwidth	21.615 MHz



Page 16 of 135

802.11a 116ch (5580 MHz)



Transmit	Freq Error	43.699 kHz
Occupied	Bandwidth	21.508 MHz





Transmit Freq Error	39.892 kHz
Occupied Bandwidth	21.580 MHz



7.1.5.2 802.11n (20 MHz BW) 26dB/ 99% OBW

Page 17 of 135

Mode of EUT: Tx 802.11n(20 MHz) Test Port: Temporary antenna connector

Channel	Frequency	26dB OBW	99% OBW
	(MHz)	(MHz)	(MHz)
36	5180	21.791	17.795
44	5220	22.165	17.787
48	5240	21.676	17.781
52	5260	21.683	17.824
56	5280	21.880	17.797
64	5320	22.097	17.816
100	5500	21.521	17.823
116	5580	22.100	17.869
140	5700	21.992	17.864





Transmit	Freq Error	49.671	kHz
Occupied	Bandwidth	21.791	MHz



Page 18 of 135

802.11n (20 MHz) 44ch (5220 MHz)



Transmit Freq Error	42.015 kHz
Occupied Bandwidth	22.165 MHz

802.11n (20 MHz) 48ch (5240 MHz)



Transmit F	req Error	48.321	kHz
Occupied	Bandwidth	21.676	MHz



Page 19 of 135

802.11n (20 MHz) 52ch (5260 MHz)



Transmit Freq Error	66.329 kHz
Occupied Bandwidth	21.683 MHz

802.11n (20 MHz) 56ch (5280 MHz)



Transmit	Freq Error	33.215 kHz
Occupied	Bandwidth	21.880 MHz

Technical document No. 23199-1201



Page 20 of 135

802.11n (20 MHz) 64ch (5320 MHz)



Transmit Freq Error	51.018 kHz
Occupied Bandwidth	22.097 MHz





Transmit Freq Error	49.999 kHz
Occupied Bandwidth	21.521 MHz

```
Technical document No. 23199-1201
```



Page 21 of 135

802.11n (20 MHz) 116ch (5580 MHz)



Transmit Freq Error	47.760 kHz
Occupied Bandwidth	22.100 MHz





Transmit Freq Error	59.140 kHz	
Occupied Bandwidth	21.992 MHz	



7.1.5.3 802.11n (40 MHz BW) 26dB/ 99% OBW

Page 22 of 135

Mode of EUT: Tx 802.11n(40 MHz) Test Port: Temporary antenna connector

Channel	Frequency	26dB OBW	99% OBW
	(MHz)	(MHz)	(MHz)
38	5190	42.778	36.161
46	5230	43.217	36.109
54	5270	42.479	36.104
62	5310	43.267	36.114
102	5510	43.255	36.134
134	5670	43.601	36.150

802.11n (40 MHz) 38ch (5190 MHz)



Transmit Freq Error	42.198 kHz
Occupied Bandwidth	42.778 MHz



Page 23 of 135

802.11n (40 MHz) 46ch (5230 MHz)



Transmit Freq Error	28.559 kHz
Occupied Bandwidth	43.217 MHz

802.11n (40 MHz) 54ch (5270 MHz)



Transmit Freq Error	33.908 kHz
Occupied Bandwidth	42.479 MHz

Technical document No. 23199-1201



Page 24 of 135

802.11n (40 MHz) 62ch (5310 MHz)



Transmit Freq Error	28.863 kHz
Occupied Bandwidth	43.267 MHz





Transmit Freq Error	47.407 kHz
Occupied Bandwidth	43.255 MHz

Technical document No. 23199-1201



Page 25 of 135

802.11n (40 MHz) 134ch (5670 MHz)



Transmit Fr	eq Error	46.455 kHz
Occupied Ba	andwidth	43.601 MHz



Page 26 of 135

7.1.5.4 802.11ac (80 MHz BW) 26dB/ 99% OBW

Mode of EUT: Tx 802.11ac(80 MHz)

Test Port: Temporary antenna connector

Channel	Frequency	26dB OBW	99% OBW
	(MHz)	(MHz)	(MHz)
42	5210	83.125	74.597
58	5290	82.968	74.576
106	5530	82.505	74.545

802.11ac (80 MHz) 42ch (5210 MHz)



Transmit Freq Error-3.047 kHzOccupied Bandwidth83.125 MHz



Page 27 of 135





Transmit	Freq Error	-5.104 kHz
Occupied	Bandwidth	82.968 MHz





Transmit F	req Error	–8.928 kHz
Occupied	Bandwidth	82.505 MHz

JQA Fil Model N	e No. :KL80130675S Jo. :304SH	Issue Date : April 11, 2014 FCC ID : APYHRO00205
Standar	d : CFR 47 FCC Rules and	Regulations Part 15
		Page 28 of 13
7.2 Maximum Conducted O	utput Power	
For the requirements, \square	- Applicable [2] - Tested.] - Not tested by applicant request.]
For the limits,	- Passed Failed	Not judged
7.2.1 Worst Point and Mea	surement Uncertainty	
Min. Limit Margin		<u>5.82</u> dB at <u>5180.0</u> MHz
Remarks: <u>Worst case is</u>	802.11n (20MHz BW) channel 3	6.
Max Output Power		11.79 dBm at <u>5310.0</u> MHz
Remarks: Worst case is	802 11n (40MHz BW) channel 6	9
Uncontainty of Macaurom	ant Deculta	
Oncertainty of measurem	ent Results	<u> </u>
7.2.2 Test Site and Instru	nents	
7.2.2.1 Test Site		
KITA-KANSAI Testing Co	enter	
Test site : SAITO	 Anechoic chamber (A1) Measurement room (M2) Shielded room (S1) Shielded room (S3) 	 Measurement room (M1) Measurement room (M3) Shielded room (S2) Shielded room (S4)
7.2.2.2 Test Instruments		

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
RF Cable	SUCOFLEX102	SUHNER	C-52	2013/7	1 Year
Power Mater	ML2495A	Anritsu	210	2013/12	1 Year
Pulse Power Sensor	MA2411B	Anritsu	212	2013/12	1 Year
Attenuator	54A-10	Weinschel	D-28	2013/9	1 Year
Spectrum Analyzer	E4446A	Agilent	A-39	2013/9	1 Year



Page 29 of 135

7.2.3 Test Method and Test Setup (Diagrammatic illustration)

The maximum conducted output power measurements were carried out connecting to the power meter and the pulse power sensor or spectrum analyzer listed above.

Measurement Method:

- 1) WLAN 20 MHz/40 MHz BW mode
- KDB 789033 D01 E)4)a) Method PM (Measurement using an RF average power meter) 2) WLAN 80 MHz BW mode
 - KDB 789033 D01 E)2)d) Method SA-2 (trace averaging across on and off times of the EUT transmissions, followed by duty cycle correction)

The EUT transmits non-continuously therefore the duty cycle measurements were performed. The measurements of duty cycle and transmission duration were performed connecting to the spectrum analyzer in accordance with KDB 789033 D01 Method B)2) as follows; Span: Zero/ RBW: 5 MHz/ VBW \geq 5 MHz/ Sweep: Auto/ Detector: Peak

(referred documentation is No. G70364M)





Page 30 of 135

7.2.4 Test Data

7.2.5.1 802.11a Maximum conducted output power

<u>Test Date : March 6, 2014</u> <u>Temp.: 22°C, Humi: 25%</u>

Mode of EUT: Tx Mode (802.11a) Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	Power	EBW	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(MHz)	(dBm)	(dB)
36	5180	10.40	0.63	11.03	21.776	17.00	5.97
44	5220	10.41	0.42	10.83	21.390	17.00	6.17
48	5240	10.41	0.73	11.14	21.335	17.00	5.86
52	5260	10.42	0.67	11.09	21.607	24.00	12.91
56	5280	10.42	0.53	10.95	21.199	24.00	13.05
64	5320	10.42	1.04	11.46	21.329	24.00	12.54
100	5500	10.43	0.24	10.67	21.615	24.00	13.33
116	5580	10.43	0.62	11.05	21.508	24.00	12.95
140	5700	10.45	0.76	11.21	21.580	24.00	12.79

The test results (Power) is calculated as follows;

For 36 channel (5180 MHz)

Power = Correction Factor + Meter Reading = 10.40 + (0.63) = 11.03 dBm

Correction Factor = cable loss + 10 dB attenuator + Duty Factor

Duty Factor at 802.11a/ TX rate 6 Mbps is 0.06 dB

Frequency range 5150 MHz to 5250 MHz Limitation is lesser of 17 dBm(50 mW) or 4 dBm + 10log EBW. Frequency range 5250 MHz to 5350 MHz and 5470 MHz to 5725 MHz Limitation is lesser of 24 dBm(250 mW) or 11 dBm + 10log EBW.



Duty Factor = 10 log ((Duty Cycle)/(Burst On-period))= 10 log (1382/(1382-18.4)) = 0.06 dB



Page 31 of 135

7.2.5.2 802.11n (20 MHz BW) Maximum conducted output power

Mode of EUT: Tx Mode (802.11n: 20 MHz)

Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	Power	EBW	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(MHz)	(dBm)	(dB)
36	5180	10.40	0.78	11.18	21.791	17.00	5.82
44	5220	10.41	0.17	10.58	22.165	17.00	6.42
48	5240	10.41	0.30	10.71	21.676	17.00	6.29
52	5260	10.42	0.67	11.09	21.683	24.00	12.91
56	5280	10.42	0.70	11.12	21.880	24.00	12.88
64	5320	10.42	1.18	11.60	22.097	24.00	12.40
100	5500	10.43	-0.09	10.34	21.521	24.00	13.66
116	5580	10.43	0.63	11.06	22.100	24.00	12.94
140	5700	10.45	0.34	10.79	21.992	24.00	13.21

The test results (Power) is calculated as follows;

For 36 channel (5180 MHz)

Power = Correction Factor + Meter Reading = 10.40 + (0.78) = 11.18 dBm

Correction Factor = cable loss + 10 dB attenuator + Duty Factor Duty Factor $= 202.11 \text{ m}(20.011 \text{ m} \text{$

Duty Factor at 802.11n(20 MHz BW) / TX rate 6.5 Mbps is 0.06 dB Frequency range 5150 MHz to 5250 MHz Limitation is lesser of 17 dBm(50 mW) or 4 dBm + 10log EBW. Frequency range 5250 MHz to 5350 MHz and 5470 MHz to 5725 MHz Limitation is lesser of 24 dBm(250 mW) or 11 dBm + 10log EBW.



Duty Factor = 10 log ((Duty Cycle)/(Burst On-period))= 10 log (1294/(1294-18.24)) = 0.06 dB



Page 32 of 135

7.2.5.3 802.11n (40 MHz BW) Maximum conducted output power

Mode of EUT: Tx Mode (802.11n: 40 MHz)

 $Test \ Port : Temporary \ antenna \ connector$

Channel	Frequency	Correction	Meter	Power	EBW	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(MHz)	(dBm)	(dB)
38	5190	10.47	0.53	11.00	42.778	17.00	6.00
46	5230	10.48	0.11	10.59	43.217	17.00	6.41
54	5270	10.49	0.71	11.20	42.479	24.00	12.80
62	5310	10.49	1.30	11.79	43.267	24.00	12.21
102	5510	10.50	-0.09	10.41	43.255	24.00	13.59
134	5670	10.52	0.31	10.83	43.601	24.00	13.17

The test results (Power) is calculated as follows;

For 38 channel (5190 MHz)

Power = Correction Factor + Meter Reading = 10.47 + (0.53) = 11.00 dBm Correction Factor = cable loss + 10 dB attenuator + Duty Factor

```
Duty Factor at 802.11n(40 MHz BW) / TX rate 13.5 Mbps is 0.13 dB
```

Frequency range 5150 MHz to 5250 MHz Limitation is lesser of 17 dBm(50 mW) or 4 dBm + 10log EBW. Frequency range 5250 MHz to 5350 MHz and 5470 MHz to 5725 MHz Limitation is lesser of 24 dBm(250 mW) or 11 dBm + 10log EBW.



Duty Factor = 10 log ((Duty Cycle)/(Burst On-period))= 10 log (654.1/(654.1-19.46)) = 0.13 dB



Page 33 of 135

7.2.5.4 802.11ac (80 MHz BW) Maximum conducted output power

Mode of EUT: Tx Mode (802.11ac: 80 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	Power	EBW	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(MHz)	(dBm)	(dB)
42	5210	10.68	0.28	10.96	83.125	17.00	6.04
58	5290	10.70	0.98	11.68	82.968	24.00	12.32
106	5530	10.71	-0.07	10.64	82.505	24.00	13.36

The test results (Power) is calculated as follows;

For 38 channel (5210 MHz)

Power = Correction Factor + Meter Reading = 10.68 + (0.28) = 10.96 dBm

Correction Factor = cable loss + 10 dB attenuator + Duty Factor

Duty Factor at 802.11ac(80 MHz BW) / TX rate 29.3 Mbps is 0.34 dB

 $\label{eq:starsest} Frequency\ range\ 5150\ MHz\ to\ 5250\ MHz\ Limitation\ is\ lesser\ of\ 17\ dBm(50\ mW)\ or\ 4\ dBm\ +\ 10log\ EBW.$ Frequency\ range\ 5250\ MHz\ to\ 5350\ MHz\ and\ 5470\ MHz\ to\ 5725\ MHz\ Limitation\ is\ lesser\ of

 $24 \text{ dBm}(250 \text{ mW}) \text{ or } 11 \text{ dBm} + 10 \log \text{EBW}.$



Duty Factor = 10 log ((Duty Cycle)/(Burst On-period))= 10 log (267.9/(267.9-19.92)) = 0.34 dB



Page 34 of 135

Output Power Test Plot





Page 35 of 135



JGA JQ Ma St:	A File No. : KL80130675S odel No. : 304SH andard : CFR 47 FCC F	Rules and Regulatio	Issue Date FCC ID ons Part 15	e : April 11, 2014 : APYHRO00205
				Page 36 of 135
7.3 Peak Power Spect	ral Density			
For the requirements	s, ⊠ - Applicable [⊠ - To □ - Not Applicable	ested. 🗌 - Not tes	sted by appl	icant request.]
For the limits,	🛛 - Passed 🗌 - Faile	d 🗌 - Not judge	ed	
7.3.1 Worst Point and	d Measurement Uncertainty			
Min. Limit Margin		3.67	dB at _	<u>5240.0</u> MHz
Uncertainty of Meas	urement Results		-	+/- 1.2 dB
Remarks : <u>Worst ca</u>	se is 802.11a channel 48.			
7.3.2 Test Site and Ir	nstruments			
7.3.2.1 Test Site				
KITA-KANSAI Testi	ng Center			
Test site : SAITO	 Anechoic cham Measurement Shielded room Shielded room 	ber (A1) \square · M coom (M2) \square · M (S1) \square · S (S3) \square · S	Measuremen Measuremen Shielded roon Shielded roon	t room (M1) t room (M3) m (S2) m (S4)


Page 37 of 135

7.3.2.2 Test Instruments

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
RF Cable	SUCOFLEX102	SUHNER	C-52	2013/7	1 Year
Spectrum Analyzer	E4446A	Agilent	A-39	2013/9	1 Year
Attenuator	54A-10	Weinschel	D-28	2013/9	1 Year

7.3.3 Test Method and Test Setup (Diagrammatic illustration)

The peak power spectral density measurements were carried out connecting to the spectrum analyzer. The EUT transmits non-continuously therefore the spectrum analyzer was set in accordance with KDB 789033 D01 Method SA-3 as follows;.

Span: encompass the EBW/ RBW: 1 MHz/ VBW \geq 3 MHz/ Sweep: Time: 100 msec.(enough to be short)/ Number Sweep Points: 1001 pts (\geq 2*Span/RBW)/

Detector: RMS(power averaging)/ Trace Mode: Max. Hold

The peak marker function in the analyzer was use for finding the peak point.

(referred documentation is No. G70364M)





Page 38 of 135

7.3.4 Test Data

7.3.5.1 802.11a Peak power spectral density

<u>Test Date : March 8, 2014</u> <u>Temp.: 21°C, Humi: 25%</u>

Mode of EUT: Tx Mode (802.11a) Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	PPSD	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(dBm)	(dB)
36	5180	10.34	-10.67	-0.33	4.00	4.33
44	5220	10.35	-10.35	0.00	4.00	4.00
48	5240	10.35	-10.02	0.33	4.00	3.67
52	5260	10.36	-9.97	0.39	11.00	10.61
56	5280	10.36	-10.11	0.25	11.00	10.75
64	5320	10.36	-9.46	0.90	11.00	10.10
100	5500	10.37	-10.44	-0.07	11.00	11.07
116	5580	10.37	-10.28	0.09	11.00	10.91
140	5700	10.39	-10.95	-0.56	11.00	11.56

The test results (PPSD) is calculated as follows;

For 36 channel (5180 MHz)

PPSD = Correction Factor + Meter Reading = 10.34 + (-10.67) = -0.33 dBm Correction Factor = cable loss + 10 dB attenuator

802.11a 36ch (5180 MHz)





Page 39 of 135











Page 40 of 135











Page 41 of 135











Page 42 of 135



802.11a 116ch (5580 MHz)







Page 43 of 135

7.3.5.2 802.11n (20 MHz BW) Peak power spectral density

Mode of EUT: Tx Mode (802.11n: 20 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	PPSD	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(dBm)	(dB)
36	5180	10.34	-10.69	-0.35	4.00	4.35
44	5220	10.35	-10.99	-0.64	4.00	4.64
48	5240	10.35	-10.87	-0.52	4.00	4.52
52	5260	10.36	-10.52	-0.16	11.00	11.16
56	5280	10.36	-10.53	-0.17	11.00	11.17
64	5320	10.36	-9.78	0.58	11.00	10.42
100	5500	10.37	-11.39	-1.02	11.00	12.02
116	5580	10.37	-10.84	-0.47	11.00	11.47
140	5700	10.39	-11.84	-1.45	11.00	12.45

The test results (PPSD) is calculated as follows;

For 36 channel (5180 MHz)

PPSD = Correction Factor + Meter Reading = 10.34 + (-10.69) = -0.35 dBm Correction Factor = cable loss + 10 dB attenuator



802.11n (20 MHz BW) 36ch (5180 MHz)



Page 44 of 135



802.11n (20 MHz BW) 44ch (5220 MHz)







Page 45 of 135



802.11n (20 MHz BW) 52ch (5260 MHz)







Page 46 of 135



802.11n (20 MHz BW) 64ch (5320 MHz)







Page 47 of 135



802.11n (20 MHz BW) 116ch (5580 MHz)







Page 48 of 135

7.3.5.3 802.11n (40 MHz BW) Peak power spectral density

Mode of EUT: Tx Mode (802.11n: 40 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	PPSD	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(dBm)	(dB)
38	5190	10.34	-13.69	-3.35	4.00	7.35
46	5230	10.35	-13.78	-3.43	4.00	7.43
54	5270	10.36	-13.07	-2.71	11.00	13.71
62	5310	10.36	-12.25	-1.89	11.00	12.89
102	5510	10.37	-13.94	-3.57	11.00	14.57
134	5670	10.39	-14.54	-4.15	11.00	15.15

The test results (PPSD) is calculated as follows;

For 38 channel (5190 MHz)

PPSD = Correction Factor + Meter Reading = 10.34 + (-13.69) = -3.35 dBm Correction Factor = cable loss + 10 dB attenuator

802.11n (40 MHz BW) 38ch (5190 MHz)





Page 49 of 135



802.11n (40 MHz BW) 46ch (5230 MHz)







Page 50 of 135



802.11n (40 MHz BW) 62ch (5310 MHz)







Page 51 of 135



802.11n (40 MHz BW) 134ch (5670 MHz)



Page 52 of 135

7.3.5.4 802.11ac (80 MHz BW) Peak power spectral density

Mode of EUT: Tx Mode (802.11ac: 80 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Correction	Meter	PPSD	Limit	Margin
	(MHz)	Factor(dB)	Reading(dBm)	(dBm)	(dBm)	(dB)
42	5210	10.34	-16.58	-6.24	4.00	10.24
58	5290	10.36	-15.72	-5.36	11.00	16.36
106	5530	10.37	-16.31	-5.94	11.00	16.94

The test results (PPSD) is calculated as follows;

For 38 channel (5210 MHz)

PPSD = Correction Factor + Meter Reading = 10.34 + (-16.58) = -6.24 dBm Correction Factor = cable loss + 10 dB attenuator

802.11ac (80 MHz BW) 42ch (5210 MHz)





Page 53 of 135



802.11ac (80 MHz BW) 58ch (5290 MHz)





JQA	JQA File No. Model No. Standard	: KL80130675S : 304SH : CFR 47 FCC Rules and	d Regulatior	Issue Date FCC ID as Part 15	e : April 11, 2014 : APYHRO00205
					Page 54 of 135
7.4 Peak Excursi	on				
For the require	ments, 🛛 - App 🗌 - Not	licable [🛛 - Tested. [Applicable	🗌 - Not tes	ted by appli	icant request.]
For the limits,	🖂 - Pas	sed 🗌 - Failed 🗌	- Not judged	l	
7.4.1 Worst Poir	nt and Measuren	ient Uncertainty			
Min. Limit Mar	gin	_	<u>2.51</u> d	B at _	<u>5280.0</u> MHz
Uncertainty of I	Measurement Re	sults		-	+/- 1.2 dB
Remarks: <u>Wo</u> r	rst case is 802.11	a QPSK			
7.4.2 Test Site a	nd Instruments				
7.4.2.1 Test Site	and Instrument	s			
KITA-KANSAI	Testing Center				
Test site : SAI		 Anechoic chamber (A1) Measurement room (M Shielded room (S1) Shielded room (S3) 	$\begin{array}{c c} & \square & -M \\ \hline 2 \end{pmatrix} & \square & -M \\ \hline & \square & -S \\ \hline & \blacksquare & -S \end{array}$	leasuremen leasuremen hielded roor hielded roor	t room (M1) t room (M3) n (S2) n (S4)



Page 55 of 135

7.4.2.2 Test Instruments

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
RF Cable	SUCOFLEX102	SUHNER	C-52	2013/7	1 Year
Spectrum Analyzer	E4446A	Agilent	A-39	2013/9	1 Year
Attenuator	54A-10	Weinschel	D-28	2013/9	1 Year

7.4.3 Test Method and Test Setup (Diagrammatic illustration)

The peak excursion measurements were carried out connecting to the spectrum analyzer. The test was performed in accordance with KDB 789033 D01 as follows;

Sweep 1)

Span: encompass the EBW/ RBW: $1 \text{ MHz}/ \text{VBW} \ge 3 \text{ MHz}/ \text{Sweep: Auto/}$ Detector: Peak/ Trace: Max Hold until trace stabilizes The peak marker function in the analyzer was use for finding the peak point(1)

Sweep 2) Same PPSD measurement

Detector: RMS(power averaging)/ Trace Mode: Max. Hold

The peak marker function in the analyzer was use for finding the peak point(2).

(Peak excursion) = peak point(1) - peak point(2)

(referred documentation is No. G70364M)





Page 56 of 135

7.4.4 Test Data

7.4.5.1 802.11a Peak excursion

<u>Test Date : March 8, 2014</u> <u>Temp.: 21°C, Humi: 25%</u>

Mode of EUT: Tx Mode (802.11a)

Test Port: Temporary antenna connector

Channel	Frequency	Modulation	Peak Excursion	Limit	Margin
	(MHz)	Type	(dB)	(dB)	(dB)
56	5280	BPSK	9.03	13	3.97
56	5280	QPSK	10.49	13	2.51
56	5280	16-QAM	9.38	13	3.62
56	5280	64-QAM	9.09	13	3.91



802.11a 56ch (5280 MHz) BPSK



Page 57 of 135





802.11a 56ch (5280 MHz) 16-QAM





Page 58 of 135



802.11a 56ch (5280 MHz) 64-QAM



Page 59 of 135

7.4.5.2 802.11n/ac (20 MHz BW) Peak excursion

Mode of EUT: Tx Mode (802.11n/ac: 20 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Modulation	Peak Excursion	Limit	Margin
	(MHz)	Туре	(dB)	(dB)	(dB)
56	5280	BPSK	8.72	13	4.28
56	5280	QPSK	9.41	13	3.59
56	5280	16-QAM	9.77	13	3.23
56	5280	64-QAM	9.53	13	3.48
56	5280	256-QAM	7.29	13	5.71

$802.11 \mathrm{n/ac}$ 56ch (5280 MHz) BPSK





Page 60 of 135



802.11n/ac 56ch (5280 MHz) QPSK

802.11n/ac 56ch (5280 MHz) 16-QAM





Page 61 of 135



802.11n/ac 56ch (5280 MHz) 64-QAM

$802.11ac \ 56ch \ (5280 \ MHz) \ 256-QAM$





Page 62 of 135

7.4.5.3 802.11n/ac (40 MHz BW) Peak excursion

Mode of EUT: Tx Mode (802.11n/ac: 40 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Modulation	Peak Excursion	Limit	Margin
	(MHz)	Туре	(dB)	(dB)	(dB)
62	5310	BPSK	9.68	13	3.32
62	5310	QPSK	9.39	13	3.61
62	5310	16-QAM	8.88	13	4.12
62	5310	64-QAM	9.56	13	3.44
62	5310	256-QAM	8.51	13	4.49

802.11n/ac 62ch (5310 MHz) BPSK





Page 63 of 135



802.11n/ac 62ch (5310 MHz) QPSK

802.11n/ac 62ch (5310 MHz) 16-QAM





Page 64 of 135





802.11ac 62ch (5310 MHz) 256-QAM





Page 65 of 135

7.4.5.4 802.11ac (80 MHz BW) Peak excursion

Mode of EUT: Tx Mode (802.11ac: 80 MHz) Test Port: Temporary antenna connector

Channel	Frequency	Modulation	Peak Excursion	Limit	Margin
	(MHz)	Type	(dB)	(dB)	(dB)
58	5290	BPSK	8.30	13	4.70
58	5290	QPSK	7.34	13	5.66
58	5290	16-QAM	7.10	13	5.90
58	5290	64-QAM	7.80	13	5.20
$\overline{58}$	5290	256-QAM	8.85	13	4.15

802.11ac 58ch (5290 MHz) BPSK





Page 66 of 135



802.11ac 58ch (5290 MHz) QPSK

802.11ac 58ch (5290 MHz) 16-QAM





Page 67 of 135





802.11ac 58ch (5290 MHz) 256-QAM



	JQA File No	: : KL80130675S	Is	sue Dat	e ÷ April 11, 2014
	Model No.	$: 304 \mathrm{SH}$	F	CC ID	APYHRO00205
	Standard	CFR 47 FCC Rul	es and Regulations l	Part 15	
					Page 68 of
7.5 AC Powerlin	ne Conducted En	nission			
For the requir	rements, 🛛 - Ap 🗌 - No	pplicable [🛛 - Test ot Applicable	ed. 🗌 - Not tested	l by appl	licant request.]
For the limits	, 🛛 - Ра	ssed 🗌 - Failed	🗌 - Not judged		
7.5.1 Worst Po	oint and Measure	ement Uncertainty			
Min. Limit Ma	argin (Quasi-Pea	nk)	<u> 13.8 </u> dB	at	<u>0.63</u> MHz
Uncertainty o	f Measurement I	Results			<u>+/-2.7</u> dB(2σ)
Remarks :					
7.5.2 Test Site	and Instrument	s			
7.5.2.1 Test Si	te				
KITA-KANSA	A Testing Center	SAITO EMC Branch	1		
🗌 - Anech	noic chamber A1		- Measurement roo	m M1	
🛛 - Mone	uromont room M	<u>я</u> П	- Mossuramont roo	m M3	

- Measurement room M2
 Shielded room S1
 KITA-KANSAI Shielded room
- Measurement room M3
 Shielded room S2
 KITA-KANSAI Anechoic chamber

7.5.2.2 Test Instruments

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
Test Receiver	ESU 26	Rohde & Schwarz	A-6	2013/4	1 Year
AMN (main)	KNW-407R	Kyoritsu	D-39	2013/9	1 Year
RF Cable	RG223/U	SUHNER	H-7	2013/11	1 Year



Page 69 of 135

7.5.3 Test Method and Test Setup (Diagrammatic illustration)

The preliminary tests were performed using the scan mode of test receiver or spectrum analyzer to observe the emissions characteristics of the EUT.

The EUT configuration, cable configuration and mode of operation were determined for producing the maximum level of emissions.

This configurations was used for final tests.

(Reference divisional instruction No. G703649)



NOTE AMN : Artificial Mains Network



7.5.4 Test Data

Page 70 of 135

Mode of EUT : All modes have been investigated and the worst case mode for channel (36ch: 5180MHz / IEEE 802.11a) has been listed.

<u>Test Date: March 14, 2014</u> <u>Temp.: 20 °C, Humi.: 39 %</u>

Frequency	Corr. Factor	Me VA	eter Readi A	ngs [dB(µV) Vl)] B	Lin [dB()	nits µV)]	Rest [dB(j	ults µV)]	Margin	Remarks
[MHz]	[dB]	QP	AVE	QP	AVE	QP	AVE	QP	AVE	[dB]	
0.21	10.2	39.1		36.8		63.2	53.2	49.3		+13.9	-
0.31	10.2	30.2		28.6		60.0	50.0	40.4		+19.6	-
0.41	10.2	27.7		26.4		57.6	47.6	37.9		+19.7	-
0.52	10.1	31.7		28.3		56.0	46.0	41.8		+14.2	-
0.63	10.2	32.0		25.2		56.0	46.0	42.2		+13.8	-
2.57	10.3	31.5		17.7		56.0	46.0	41.8		+14.2	-
4.34	10.4	27.2		16.0		56.0	46.0	37.6		+18.4	-
30.00	11.5	26.2		20.4		60.0	50.0	37.7		+22.3	-



NOTES

- 1. The spectrum was checked from $0.15\ \mathrm{MHz}$ to 30 MHz.
- 2. The correction factor includes the AMN insertion loss and the cable loss.
- 3. The symbol of "<" means "or less".
- 4. The symbol of ">" means "more than".
- 5. The symbol of "--" means "not applicable".
- 6. Calculated result at 0.63 MHz, as the worst point shown on underline: Correction Factor + Meter Reading = $10.2 + 32.0 = 42.2 \text{ dB}(\mu \text{V})$
- 7. QP : Quasi-Peak Detector / AVE : Average Detector
- 8. Test receiver setting(s) : CISPR QP 9 kHz / Average 9 kHz



Page 71 of 135

7.6 Unwanted Radiated Emission

For the requirements,		- Applicable - Not Applic	[🛛 - ' able	Tested.	- []	Not tested by applicant request	.]
For the limits,	\boxtimes	Passed	🗌 - Fai	led 🗌] - No	ot judged	

Worst Point and Measurement Uncertainty 7.6.1

Min. Limit Margin (Average)	<u>>3.1</u> dB at	<u> 39690.0 </u> MHz
Uncertainty of Measurement Results	9 kHz - 30 MHz 30 MHz - 300 MHz 300 MHz - 1000 MHz 1 GHz - 6 GHz 6 GHz - 18 GHz 18 GHz - 40 GHz	$\begin{array}{c c} +/-1.9 & dB(2\sigma) \\ \hline +/-4.3 & dB(2\sigma) \\ \hline +/-5.4 & dB(2\sigma) \\ \hline +/-4.6 & dB(2\sigma) \\ \hline +/-5.2 & dB(2\sigma) \\ \hline +/-5.4 & dB(2\sigma) \end{array}$
Test Distance Test Distance	$9 \mathrm{kHz} - 26 \mathrm{GHz}$ $26 \mathrm{GHz} - 40 \mathrm{GHz}$	<u>3</u> m <u>1</u> m

Remarks: <u>Remarks</u>: Worst case is 802.11n(40 MHz BW) channel 134. The measurement result is within the range of measurement uncertainty.

7.6.2 Test Site and Instruments

7.6.2.1 Test Site

KITA-KANSAI Testing Center SAITO EMC Branch

 \boxtimes - Anechoic chamber A2 - Anechoic chamber A1



Page 72 of 135

7.6.2.2 Test Instruments

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
Test Receiver	ESU 26	Rohde & Schwarz	A-6	2013/4	1 Year
Spectrum Analyzer	E4446A	Agilent	A-39	2013/9	1 Year
Loop Antenna	HFH2-Z2	Rohde & Schwarz	C-2	2013/8	1 Year
RF Cable	RG213/U	SUHNER	H-28	2013/8	1 Year
Biconical Antenna	VHA9103/BBA9106	Schwarzbeck	C-30	2013/5	1 Year
Log-periodic Antenna	UHALP9108-A1	Schwarzbeck	C-31	2013/5	1 Year
RF Cable	S 10162 B-11 etc.	SUHNER	H-4	2013/4	1 Year
Site Attenuation			H-15	2014/1	1 Year
Pre-Amplifier	WJ-6882-824	Watkins Johnson	A-21	2014/1	1 Year
Pre-Amplifier	WJ-6611-513	Watkins Johnson	A-23	2014/1	1 Year
Pre-Amplifier	BZ1840LD1	B&Z	A-29	2014/1	1 Year
Pre-Amplifier	DBL-0618N515	DBS Microwave	A-33	2014/1	1 Year
Horn Antenna	91888-2	EATON	C-41-1	2013/6	1 Year
Horn Antenna	91889-2	EATON	C-41-2	2013/6	1 Year
Horn Antenna	3160-04	EMCO	C-55	2013/7	1 Year
Horn Antenna	3160-05	EMCO	C-56	2013/7	1 Year
Horn Antenna	3160-06	EMCO	C-57	2013/7	1 Year
Horn Antenna	3160-07	EMCO	C-58	2013/7	1 Year
Horn Antenna	3160-08	EMCO	C-59	2013/7	1 Year
Horn Antenna	3160-09	EMCO	C-48	2013/7	1 Year
Horn Antenna	3160-10	EMCO	C-49	2013/7	1 Year
Attenuator	54A-10	Weinschel	D-29	2013/9	1 Year
Attenuator	2-10	Weinschel	D-79	2013/11	1 Year
RF Cable	SUCOFLEX102E	SUHNER	C-75	2014/2	1 Year
RF Cable	SUCOFLEX104	SUHNER	C-66	2014/1	1 Year
RF Cable	SUCOFLEX104	SUHNER	C-67	2014/1	1 Year
RF Cable	SUCOFLEX102EA	SUHNER	C-69	2014/2	1 Year
SVSWR			H-19	2013/9	1 Year
High Pass Filter	HPM13900	MICRO-TRONICS	D-95	2013/2	1 Year
Pre-Amplifier	310N	SONOMA	A-17	2013/4	1 Year


Page 73 of 135

7.6.3 Test Method and Test Setup (Diagrammatic illustration)7.6.3.1 Radiated Emission 9 kHz - 30 MHz

The preliminary tests were performed at the measurement distance that specified for compliance to determine the emission characteristics of the EUT.

The EUT configuration, cable configuration and mode of operation were determined for producing the maximum level of emissions.

This configurations was used for the final tests.

(Reference divisional instruction No. G70364B)





Page 74 of 135

7.6.3.2 Radiated Emission 30 MHz – 1000 MHz

The preliminary tests were performed at the measurement distance that specified for compliance to determine the emission characteristics of the EUT.

The EUT configuration, cable configuration and mode of operation were determined for producing the maximum level of emissions.

This configurations was used for the final tests.

(Reference divisional instruction No. G70364B)





Page 75 of 135

7.6.3.3 Radiated Emission Above 1000 MHz

The preliminary tests were performed at the measurement distance that specified for compliance to determine the emission characteristics of the EUT.

The EUT configuration(in X, Y and Z axis), cable configuration and mode of operation were determined for producing the maximum level of emissions.

This configurations was used for the final tests.

The average unwanted emissions measurements were performed in accordance with KDB 789033 D01 Method VB described in H)6)d) in this document.

The setting of the measuring instruments are shown as follows:

Type	Peak	Average
Detector Function	Peak	RMS
Res. Bandwidth	1 MHz	1 MHz
Video Bandwidth	3 MHz	≥ 1/T *1)
Sweep Time	AUTO	AUTO
Trace	Max Hold	Max Hold

Note: 1. T: Minimum transmission duration

(Reference divisional instruction No. G70364C)





The antenna height is scanned depending on the EUT's size and mounting height.



Page 76 of 135

7.6.4 Test Data

7.6.4.1 Radiated Band Edge

<u>Test Date : March 6, 2014</u> <u>Temp.:20°C, Humi:34%</u>

Mode of EUT : TX mode (802.11a, 36ch: 5180 MHz) Antenna Polarization : Horizontal





Page 77 of 135







Page 78 of 135







Page 79 of 135







Page 80 of 135







Page 81 of 135







Page 82 of 135







Page 83 of 135







Page 84 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 36ch: 5180 MHz) Antenna Polarization : Horizontal





Page 85 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 36ch: 5180 MHz) Antenna Polarization : Vertical





Page 86 of 135







Page 87 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 64ch: 5320 MHz) Antenna Polarization : Vertical





Page 88 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 100ch: 5500 MHz) Antenna Polarization : Horizontal





Page 89 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 100ch: 5500 MHz) Antenna Polarization : Vertical





Page 90 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 140ch: 5700 MHz) Antenna Polarization : Horizontal





Page 91 of 135

Mode of EUT : TX mode (802.11n: 20 MHz BW, 140ch: 5700 MHz) Antenna Polarization : Vertical





Page 92 of 135

Mode of EUT : TX mode (802.11n: 40 MHz BW, 38ch: 5190 MHz) Antenna Polarization : Horizontal





Page 93 of 135

Mode of EUT : TX mode (802.11n: 40 MHz BW, 38ch: 5190 MHz) Antenna Polarization : Vertical





Page 94 of 135







Page 95 of 135







Page 96 of 135

Mode of EUT : TX mode (802.11n: 40 MHz BW, 102ch: 5510 MHz) Antenna Polarization : Horizontal





Page 97 of 135

Mode of EUT : TX mode (802.11n: 40 MHz BW, 102ch: 5510 MHz) Antenna Polarization : Vertical





Page 98 of 135







Page 99 of 135







Page 100 of 135







Page 101 of 135







Page 102 of 135







Page 103 of 135







Page 104 of 135

Mode of EUT : TX mode (802.11ac: 80 MHz BW, 106ch: 5530 MHz) Antenna Polarization : Horizontal





Page 105 of 135







Page 106 of 135

7.6.4.2 Unwanted Radiated Emission 9 kHz - 30 MHz

Test Date : March 14, 2014

Temp.:20°C, Humi:39%

Mode of EUT : All mode have been investigated in accordance with clause 6.4 in this report. Results : No spurious emissions in the range 20dB below the limit.

7.6.4.3 Unwanted Radiated Emission 30 MHz - 1000 MHz

Mode of EUT : All modes have been investigated and the worst case mode for channel (36ch: 5180MHz / IEEE802.11a) has been listed.

							<u>Test l</u> Temp	<u>Date: March</u> .: 20 °C, H	<u>h 14, 2014</u> umi: 39 %
Frequency	Antenna Factor	Cable Loss	Meter Re [dB(µ	eadings (V)]	Limits [dB(µV/m)]	Rest [dB(µ'	ults V/m)]	Margin [dB]	Remarks
[MHz]	[dB(1/m)]	[dB]	Hori.	Vert.		Hori.	Vert.		
30.7	18.6	-27.7	< 25.0	25.8	40.0	< 15.9	16.7	+23.3	-
36.0	16.5	-27.6	< 25.0	27.1	40.0	< 13.9	16.0	+24.0	-
40.5	14.8	-27.5	< 25.0	27.9	40.0	< 12.3	15.2	+24.8	-
192.0	16.3	-26.1	27.9	26.2	43.5	18.1	16.4	+25.4	-
207.6	16.7	-25.9	34.6	31.0	43.5	25.4	21.8	+18.1	-
311.4	14.1	-25.3	33.9	27.1	46.0	22.7	15.9	+23.3	-



NOTES

- 2. The spectrum was checked from 30 MHz to 1000 MHz.
- 3. The symbol of "<" means "or less".
- 4. The symbol of ">" means "more than".
- 5. Calculated result at 207.6 MHz, as the worst point shown on underline:
- Antenna Factor + Cable Loss + Meter Reading = $16.7 + 25.9 + 34.6 = 25.4 \text{ dB}(\mu\text{V/m})$
- 6. Test receiver setting (s) : CISPR QP 120 kHz (QP : Quasi-Peak)

^{1.} Test Distance : 3 m $\,$



Page 107 of 135

7.6.4.4 Unwanted Radiated Emission(Above 1 GHz)

7.6.4.4.1 Mode of TX

7.6.4.4.1.1 802.11a Radiated Emission Above 1 GHz

Mode of EUT : TX mode (802.11a, 5150 - 5250 MHz Band)

<u>Test Date: March 10, 2014</u> <u>Temp.: 19 °C, Humi: 33 %</u>

Frequency Antenna		nna Corr.	Meter Readings [dB(µV)]			Limits		Results		Margin	Remarks	
	Factor	Factor	Ho	rizontal	Ve	rtical	[dB()	µV/m)]	[dB ((µV/m)]	[dB]	
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	РК	AVE	РК	AVE		
Test condition	: Tx 36 Ch											
10360.0	33.5	-26.0	43.2	40.3	42.2	39.0	74.0	54.0	50.7	47.8	+ 6.2	
15540.0	36.5	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.1	< 40.1	> +13.9	
20720.0	40.2	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.4	< 46.4	> + 7.6	
25900.0	40.8	-20.3	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 58.5	< 48.5	> + 5.5	
31080.0	43.9	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.2	< 44.2	> + 9.8	
36260.0	44.2	-28.0	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.2	< 49.2	> + 4.8	
Test condition	: Tx 44 Ch											
10440.0	33.4	-26.0	43.3	40.4	42.2	38.8	74.0	54.0	50.7	47.8	+ 6.2	
15660.0	36.5	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.0	< 40.0	> +14.0	
20880.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5	
26100.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1	
31320.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36540.0	44.4	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.6	< 49.6	> + 4.4	
Test condition	: Tx 48 Ch											
10480.0	33.4	-26.0	43.4	40.6	42.2	39.0	74.0	54.0	50.8	48.0	+ 6.0	
15720.0	36.5	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.0	< 40.0	> +14.0	
20960.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5	
26200.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1	
31440.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36680.0	44.5	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	

Calculated result at 36680.0 MHz, as the worst point shown on underline:

			-					
Antenna Factor	=	44.5	dB(1/m)					
Corr. Factor	=	-27.8	dB					
+) Meter Reading	=	<33.0	dB(µV)					
Result	=	<49.7	dB(µV/m)					
Minimum Margin: 54.0 - <49.7 = >4.3 (dB)								

NOTES

- 1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)
- 2. The spectrum was checked from 1 GHz to 40 GHz.
- 3. The correction factor is shown as follows:
 - Corr. Factor [dB] = Cable Loss + 20dB Pad Att. Pre-Amp. Gain [dB] (1.0 7.6GHz)
 - Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
 - Corr. Factor [dB] = Cable Loss Pre-Amp. Gain [dB] (18 26GHz)
 - Corr. Factor [dB] = Cable Loss Pre-Amp. Gain Distance Factor [dB] (over 26GHz)
- 4. The symbol of "<" means "or less".
- 5. The symbol of ">" means "more than".
- 6. PK : Peak Detector / AVE : RMS Detector



Page 108 of 135

<u>Test Date: March 10, 2014</u> Temp.: 19 °C, Humi: 33 %

Mode of EUT : TX mode (802.11a, 5250 - 5350 MHz Band)

Frequency	Antenna	Corr.		Meter Rea	dings [dB(µ)	V)]	Lir	nits	Re	sults	Margin	Remarks
IMH-1	Factor	Factor	H0 PK	rizontai A VF	ve PK	rtical	ых [ав(†	(V/M)]	DK [ar	μ ν/m)] Δ VF	[013]	
[MHZ]	[ab(1/m)]	լաթյ	IK	AVL	IK	AVE	PK	AVE	IK	AVE		
Test condition	: Tx 52 Ch											
10520.0	33.4	-26.0	44.0	41.4	42.5	39.3	74.0	54.0	51.4	48.8	+ 5.2	
15780.0	36.4	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.9	< 39.9	> +14.1	
21040.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5	
26300.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1	
31560.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36820.0	44.5	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	
Test condition	: Tx 56 Ch											
10560.0	33.4	-26.0	43.6	40.7	42.6	39.2	74.0	54.0	51.0	48.1	+ 5.9	
15840.0	36.4	-26.6	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	
21120.0	40.3	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.6	< 46.6	> + 7.4	
26400.0	40.6	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.8	< 38.8	> +15.2	
31680.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36960.0	44.4	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	
Test condition	: Tx 64 Ch											
10640.0	33.5	-26.0	43.1	40.7	41.9	38.7	74.0	54.0	50.6	48.2	+ 5.8	
15960.0	36.4	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.9	< 39.9	> +14.1	
21280.0	40.4	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.7	< 46.7	> + 7.3	
26600.0	43.4	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.6	< 41.6	> +12.4	
31920.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
37240.0	44.3	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.6	< 49.6	> + 4.4	

Calculated result at 36820.0 MHz, as the worst point shown on underline: Antenna Factor = 44.5 dB(1/m) Corr Factor = -27.8 dB

Corr. Factor	=	-27.8	αв					
+) Meter Reading	=	<33.0	dB(µV)					
Result	=	<49.7	$dB(\mu V/m)$					
Minimum Margin: 54.0 - <49.7 = >4.3 (dB)								

NOTES

- 1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)
- 2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

- Corr. Factor [dB] = Cable Loss + 20dB Pad Att. Pre-Amp. Gain [dB] (1.0 7.6GHz)
- Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain [dB] (18 26GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain Distance Factor [dB] (over 26GHz)
- 4. The symbol of "<" means "or less".
- 5. The symbol of ">" means "more than".
- 6. PK : Peak Detector / AVE : RMS Detector


Page 109 of 135

Mode of EUT : TX mode (802.11a, 5470 - 5725 MHz Band)

Test Date: Ma	rch 10, 2014
Temp.: 19 °C.	Humi: 33 %

Frequency	Antenna	Corr.		Meter Rea	dings [dB(µ`	V)]	Li	nits	Re	sults	Margin	Remarks
	Factor	Factor	Ho	rizontal	Ve	rtical	[dB()	1V/m)]	[dB (μV/m)]	[dB]	
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	РК	AVE	РК	AVE		
Test condition	: Tx 100 Ch											
11000.0	33.5	-25.9	41.1	36.8	42.3	38.3	74.0	54.0	49.9	45.9	+ 8.1	A/B
16500.0	36.2	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	A/B
22000.0	40.5	-21.4	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.1	< 47.1	> + 6.9	A/B
27500.0	43.9	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 52.1	< 42.1	> +11.9	A/B
33000.0	44.0	-29.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.5	< 44.5	> + 9.5	A/B
38500.0	44.3	-27.2	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.1	< 50.1	> + 3.9	A/B
Test condition	: Tx 116 Ch											
11160.0	33.4	-26.1	40.5	36.6	41.4	37.2	74.0	54.0	48.7	44.5	+ 9.5	A/B
16740.0	36.1	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.7	< 39.7	> +14.3	A/B
22320.0	40.6	-21.2	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.4	< 47.4	> + 6.6	A/B
27900.0	43.8	-29.9	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.9	< 41.9	> +12.1	A/B
33480.0	44.0	-29.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.6	< 44.6	> + 9.4	A/B
39060.0	44.3	-27.0	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.3	< 50.3	> + 3.7	A/B
Test condition	: Tx 140 Ch											
11400.0	33.3	-26.2	41.1	37.2	40.1	35.5	74.0	54.0	48.2	44.3	+ 9.7	A/B
17100.0	35.9	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.4	< 39.4	> +14.6	A/B
22800.0	40.5	-21.0	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.5	< 47.5	> + 6.5	A/B
28500.0	43.8	-30.1	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.7	< 41.7	> +12.3	A/B
34200.0	44.0	-29.2	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.8	< 44.8	> + 9.2	A/B
39900.0	44.6	-26.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.8	< 50.8	> + 3.2	A/B

Calculated result at 39900.0 MHz, as the worst point shown on underline: Antenna Factor = 44.6 dB(1/m)

rinconna i accor		11.0	uD(1/m)					
Corr. Factor	=	-26.8	dB					
+) Meter Reading	=	<33.0	dB(µV)					
Result	=	<50.8	$dB(\mu V/m)$					
Minimum Margin: 54.0 - <50.8 = >3.2 (dB)								

NOTES

- 1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)
- 2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

- Corr. Factor [dB] = Cable Loss + 20dB Pad Att. Pre-Amp. Gain [dB] (1.0 7.6GHz)
- Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain [dB] (18 26GHz)
- Corr. Factor [dB] = Cable Loss · Pre·Amp. Gain · Distance Factor [dB] (over 26GHz)
- 4. The symbol of "<" means "or less".
- 5. The symbol of ">" means "more than".
- 6. PK : Peak Detector / AVE : RMS Detector



7.6.4.4.1.2 802.11n (20 MHz) Radiated Emission Above 1 GHz

Mode of EUT : TX mode (802.11n: 20 MHz BW, 5150 - 5250 MHz Band)

Page 110 of 135

<u>Test Date: March 10, 2014</u> Temp.: 19 °C, Humi: 33 %

Frequency	Antenna	Corr.		Meter Rea	dings [dB(µ	V)]	Li	mits	Re	esults	Margin	Remarks					
	Factor	Factor	Ho	rizontal	Ve	rtical	[dB (μV/m)]	[d B((µV/m)]	[dB]						
[MHz]	[dB(1/m)]	Hz] [dB(1/m)]	[dB(1/m)]	$[z] \qquad [dB(1/m)]$	[dB(1/m)]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	PK	AVE	РК	AVE		
Test condition	: Tx 36 Ch																
10360.0	33.5	-26.0	43.2	40.3	42.2	39.0	74.0	54.0	50.7	47.8	+ 6.2						
15540.0	36.5	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.1	< 40.1	> +13.9						
20720.0	40.2	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.4	< 46.4	> + 7.6						
25900.0	40.8	-20.3	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 58.5	< 48.5	> + 5.5						
31080.0	43.9	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.2	< 44.2	> + 9.8						
36260.0	44.2	-28.0	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.2	< 49.2	> + 4.8						
Test condition	: Tx 44 Ch																
10440.0	33.4	-26.0	43.3	40.4	42.2	38.8	74.0	54.0	50.7	47.8	+ 6.2						
15660.0	36.5	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.0	< 40.0	> +14.0						
20880.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5						
26100.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1						
31320.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9						
36540.0	44.4	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.6	< 49.6	> + 4.4						
Test condition	: Tx 48 Ch																
10480.0	33.4	-26.0	43.4	40.6	42.2	39.0	74.0	54.0	50.8	48.0	+ 6.0						
15720.0	36.5	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.0	< 40.0	> +14.0						
20960.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5						
26200.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1						
31440.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9						
36680.0	44.5	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3						

Calculated result at 36680.0 MHz, as the worst point shown on underline: Antenna Factor = 44.5 dB(1/m)

Antenna Pactor	_	44.0	uD(1/III)					
Corr. Factor	=	-27.8	dB					
+) Meter Reading	=	<33.0	dB(µV)					
Result	=	<49.7	$dB(\mu V\!/m)$					
Minimum Margin: 54.0 - <49.7 = >4.3 (dB)								

NOTES

- 1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)
- 2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

- Corr. Factor [dB] = Cable Loss + 20dB Pad Att. Pre-Amp. Gain [dB] (1.0 7.6GHz)
- Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
- Corr. Factor [dB] = Cable Loss · Pre-Amp. Gain [dB] (18 · 26GHz)
- Corr. Factor [dB] = Cable Loss · Pre·Amp. Gain · Distance Factor [dB] (over 26GHz)
- 4. The symbol of "<" means "or less".
- 5. The symbol of ">" means "more than".
- 6. PK : Peak Detector / AVE : RMS Detector



Mode of EUT : TX mode (802.11n: 20 MHz BW, 5250 - 5350 MHz Band)

Page 111 of 135

<u>Test Date: March 10, 2014</u> <u>Temp.: 19 °C, Humi: 33 %</u>

Frequency	Antenna Factor	Corr. Factor	Ho	Meter Read	dings [dB(µ` Ve	V)] rtical	Lir [dB(1	nits 1V/m)]	Re [dB(sults uV/m)]	Margin [dB]	Remarks
[MHz]	[dB(1/m)]	[dB]	PK	AVE	РК	AVE	PK	AVE	PK	AVE	[ub]	
Test condition	: Tx 52 Ch											
10520.0	33.4	-26.0	44.0	41.4	42.5	39.3	74.0	54.0	51.4	48.8	+ 5.2	
15780.0	36.4	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.9	< 39.9	> +14.1	
21040.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5	
26300.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1	
31560.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36820.0	44.5	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	
Test condition	: Tx 56 Ch											
10560.0	33.4	-26.0	43.6	40.7	42.6	39.2	74.0	54.0	51.0	48.1	+ 5.9	
15840.0	36.4	-26.6	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	
21120.0	40.3	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.6	< 46.6	> + 7.4	
26400.0	40.6	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.8	< 38.8	> +15.2	
31680.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36960.0	44.4	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	
Test condition	: Tx 64 Ch											
10640.0	33.5	-26.0	43.1	40.7	41.9	38.7	74.0	54.0	50.6	48.2	+ 5.8	
15960.0	36.4	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.9	< 39.9	> +14.1	
21280.0	40.4	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.7	< 46.7	> + 7.3	
26600.0	43.4	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.6	< 41.6	> +12.4	
31920.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
37240.0	44.3	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.6	< 49.6	> + 4.4	

Calculated result at 36820.0 MHz, as the worst point shown on underline:

Antenna Factor	=	44.5	dB(1/m)
Corr. Factor	=	-27.8	dB

- +) Meter Reading = $<33.0 \text{ dB}(\mu \text{V})$
- $\frac{1}{\text{Result}} = \frac{1}{\text{Result}} = \frac{1}{\text{Res$

Minimum Margin: 54.0 - <49.7 = >4.3 (dB)

NOTES

- 1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)
- 2. The spectrum was checked from 1 GHz to 40 GHz.
- 3. The correction factor is shown as follows:
 - Corr. Factor [dB] = Cable Loss + 20dB Pad Att. Pre-Amp. Gain [dB] (1.0 7.6GHz)
 - Corr. Factor [dB] = Cable Loss + 10dB Pad Att. · Pre-Amp. Gain [dB] (7.6 · 18.0GHz)
- Corr. Factor [dB] = Cable Loss · Pre-Amp. Gain [dB] (18 · 26GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

- 5. The symbol of ">" means "more than".
- 6. PK : Peak Detector / AVE : RMS Detector



Mode of EUT : TX mode (802.11n: 20 MHz BW, 5470 - 5725 MHz Band)

Page 112 of 135

<u>Test Date: March 10, 2014</u> <u>Temp.: 19 °C, Humi: 33 %</u>

Frequency	Antenna	Corr.	TT -	Meter Rea	dings [dB(µ)	V)]	Li	mits	Re	esults	Margin	Remarks
[MHz]	Factor [dB(1/m)]	Factor [dB]	но PK	rizontai AVE	ve PK		[ав() РК	uv/m)j AVE	Lar Lar	µv/m)] AVE	[ar]	
[]	[[]										
Test condition	: Tx 100 Ch											
11000.0	33.5	-25.9	41.1	36.8	42.3	38.3	74.0	54.0	49.9	45.9	+ 8.1	A/B
16500.0	36.2	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	A/B
22000.0	40.5	-21.4	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.1	< 47.1	> + 6.9	A/B
27500.0	43.9	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 52.1	< 42.1	> +11.9	A/B
33000.0	44.0	-29.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.5	< 44.5	> + 9.5	A/B
38500.0	44.3	-27.2	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.1	< 50.1	> + 3.9	A/B
Test condition	• Ty 116 Ch											
11160.0	33.4	-26.1	40.5	36.6	41.4	37.2	74.0	54.0	48.7	44.5	+ 9.5	A/B
16740 0	36 1	-26 4	< 40 0	< 30 0	< 40 0	< 30 0	74 0	54 0	< 49 7	< 39 7	> +14 3	A/B
22320 0	40 6	-21 2	< 38 0	< 28 0	< 38 0	< 28 0	74 0	54 0	< 57 4	< 47 4	> + 6 6	A/B
27900 0	43 8	-29 9	< 38 0	< 28 0	< 38 0	< 28 0	74 0	54 0	< 51 9	< 41 9	> +12 1	A/B
33480 0	44 0	-29.4	< 40 0	< 30.0	< 40 0	< 30.0	74 0	54 0	< 54 6	< 44 6	> + 9 4	A/B
39060.0	44.3	-27.0	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.3	< 50.3	> + 3.7	A/B
Test condition	: Tx 140 Ch											
11400.0	33.3	-26.2	41.1	37.2	40.1	35.5	74.0	54.0	48.2	44.3	+ 9.7	A/B
17100.0	35.9	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.4	< 39.4	> +14.6	A/B
22800.0	40.5	-21.0	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.5	< 47.5	> + 6.5	A/B
28500.0	43.8	-30.1	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.7	< 41.7	> +12.3	A/B
34200.0	44.0	-29.2	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.8	< 44.8	> + 9.2	A/B
39900.0	44.6	-26.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.8	< 50.8	> + 3.2	A/B

Calculated result at 39900.0 MHz, as the worst point shown on underline:

Antenna Factor	=	44.6 dB(1/r	n)
Corr. Factor	=	-26.8 dB	

- Corr. Factor = 20.8 dB
- +) Meter Reading = $<33.0 \text{ dB}(\mu \text{V})$ Result = $<50.8 \text{ dB}(\mu \text{V/m})$

Result = <50.8 Minimum Margin: 54.0 - <50.8 = >3.2 (dB)

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from $1\,\mathrm{GHz}$ to $40\,\mathrm{GHz}.$

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

Corr. Factor [dB] = Cable Loss + 10dB Pad Att. - Pre-Amp. Gain [dB] (7.6 - 18.0GHz)

Corr. Factor [dB] = Cable Loss · Pre-Amp. Gain [dB] (18 · 26GHz)

Corr. Factor [dB] = Cable Loss · Pre·Amp. Gain · Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



7.6.4.4.1.3 802.11n (40 MHz) Radiated Emission Above 1 GHz

Mode of EUT : TX mode (802.11n: 40 MHz BW, 5150 - 5250 MHz Band)

Page 113 of 135

<u>Test Date: March 10, 2014</u> Temp.: 19 °C, Humi: 33 %

Frequency Antenr		ntenna Corr.		Meter Readings [dB(µV)]				Limits		sults	Margin	Remarks
	Factor	Factor	Ног	izontal	Ve	rtical	[dB()	ıV/m)]	[dB ([µV/m)]	[dB]	
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	РК	AVE	РК	AVE		
Test condition	: Tx 38 Ch											
10380.0	33.5	-26.0	44.1	41.4	43.5	40.9	74.0	54.0	51.6	48.9	+ 5.1	
15570.0	36.5	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.1	< 40.1	> +13.9	
20760.0	40.2	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.4	< 46.4	> + 7.6	
25950.0	40.8	-20.3	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 58.5	< 48.5	> + 5.5	
31140.0	43.9	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.2	< 44.2	> + 9.8	
36330.0	44.2	-28.0	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.2	< 49.2	> + 4.8	
Test condition	: Tx 46 Ch											
10460.0	33.4	-26.0	43.4	40.7	43.2	40.6	74.0	54.0	50.8	48.1	+ 5.9	
15690.0	36.5	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.0	< 40.0	> +14.0	
20920.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5	
26150.0	40.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.9	< 38.9	> +15.1	
31380.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36610.0	44.4	-27.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.6	< 49.6	> + 4.4	

Calculated result at 36610.0 MHz, as the worst point shown on underline: Antenna Factor = 44.4 dB(1/m)Corr. Factor = 27.8 dB+) Meter Reading = $33.0 \text{ dB}(\mu \text{V})$

Minimum Margin: 54.0 - <49.6 = >4.4 (dB)

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

- Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain [dB] (18 26GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



Page 114 of 135

Mode of EUT : TX mode (802.11n: 40 MHz BW, 5250 - 5350 MHz Band)

Test Date	Ma	rch	10,	20	14
Temp. 19	°C.	Hu	mi	33	%

Frequency	Antenna	Corr.		Meter Rea	dings [dB(µ	V)]	Lir	nits	Re	sults	Margin	Remarks
	Factor	Factor	Hor	izontal	Ve	rtical	[dB(µ	ιV/m)]	[dB (μV/m)]	[dB]	
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	РК	AVE	РК	AVE		
Test condition :	: Tx 54 Ch											
10540.0	33.4	-26.0	43.7	40.9	43.1	39.8	74.0	54.0	51.1	48.3	+ 5.7	
15810.0	36.4	-26.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.9	< 39.9	> +14.1	
21080.0	40.3	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.6	< 46.6	> + 7.4	
26350.0	40.6	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.8	< 38.8	> +15.2	
31620.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36890.0	44.5	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.8	< 49.8	> + 4.2	
Test condition .	T. 62 Ch											
10620 0	33 A	-26 0	42 3	2 Q Q	43 3	40 4	74 0	54 0	50 7	47 8	+ 6 2	
15020.0	26 1	-20.0	42.5	- 20 0	43.3	40.4	74.0	54.0	- 10 0	- 20 0	+ 0.2	
15930.0	30.4	-20.0	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.0	< 39.0	> +14.2	
21240.0	40.3	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.6	< 46.6	> + 7.4	
26550.0	43.5	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.7	< 41.7	> +12.3	
31860.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
37170.0	44.4	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	

Calculated result at 36890.0 MHz, as the worst point shown on underline:

Antenna Factor	=	44.5	dB(1/m)
Corr. Factor	=	-27.7	dB
+) Meter Reading	=	<33.0	dB(µV)
Result	=	<49.8	dB(µV/m)
	1		

Minimum Margin: 54.0 - <49.8 = >4.2 (dB)

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

- Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain [dB] (18 26GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain - Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



Page 115 of 135

Mode of EUT : TX mode (802.11n: 40 MHz BW, 5470 - 5725 MHz Band)

Test Date: Ma	arch 10,	2014
Temp.: 19 °C.	Humi	33%

Frequency	Antenna	Corr.		Meter Read	dings [dB(µ`	V)]	Li	mits	Re	sults	Margin	Remarks
	Factor	Factor	Ног	izontal	Ve	rtical	[dB()	ıV/m)]	[dB (μV/m)]	[dB]	
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	РК	AVE	РК	AVE		
Test condition	: Tx 102 Ch											
11020.0	33.5	-25.9	40.2	36.1	41.9	38.5	74.0	54.0	49.5	46.1	+ 7.9	
16530.0	36.1	-26.3	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	
22040.0	40.5	-21.4	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.1	< 47.1	> + 6.9	
27550.0	43.8	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 52.0	< 42.0	> +12.0	
33060.0	44.0	-29.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.5	< 44.5	> + 9.5	
38570.0	44.3	-27.2	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.1	< 50.1	> + 3.9	
Test condition	: Tx 134 Ch											
11340.0	33.3	-26.2	41.0	37.2	40.4	36.3	74.0	54.0	48.1	44.3	+ 9.7	
17010.0	36.0	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.6	< 39.6	> +14.4	
22680.0	40.5	-21.0	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.5	< 47.5	> + 6.5	
28350.0	43.8	-30.0	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.8	< 41.8	> +12.2	
34020.0	44.0	-29.3	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.7	< 44.7	> + 9.3	
39690.0	44.7	-26.8	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.9	< 50.9	> + 3.1	

Minimum Margin: 54.0 - <50.9 = >3.1 (dB)

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

- Corr. Factor [dB] = Cable Loss + 10dB Pad Att. Pre-Amp. Gain [dB] (7.6 18.0GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain [dB] (18 26GHz)
- Corr. Factor [dB] = Cable Loss Pre-Amp. Gain Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



7.6.4.4.1.4 802.11ac (80 MHz) Radiated Emission Above 1 GHz

Mode of EUT : TX mode (802.11ac: 80 MHz BW, 5150 - 5250 MHz Band)

Page 116 of 135

Test Date:	Ma	rch	10,	20	14
Temp:19	°C	Hu	mi	33	%

Frequency	Antenna	Corr.	Meter Readings $[dB(\mu V)]$				Limits		Results		Margin	Remarks
	Factor	Factor	Ho	rizontal	Ve	rtical	[dB()	uV/m)]	[dB (μV/m)]	[dB]	
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	РК	AVE	РК	AVE		
Test condition	: Tx 42 Ch											
10420.0	33.4	-26.0	43.2	40.3	43.2	40.9	74.0	54.0	50.6	48.3	+ 5.7	
15630.0	36.5	-26.4	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 50.1	< 40.1	> +13.9	
20840.0	40.3	-21.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.5	< 46.5	> + 7.5	
26050.0	40.7	-20.3	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 58.4	< 48.4	> + 5.6	
31260.0	43.8	-29.7	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.1	< 44.1	> + 9.9	
36470.0	44.3	-27.9	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.4	< 49.4	> + 4.6	

Calculated result at 36470.0 MHz, as the worst point shown on underline:

Antenna Factor	=	44.3	dB(1/m)
Corr. Factor	=	-27.9	dB
+) Meter Reading	=	<33.0	dB(µV)
Result	=	<49.4	dB(µV/m)
35 1	1 0 (17		

Minimum Margin: 54.0 - <49.4 = >4.6 (dB)

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

Corr. Factor [dB] = Cable Loss + 10dB Pad Att. - Pre-Amp. Gain [dB] (7.6 - 18.0GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain [dB] (18 - 26GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain - Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



Page 117 of 135

Mode of EUT : TX mode (802.11ac: 80 MHz, 5250 - 5350 MHz Band)

Test Date:	Ma	rch	10,	20	14
Temp.: 19	°C.	Hu	mi	33	%

Frequency	Antenna Factor	Corr. Meter R Eactor Horizontal		Meter Read	idings [dB(µV)] Vertical		Limits [dB(uV/m)]		Results		Margin [dB]	Remarks
[MHz]	[dB(1/m)]	[dB]	PK	AVE	РК	AVE	PK	AVE	PK	AVE	լայ	
Test condition :	Tx 58 Ch											
10580.0	33.4	-26.0	44.3	42.0	43.0	39.8	74.0	54.0	51.7	49.4	+ 4.6	
15870.0	36.4	-26.6	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	
21160.0	40.3	-21.7	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 56.6	< 46.6	> + 7.4	
26450.0	40.6	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 48.8	< 38.8	> +15.2	
31740.0	43.8	-29.6	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.2	< 44.2	> + 9.8	
37030.0	44.4	-27.7	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 59.7	< 49.7	> + 4.3	

Calculated result at 37030.0 MHz, as the worst point shown on underline:

 $\begin{array}{rcl} Antenna \ Factor &=& 44.4 \ dB(1/m) \\ Corr. \ Factor &=& -27.7 \ dB \\ + \) \ \underline{Meter \ Reading} &=& <33.0 \ dB(\mu V) \\ \hline Result &=& <49.7 \ dB(\mu V/m) \\ \end{array}$ $\begin{array}{rcl} Minimum \ Margin: \ 54.0 \ \cdot \ <49.7 \ =>4.3 \ (dB) \end{array}$

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

Corr. Factor [dB] = Cable Loss + 10dB Pad Att. · Pre·Amp. Gain [dB] (7.6 · 18.0GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain [dB] (18 - 26GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain - Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



Page 118 of 135

Mode of EUT : TX mode (802.11ac: 80 MHz, 5470 - 5725 MHz Band)

Test Date:	Ma	rch	10,	20	14
Temp.: 19	°C.	Hu	mi:	33	%

Frequency	Antenna Factor	Corr. Factor	Ho	Meter Read	lings [dB(پر Ve	V)] rtical	Lir [dB(1	nits 1V/m)]	Re [dB(sults uV/m)]	Margin [dB]	Remarks
[MHz]	[dB(1/m)]	[dB]	РК	AVE	РК	AVE	PK	AVE	PK	AVE	L.]	
Test condition	: Tx 106 Ch											
11060.0	33.5	-26.0	42.3	38.8	43.3	40.4	74.0	54.0	50.8	47.9	+ 6.1	
16590.0	36.1	-26.3	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 49.8	< 39.8	> +14.2	
22120.0	40.6	-21.4	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 57.2	< 47.2	> + 6.8	
27650.0	43.7	-29.8	< 38.0	< 28.0	< 38.0	< 28.0	74.0	54.0	< 51.9	< 41.9	> +12.1	
33180.0	44.0	-29.5	< 40.0	< 30.0	< 40.0	< 30.0	74.0	54.0	< 54.5	< 44.5	> + 9.5	
38710.0	44.3	-27.2	< 43.0	< 33.0	< 43.0	< 33.0	74.0	54.0	< 60.1	< 50.1	> + 3.9	

Calculated result at 38710.0 MHz, as the worst point shown on underline:

 $\begin{array}{rcl} Antenna \ Factor &=& 44.3 \ dB(1/m) \\ Corr. \ Factor &=& -27.2 \ dB \\ + \) \ \underline{Meter \ Reading} &=& <33.0 \ dB(\mu V) \\ \hline Result &=& <50.1 \ dB(\mu V/m) \\ \end{array}$ $\begin{array}{rcl} Minimum \ Margin: \ 54.0 \ \cdot \ <50.1 \ =>3.9 \ (dB) \end{array}$

NOTES

1. Test Distance : 3 m (1 GHz to 26 GHz) / 1m (26 GHz to 40 GHz)

2. The spectrum was checked from 1 GHz to 40 GHz.

3. The correction factor is shown as follows:

Corr. Factor [dB] = Cable Loss + 20dB Pad Att. - Pre-Amp. Gain [dB] (1.0 - 7.6GHz)

Corr. Factor [dB] = Cable Loss + 10dB Pad Att. - Pre-Amp. Gain [dB] (7.6 - 18.0GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain [dB] (18 - 26GHz)

Corr. Factor [dB] = Cable Loss - Pre-Amp. Gain - Distance Factor [dB] (over 26GHz)

4. The symbol of "<" means "or less".

5. The symbol of ">" means "more than".



operating mode of 20MHz/40MHz BW. (Refer to the KDB publication 848637.)

7.7.2 Test Site

KITA-KANSAI Testing Center

- Anechoic chamber (A1)
 Measurement room (M2)
- □ Measurement room (M1)
- □ Measurement room (M3)
- □ Shielded room (S2)
- \boxtimes Shielded room (S4)
- Shielded room (S1)
 Shielded room (S3)



Page 120 of 135

7.7.3 Test Instruments

Туре	Model	Manufacturer	ID No.	Last Cal.	Interval
Spectrum Analyzer	E4446A	Agilent	A-39	2013/9	1 Year
Vector Signal Generator	MG3710A	Anritsu	B41	2013/9	1 Year
Horn Antenna(*1)	3160-05	EMCO	C-56	2013/7	1 Year
Double-Ridge Guide Horn Antenna(*2)	TR17206	ADVANTEST	C-29	2013/6	1 Year
RF Cable(*1)	SUCOFLEX104	SUHNER	C-67	2014/1	1 Year
RF Cable(*2)	SUCOFLEX102E	SUHNER	C-70	2013/11	1 Year

(*1) Radar Antenna and the cable

(*2) Monitor Antenna and the cable

7.7.4 Test Method and Test Setup (Diagrammatic illustration)

The Dynamic Frequency Selection(DFS) measurements were carried out in accordance with FCC Part 15.407(h) and FCC 06-96 Appendix " COMPLIANCE MEASUREMENT PROCEDURES FOR UNII DEVICES OPERATIONG IN THE 5250-5350 MHz AND 5470-5725 MHz BANDS INCORPORATING DYNAMIC FREQUENCY SELECTION".

7.7.4.1 DFS Detection Threshold and DFS Response Requirement

DFS Detection Thresholds for Master Devices and Client Devices With Radar Detection

Maximum Transmit Power	Value
	(See Notes 1 and 2)
\geq 200 milliwatt	-64 dBm
< 200 milliwatt	-62 dBm

Note 1: This is the level at the input of the receiver assuming a 0 dBi receive antenna.

Note 2: Throughout these test procedures an additional 1 dB has been added to the amplitude of the test transmission waveforms to account for variations in measurement equipment. This will ensure that the test signal is at or above the detection threshold level to trigger a DFS response.



Page 121 of 135

Table 4: DFS	Response	Requirement	Values

Parameter	Value
Non-Occupancy Period	Minimum 30 minutes
Channel Availability Check Time	60 seconds
Channel Move Time	10 seconds (See Note 1.)
Channel Closing Transmission Time	200 milliseconds + an aggregate of 60 milliseconds over
	remaining 10 second period. (See Notes 1 and 2.)
U-NII Detection Bandwidth	Minimum 80% of the U-NII 99% transmission power
	bandwidth. (See Note 3.)

Note 1: The instant that the Channel Move Time and the Channel Closing Transmission Time begins is as follows:

- For the Short Pulse Radar Test Signals this instant is the end of the Burst.
- For the Frequency Hopping radar Test Signal, this instant is the end of the last radar Burst generated.
 For the Long Pulse Radar Test Signal this instant is the end of the 12 second period defining the Radar
- For the Long Pulse Radar Test Signal this instant is the end of the 12 second period defining the Radar Waveform.

Note 2: The Channel Closing Transmission Time is comprised of 200 milliseconds starting at the beginning of the Channel Move Time plus any additional intermittent control signals required to facilitate a Channel move (an aggregate of 60 milliseconds) during the remainder of the 10 second period. The aggregate duration of control signals will not count quiet periods in between transmissions.

Note 3: During the U-NII Detection Bandwidth detection test, radar type 1 is used and for each frequency step the minimum percentage of detection is 90 percent. Measurements are performed with no data traffic.

7.7.4.2 Radar Test Waveforms

This section provides the parameters for required test waveforms, minimum percentage of successful detections, and the minimum number of trials that must be used for determining DFS conformance. Step intervals of 0.1 microsecond for Pulse Width, 1 microsecond for PRI, 1 MHz for chirp width and 1 for the number of pulses will be utilized for the random determination of specific test waveforms.

Radar	Pulse Width	PRI	Number	Minimum	Minimum
Туре	(µsec)	(µsec)	of Pulses	Percentage of	Number of
				Successful	Trials
				Detection	
1	1	1428	18	60%	30
2	1-5	150-230	23-29	60%	30
3	6-10	200-500	16-18	60%	30
4	11-20	200-500	12-16	60%	30
Aggregate (Radar Types 1-4)			80%	120	

Short Pulse Radar Test Waveforms

A minimum of 30 unique waveforms are required for each of the Short Pulse Radar Types 2 through 4. For Short Pulse Radar Type 1, the same waveform is used a minimum of 30 times. If more than 30 waveforms are used for Short Pulse Radar Types 2 through 4, then each additional waveform must also be unique and not repeated from the previous waveforms. The aggregate is the average of the percentage of successful detections of Short Pulse Radar Types 1-4.



Page 122 of 135

Long Pulse Radar Test Waveforms

0							
Radar	Pulse Width	Chirp	PRI	Number	Number	Minimum	Minimum
Type	(µsec)	Width	(µsec)	of Pulses	of Bursts	Percentage of	Number of
		(MHz)		per Burst		Successful	Trials
						Detection	
5	50-100	5-20	1000-2000	1-3	8-20	80%	30

The parameters for this waveform are randomly chosen. Thirty unique waveforms are required for the Long Pulse Radar Type waveforms. If more than 30 waveforms are used for the Long Pulse Radar Type waveforms, then each additional waveform must also be unique and not repeated from the previous waveforms. Each waveform is defined as follows:

1) The transmission period for the Long Pulse Radar test signal is 12 seconds.

- 2) There are a total of 8 to 20 Bursts in the 12 second period, with the number of Bursts being randomly chosen. This number is Burst_Count.
- 3) Each Burst consists of 1 to 3 pulses, with the number of pulses being randomly chosen. Each Burst within the 12 second sequence may have a different number of pulses.
- 4) The pulse width is between 50 and 100 microseconds, with the pulse width being randomly chosen. Each pulse within a Burst will have the same pulse width. Pulses in different Bursts may have different pulse widths.
- 5) Each pulse has a linear frequency modulated chirp between 5 and 20 MHz, with the chirp width being randomly chosen. Each pulse within a Burst will have the same chirp width. Pulses in different Bursts may have different chirp widths. The chirp is centered on the pulse. For example, with a radar frequency of 5300 MHz and a 20 MHz chirped signal, the chirp starts at 5290 MHz and ends at 5310 MHz.
- 6) If more than one pulse is present in a Burst, the time between the pulses will be between 1000 and 2000 microseconds, with the time being randomly chosen. If three pulses are present in a Burst, the random time interval between the first and second pulses is chosen independently of the random time interval between the second and third pulses.
- 7) The 12 second transmission period is divided into even intervals. The number of intervals is equal to Burst_Count. Each interval is of length (12,000,000 / Burst_Count) microseconds. Each interval contains one Burst. The start time for the Burst, relative to the beginning of the interval, is between 1 and [(12,000,000 / Burst_Count) (Total Burst Length) + (One Random PRI Interval)] microseconds, with the start time being randomly chosen. The step interval for the start time is 1 microsecond. The start time for each Burst is chosen independently.

ricqueii	requeitey hopping hadar rest wavelorm						
Radar	Pulse	PRI	Pulses	Hopping	Hopping	Minimum	Minimum
Type	Width	(µsec)	per	Rate	Sequence	Percentage of	Number of
	(µsec)		Hop	(kHz)	Length	Successful	Trials
					(msec)	Detection	
6	1	333	9	0.333	300	70%	30

Frequency Hopping Radar Test Waveform

For the Frequency Hopping Radar Type, the same Burst parameters are used for each waveform. The hopping sequence is different for each waveform and a 100-length segment is selected from the hopping sequence defined by the following algorithm:

The first frequency in a hopping sequence is selected randomly from the group of 475 integer frequencies from 5250 - 5724 MHz. Next, the frequency that was just chosen is removed from the group and a frequency is randomly selected from the remaining 474 frequencies in the group. This process continues until all 475 frequencies are chosen for the set. For selection of a random frequency, the frequencies remaining within the group are always treated as equally likely.



Page 123 of 135

7.7.4.3 Rader Waveform Calibration



The EUT is the client device without radar detection, then master device is a RDD. Therefore the radar test signal level is set at the Radar Detection Threshold Level of master device.

The Radar Detection Threshold Level is employed -64dBm + 1dB = -63 dBm at the antenna port.

Where the antenna gain of master device is X dBi then the threshold level is corrected as

"-63 – X" dBm (Rated output power and Antenna Gain of the master device is described in EUT Description).

The spectrum analyzer is connected to the monitor antenna via a coaxial cable. The antenna is set vertical polarization for testing. The reference level offset of a spectrum analyzer set to "Monitoring Antenna Gain – Cable loss". The Radar Signal Generator is set to CW output mode and the signal level is adjusted to "-63 – X" dBm on the spectrum analyze setting as below;

Frequency: Radar Signal Frequency Span: Zero Span(Time Domain) RBW/VBW: 3 MHz Detection: Peak

The spectrum analyzer plots of the calibrated radar waveform on the Channel frequency is attached in clause 7.7.5.1 in this report.



Page 124 of 135

7.7.4.4 Test Setup and Operation Radiated Method



Support Equipment: The following support equipment was used for in this DFS testing

Item	Manufacturer	Model No.	Serial No.	FCC ID
Wireless Access Point	Cisco	AIR-AP1042N-A-K9	FTX1637E2NC	LDK102070
AC Adaptor for AP	Cisco	AA2548L	ALD0516GFDA	N/A
PC(Controller/Server)	HP Compaq	D330 uT	JPA42500TB	DoC

Used Test File and Displayed Traffic Level Adjustment:

The test is performed with the designated MPEG test file that is streamed from the access point to the client in full motion video mode using the media player with the V2.61 Codec package. This file is used by IP and Frame based systems for loading the test channel during the In-service compliance testing of the U-NII device.

By control PC, the radio link is established between the master and slave and the test file in saver(PC) is streamed via master(access point) to generate WLAN traffic.

The monitoring antenna is adjusted so that the WLAN traffic level on the spectrum analyzer is lower than the radar detection threshold level.

The spectrum analyzer plots of the slave(EUT) data traffic plot is attached in clause 7.7.5.2 and the nominal noise floor plots is attached in clause 7.7.5.3 in this report.



Page 125 of 135 $\,$

7.7.4.5 Description of EUT

Item	Specification
Operating Frequency(MHz)	5150 to 5250 / 5250 to 5350 / 5470 to 5725
Operating Mode of EUT	Client(Slave) Device without Radar Detection
FCC ID for Master Device(*1)	LDK102070 (Antenna Gain: 3.0 dBi)
Antenna Type of EUT	Inverted-L Type Antenna
Highest Power Level(EIRP)/	802.11a/n/ac 12.0 dBm Max.
Antenna Gain of EUT	802.11n/ac(40 MHz BW) 12.0 dBm Max.
	802.11ac(80 MHz) 12.0 dBm Max.
	Antenna Gain: 0 dBi
System Architecture	IEEE802.11 a/n/ac, IP based system
TPC Description	N/A(Not Required EIRP below 500 mW)
Data Rate/ Channel Bandwidth	Refer below table.
Power-on Cycle	N/A(No Channel Availability Check Function)

(*1) The rated output power of the master device is greater than 20dBm(EIRP), then the interference threshold level is employed -64 dBm. After correction for procedural adjustments, the radiated threshold level at the master device is -64 + 1 - 3 dBi(Master antenna Gain) = -66 dBm.

Data Rate/ Channel Bandwidth

	IEEE802.11 a			IEEE802.11 n			
Modulation	Data Rate	Channel	Modulation	Data Rat	te(Mbps)		
	(Mbps)	Bandwidth		Channel Ban	dwidth(MHz)		
		(MHz)		20	40		
BPSK	6	20	BPSK	6.5	13.5		
BPSK	9	20	QPSK	13.0	27.0		
QPSK	12	20	QPSK	19.5	40.5		
QPSK	18	20	16-QAM	26.0	54.0		
16-QAM	24	20	16-QAM	39.0	81.0		
16-QAM	36	20	64-QAM	52.0	108.0		
64-QAM	48	20	64-QAM	58.5	121.5		
64-QAM	54	20	64-QAM	65.0	135.0		
	IEEE80)2.11 ac					

IEEE802.11 ac								
Modulation	Data Rate(Mbps)							
	Channel Bandwidth(MHz)							
	20	20 40 80						
BPSK	6.5	13.5	29.3					
QPSK	13.0	27.0	58.5					
QPSK	19.5	40.5	87.8					
16-QAM	26.0	54.0	117.0					
16-QAM	39.0	81.0	175.5					
64-QAM	52.0	108.0	234.0					
64-QAM	58.5	121.5	263.3					
64-QAM	65.0	135.0	292.5					
$256 \cdot \text{QAM}$	78.0	$16\overline{2.0}$	351.0					
256-QAM	N/A	180.0	390.0					

7.7.4.6 Deviation to the procedures and equipment from the standards:

There is no deviation from FCC Rule and FCC 06-96.



7.7.5 Test Data

Page 126 of 135

<u>Test Date : March 13, 2014</u> <u>Temp.: 22°C, Humi: 45%</u>

7.7.5.1 Radar Waveform Calibration Results (Type 1 Short Pulse)





Page 127 of 135

7.7.5.2 EUT (Slave) Traffic Plots









Page $128 \ \mathrm{of} \ 135$

7.7.5.3 No Traffic (Noise Floor) Plots



#VBW 3 MHz Sweep 16 s (8001 pts)



Page 129 of 135

7.7.5.4 Channel Move Time

The channel move time is measured using delta-marker function of the spectrum analyzer. The reference marker is adjusted at the end of radar pulse and the delta marker is adjusted at the end the WLAN transmission. The displayed delta value is the result of move time. It shall be within the 10 seconds. The measurements are carried out 802.11 n CH.100 (5500MHz)/ 20 MHz and CH.102(5510 MHz)/ 40 MHz.







Page 130 of 135

7.7.5.5 Channel Closing Transmission Time

The aggregate channel closing transmission time is calculated as follows;

 \boldsymbol{D} is the dwell time per spectrum analyzer sampling bin.

S is the sweep time.

 ${\boldsymbol{B}}$ is the number of spectrum analyzer sampling bin.

N is the number of spectrum analyzer sampling bins showing a UNII transmission(intermittent control signal).

Channel Closing Time = D * N = S / B * N

The observation period over which the aggregate transmission time is calculated begins at (the reference marker + 200 msec.) and end on earlier than (the reference marker + 10 sec.).

The measurements are carried out 802.11 n CH.100 (5500 MHz)/ 20 MHz BW and CH.102 (5510 MHz)/ 40 MHz BW.

Test Results

Channel	Frequency	Mode	Sweep Time(S)	(B)	(N)	Channel Closing
	(MHz)		(msec)			Time (msec)
100	5500	20 MHz BW	1000	500	0	0
140	5510	40 MHz BW	1000	500	0	0

The test result (Channel Closing Time) is calculated as follows; For 100 channel (5500 MHz)

Channel Closing Time = $\mathbf{D} * \mathbf{N} = \mathbf{S} / \mathbf{B} * \mathbf{N} = 1000 / 500 * 0 = 0$ msec







Channel Closing Transmission Time Plots for 20 MHz, 5500 MHz





Page 132 of 135

7.7.5.6 Non-Occupancy Period

During the 30 minutes observation time, EUT did not make any transmissions on a channel. The measurements are carried out 802.11 n CH.100 (5500MHz)/ 20 MHz and CH.102(5510 MHz)/ 40 MHz.

