

**SAR evaluation**  
**FCC ID: 2AACS-INF431**

MPE Calculation Method

$$E \text{ (V/m)} = (30 \cdot P \cdot G)^{0.5} / d$$

$$\text{Power Density: } P_d \text{ (W/m}^2\text{)} = E^2 / 377$$

E = Electric Field (V/m)

P = Peak RF output Power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

The formula can be changed to

$$P_d = (30 \cdot P \cdot G) / (377 \cdot d^2)$$

From the peak EUT RF output power, the minimum mobile separation distance, d=0.2m, as well

as the gain of the used antenna, the RF power density can be obtained.

**Calculated WIFI Result and Limit (WORSE CASE IS AS BELOW)**

Antenna Gain (Numeric)	Peak Output Power (mW)	Power Density (S) (mW/cm <sup>2</sup> )	Limit of Power Density (S) (mW/cm <sup>2</sup> )	Test Result
4.40 dBi (2.754)	145.21116 (21.62dBm)	0.08	1	Compiles

Note:

Antenna Gain: 1.39dBi (2.4G Band)

Assembly Antenna Gain: 4.40dBi

Assembly Antenna Gain (Numeric): 2.754dBi

$$\text{ERP} = 21.62 + 4.40 - 2.15 = 23.87 \text{ dBm (243.7811 mW)}$$

WIFI 2.4G band and 5G band cannot transmit Simultaneously

**Calculated Bluetooth Result and Limit (WORSE CASE IS AS BELOW)**

$$\text{eirp} = p_t \times g_t = (E \cdot d)^2 / 30$$

where:

$p_t$  = transmitter output power in watts,

$g_t$  = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, ---  $10^{((\text{dBuV/m})/20)} / 10^6$

d = measurement distance in meters (m)---3m

$$\text{So } p_t = (E \cdot d)^2 / (30 \times g_t)$$

Ant gain =1.39dBi so Ant numeric gain= 1.377

Field strength =85.73dBμV/m @3m@2480MHz

So Pt=85.73-95.2=-9.47dBm

Antenna Gain (Numeric)	Peak Output Power (mW)	Power Density (S) (mW/cm2)	Limit of Power Density (S) (mW/cm2)	Test Result
1.39 dBi (1.377)	0.113 (-9.47dBm)	0.000031	1	Compiles

Note:

Antenna Gain: 1.39dBi (2.4G Band)

Assembly Antenna Gain (Numeric): 1.377

ERP=-9.47dBm-2.15=-11.62 dBm(0.07mW)

BT BDR/EDR and BLE cannot transmit Simultaneously

$$\sum_{i=1}^a \frac{P_i}{P_{th,i}} = 145.21116/3060 + 0.113/3060 = 0.0475$$

$$\sum_{j=1}^b \frac{ERP_j}{ERP_{th,j}} = (243.7811 + 0.07) / 3060 = 0.08$$

$$\sum_{k=1}^c \frac{Evaluated_k}{Exposure Limit_k} = (0.08 + 0.000031) / 1 = 0.080031$$

$$\sum_{i=1}^a \frac{P_i}{P_{th,i}} + \sum_{j=1}^b \frac{ERP_j}{ERP_{th,j}} + \sum_{k=1}^c \frac{Evaluated_k}{Exposure Limit_k} \leq 1$$

$$0.0475 + 0.08 + 0.080031 = 0.21 < 1$$