



RF EXPOSURE REPORT

REPORT NO.: SA950714H02

MODEL NO.: J20H031

FCC ID: MCLJ20H031

ACCORDING: FCC Guidelines for Human Exposure
IEEE C95.1

APPLICANT: HON HAI PRECISION IND. CO., LTD.
HSINCHU SCIENCE PARK BRANCH OFFICE

ADDRESS: 5F-1,5 Hsin-An Road Hsinchu, Science-Based
Industrial Park Taiwan, R.O.C.

ISSUED BY: Advance Data Technology Corporation

LAB LOCATION: No. 81-1, Lu Liao Keng, 9 Ling, Wu Lung
Tsuen, Chiung Lin Hsiang, Hsin Chu Hsien,
Taiwan, R.O.C.

RF Exposure Measurement

1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
(A)Limits For Occupational / Control Exposures				
300-1500	F/300	6
1500-100,000	5	6
(B)Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	6
1500-100,000	1.0	30

F = Frequency in MHz

3. Friis Formula

Friis transmission formula : $P_d = (P_{out} * G) / (4 * \pi * r^2)$

where

P_d = power density in mW/cm^2

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

P_d is the limit of MPE, $1 mW/cm^2$. If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,
Page 640, Eq. (11-133).

4 EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

5. Classification

This is a stand alone radio device. So under normal use condition, it is easy to be re-located in the place where at least 20 cm far away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**.

6 Test Results

6.1 Antenna Gain

For 2.4GHz

The maximum Gain measured in Fully Anechoic Chamber is -0.49dBi or 0.893305 (numeric)

For 5GHz

The maximum Gain measured in Fully Anechoic Chamber is 2.14dBi or 1.63682 (numeric)

No.	Gain (dBi)	Antenna Type	Antenna Connector	Description
1	-0.49 (for 2.4GHz)	Printed	HRS connector	Tx / Rx (Right Antenna)
	2.14 (for 5.0GHz)			
2	-1.21 (for 2.4GHz)	Printed	HRS connector	Rx function only (Left Antenna)
	2.14 (for 5.0GHz)			

6.2 Output Power Into Antenna & RF Exposure value at distance 20cm:

For 2.4GHz

802.11b:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	72.444	0.013	1.0
6	2437	138.038	0.025	1.0
11	2462	104.713	0.019	1.0

802.11g:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	74.131	0.013	1.0
6	2437	218.776	0.039	1.0
11	2462	77.625	0.014	1.0

For 5GHz

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5180	49.204	0.0160	1.0
2	5200	48.641	0.0158	1.0
4	5240	49.545	0.0161	1.0