



Technical Note

## **WipLL 900 MHz**

Wireless IP-Based Local Loop System

# **Hopping Algorithms and Compliance with FCC 15.247 (a) (1)**

**Connecting the World with Wireless Access Solutions**

| Revision Record: Hopping Compliance |        |                           |
|-------------------------------------|--------|---------------------------|
| Pub/ Rev                            | Date   | Update Description        |
| 01                                  | Jul-03 | Airspan. Author: InterDoc |
|                                     |        |                           |
| Publication No. 16110300-01         |        |                           |

© Copyright by **Airspan Networks LTD.**, 2003. All rights reserved worldwide.

The information contained in this document is proprietary and is subject to all relevant copyright, patent and other laws protecting intellectual property, as well as any specific agreement protecting **Airspan Networks LTD.** rights in the aforesaid information. Neither this document nor the information contained herein may be published, reproduced or disclosed to third parties, in whole or in part, without the express, prior, written permission of **Airspan Networks LTD.** In addition, any use of this document or the information contained herein for any purposes other than those for which it was disclosed is strictly forbidden.

**Airspan Networks LTD.** reserves the right, without prior notice or liability, to make changes in equipment design or specifications.

Information supplied by **Airspan Networks LTD.** is believed to be accurate and reliable. However, no responsibility is assumed by **Airspan Networks LTD.** for the use thereof nor for the rights of third parties which may be effected in any way by the use thereof.

Any representation(s) in this document concerning performance of **Airspan Networks LTD.** product(s) are for informational purposes only and are not warranties of future performance, either express or implied. **Airspan Networks LTD.** standard limited warranty, stated in its sales contract or order confirmation form, is the only warranty offered by **Airspan Networks LTD.** in relation thereto.

This document may contain flaws, omissions or typesetting errors; no warranty is granted nor liability assumed in relation thereto unless specifically undertaken in Airspan Networks LTD. sales contract or order confirmation. Information contained herein is periodically updated and changes will be incorporated into subsequent editions. If you have encountered an error, please notify Airspan Networks LTD. All specifications are subject to change without prior notice.

# Contents

|                                                                |          |
|----------------------------------------------------------------|----------|
| <b>1. Introduction</b>                                         | <b>4</b> |
| <b>2. Hybrid System Algorithms</b>                             | <b>4</b> |
| <b>3. Hopping Time</b>                                         | <b>4</b> |
| <b>4. Number of Channels</b>                                   | <b>4</b> |
| <b>5. Resolution</b>                                           | <b>4</b> |
| <b>6. Channel Distribution</b>                                 | <b>4</b> |
| <b>7. Pseudo-random Frequencies for Hybrid Mode</b>            | <b>5</b> |
| <b>8. Receiver and Transmitter Compliance</b>                  | <b>6</b> |
| 8.1. Receiver Compliance with 15.247 (a) (1) / 2.1033 (a) (10) | 6        |
| 8.2. Transmitter Compliance with 15.247 (g), 15.247 (h)        | 6        |

## 1. Introduction

This document provides a description of the Hybrid system (HS) for WipLL 900 MHz products. The HS is for 1 Mbps, 2 Mbps, and 3 Mbps, and 1.33 Mbps and 4 Mbps.

## 2. Hybrid System Algorithms

- The hopping algorithm is defined by a table of  $n$  frequencies, where  $n$  is equal to 25 when the system is configured for 1 Mbps, 2 Mbps, and 3 Mbps, and where  $n$  is equal to 13 when the system is configured for 1.33 Mbps and 4 Mbps. The hopping sequence follows cyclically the frequencies in the table, remaining in each frequency for a constant period. The frequencies in the table are all in the 903 to 927 MHz range, with at least 1 MHz between any two frequencies in the table for systems configured for 1 Mbps, 2 Mbps, and 3 Mbps; and at least 2 MHz for systems configured for 1.33 Mbps and 4 Mbps. The order of frequencies in the table is pseudorandom.
- In Section **Error! Reference source not found.**, “**Error! Reference source not found.**”, two modes (1 MHz-channel spacing and 2 MHz-channel spacing) are described in **Error! Reference source not found.**.

## 3. Hopping Time

The hopping time in a given is constant (typically WipLL uses 50 msec).

## 4. Number of Channels

The number of channels is determined by the table size  $n$  frequencies, depending on transmission speed configured for the WipLL system:

- For 1 Mbps, 2 Mbps, and 3 Mbps,  $n$  is equal to at least 25 (i.e., WipLL uses  $n = 25$ )
- For 1.33 Mbps and 4 Mbps,  $n$  is equal to 13

## 5. Resolution

The minimum difference between any two channels is:

- 1 MHz for 1 Mbps, 2 Mbps, and 3 Mbps
- 2 MHz for 1.33 Mbps and 4 Mbps

## 6. Channel Distribution

Since any used channel is included once in the table, all the channels are equally used, each channel occupying  $1/n$  of the time.

## 7. Pseudo-random Frequencies for Hybrid Mode

The following tables provide an example of pseudo-random hopping frequencies for the Hybrid mode for 4 Mbps and 3 Mbps.

**Table 1: Example of Hybrid Mode with Pseudo-Random Hopping**

| 4 Mbps               |                 |
|----------------------|-----------------|
| Frequency Assignment | Frequency (MHz) |
| F1                   | 921             |
| F2                   | 913             |
| F3                   | 919             |
| F4                   | 905             |
| F5                   | 903             |
| F6                   | 917             |
| F7                   | 909             |
| F8                   | 925             |
| F9                   | 915             |
| F10                  | 927             |
| F11                  | 907             |
| F12                  | 923             |
| F13                  | 911             |

| 3 Mbps               |                 |
|----------------------|-----------------|
| Frequency Assignment | Frequency (MHz) |
| F1                   | 908             |
| F2                   | 917             |
| F3                   | 903             |
| F4                   | 922             |
| F5                   | 909             |
| F6                   | 916             |
| F7                   | 907             |
| F8                   | 914             |
| F9                   | 923             |
| F10                  | 912             |
| F11                  | 927             |
| F12                  | 919             |
| F13                  | 926             |
| F14                  | 913             |
| F15                  | 925             |
| F16                  | 904             |
| F17                  | 910             |
| F18                  | 918             |
| F19                  | 905             |
| F20                  | 924             |
| F21                  | 911             |
| F22                  | 920             |
| F23                  | 906             |
| F24                  | 915             |
| F25                  | 921             |

## 8. Receiver and Transmitter Compliance

### 8.1. Receiver Compliance with 15.247 (a) (1) / 2.1033 (a) (10)

The system receiver has an input bandwidth that matches the hopping bandwidth of the corresponding transmitters. The receiver shifts its frequency in accordance with the same frequency hopping table and pattern as the transmitters.

### 8.2. Transmitter Compliance with 15.247 (g), 15.247 (h)

■ **15.247 (g):**

The equipment fully complies with the requirements of this section. In our case, each transmission employs all available hopping channels, performed according to the requirements of 15.247.

■ **15.247 (h):**

The equipment fully complies with the requirements of this section. There is no coordination between the systems to avoid simultaneous occupancy of the hopping frequencies by multiple transmitters. Each transmitter operates independently and there is no synchronization with other transmitters.