

FCC Test Report (Part 24)

Report No.: RF170208C16B

FCC ID: H8NSFE3046

Test Model: SS2FII Femtocell Multi-band SOHO

Received Date: Jun. 11, 2018

Test Date: Jun. 13 ~ Jul. 02, 2018

Issued Date: Jul. 03, 2018

Applicant: ASKEY COMPUTER CORP.

Address: 10F, No. 119, Jiankang Rd., Zhonghe Dist., New Taipei City 23585, Taiwan

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan
(R.O.C.)

Test Location: No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City
33383, TAIWAN (R.O.C.)



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies

Table of Contents

Release Control Record	4
1 Certificate of Conformity	5
2 Summary of Test Results	6
2.1 Measurement Uncertainty	6
2.2 Test Site and Instruments	7
3 General Information	8
3.1 General Description of EUT	8
3.2 Configuration of System Under Test	9
3.2.1 Description of Support Units	9
3.3 Test Mode Applicability and Tested Channel Detail	10
3.4 EUT Operating Conditions	12
3.5 General Description of Applied Standards	13
4 Test Types and Results	14
4.1 Output Power Measurement	14
4.1.1 Limits of Output Power Measurement	14
4.1.2 Test Procedures	14
4.1.3 Test Setup	15
4.1.4 Test Results	16
4.2 Modulation Characteristics Measurement	30
4.2.1 Limits of Modulation Characteristics	30
4.2.2 Test Procedure	30
4.2.3 Test Setup	30
4.2.4 Test Results	31
4.3 Frequency Stability Measurement	33
4.3.1 Limits of Frequency Stability Measurement	33
4.3.2 Test Procedure	33
4.3.3 Test Setup	33
4.3.4 Test Results	34
4.4 Emission Bandwidth Measurement	35
4.4.1 Test Procedure	35
4.4.2 Test Setup	35
4.4.3 Test Result	36
4.5 Band Edge Measurement	43
4.5.1 Limits of Band Edge Measurement	43
4.5.2 Test Setup	43
4.5.3 Test Procedures	43
4.5.4 Test Results	43
4.6 Peak to Average Ratio	48
4.6.1 Limits of Peak to Average Ratio Measurement	48
4.6.2 Test Setup	48
4.6.3 Test Procedures	48
4.6.4 Test Results	49
4.7 Conducted Spurious Emissions	52
4.7.1 Limits of Conducted Spurious Emissions Measurement	52
4.7.2 Test Setup	52
4.7.3 Test Procedure	52
4.7.4 Test Results	53
4.8 Radiated Emission Measurement	80
4.8.1 Limits of Radiated Emission Measurement	80
4.8.2 Test Procedure	80
4.8.3 Deviation from Test Standard	80
4.8.4 Test Setup	81
4.8.5 Test Results	82

5	Pictures of Test Arrangements.....	92
	Appendix – Information on the Testing Laboratories	93

Release Control Record

Issue No.	Description	Date Issued
RF170208C16B	Original release	Jul. 03, 2018

1 Certificate of Conformity

Product: Femtocell

Brand: Nokia

Test Model: SS2FII Femtocell Multi-band SOHO

Sample Status: Engineering sample

Applicant: ASKEY COMPUTER CORP.

Test Date: Jun. 13 ~ Jul. 02, 2018

Standards: FCC Part 24, Subpart E
FCC Part 2

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's RF characteristics under the conditions specified in this report.

Prepared by :



Date:

Jul. 03, 2018

Pettie Chen / Senior Specialist

Approved by :



Date:

Jul. 03, 2018

Dylan Chiou / Project Engineer

2 Summary of Test Results

Applied Standard: FCC Part 24 & Part 2			
FCC Clause	Test Item	Result	Remarks
2.1046 24.232	Output power	Pass	Meet the requirement of limit.
2.1046 24.232(d)	Peak To Average Ratio	Pass	Meet the requirement of limit.
2.1047	Modulation characteristics	Pass	Meet the requirement
2.1055 24.235	Frequency Stability	Pass	Meet the requirement of limit.
2.1049 24.238(b)	Occupied Bandwidth	Pass	Meet the requirement of limit.
24.238(b)	Band Edge Measurements	Pass	Meet the requirement of limit.
2.1051 24.238	Conducted Spurious Emissions	Pass	Meet the requirement of limit.
2.1053 24.238	Radiated Spurious Emissions	Pass	Meet the requirement of limit. Minimum passing margin is -28.2dB at 3865.00MHz.

2.1 Measurement Uncertainty

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the EUT as specified in CISPR 16-4-2:

Measurement	Frequency	Expanded Uncertainty (k=2) ($\pm$)
Radiated Emissions up to 1 GHz	30MHz ~ 200MHz	3.59 dB
	200MHz ~1000MHz	3.60 dB
Radiated Emissions above 1 GHz	1GHz ~ 18GHz	2.29 dB
	18GHz ~ 40GHz	2.29 dB

2.2 Test Site and Instruments

Description & Manufacturer	Model No.	Serial No.	Cal. Date	Cal. Due
Test Receiver KEYSIGHT	N9038A	MY55420137	Apr. 11, 2018	Apr. 10, 2019
Spectrum Analyzer ROHDE & SCHWARZ	FSP40	100269	May 29, 2018	May 28, 2019
BILOG Antenna SCHWARZBECK	VULB9168	9168-148	Dec. 11, 2017	Dec. 10, 2018
HORN Antenna SCHWARZBECK	BBHA 9120 D	9120D-1169	Dec. 12, 2017	Dec. 11, 2018
HORN Antenna SCHWARZBECK	BBHA 9170	BBHA9170241	Dec. 01, 2017	Nov. 30, 2018
Loop Antenna EMCI	EM-6879	269	Aug. 11, 2017	Aug. 10, 2018
Preamplifier Agilent (Below 1GHz)	8447D	2944A10638	Aug. 08, 2017	Aug. 07, 2018
Preamplifier Agilent (Above 1GHz)	8449B	3008A01638	Feb. 22, 2018	Feb. 21, 2019
RF signal cable HUBER+SUHNER&EMCI	SUCOFLEX 104 & EMC104-SM-SM8000	CABLE-CH9-02 (248780+171006)	Jan. 15, 2018	Jan. 14, 2019
RF signal cable HUBER+SUHNER	SUCOFLEX 104	CABLE-CH9-(250795/4)	Aug. 08, 2017	Aug. 07, 2018
RF signal cable Woken	8D-FB	Cable-CH9-01	Aug. 01, 2017	Jul. 31, 2018
Software BV ADT	ADT_Radiated_ V7.6.15.9.5	NA	NA	NA
Antenna Tower EMCO	2070/2080	512.835.4684	NA	NA
Turn Table EMCO	2087-2.03	NA	NA	NA
Antenna Tower & Turn BV ADT	AT100	AT93021705	NA	NA
Turn Table BV ADT	TT100	TT93021705	NA	NA
Turn Table Controller BV ADT	SC100	SC93021705	NA	NA
Boresight Antenna Fixture	FBA-01	FBA-SIP01	NA	NA
Turn Table Controller BV ADT	SC100	SC93021702	NA	NA
Temperature And Humidity Chamber TERCHY	HRM-120RF	931022	Nov. 20, 2017	Nov. 19, 2018
JFW 20dB attenuation	50HF-020-SMA	NA	NA	NA
Radio Communication Analyzer	MT8821C	6261786083	Dec. 21, 2017	Dec. 20, 2018

- Note: 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.
2. The test was performed in HwaYa Chamber 9.
3. The horn antenna and preamplifier (model: 8449B) are used only for the measurement of emission frequency above 1GHz if tested.
4. The FCC Site Registration No. is 215374.
5. The IC Site Registration No. is IC 7450F-9.

3 General Information

3.1 General Description of EUT

Product	Femtocell			
Brand	Nokia			
Test Model	SS2FII Femtocell Multi-band SOHO			
Sample Status	Engineering sample			
Power Supply Rating	12Vdc (Adapter)			
Modulation Type	WCDMA: BPSK, QPSK LTE: QPSK, 16QAM, 64QAM			
Operating Frequency	WCDMA: 1932.4MHz ~ 1987.6MHz LTE Band 2 (Channel Bandwidth 5MHz): 1932.5MHz ~ 1987.5MHz LTE Band 2 (Channel Bandwidth 10MHz): 1935.0MHz ~ 1985.0MHz LTE Band 2 (Channel Bandwidth 15MHz): 1937.5MHz ~ 1982.5MHz LTE Band 2 (Channel Bandwidth 20MHz): 1940.0MHz ~ 1980.0MHz			
Max. EIRP Power	WCDMA	190.546mW (22.8dBm)		
		QPSK	16QAM	64QAM
	LTE Band 2 (Channel Bandwidth 5MHz)	269.153mW (24.3dBm)	213.796mW (23.3dBm)	190.546mW (22.8dBm)
	LTE Band 2 (Channel Bandwidth 10MHz)	269.153mW (24.4dBm)	218.776mW (23.4dBm)	194.984mW (22.9dBm)
	LTE Band 2 (Channel Bandwidth 15MHz)	288.403mW (24.6dBm)	229.087mW (23.6dBm)	204.174mW (23.1dBm)
	LTE Band 2 (Channel Bandwidth 20MHz)	288.403mW (24.6dBm)	229.087mW (23.6dBm)	199.526mW (23.0dBm)
Emission Designator	WCDMA	4M16F9W		
		QPSK	16QAM	64QAM
	LTE Band 2 (Channel Bandwidth 5MHz)	4M43G7D	4M43W7D	4M45W7D
	LTE Band 2 (Channel Bandwidth 10MHz)	8M90G7D	8M93W7D	8M93W7D
	LTE Band 2 (Channel Bandwidth 15MHz)	13M3G7D	13M3W7D	13M3W7D
	LTE Band 2 (Channel Bandwidth 20MHz)	18M0G7D	17M9W7D	17M9W7D
Antenna Type	WCDMA: Antenna 1: PIFA antenna with 2.6dBi gain LTE Band 2: Antenna 2: PIFA antenna with 2.9dBi gain Antenna 4: PIFA antenna with 3.7dBi gain			
Antenna Connector	NA			
Accessory Device	Adapter, GPS antenna (Brand: INPAQ, model: GPSGLONASS15D-S6-0341-A, cable: 4.55m non-shielded cable w/o core)			
Data Cable Supplied	2.95m non-shielded RJ45 cable w/o core			

Note:

1. The EUT uses following adapters.


Adapter 1	
Brand	SHENZHEN FRECOM ELECTRONICS CO., LTD
Model	F24W5-120200SPA
Input Power	100-240Vac, 50/60Hz, 0.6A
Output Power	12Vdc, 2A
Power Line	1.5m DC cable without core attached on adapter

Adapter 2	
Brand	AOEM
Model	ADS0248T-W120200(H)
Input Power	100-240V~50-60Hz 0.6A
Output Power	12V / 2.0A
Power Line	1.55m DC cable without core attached on adapter

*After pre-testing, adapter 1 was the worst case for the final tests.

- Carrier Aggregation technology supported for this device, the operation behavior is LTE Band 2 + LTE Band 4, for more details information please refer to "CA Mode" of test report.

3.2 Configuration of System under Test



3.2.1 Description of Support Units

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

ID	Product	Brand	Model No.	Serial No.	FCC ID	Remarks
A.	Notebook Computer	DELL	E5410	1HC2XM1	FCC DoC Approved	-

Note:

- All power cords of the above support units are non-shielded (1.8m).
- Item A acted as communication partner to transfer data.

ID	Descriptions	Qty.	Length (m)	Shielding (Yes/No)	Cores (Qty.)	Remarks
1.	RJ45 Cable	1	10	N	0	Cat5e

3.3 Test Mode Applicability and Tested Channel Detail

Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates, XYZ axis and antenna ports. The worst case was found when positioned on X-plane. Following channel(s) was (were) selected for the final test as listed below:

WCDMA Mode

EUT Configure Mode	Test Item	Available Channel	Tested Channel	Mode
-	EIRP	9662 to 9938	9662(1932.4MHz), 9800(1960.0MHz), 9938(1987.6MHz)	WCDMA (BPSK)
-	Modulation characteristics	9662 to 9938	9800(1960.0MHz)	WCDMA (BPSK)
-	Frequency Stability	9662 to 9938	9800(1960.0MHz)	WCDMA (BPSK)
-	Emission Bandwidth	9662 to 9938	9662(1932.4MHz), 9800(1960.0MHz), 9938(1987.6MHz)	WCDMA (BPSK)
-	Band Edge	9662 to 9938	9662(1932.4MHz), 9938(1987.6MHz)	WCDMA (BPSK)
-	Peak To Average Ratio	9662 to 9938	9662(1932.4MHz), 9800(1960.0MHz), 9938(1987.6MHz)	WCDMA (BPSK)
-	Conducted Emission	9662 to 9938	9662(1932.4MHz), 9800(1960.0MHz), 9938(1987.6MHz)	WCDMA (BPSK)
-	Radiated Emission Below 1GHz	9662 to 9938	9800(1960.0MHz)	WCDMA (BPSK)
-	Radiated Emission Above 1GHz	9662 to 9938	9662(1932.4MHz), 9800(1960.0MHz), 9938(1987.6MHz)	WCDMA (BPSK)

LTE Band 2

Test item	Available channel	Tested channel	Channel Bandwidth	Modulation
Output Power	625 to 1175	625(1932.5MHz), 900(1960.0MHz), 1175(1987.5MHz)	5MHz	QPSK / 16QAM / 64QAM
	650 to 1150	650(1935.0MHz), 900(1960.0MHz), 1150(1985.0MHz)	10MHz	QPSK / 16QAM / 64QAM
	675 to 1125	675(1937.5MHz), 900(1960.0MHz), 1125(1982.5MHz)	15MHz	QPSK / 16QAM / 64QAM
	700 to 1100	700(1940.0MHz), 900(1960.0MHz), 1100(1980.0MHz)	20MHz	QPSK / 16QAM / 64QAM
Modulation characteristics	625 to 1175	900(1960.0MHz)	5MHz	QPSK / 16QAM
	700 to 1100	900(1960.0MHz)	20MHz	QPSK / 16QAM
Frequency Stability	625 to 1175	900(1960.0MHz)	5MHz	QPSK
Emission Bandwidth	625 to 1175	625(1932.5MHz), 900(1960.0MHz), 1175(1987.5MHz)	5MHz	QPSK / 16QAM / 64QAM
	650 to 1150	650(1935.0MHz), 900(1960.0MHz), 1150(1985.0MHz)	10MHz	QPSK / 16QAM / 64QAM
	675 to 1125	675(1937.5MHz), 900(1960.0MHz), 1125(1982.5MHz)	15MHz	QPSK / 16QAM / 64QAM
	700 to 1100	700(1940.0MHz), 900(1960.0MHz), 1100(1980.0MHz)	20MHz	QPSK / 16QAM / 64QAM
Band Edge	625 to 1175	625(1932.5MHz), 1175(1987.5MHz)	5MHz	QPSK
	650 to 1150	650(1935.0MHz), 1150(1985.0MHz)	10MHz	QPSK
	675 to 1125	675(1937.5MHz), 1125(1982.5MHz)	15MHz	QPSK
	700 to 1100	700(1940.0MHz), 1100(1980.0MHz)	20MHz	QPSK
Peak to Average Ratio	625 to 1175	625(1932.5MHz), 900(1960.0MHz), 1175(1987.5MHz)	5MHz	QPSK / 16QAM / 64QAM
	650 to 1150	650(1935.0MHz), 900(1960.0MHz), 1150(1985.0MHz)	10MHz	QPSK / 16QAM / 64QAM
	675 to 1125	675(1937.5MHz), 900(1960.0MHz), 1125(1982.5MHz)	15MHz	QPSK / 16QAM / 64QAM
	700 to 1100	700(1940.0MHz), 900(1960.0MHz), 1100(1980.0MHz)	20MHz	QPSK / 16QAM / 64QAM
Conducuted Emission	625 to 1175	625(1932.5MHz), 900(1960.0MHz), 1175(1987.5MHz)	5MHz	QPSK
	650 to 1150	650(1935.0MHz), 900(1960.0MHz), 1150(1985.0MHz)	10MHz	QPSK
	675 to 1125	675(1937.5MHz), 900(1960.0MHz), 1125(1982.5MHz)	15MHz	QPSK
	700 to 1100	700(1940.0MHz), 900(1960.0MHz), 1100(1980.0MHz)	20MHz	QPSK

Test item	Available channel	Tested channel	Channel Bandwidth	Modulation
Radiated Emission Below 1GHz	625 to 1175	625(1932.5MHz)	5MHz	QPSK
	650 to 1150	650(1935.0MHz)	10MHz	QPSK
	675 to 1125	675(1937.5MHz)	15MHz	QPSK
	700 to 1100	700(1940.0MHz)	20MHz	QPSK
Radiated Emission Above 1GHz	625 to 1175	625(1932.5MHz), 900(1960.0MHz), 1175(1987.5MHz)	5MHz	QPSK
	650 to 1150	650(1935.0MHz), 900(1960.0MHz), 1150(1985.0MHz)	10MHz	QPSK
	675 to 1125	675(1937.5MHz), 900(1960.0MHz), 1125(1982.5MHz)	15MHz	QPSK
	700 to 1100	700(1940.0MHz), 900(1960.0MHz), 1100(1980.0MHz)	20MHz	QPSK

Note:

1. For radiated emission below 1 GHz, the low, mid and high channels were pre-tested in chamber. The low channel was the worst case and chosen for final test.
2. The conducted output power for QPSK, 16QAM and 64QAM, measured value of QPSK is higher than 16QAM and 64QAM mode. Therefore, Frequency Stability, Channel edge, Conducted Emission, Radiated Emission were presented under QPSK mode only.

Test Condition:

Test Item	Environmental Conditions	Input Power (System)	Tested By
EIRP	25deg. C, 66%RH	120Vac, 60Hz	Greg Lin Han Wu
Modulation characteristics	24deg. C, 64%RH	120Vac, 60Hz	James Yang
Frequency Stability	24deg. C, 64%RH	120Vac, 60Hz	James Yang
Emission Bandwidth	24deg. C, 64%RH	120Vac, 60Hz	James Yang
Band Edge	24deg. C, 64%RH	120Vac, 60Hz	James Yang
Peak To Average Ratio	24deg. C, 64%RH	120Vac, 60Hz	James Yang
Conducted Emission	24deg. C, 64%RH	120Vac, 60Hz	James Yang
Radiated Emission	25deg. C, 66%RH 20deg. C, 69%RH	120Vac, 60Hz	Han Wu Tank Wu, Bayu Chen

3.4 EUT Operating Conditions

The EUT makes a call to the communication simulator. The communication simulator station system controlled a EUT to export maximum output power under transmission mode and specific channel frequency

3.5 General Description of Applied Standards

The EUT is a RF Product. According to the specifications of the manufacturer, it must comply with the requirements of the following standards:

FCC 47 CFR Part 2

FCC 47 CFR Part 24

KDB 971168 D01 Power Meas License Digital Systems v03r01

KDB 412172 D01 Determining ERP and EIRP v01r01

KDB 662911 D01 multiple transmitter output v02r01

ANSI/TIA/EIA-603-E 2016

ANSI 63.26-2015

All test items have been performed and recorded as per the above standards.

4 Test Types and Results

4.1 Output Power Measurement

4.1.1 Limits of Output Power Measurement

Base stations with an emission bandwidth greater than 1MHz are limited to 1640 watts/MHz EIRP with an antenna height up to 300 meters HAAT.

4.1.2 Test Procedures

EIRP / ERP Measurement:

- All measurements were done at low, middle and high operational frequency range. RBW and VBW is 5MHz for WCDMA mode, 10MHz for LTE Mode.
- Substitution method is used for E.I.R.P measurement. In the semi-anechoic chamber, EUT placed on the 0.8m height of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The "Read Value" is the spectrum reading the maximum power value.
- The substitution horn antenna is substituted for EUT at the same position and signals generator export the CW signal to the substitution antenna via a TX cable. Rotated the Turn Table and moved receiving antenna to find the maximum radiation power. Adjust output power level of S.G to get a Value of spectrum reading equal to "Read Value" of step b. Record the power level of S.G
- $EIRP = \text{Output power level of S.G} - \text{TX cable loss} + \text{Antenna gain of substitution horn}$. E.R.P power can be calculated form E.I.R.P power by subtracting the gain of dipole, $E.R.P \text{ power} = E.I.R.P \text{ power} - 2.15\text{dB}$.

Where:

$$ERP/EIRP = P_{Meas} + G_T - L_C$$

P_{Meas} : Measure transmitter output power.

G_T : Gain of the transmitting antenna.

L_C : signal attenuation in the connecting cable between the transmitter and antenna.


Conducted Power Measurement:

The EUT was set up for the maximum power with WCDMA, LTE link data modulation and link up with simulator. Set the EUT to transmit under low, middle and high channel and record the power level shown on simulator.


4.1.3 Test Setup

EIRP / ERP Measurement:

For Radiated Emission below or equal 1GHz



For Radiated Emission above 1GHz



For the actual test configuration, please refer to the attached file (Test Setup Photo).

CONDUCTED POWER MEASUREMENT:



For the actual test configuration, please refer to the attached file (Test Setup Photo)

4.1.4 Test Results

Conducted Output Power (dBm)

Band	WCDMA II		
Channel	9662	9800	9938
Frequency	1932.4	1960	1987.6
RMC 12.2K	19.95	20.65	20.76

Band / BW	RB Size	RB Offset	QPSK						16QAM						64QAM					
			Low CH 625		Mid CH 900		High CH 1175		Low CH 625		Mid CH 900		High CH 1175		Low CH 625		Mid CH 900		High CH 1175	
			1932.5 MHz		1960 MHz		1987.5 MHz		1932.5 MHz		1960 MHz		1987.5 MHz		1932.5 MHz		1960 MHz		1987.5 MHz	
			Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1
2/5M	25	0	19.95	18.53	20.22	20.56	19.81	20.62	19.43	18.12	19.76	20.04	19.35	20.21	18.98	17.68	19.24	19.67	18.87	19.84
			Total		Total		Total		Total		Total		Total		Total		Total		Total	
			22.31		23.40		23.24		21.83		22.91		22.81		21.39		22.47		22.39	
Band / BW	RB Size	RB Offset	QPSK						16QAM						64QAM					
			Low CH 650		Mid CH 900		High CH 1150		Low CH 650		Mid CH 900		High CH 1150		Low CH 650		Mid CH 900		High CH 1150	
			1935 MHz		1960 MHz		1985 MHz		1935 MHz		1960 MHz		1985 MHz		1935 MHz		1960 MHz		1985 MHz	
			Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1
2/10M	50	0	19.66	19.17	20.44	20.53	20.83	20.92	19.13	18.68	20.01	20.09	20.28	20.43	18.65	18.14	19.64	19.68	19.74	19.99
			Total		Total		Total		Total		Total		Total		Total		Total		Total	
			22.43		23.50		23.89		21.92		23.06		23.37		21.41		22.67		22.88	
Band / BW	RB Size	RB Offset	QPSK						16QAM						64QAM					
			Low CH 675		Mid CH 900		High CH 1125		Low CH 675		Mid CH 900		High CH 1125		Low CH 675		Mid CH 900		High CH 1125	
			1937.5 MHz		1960 MHz		1982.5 MHz		1937.5 MHz		1960 MHz		1982.5 MHz		1937.5 MHz		1960 MHz		1982.5 MHz	
			Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1
2/15M	75	0	20.94	20.76	21.65	21.70	22.09	21.93	20.54	20.22	21.14	21.21	21.64	21.48	20.01	19.78	20.60	20.73	21.13	20.89
			Total		Total		Total		Total		Total		Total		Total		Total		Total	
			23.86		24.69		25.02		23.39		24.19		24.57		22.91		23.68		24.02	
Band / BW	RB Size	RB Offset	QPSK						16QAM						64QAM					
			Low CH 700		Mid CH 900		High CH 1100		Low CH 700		Mid CH 900		High CH 1100		Low CH 700		Mid CH 900		High CH 1100	
			1940 MHz		1960 MHz		1980 MHz		1940 MHz		1960 MHz		1980 MHz		1940 MHz		1960 MHz		1980 MHz	
			Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1	Chain0	Chain1
2/20M	100	0	19.90	19.78	20.18	20.52	20.69	21.00	19.48	19.34	19.84	20.10	20.14	20.53	19.02	18.75	19.36	19.63	19.64	20.11
			Total		Total		Total		Total		Total		Total		Total		Total		Total	
			22.85		23.36		23.86		22.42		22.98		23.35		21.90		22.51		22.89	

EIRP Power (dBm)

WCDMA Mode

MODE		TX channel 9662					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.4	-19.7	20.9	-0.2	20.7	33.0	-12.3
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.4	-18.6	22.4	-0.2	22.2	33.0	-10.8

MODE		TX channel 9800					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-19.3	21.2	-0.3	20.9	33.0	-12.1
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-18.1	23.1	-0.3	22.8	33.0	-10.2

MODE		TX channel 9938					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.60	-20.2	20.2	-0.4	19.8	33.0	-13.2
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.60	-19.2	22.2	-0.4	21.8	33.0	-11.2

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

LTE Band 2

Modulation Type: QPSK

Channel Bandwidth: 5MHz

MODE		TX channel 625					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.50	-16.3	24.3	-0.2	24.1	33.0	-8.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.50	-17.4	23.6	-0.2	23.4	33.0	-9.6

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-16.1	24.4	-0.3	24.1	33.0	-8.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.4	23.8	-0.3	23.5	33.0	-9.5

MODE		TX channel 1175					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.50	-15.7	24.7	-0.4	24.3	33.0	-8.7
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.50	-17.6	23.8	-0.4	23.4	33.0	-9.6

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 10MHz

MODE		TX channel 650					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1935.00	-16.2	24.4	-0.2	24.2	33.0	-8.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1935.00	-17.7	23.3	-0.2	23.1	33.0	-9.9

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-15.9	24.6	-0.3	24.3	33.0	-8.7
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.5	23.7	-0.3	23.4	33.0	-9.6

MODE		TX channel 1150					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1985.00	-15.6	24.8	-0.4	24.4	33.0	-8.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1985.00	-17.8	23.6	-0.4	23.2	33.0	-9.8

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 15MHz

MODE		TX channel 675					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1937.50	-15.9	24.8	-0.3	24.5	33.0	-8.5
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1937.50	-17.6	23.5	-0.3	23.2	33.0	-9.8

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-16.0	24.5	-0.3	24.2	33.0	-8.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.5	23.7	-0.3	23.4	33.0	-9.6

MODE		TX channel 1125					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1982.50	-15.5	25.0	-0.4	24.6	33.0	-8.4
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1982.50	-17.9	23.5	-0.4	23.1	33.0	-9.9

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 20MHz

MODE		TX channel 700					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1940.00	-15.7	24.9	-0.3	24.6	33.0	-8.4
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1940.00	-17.2	23.9	-0.3	23.6	33.0	-9.4

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-16.0	24.5	-0.3	24.2	33.0	-8.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.4	23.8	-0.3	23.5	33.0	-9.5

MODE		TX channel 1100					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1980.00	-15.8	24.7	-0.4	24.3	33.0	-8.7
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1980.00	-17.8	23.6	-0.4	23.2	33.0	-9.8

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Modulation Type: 16QAM

Channel Bandwidth: 5MHz

MODE		TX channel 625					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.50	-17.3	23.3	-0.2	23.1	33.0	-9.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.50	-18.4	22.6	-0.2	22.4	33.0	-10.6

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.1	23.4	-0.3	23.1	33.0	-9.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-18.4	22.8	-0.3	22.5	33.0	-10.5

MODE		TX channel 1175					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.50	-16.7	23.7	-0.4	23.3	33.0	-9.7
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.50	-18.7	22.7	-0.4	22.3	33.0	-10.7

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 10MHz

MODE		TX channel 650					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1935.00	-17.2	23.4	-0.2	23.2	33.0	-9.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1935.00	-17.7	23.3	-0.2	23.1	33.0	-9.9

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-16.8	23.7	-0.3	23.4	33.0	-9.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-18.5	22.7	-0.3	22.4	33.0	-10.6

MODE		TX channel 1150					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1985.00	-16.6	23.8	-0.4	23.4	33.0	-9.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1985.00	-18.9	22.5	-0.4	22.1	33.0	-10.9

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 15MHz

MODE		TX channel 675					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1937.50	-16.9	23.8	-0.3	23.5	33.0	-9.5
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1937.50	-18.6	22.5	-0.3	22.2	33.0	-10.8

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.0	23.5	-0.3	23.2	33.0	-9.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-18.5	22.7	-0.3	22.4	33.0	-10.6

MODE		TX channel 1125					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1982.50	-16.5	24.0	-0.4	23.6	33.0	-9.4
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1982.50	-18.9	22.5	-0.4	22.1	33.0	-10.9

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 20MHz

MODE		TX channel 700					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1940.00	-16.7	23.9	-0.3	23.6	33.0	-9.4
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1940.00	-18.2	22.9	-0.3	22.6	33.0	-10.4

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.1	23.4	-0.3	23.1	33.0	-9.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-18.4	22.8	-0.3	22.5	33.0	-10.5

MODE		TX channel 1100					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1980.00	-16.9	23.6	-0.4	23.2	33.0	-9.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1980.00	-17.8	23.6	-0.4	23.2	33.0	-9.8

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Modulation Type: 64QAM

Channel Bandwidth: 5MHz

MODE		TX channel 625					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.50	-17.7	22.9	-0.2	22.7	33.0	-10.3
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1932.50	-19.0	22.0	-0.2	21.8	33.0	-11.2

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.9	22.6	-0.3	22.3	33.0	-10.7
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-19.3	21.9	-0.3	21.6	33.0	-11.4

MODE		TX channel 1175					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.50	-17.2	23.2	-0.4	22.8	33.0	-10.2
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1987.50	-19.6	21.8	-0.4	21.4	33.0	-11.6

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 10MHz

MODE		TX channel 650					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1935.00	-17.8	22.8	-0.2	22.6	33.0	-10.4
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1935.00	-18.0	23.0	-0.2	22.8	33.0	-10.2

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.3	23.2	-0.3	22.9	33.0	-10.1
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-19.2	22.0	-0.3	21.7	33.0	-11.3

MODE		TX channel 1150					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1985.00	-17.6	22.8	-0.4	22.4	33.0	-10.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1985.00	-19.6	21.8	-0.4	21.4	33.0	-11.6

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 15MHz

MODE		TX channel 675					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1937.50	-17.3	23.4	-0.3	23.1	33.0	-9.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1937.50	-19.2	21.9	-0.3	21.6	33.0	-11.4

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.5	23.0	-0.3	22.7	33.0	-10.3
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-19.0	22.2	-0.3	21.9	33.0	-11.1

MODE		TX channel 1125					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1982.50	-17.0	23.5	-0.4	23.1	33.0	-9.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1982.50	-19.5	21.9	-0.4	21.5	33.0	-11.5

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

Channel Bandwidth: 20MHz

MODE		TX channel 700					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1940.00	-17.3	23.3	-0.3	23.0	33.0	-10.0
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1940.00	-18.7	22.4	-0.3	22.1	33.0	-10.9

MODE		TX channel 900					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-17.7	22.8	-0.3	22.5	33.0	-10.5
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1960.00	-18.9	22.3	-0.3	22.0	33.0	-11.0

MODE		TX channel 1100					
Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1980.00	-17.7	22.8	-0.4	22.4	33.0	-10.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	1980.00	-18.4	23.0	-0.4	22.6	33.0	-10.4

Note: EIRP (dBm) = S.G Power Value (dBm) + Correction Factor (dB).

4.2 Modulation Characteristics Measurement

4.2.1 Limits of Modulation Characteristics

N/A


4.2.2 Test Procedure

Connect the EUT to Communication Simulator via the antenna connector, The frequency band is set as EUT supported Modulation and Channels, the EUT output is matched with 50 ohm load, the waveform quality and constellation of the EUT was tested.

4.2.3 Test Setup



4.2.4 Test Results




LTE Band 2


Spectrum Plot of Measurement Value

Channel: 900 / Frequency (MHz): 1960.0MHz


Channel Bandwidth: 5MHz / QPSK




Channel Bandwidth: 5MHz / 16QAM



Channel Bandwidth: 20MHz / QPSK



Channel Bandwidth: 20MHz / 16QAM



4.3 Frequency Stability Measurement

4.3.1 Limits of Frequency Stability Measurement


The frequency stability shall be sufficient to ensure that the fundamental emission stays within the authorized frequency block.

4.3.2 Test Procedure

- Device is placed at the oven room. The oven room could control the temperatures and humidity. Power warm up is at least 15 min and power applied should perform before recording frequency error.
- EUT is connected the external power supply to control the AC input power. The test voltage range is from minimum to maximum working voltage. Each step shall be record the frequency error rate.
- The temperature range step is 10 degrees in this test items. All temperature levels shall be hold the $\pm 0.5^{\circ}\text{C}$ during the measurement testing. The each temperature step shall be at least 0.5 hours, consider the EUT could be test under the stability condition.

NOTE: The frequency error was recorded frequency error from the communication simulator.

4.3.3 Test Setup



4.3.4 Test Results

Frequency Error vs. Voltage

Voltage (Volts)	Frequency Error (ppm)		Limit (Pass/Fail)
	WCDMA	LTE Band 2	
138	0.08365	0.08475	Pass
120	0.05467	0.01213	Pass
102	0.06930	0.05277	Pass

Note: The applicant defined the normal working voltage is from 102Vac to 138Vac.

Frequency Error vs. Temperature.

TEMP. (°C)	Frequency Error (ppm)		Limit (Pass/Fail)
	WCDMA	LTE Band 2	
50	0.02295	0.00187	Pass
40	0.00642	0.07577	Pass
30	0.03831	0.07020	Pass
20	0.05467	0.08974	Pass
10	0.00911	0.01557	Pass
0	0.06825	0.07735	Pass
-10	0.04721	0.05855	Pass
-20	0.08572	0.11882	Pass
-30	0.10723	0.01509	Pass

4.4 Emission Bandwidth Measurement

4.4.1 Test Procedure


The EUT connected with Spectrum Analyzer. All measurements were done at low, middle and high operational frequency range. The control system connected a EUT to export maximum output power under transmission mode and specific channel frequency. Use OBW measurement function of Spectrum analyzer to measure 99 % occupied bandwidth.

4.4.2 Test Setup



4.4.3 Test Result

Channel	Frequency (MHz)	WCDMA	
		26dBc Bandwidth (MHz)	99% Occupied Bandwidth (MHz)
9662	1932.4	4.639	4.15
9800	1960.0	4.624	4.16
9938	1987.6	4.617	4.16



LTE Band 2 / Chain 0

Channel Bandwidth 5MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
625	1932.5	4.707	4.726	4.731	4.43	4.43	4.45
900	1960.0	4.691	4.718	4.716	4.43	4.41	4.43
1175	1987.5	4.712	4.699	4.703	4.43	4.43	4.43

Channel Bandwidth 10MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
650	1935.0	9.590	9.574	9.579	8.90	8.90	8.90
900	1960.0	9.554	9.539	9.520	8.90	8.90	8.90
1150	1985.0	9.541	9.560	9.561	8.83	8.93	8.90


Channel Bandwidth 15MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
675	1937.5	14.168	14.183	14.191	13.30	13.26	13.26
900	1960.0	14.242	14.210	14.218	13.26	13.26	13.33
1125	1982.5	14.172	14.176	14.209	13.26	13.26	13.26

Channel Bandwidth 20MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
700	1940.0	19.318	19.298	19.375	18.00	17.93	17.93
900	1960.0	19.330	19.277	19.228	17.86	17.86	17.93
1100	1980.0	19.310	19.334	19.321	17.86	17.86	17.86


Spectrum Plot of Worst Value

26dBc Bandwidth


5MHz / 64QAM / Ch 625




10MHz / 64QAM / Ch 650



15MHz / QPSK / Ch 900




20MHz / 64QAM / Ch 700




Spectrum Plot of Worst Value

Occupied Bandwidth


5MHz / 64QAM / Ch 625




10MHz / 16QAM / Ch 1150



15MHz / 64QAM / Ch 900



20MHz / QPSK / Ch 700



LTE Band 2 / Chain 1

Channel Bandwidth 5MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
625	1932.5	4.732	4.717	4.719	4.41	4.41	4.41
900	1960.0	4.680	4.719	4.711	4.43	4.43	4.45
1175	1987.5	4.699	4.687	4.719	4.43	4.43	4.43

Channel Bandwidth 10MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
650	1935.0	9.550	9.564	9.538	8.90	8.90	8.90
900	1960.0	9.530	9.549	9.567	8.90	8.90	8.90
1150	1985.0	9.524	9.576	9.572	8.93	8.90	8.93

Channel Bandwidth 15MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
675	1937.5	14.185	14.112	14.189	13.30	13.30	13.30
900	1960.0	14.210	14.189	14.212	13.30	13.30	13.33
1125	1982.5	14.204	14.177	14.138	13.30	13.30	13.30



Channel Bandwidth 20MHz							
Channel	Frequency (MHz)	26dBc Bandwidth (MHz)			Occupied Bandwidth (MHz)		
		QPSK	16QAM	64QAM	QPSK	16QAM	64QAM
700	1940.0	19.350	19.316	19.395	17.93	17.93	17.93
900	1960.0	19.428	19.430	19.449	17.86	17.86	17.93
1100	1980.0	19.255	19.330	19.330	17.93	17.93	17.93

Spectrum Plot of Worst Value

26dBc Bandwidth



5MHz / QPSK / Ch 625

10MHz / 16QAM / Ch 1150



15MHz / 64QAM / Ch 900


20MHz / 64QAM / Ch 900




Spectrum Plot of Worst Value

Occupied Bandwidth


5MHz / 64QAM / Ch 900




10MHz / QPSK / Ch 1150



15MHz / 64QAM / Ch 900



20MHz / QPSK / Ch 1100




4.5 Band Edge Measurement

4.5.1 Limits of Band Edge Measurement

Power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. In the 1 MHz bands immediately outside and adjacent to the frequency block a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed.

This device can be implement MIMO function, so the limit of spurious emissions needs to be reduced by $10\log(\text{Numbers}_{\text{Ant}})$ according to FCC KDB 662911 D01 guidance.


4.5.2 Test Setup



4.5.3 Test Procedures


- All measurements were done at low and high operational frequency range.
- The center frequency of spectrum is the band edge frequency and span is 10MHz. RB of the spectrum is 100kHz and VB of the spectrum is 300kHz (WCDMA).
- The center frequency of spectrum is the band edge frequency and span is 1.5MHz. RB of the spectrum is 50kHz and VB of the spectrum is 150kHz (LTE).
- Record the max trace plot into the test report.

4.5.4 Test Results




LTE Band 2 / Chain 0

Channel Bandwidth 5MHz




Channel Bandwidth 10MHz




LTE Band 2 / Chain 0

Channel Bandwidth 15MHz




Channel Bandwidth 20MHz




LTE Band 2 / Chain 1

Channel Bandwidth 5MHz




Channel Bandwidth 10MHz




LTE Band 2 / Chain 1

Channel Bandwidth 15MHz



Channel Bandwidth 20MHz




4.6 Peak to Average Ratio

4.6.1 Limits of Peak to Average Ratio Measurement

In measuring transmissions in this band using an average power technique, the peak to-average ratio (PAR) of the transmission may not exceed 13 dB

4.6.2 Test Setup




4.6.3 Test Procedures

- Set resolution/measurement bandwidth $\geq$ signal's occupied bandwidth;
- Set the number of counts to a value that stabilizes the measured CCDF curve;
- Record the maximum PAPR level associated with a probability of 0.1%.

4.6.4 Test Results


Channel	Frequency (MHz)	Peak To Average Ratio (dB)
		WCDMA
9262	1932.4	7.98
9800	1960.0	8.04
9938	1987.6	8.13



LTE Band 2 / Chain 0

Channel Bandwidth 5MHz					Channel Bandwidth 10MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)			Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM			QPSK	16QAM	64QAM
625	1932.5	7.99	8.00	8.00	650	1935.0	7.63	7.63	7.63
900	1960.0	8.01	8.03	8.00	900	1960.0	7.64	7.64	7.64
1175	1987.5	8.00	8.01	8.00	1150	1985.0	7.68	7.68	7.69
Channel Bandwidth 15MHz					Channel Bandwidth 20MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)			Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM			QPSK	16QAM	64QAM
675	1937.5	8.11	8.10	8.11	700	1940.0	7.46	7.46	7.48
900	1960.0	8.09	8.10	8.10	900	1960.0	7.46	7.46	7.46
1125	1982.5	8.12	8.11	8.13	1100	1980.0	7.50	7.50	7.50


Spectrum Plot Of Worst Value



LTE Band 2 / Chain 1

Channel Bandwidth 5MHz					Channel Bandwidth 10MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)			Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM			QPSK	16QAM	64QAM
625	1932.5	7.98	7.98	7.99	650	1935.0	7.65	7.65	7.65
900	1960.0	8.05	8.02	8.02	900	1960.0	7.65	7.65	7.66
1175	1987.5	8.04	8.05	8.03	1150	1985.0	7.58	7.57	7.57
Channel Bandwidth 15MHz					Channel Bandwidth 20MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)			Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM			QPSK	16QAM	64QAM
675	1937.5	8.04	8.04	8.04	700	1940.0	7.49	7.50	7.50
900	1960.0	8.10	8.10	8.10	900	1960.0	7.47	7.47	7.46
1125	1982.5	7.95	7.95	7.94	1100	1980.0	7.53	7.53	7.53

Spectrum Plot Of Worst Value



4.7 Conducted Spurious Emissions


4.7.1 Limits of Conducted Spurious Emissions Measurement

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. The emission limit equal to -13dBm .

Note:

This device can be implement MIMO function, so the limit of spurious emissions needs to be reduced by $10\log(\text{Numbers}_{\text{Ant}})$ according to FCC KDB 662911 D01 guidance.

4.7.2 Test Setup



4.7.3 Test Procedure

- All measurements were done at 3 channels: low, middle and high operational frequency range.
- When the spectrum scanned from 9kHz to 26.5GHz for LTE Band 4, it shall be connected to the attenuator with the carried frequency.



4.7.4 Test Results

WCDMA


Channel 9662

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





WCDMA


Channel 9800

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





WCDMA


Channel 9938

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 5MHz


Channel 625

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 5MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 5MHz


Channel 1175

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 10MHz


Channel 650

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 10MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 10MHz


Channel 1150

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 15MHz


Channel 675

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 15MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 15MHz


Channel 1125

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 20MHz


Channel 700

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 20MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 0 / Channel Bandwidth: 20MHz


Channel 1100

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 5MHz


Channel 625

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 5MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 5MHz


Channel 1175

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 10MHz


Channel 650

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 10MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 10MHz


Channel 1150

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 15MHz


Channel 675

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 15MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 15MHz


Channel 1125

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 20MHz


Channel 700

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 20MHz


Channel 900

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz





LTE Band 2 / Chain 1 / Channel Bandwidth: 20MHz


Channel 1100

Frequency Range : 9kHz~1GHz

Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~26.5GHz



4.8 Radiated Emission Measurement

4.8.1 Limits of Radiated Emission Measurement

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. The emission limit equal to -13dBm .

4.8.2 Test Procedure


- a. Substitution method is used for E.I.R.P measurement. In the semi-anechoic chamber, EUT placed on the 0.8m height of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The "Read Value" is the spectrum reading the maximum power value.
- b. The substitution horn antenna is substituted for EUT at the same position and signals generator export the CW signal to the substitution antenna via a TX cable. Rotated the Turn Table and moved receiving antenna to find the maximum radiation power. Adjust output power level of S.G to get a Value of spectrum reading equal to "Read Value" of step a. Record the power level of S.G
- c. $\text{EIRP} = \text{Output power level of S.G} - \text{TX cable loss} + \text{Antenna gain of substitution horn}$.
- d. E.R.P power can be calculated form E.I.R.P power by subtracting the gain of dipole, $\text{E.R.P power} = \text{E.I.R.P power} - 2.15\text{dB}$.

NOTE: The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 1MHz/3MHz.

4.8.3 Deviation from Test Standard

No deviation.

4.8.4 Test Setup



For the actual test configuration, please refer to the attached file (Test Setup Photo).

4.8.5 Test Results

Below 1GHz
WCDMA Mode

Mode	TX channel 9800	Frequency Range	Below 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	77.53	-53.6	-59.4	0.5	-58.9	-13.0	-45.9
2	121.18	-49.6	-54.2	-3.2	-57.4	-13.0	-44.4
3	206.54	-50.1	-56.3	-2.0	-58.3	-13.0	-45.3
4	268.62	-62.5	-65.1	-1.5	-66.6	-13.0	-53.6
5	332.64	-63.5	-71.3	4.0	-67.3	-13.0	-54.3
6	434.49	-64.9	-68.8	3.6	-65.2	-13.0	-52.2
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	30.97	-40.5	-31.9	-18.8	-50.7	-13.0	-37.7
2	56.19	-52.6	-54.4	-5.1	-59.5	-13.0	-46.5
3	76.56	-50.1	-56.1	0.3	-55.8	-13.0	-42.8
4	120.21	-49.2	-52.6	-3.2	-55.8	-13.0	-42.8
5	205.57	-54.9	-55.1	-2.0	-57.1	-13.0	-44.1
6	280.26	-62.6	-57.8	-1.6	-59.4	-13.0	-46.4

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2

Channel Bandwidth: 5MHz

Mode	TX channel 625	Frequency Range	Below 1000 MHz
------	----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	114.39	-61.2	-66.3	-2.8	-69.1	-13.0	-56.1
2	205.57	-55.7	-61.8	-2.0	-63.8	-13.0	-50.8
3	278.32	-65.5	-68.4	-1.6	-70.0	-13.0	-57.0
4	316.15	-66.2	-74.2	4.0	-70.2	-13.0	-57.2
5	499.48	-70.9	-74.8	3.8	-71.0	-13.0	-58.0
6	637.22	-71.0	-72.5	3.6	-68.9	-13.0	-55.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	61.04	-60.7	-64.3	-3.2	-67.5	-13.0	-54.5
2	117.30	-51.4	-55.4	-2.9	-58.3	-13.0	-45.3
3	195.87	-67.6	-66.0	-2.5	-68.5	-13.0	-55.5
4	233.70	-71.2	-71.8	-1.7	-73.5	-13.0	-60.5
5	408.30	-71.2	-75.0	3.2	-71.8	-13.0	-58.8
6	564.47	-70.4	-72.4	3.7	-68.7	-13.0	-55.7

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Channel Bandwidth: 10MHz

Mode	TX channel 650	Frequency Range	Below 1000 MHz
------	----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	35.82	-52.7	-33.3	-15.9	-49.2	-13.0	-36.2
2	61.04	-59.6	-61.7	-3.2	-64.9	-13.0	-51.9
3	86.26	-61.1	-68.0	0.1	-67.9	-13.0	-54.9
4	116.33	-50.4	-55.4	-3.0	-58.4	-13.0	-45.4
5	210.42	-53.9	-60.4	-2.0	-62.4	-13.0	-49.4
6	295.78	-64.0	-65.1	-1.8	-66.9	-13.0	-53.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	33.88	-49.8	-43.3	-17.1	-60.4	-13.0	-47.4
2	64.92	-61.5	-66.6	-1.9	-68.5	-13.0	-55.5
3	88.20	-62.0	-68.2	-0.2	-68.4	-13.0	-55.4
4	119.24	-51.3	-54.8	-3.1	-57.9	-13.0	-44.9
5	201.69	-64.7	-63.8	-2.2	-66.0	-13.0	-53.0
6	272.50	-70.7	-66.8	-1.5	-68.3	-13.0	-55.3

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Channel Bandwidth: 15MHz

Mode	TX channel 675	Frequency Range	Below 1000 MHz
------	----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	36.79	-65.1	-46.5	-15.2	-61.7	-13.0	-48.7
2	114.39	-63.9	-69.0	-2.8	-71.8	-13.0	-58.8
3	159.98	-71.5	-73.8	-3.0	-76.8	-13.0	-63.8
4	212.36	-58.9	-65.3	-2.1	-67.4	-13.0	-54.4
5	296.75	-65.3	-66.3	-1.8	-68.1	-13.0	-55.1
6	322.94	-66.2	-74.2	4.1	-70.1	-13.0	-57.1
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	40.67	-64.3	-60.6	-13.1	-73.7	-13.0	-60.7
2	64.92	-60.6	-65.7	-1.9	-67.6	-13.0	-54.6
3	90.14	-62.1	-68.2	-0.2	-68.4	-13.0	-55.4
4	117.30	-52.3	-56.3	-2.9	-59.2	-13.0	-46.2
5	200.72	-64.0	-62.9	-2.3	-65.2	-13.0	-52.2
6	280.26	-72.8	-68.0	-1.6	-69.6	-13.0	-56.6

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Channel Bandwidth: 20MHz

Mode	TX channel 700	Frequency Range	Below 1000 MHz
------	----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	36.79	-67.0	-48.4	-15.2	-63.6	-13.0	-50.6
2	76.56	-62.2	-68.1	0.3	-67.8	-13.0	-54.8
3	110.51	-53.3	-58.6	-2.6	-61.2	-13.0	-48.2
4	146.40	-67.9	-69.7	-3.0	-72.7	-13.0	-59.7
5	296.75	-63.8	-64.8	-1.8	-66.6	-13.0	-53.6
6	330.70	-62.5	-70.4	4.0	-66.4	-13.0	-53.4
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	33.88	-50.4	-43.9	-17.1	-61.0	-13.0	-48.0
2	56.19	-60.5	-62.3	-5.1	-67.4	-13.0	-54.4
3	109.54	-50.0	-55.7	-2.5	-58.2	-13.0	-45.2
4	201.69	-62.8	-61.9	-2.2	-64.1	-13.0	-51.1
5	278.32	-71.2	-66.3	-1.6	-67.9	-13.0	-54.9
6	451.95	-69.5	-73.2	3.5	-69.7	-13.0	-56.7

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Above 1GHz
WCDMA Mode

Mode	TX channel 9662	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3864.80	-60.6	-52.2	1.3	-50.9	-13.0	-37.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3864.80	-65.8	-57.2	1.3	-55.9	-13.0	-42.9

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 9800	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-61.6	-53.1	1.3	-51.8	-13.0	-38.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-66.8	-58.1	1.3	-56.8	-13.0	-43.8

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 9938	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3975.20	-60.1	-51.6	1.3	-50.3	-13.0	-37.3
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3975.20	-65.5	-56.9	1.3	-55.6	-13.0	-42.6

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2

Channel Bandwidth: 5MHz

Mode	TX channel 625	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3865.00	-50.9	-42.5	1.3	-41.2	-13.0	-28.2
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3865.00	-54.1	-45.5	1.3	-44.2	-13.0	-31.2

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 900	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-51.7	-43.2	1.3	-41.9	-13.0	-28.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-54.5	-45.8	1.3	-44.5	-13.0	-31.5

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1175	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3975.00	-51.5	-43.0	1.3	-41.7	-13.0	-28.7
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3975.00	-54.5	-45.9	1.3	-44.6	-13.0	-31.6

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Channel Bandwidth: 10MHz

Mode	TX channel 650	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3870.00	-51.8	-43.4	1.3	-42.1	-13.0	-29.1
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3870.00	-55.2	-46.6	1.3	-45.3	-13.0	-32.3

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 900	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-52.4	-43.9	1.3	-42.6	-13.0	-29.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-55.6	-46.9	1.3	-45.6	-13.0	-32.6

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1150	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3970.00	-52.1	-43.6	1.3	-42.3	-13.0	-29.3
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3970.00	-55.7	-47.1	1.3	-45.8	-13.0	-32.8

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Channel Bandwidth: 15MHz

Mode	TX channel 675	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3875.00	-52.8	-44.4	1.3	-43.1	-13.0	-30.1
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3875.00	-56.1	-47.5	1.3	-46.2	-13.0	-33.2

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 900	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-53.4	-44.9	1.3	-43.6	-13.0	-30.6
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-56.1	-47.4	1.3	-46.1	-13.0	-33.1

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1125	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3965.00	-53.0	-44.5	1.3	-43.2	-13.0	-30.2
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3965.00	-56.4	-47.8	1.3	-46.5	-13.0	-33.5

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Channel Bandwidth: 20MHz

Mode	TX channel 700	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3880.00	-53.5	-45.1	1.3	-43.8	-13.0	-30.8
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3880.00	-56.8	-48.1	1.3	-46.8	-13.0	-33.8

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 900	Frequency Range	Above 1000MHz
------	----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-53.7	-45.2	1.3	-43.9	-13.0	-30.9
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3920.00	-56.7	-48.0	1.3	-46.7	-13.0	-33.7

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1100	Frequency Range	Above 1000MHz
------	-----------------	-----------------	---------------

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3960.00	-54.0	-45.5	1.3	-44.2	-13.0	-31.2
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3960.00	-56.5	-47.9	1.3	-46.6	-13.0	-33.6

Remarks:

1. Output Power (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

5 Pictures of Test Arrangements

Please refer to the attached file (Test Setup Photo).

Appendix – Information on the Testing Laboratories

We, Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch, were founded in 1988 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

If you have any comments, please feel free to contact us at the following:

Linko EMC/RF Lab

Tel: 886-2-26052180

Fax: 886-2-26051924

Hsin Chu EMC/RF/Telecom Lab

Tel: 886-3-6668565

Fax: 886-3-6668323

Hwa Ya EMC/RF/Safety Lab

Tel: 886-3-3183232

Fax: 886-3-3270892

Email: service.adt@tw.bureauveritas.com

Web Site: www.bureauveritas-adt.com

The address and road map of all our labs can be found in our web site also.

--- END ---