User Manual

Name: RF Remote Control

Size : 150*38*15mm

Model: RM030

Input Voltage : DC 3V By Button Battery

Operating voltage range: 2.3V to 3.2V

Working Current :DC ≤20mA

Standby current : <10uA

Remote Control Distance : 12M

Operating frequency and modulation mode:433.92MHz,FSK

Transmit power:10dBm

Storage Temperature : -20-50°C

Receive decoding programming instructions

When the remote control does not send a 433 signal, the wireless receiver chip signal pin (DATA) Sending is irregular clutter, which is normal. When the remote control starts sending a 433 signal, The receiving signal pin will appear a regular waveform, and the receiver program usually detects each frame code THE SIGNAL WITH AN INTERVAL TIME OF 12MS, THE DECODING PROGRAM ENTERS TO START DECODING When writing a decoding program, pay attention to the actual high level time is higher than the theoretical value It's shorter, and the high level time out of each remote control will also be a little different, so I When writing a decoding program, pay attention to the actual high level time is higher than the theoretical value It's shorter, and the high level time out of each remote control will also be a little different, so I
We set the high level time range as large as possible
0:0.4MS+ 1.2MS When programming for 0, the pulse width range of 0.4 is enlarged as much as possible, 0.4
The range in is between 0.2-0.6
1:1.2MS+0.4MS When programming for 1, the pulse width range of 1.2 is enlarged as much as possible, 1.2
The range in is between 0.8- 1.4

THE RECEPTION DECODING IS BASED ON THE RECEPTION OF 12MS INTERVAL TIME, WHICH IS THE START SIGNAL, AND THE 12MS SIGNAL INTERVAL IS REGULAR

Definition of Remote Control

The system has an LCD display, five keys to achieve the input and feedback of the operation.



FCC Warning

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Radiation Exposure Statement

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.