



A D T

RF Exposure Report

Report No.: SA150706E06

FCC ID: PPD-QCASP241

Test Model: QCASP241

Received Date: July 06, 2015

Test Date: July 31, 2015

Issued Date: Dec. 17, 2015

Applicant: Qualcomm Atheros, Inc.

Address: 1700 Technology Drive, San Jose, CA 95110

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch
Hsin Chu Laboratory

Lab Address: E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,
Taiwan R.O.C.

Test Location (1): E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,
Taiwan R.O.C.

Test Location (2): No. 49, Ln. 206, Wende Rd., Shangshan Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by any government agencies.



Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE)	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
2.4 Antenna Gain	6
2.5 Calculation Result	7



A D T

Release Control Record

Issue No.	Description	Date Issued
SA150706E06	Original release.	Dec. 17, 2015



A D T

1 Certificate of Conformity

Product: Low-Energy WiFi Single-Band 802.11b/g/n

Brand: Qualcomm Atheros

Test Model: QCASP241

Sample Status: R&D SAMPLE

Applicant: Qualcomm Atheros, Inc.

Test Date: July 31, 2015

Standards: FCC Part 2 (Section 2.1091)

447498 D01 GENERAL RF EXPOSURE GUIDANCE V06

IEEE STD C95.1-2005

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by : , **Date:** Dec. 17, 2015
Lori Chung / Specialist

Approved by : , **Date:** Dec. 17, 2015
May Chen / Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user.

So, this device is classified as **Mobile Device**.

2.4 Antenna Gain

The antenna gain was declared by client; please refer to the following table:

Set No.	Transmitter Circuit	Brand	Model	Ant. Type	2.4GHz Gain with cable loss (dBi)	2.4GHz Cable Loss (dB)	Connector Type	Cable Length (mm)
1	Chain (0)	WNC	81-EBJ15.005	PIFA	3.00	1.15	IPEX	300
	Chain (1)	WNC	81-EBJ15.005	PIFA	3.62	1.15	IPEX	300
Set No.	Transmitter Circuit	Brand		Model		Ant. Type		2.4GHz Gain with cable loss (dBi)
2	Chain (0)	QCA		QCASP241-Ant		PCB		0.85

Note: 1. Above antenna gains of antenna No. 1 is Total (H+V).

Following antenna combination(s) was (were) selected as representative mode for test or evaluate in this report as listed.

Set No.	Transmitter Circuit	Brand	Model	Ant. Type	2.4GHz Gain with cable loss (dBi)	2.4GHz Cable Loss (dB)	Connector Type	Cable Length (mm)
1	Chain (0)+(1)	WNC	81-EBJ15.005	PIFA	3.62	1.15	IPEX	300

For QCASP241 SKU#1, the main or aux antenna port all equip the same antenna of highest gain for each frequency band.

2.5 Calculation Result

802.11b

Frequency Band (MHz)	Max Power Avg. (dBm)	Max Power Avg. (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (W/m ²)
2412 - 2462	19.50	89.125	3.62	20	0.04081	1

NOTE: 1. This power include tune-up tolerance range that specified in QCASP241 Tune Up power table

802.11g

Frequency Band (MHz)	Max Power Avg. (dBm)	Max Power Avg. (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (W/m ²)
2412 - 2462	19.50	89.125	3.62	20	0.04081	1

NOTE: 1. This power include tune-up tolerance range that specified in QCASP241 Tune Up power table

802.11n (HT20)

Frequency Band (MHz)	Max Power Avg. (dBm)	Max Power Avg. (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (W/m ²)
2412 - 2462	19.50	89.125	3.62	20	0.04081	1

NOTE: 1. This power include tune-up tolerance range that specified in QCASP241 Tune Up power table

802.11n (HT40)

Frequency Band (MHz)	Max Power Avg. (dBm)	Max Power Avg. (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (W/m ²)
2422 - 2452	17.50	56.234	3.62	20	0.02575	1

NOTE: 1. This power include tune-up tolerance range that specified in QCASP241 Tune Up power table

--- END ---