

# **TEST REPORT**

Report No.	CISRR25032219105	
Project No.	CISR250322191	
FCC ID	2BOH9-Y40812A	
Applicant	YUYAO SUNNY OPTICAL INTELLIGENCE TECHNOLOGY CO.,LTD.	
Address	No.1898,Shinan West Road,Yuyao,Zhejiang China	
Manufacturer	YUYAO SUNNY OPTICAL INTELLIGENCE TECHNOLOGY CO.,LTD.	
Address	No.1898,Shinan West Road,Yuyao,Zhejiang China	
Product Name	LUCI PIN	
Trade Mark	N/A	
Model/Type reference	Y40812A-210-01-00_PIN	
Listed Model(s)	N/A	
Standard	Part 15 Subpart E Section 15.407	
Test date	March 22, 2025 to April 15, 2025	
Issue date	April 15, 2025	
Test result	Complied	

Kory Huang

Prepared by: Rory Huang

GenryLong

Approved by: Genry Long

The test results relate only to the tested samples.

The test report should not be reproduced except in full without the written approval of Shenzhen Bangce Testing Technology Co., Ltd.



### Contents

1. REPORT VERSION	3
2. SUMMARY OF TEST RESULT	.4
3. SUMMARY	5
<ul> <li>3.1. Product Description</li> <li>3.2. Radio Specification Description</li> <li>3.3. Modification of EUT</li> <li>3.4. Testing Site</li> </ul>	. 5 . 5 . 5
4. DFS DETECTION THRESHOLDS	.6
<ul> <li>4.1. Applicability</li> <li>4.2. DFS Devices Requirements</li></ul>	6 .7 .8
5. TEST CONFIGURATION	.9
5.1. Test frequency list         5.2. Test mode         5.3. Support unit used in test configuration and system         5.4. Test sample information         5.5. Testing environmental condition         1         5.6. Statement of the measurement uncertainty         1         5.7. Equipment Used during the Test	.9 .9 10 10 10 10
6. TEST CONDITIONS AND RESULTS1	1
6.1. Statistical Performance Check       1         6.2. Radar Waveform Calibration       1         6.3. Channel Loading Test Result       1         6.4. Channel Move Time, Channel Closing Transmission Time       1         6.5. Non-Occupancy Period Test       2	11 13 15 17 20
7. TEST SETUP PHOTOS	2
8. EXTERNAL AND INTERNAL PHOTOS	3
8.1. External Photos	23 23



### 1. <u>REPORT VERSION</u>

Version No.	Issue date	Description
00	April 15, 2025	Original



### 2. SUMMARY OF TEST RESULT

No.	Test Item	Standard Requirement	Result
1	Non-Occupancy Period	FCC Part 15.407	PASS
2	DFS Detection Threshold	FCC Part 15.407	Not required
3	Channel Availability Check Time	FCC Part 15.407	Not required
4	Channel Closing Transmission Time	FCC Part 15.407	PASS
5	Channel Move Time	FCC Part 15.407	PASS
6	U-NII Detection Bandwidth	FCC Part 15.407	Not required
7	Statistical Performance Check	FCC Part 15.407	Not required

Note:

- The measurement uncertainty is not included in the test result.

- client device without radar detection capability.



### 3. SUMMARY

### 3.1. Product Description

Main unit information:		
Product Name:	LUCI PIN	
Trade Mark:	N/A	
Model No.:	Y40812A-210-01-00_PIN	
Listed Model(s):	N/A	
Model difference:	N/A	
Power supply:	input: DC 5V	
Hardware version:	V01	
Software version:	V1.2.0	
Accessory unit (AU) information:		
Battery:	DC 3.7V	

### 3.2. Radio Specification Description

Technology:	802.11a/n/ac(HT20), 802.11n/ac(HT40),802.11ac(HT80)
Modulation:	802.11a: OFDM (64QAM, 16QAM, QPSK, BPSK) 802.11n: OFDM (64QAM, 16QAM, QPSK, BPSK) 802.11ac:OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)
Operation frequency:	5250MHz~5350MHz 5470MHz~5725MHz
Antenna type:	FPC antenna+copper axis
Antenna gain:	2.99dBi

### 3.3. Modification of EUT

No modifications are made to the EUT during all test items.

### 3.4. Testing Site

Laboratory Name	Shenzhen Bangce Testing Technology Co., Ltd.	
Laboratory Location	101, building 10, Yunli Intelligent Park, Shutianpu community, Matian Street, Guangming District, Shenzhen, Guangdong, China	
FCC registration number	736346	



### 4. DFS DETECTION THRESHOLDS

### 4.1. Applicability

The following table from FCC KDB 905462 D02 UNII DFS Compliance Procedures New Rules v02 lists the applicable requirements for the DFS testing.

Requirement	Operational Mode		
	Master	Client Without Radar Detection	Client With Radar Detection
Non-Occupancy Period	Yes	Not required	Yes
DFS Detection Threshold	Yes	Not required	Yes
Channel Availability Check Time	Yes	Not required	Not required
U-NII Detection Bandwidth	Yes	Not required	Yes

Requirement	Operational Mode	
	Master Device or Client With Radar Detection	Client Without Radar Detection
DFS Detection Threshold	Yes	Not required
Channel Closing Transmission Time	Yes	Yes
Channel Move Time	Yes	Yes
U-NII Detection Bandwidth	Yes	Not required

Additional requirements for devices with multiple bandwidth modes	Master Device or Client with Radar Detection	Client Without Radar Detection
U-NII Detection Bandwidth and Statistical Performance Check	All BW modes must be tested	Not required
Channel Move Time and Channel Closing Transmission Time	Test using widest BW mode available	Test using the widest BW mode available for the link
All other tests	Any single BW mode	Not required

**Note:**Frequencies selected for statistical performance check should include several frequencies within the radar detection bandwidth and frequencies near the edge of the radar detection

bandwidth.For 802.11 devices it is suggested to select frequencies in each of the bonded 20 MHz channels and the channel center frequency.



### 4.2. DFS Devices Requirements

## Per FCC KDB 905462 D02 UNII DFS Compliance Procedures New Rules v02 the following are the requirements for Client Devices:

a)A Client Device will not transmit before having received appropriate control signals from a Master Device.

b)A Client Device will stop all its transmissions whenever instructed by a Master Device to which it is associated and will meet the Channel Move Time and Channel Closing transmission time

requirements.The Client Device will not resume any transmissions until it has again received control signals from a Master Device.

c)If a Client Device is performing In-Service Monitoring and detects a Radar Waveform above the DFS Detection Threshold, it will inform the Master Device. This is equivalent to the Master Device detecting the Radar Waveform.

d)Irrespective of Client Device or Master Device detection the Channel Move Time and Channel Closing Transmission Time requirements remain the same.

e)The client test frequency must be monitored to ensure no transmission of any type has occurred for 30 minutes.Note:If the client moves with the master,the device is considered compliant if nothing appears in the client non-occupancy period test.For devices that shut down(rather than moving channels),no beacons should appear.

## Channel Move Time and Channel Closing Transmission Time requirements are listed in the following table.

Parameter	Value
Non-Occupancy period	Minimum 30 minutes
Channel Availability Check Time	60 seconds
Channel Move Time	10 seconds.See Note 1.
Channel Closing Transmission Time	200 milliseconds+an aggregate of 60 milliseconds over remaining 10 second period.See Notes 1 and 2.
U-NII Detection Bandwidth	Minimum 100%of the U-NII 99%transmission power bandwidth.See Note 3.

**Note 1:**Channel Move Time and the Channel Closing Transmission Time should be performed with Radar Type 0.The measurement timing begins at the end of the Radar Type 0 burst.

**Note 2:** The Channel Closing Transmission Time is comprised of 200 milliseconds starting at the beginning of the Channel Move Time plus any additional intermittent control signals required to facilitate a Channel move(an aggregate of 60 mill seconds)during the remainder of the 10 second period. The aggregate duration of control signals will not count quiet periods in between transmissions.

**Note 3:**During the U-NII Detection Bandwidth detection test,radar type 0 should be used.For each frequency step the minimum percentage of detection is 90 percent.Measurements are performed with no data traffic.



### 4.3. DFS Detection Threshold Values

## The DFS detection thresholds are defined for Master devices and Client Devices with In-service monitoring. These detection thresholds are listed in the following table.

Maximum Transmit Power	Value (See Notes 1,2,and 3)	
EIRP≥200 milliwatt	-64dBm	
EIRP<200 milliwatt and power spectral density<10 dBm/MHz	-62dBm	
EIRP<200 milliwatt that do not meet the power spectral density requirement	-64dBm	
Note 1: This is the level at the input of the receiver assuming a 0 dBi receive antenna.		
<b>Note 2:</b> Throughout these test procedures an additional 1 dB has been added to the amplitude of the test transmission waveforms to account for variations in measurement equipment. This will ensure that the test signal is at or above the detection threshold level to trigger a DFS response.		
<b>Note3:</b> EIRP is based on the highest antenna gain. For MIMO devices refer to KDB Publication 662911 D01.		



### 5. TEST CONFIGURATION

This report has been prepared to demonstrate compliance with the requirements for Dynamic Frequency Selection (DFS) as stated in FCC CFR 47 PART 15E(15.407). Testing was performed in accordance with the measurement procedure described in FCC KDB 905462 D02 v02,KDB 905462 D03,KDB 905462 D04

### 5.1. Test frequency list

U-NI-2A

Bandwidth (MHz)	Lowest Channel (LCH) (MHz)	Middle Channel (MCH) (MHz)	Highest Channel (HCH) (MHz)
20	5260	5300	5320
40	5270	1	5310
80	1	5290	1

U-NI-2C

Bandwidth (MHz)	Lowest Channel (LCH) (MHz)	Middle Channel (MCH) (MHz)	Highest Channel (HCH) (MHz)
20	5500	5580	5700
40	5550	/	5670
80	5530	/	5610

### 5.2. Test mode

Test mode:	Mode 1:Communication



#### 5.3. Support unit used in test configuration and system

The EUT has been associated with peripherals and configuration operated in a manner tended to maximize its emission characteristics in a typical application.

The following peripheral devices and interface cables were connected during the measurement:

Item	Equipment name	Trade Name	Model No.	FCC ID
1	Router	ASUS	GT-BE98 Pro	MSQ-RTBE6M00
2	Adapter	Guangdong Sangu Technology Co. Itd	SG-0501000AU	-

#### 5.4. Test sample information

Туре	sample no.
Engineer sample	CISR250322191-S01
Normal sample	CISR250322191-S02

#### 5.5. Testing environmental condition

Туре	Requirement	Actual	
Temperature:	15~35°C	25°C	
Relative Humidity:	25~75%	50%	
Air Pressure:	860~1060mbar	1000mbar	

#### 5.6. Statement of the measurement uncertainty

No.	Test Items	Measurement Uncertainty
1	DFS Threshold (radiated)	1.68dB
2	DFS Threshold (conducted)	1.74dB

This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=1.96.

### 5.7. Equipment Used during the Test

SOFTWARE USED:

The engineering test program was provided(iperf).

Item	Equipment name	Manufacturer	Model	Serial No.	Calibration date	Due date
1	MXG RF Signal Generator	Agilent	N5181A	MY50145362	2025-01-08	2026-01-07
2	Spectrum analyzer	R&S	FSV-40N	102130	2025-01-08	2026-01-07
3	Vector Signal Generator	Agilent	N5182A	MY50142364	2025-01-08	2026-01-07



### 6. TEST CONDITIONS AND RESULTS

### 6.1. Statistical Performance Check

	KDB 935210 D02, Clause 5.1 Table 2							
Test Requirement	Frequencies selected for statistical performance check (Section 7.8.4) should							
rest nequirement.	include several frequencies within the radar detection bandwidth and frequencies							
	near the	edge of th	ne radar o	detection	bandwidth.			
	Table 5	– Short Pu	Ise Rada	ar Test W	aveforms			1
	Radar	Pulse Widt	th 1	PRI	Number of Pu	lses Minimum	Minimum	
	Type	(µsec)	(†	usec)		Percentage of	Trials	
						Detection	Thats	
	0	1	1	428	18	See Note 1	See Note 1	
	1	1	Test A:	15 unique	[( 1	) ] 60%	30	
			PRI	values	360			
			from th	e list of 23	Roundup	106)		
			PRI valu	ies in Table	19.			
				5a	(( PR	$I_{\mu sec}$		
			Test B:	15 unique	·			
			PRI	values				
			random	ly selected				
			518-30	066 usec				
			with a	minimum				
			increr	ment of 1				
			µsec, e	excluding				
			PRI valu	Les selected				
	2	1-5	15	0-230	23-29	60%	30	
	3	6-10	20	0-500	16-18	60%	30	
	4	11-20	20	0-500	12-16	60%	30	
	Aggregate	(Radar Types	1-4)	1 111	10 1 1	80%	120	-
	Note 1: S	nort Pulse Ra	adar Type 0	should be u	sed for the detec	tion bandwidth test, o	channel move	
	time, and	channel clos	ing time tes	<u>is.</u>				
	A minim	um of 30 u	inique wa	aveforms	are required	for each of the S	Short Pulse	Radar
	Types 2	through 4.	If more t	than 30 w	aveforms are	e used for Short	Pulse Rada	ar
Test Limit:	Types 2	through 4,	, then ead	ch additio	nal waveforn	n must also be u	inique and i	not
	repeated	from the	previous	waveforr	ns. If more th	an 30 waveform	is are used	for
	Short Pu	ilse Radar	Type 1,	then each	n additional w	aveform is gene	erated with	I est B
	and mus	t also be l	inique ar	nd not rep	eated from the	ne previous wav	eforms in 1	ests A
	or B.							
	Table 6 .		lee Rada	r Toet W/	aveform			
	Radar	Pulse	Chirn	PRI Ni	umber Number	er Minimum	Minimum	8
	Type	Width	Width ()	usec) of	Pulses of Burs	sts Percentage of	Number of	
		(µsec) (	MHz)	per	Burst	Successful	Trials	
						Detection		
	5	50-100	5-20	2000-	1-3 8-20	80%	30	
		motors fo	r this way	veform ar	e randomly o	boson Thirty ur	igue wavef	orme
	are requ	ind for the	l unis wav Slopa Di		e randonny d	forme If more th	nque waver	oforme
	are requ	for the Le	na Dulca			me then each a	ditional	cioinis
			ny ruse	riuo ond r	ype waveloli	from the proviou		
	wavelon	ii iiiust ais		que anu i	lot repeated	from the previou	s waveloin	15.
	Table 7	Frequen	ov Honni	na Padar	Test Mayof	orm		
	Radar	Pulse PRI	Pulses	Honning	Hopping	Minimum	Minimum	
	Type	Width (used	c) per	Rate	Sequence	Percentage of	Number of	
	(	µsec)	Нор	(kHz)	Length	Successful	Trials	
					(msec)	Detection		
	6	1 333	9	0.333	300	70%	30	
	For the F	requency	Hopping	Radar T	ype, the sam	e Burst paramet	ers are use	d for
	each wa	veform. Th	ne hoppir	ng sequer	nce is differei	nt for each wave	form and a	100-
	length se	egment is	selected	from the	hopping sequ	uence defined by	/ the followi	ng
	algorithn	า: 4						
	For the Frequency Hopping Radar Type, the same Burst parameters are used for each waveform. The hopping sequence is different for each waveform and a 100- length segment is selected from the hopping sequence defined by the following algorithm: 4							



	The first frequency in a hopping sequence is selected randomly from the group of 475 integer frequencies from 5250 – 5724 MHz. Next, the frequency that was just chosen is removed from the group and a frequency is randomly selected from the remaining 474 frequencies in the group. This process continues until all 475 frequencies are chosen for the set. For selection of a random frequency, the frequencies remaining within the group are always treated as equally likely.
Test Method:	KDB 935210 D02, Clause 7.8.4,KDB 905462 D03,KDB 905462 D04
Procedure:	The steps below define the procedure to determine the minimum percentage of successful detection requirements found in <b>Tables 5-7</b> when a radar burst with a level equal to the <i>DFS Detection Threshold</i> + 1dB is generated on the <i>Operating Channel</i> of the U-NII device ( <i>In- Service Monitoring</i> ). 1. One frequency will be chosen from the <i>Operating Channels</i> of the UUT within the 5250-5350 MHz or 5470-5725 MHz bands. 2. In case the UUT is a U-NII device operating as a <i>Client Device</i> (with or without Radar Detection), a U-NII device operating as a <i>Master Device</i> in case the UUT is a <i>Master Device</i> a U-NII device operating as a <i>Client Device</i> in case the UUT is a <i>Master Device</i> a U-NII device operating as a <i>Client Device</i> in case the UUT is a <i>Master Device</i> a U-NII device operating as a <i>Client Device</i> in case the UUT is a <i>Master Device</i> a U-NII device operating as a <i>Client Device</i> in case the UUT is a <i>Master Device</i> a U-NII device operating as a <i>Client Device</i> in case the UUT is a <i>Master Device</i> a U-NII device operating on the UUT (Master). In both cases for conducted tests, the <i>Radar Waveform</i> generator will be connected to the <i>Master Device</i> . For radiated tests, the <i>Master Device</i> is the <i>Master Device</i> has antenna gain, the main beam of the antenna will be directed toward the radar emitter. Vertical polarization is used for testing. 3. Stream the channel loading test file from the <i>Master Device</i> to the Client Device on the test <i>Channel</i> for the entire period of the test. 4. At time T0 the <i>Radar Waveform</i> generator sends the individual waveform for each of the Radar Types 1- 6 in <b>Tables 5-7</b> , at levels defined in <b>Table 3</b> , on the <i>Operating Channel</i> . An additional 1 dB is added to the radar test signal to ensure it is at or above the <i>DFS Detection Threshold</i> , accounting for equipment variations/errors. 5. Observe the transmissions of the UUT at the end of the Burst on the <i>Operating Channel</i> for duration greater than 10 seconds for Radar Type 0 to ensure detection occurs. 7. In case
<u>rescoetup Diagrai</u>	<u>11</u>





### 6.2. Radar Waveform Calibration

Procedure:	The Interference Radar Detection Threshold Level Is $(-62dBm) + (-0.45)$ [dBi] + 1 dB= -61.45dBm that had been taken into account the output power range and antenna gain. The above equipment setup was used to calibrate the conducted Radar Waveform. A vector signal generator was utilized to establish the test signal level for each radar type. During this process there were replace 50ohm terminal form Master and Client device and no transmissions by either the Master or Client Device. The spectrum analyzer was switched to the zero span (Time Domain) at the frequency of the Radar Wave form generator. Peak detection was used. The spectrum analyzer resolution bandwidth (RBW and video bandwidth (VBW) were set to at least 3MHz. The vector signal generator amplitude was set so that the power level measured at the spectrum analyzer was (-63.67)+ (-0.45) [dBi] + 1 dB= -64.12dBm.Capture the spectrum analyzer plots on short pulse radar types, long pulse radar type and hopping radar waveform.
------------	--

#### E.U.T. Operation

Operating Environment:							
Temperature :	22.3 °C	;	Humidity:	55.7 %	Atmospheric Pressure:	101.5 kPa	
Pre test mode: TX mode							
Final test mode: TX mode							

#### Test Setup Diagram





## <u>Test Data</u> Radar Type 0





Sample Rate 10 MHz

#### -Trial List-

	Trial Id	Radar Type	Pulse Width (us)	PRI (us)	Number of Pulses	Waveform Length (us)
Download	0	Type O	1.0	1428.0	18	25704.0
Download	1	Type O	1.0	1428.0	18	25704.0
Download	2	Type O	1.0	1428.0	18	25704.0
Download	3	Type O	1.0	1428.0	18	25704.0
Download	4	Type O	1.0	1428.0	18	25704.0
Download	5	Type O	1.0	1428.0	18	25704.0
Download	6	Type O	1.0	1428.0	18	25704.0
Download	7	Type O	1.0	1428.0	18	25704.0
Download	8	Type O	1.0	1428.0	18	25704.0
Download	9	Type O	1.0	1428.0	18	25704.0
Download	10	Type O	1.0	1428.0	18	25704.0
Download	11	Type O	1.0	1428.0	18	25704.0
Download	12	Type O	1.0	1428.0	18	25704.0
Download	13	Type O	1.0	1428.0	18	25704.0
Download	14	Type O	1.0	1428.0	18	25704.0
Download	15	Type O	1.0	1428.0	18	25704.0
Download	16	Type O	1.0	1428.0	18	25704.0
Download	17	Type O	1.0	1428.0	18	25704.0
Download	18	Type O	1.0	1428.0	18	25704.0
Download	19	Type O	1.0	1428.0	18	25704.0
Download	20	Type O	1.0	1428.0	18	25704.0
Download	21	Type O	1.0	1428.0	18	25704.0
Download	22	Type O	1.0	1428.0	18	25704.0
Download	23	Type O	1.0	1428.0	18	25704.0
Download	24	Type O	1.0	1428.0	18	25704.0
Download	25	Type O	1.0	1428.0	18	25704.0
Download	26	Type O	1.0	1428.0	18	25704.0
Download	27	Type O	10	1428.0	18	25704.0
Download	28	Type O	1.0	1428.0	18	25704.0



### 6.3. Channel Loading Test Result

	System testing was performed with the designated MPEG test file that streams full
	motion video from the Master to the Client in full motion video mode using the
D	Houding the Master to the client in full motion video thous dailing the
Procedure:	media player with the V2.61 Codec package. This file is used by IP and Frame
	based systems for loading the test channel during the In-service compliance testing
	of the U-NII device

### E.U.T. Operation

Operating Environment:						
Temperature :	Temperature 22.3 °C		Humidity:	55.7 %	Atmospheric Pressure:	101.5 kPa
Pre test mode:		ТΧ	mode			
Final test mode: T>		ТΧ	mode			

### Test Setup Diagram



#### IEEE 802.11AC Channel 58 / 5290 MHz





IEEE 802.11AC Channel 122 / 5610 MHz



Test Mode	Test Frequency	Packet ratio	Requirement ratio	Test Result			
IEEE 802.11n- HT40	5290	60.48%	≥17%	Pass			
IEEE 802.11n- HT40	5610	56.43%	≥17%	Pass			
Note: System testing was performed with the designated iperf test file. This file is used by IP and Frame based systems for loading the test channel during the In-service compliance testing of the U-NII device. Packet ratio = Time On/ (Time On + off Time).							



### 6.4. Channel Move Time, Channel Closing Transmission Time

rest Requirement:	47  GFR Part  15.407(n)(2)(11)
Test Limit:	The EUT has In-Service Monitoring function to continuously monitor the radar signals. If the radar is detected, must leave the channel (Shutdown). The Channel Move Time to cease all transmissions on the current channel upon detection of a Radar Waveform above the DFS Detection Threshold within 10 sec. The total duration of Channel Closing Transmission Time is 260ms, consisting of data signals and the aggregate of control signals, by a U-NII device during the Channel Move Time. The Non-Occupancy Period time is 30 minute during which a Channel will not be utilized after a Radar Waveform is detected on that Channel.
Test Method:	KDB 905462 D02, Clause 7.8.3
Procedure:	<ul> <li>1. The test should be performed with Radar Type 0. The measurement timing begins at the end of the Radar Type 0.</li> <li>2. When the radar burst with a level equal to the DFS Detection Threshold+1dB is generated on the Operating Channel of the U-NII device. A U-NII device operating as a Master Device will associate with the Client Device at Channel. Stream the MPEG test file from the Master Device to the Client Device on the selected Channel for the entire period of the test. At time TO the Radar Waveform generator sends a Burst of pulses for each of the radar types at Detection Threshold+1dB.</li> <li>2. Observe the transmissions of the EUT at the end of the radar Burst on the Operating Channel. Measure and record the transmissions from the EUT during the observation time(Channel Move Time).</li> <li>3. Measurement of the aggregate duration of the Channel Closing Transmission Time method. With the spectrum analyzer set to zero span tuned to the center frequency of the EUT operating channel at the radar simulated frequency, peak detection, and max hold, the dwell time per bin is given by:</li> <li>Dwell(1.5ms)=S(12 sec)/B(8000); where Dwell is the dwell time per spectrum analyzer sampling bins. An upper bound of the aggregate duration of the intermittent control signals of Channel Closing Transmission Time is calculated by:40MHz:C(6.00 ms)=N(4)X Dwell(1.5 ms); where C is the Closing Time, N is the number of spectrum analyzer sampling bins. An upper sampling bins showing a U-NII transmission and Dwell is the dwell</li> <li>time per bin.</li> <li>4. Measure the UUT for more than 30 minutes following the channel close/move time to verify that the UUT does not resume any transmissions on this Channel.</li> </ul>

#### E.U.T. Operation

Operating Environment:						
Temperature :	emperature 22.3 °C		Humidity:	55.7 %	Atmospheric Pressure:	101.5 kPa
Pre test mode: TX		ТΧ	mode			
Final test mode: TX		mode				
Test Setup Diagram						





### <u>Test Data</u>

IEEE 802.11AC Channel 58 / 5290 MHz





IEEE 802.11AC Channel 122 / 5610 MHz





### 6.5. Non-Occupancy Period Test

Test Requirement:	47 CFR Part 15.407(h)(2)(iv)
Test Limit:	A channel that has been flagged as containing a radar system, either by a channel availability check or in-service monitoring, is subject to a non-occupancy period of at least 30 minutes. The non-occupancy period starts at the time when the radar system is detected.
Test Method:	KDB 905462 D02, Clause 7.8.3
Procedure:	The steps below define the procedure to determine the above-mentioned parameters when a radar Burst with a level equal to the DFS Detection Threshold + 1dB is generated on the Operating Channel of the U-NII device ( <i>In- Service Monitoring</i> ). 1. One frequency will be chosen from the Operating Channels of the UUT within the 5250-5350 MHz or 5470-5725 MHz bands. For 802.11 devices, the test frequency must control signals. This can be verified by disabling channel loading and monitoring the spectrum analyzer. If no control signals are detected, another frequency must be selected within the emission bandwidth where control signals are detected. 2. In case the UUT is a U-NII device operating as a <i>Client Device</i> (with or without DFS), a U-NII device operating as a <i>Master Device</i> . In case the UUT is a Master Device, a u-NII device operating as a <i>Client Device</i> . In case the UUT is a Master Device, a u-NII device operating as a <i>Client Device</i> . In the Master Device is cases for conducted tests, the Radar Waveform generator will be connected to the Master Device. For radiated tests, the emissions of the Radar Waveform generator will be directed towards the Master Device to the Client Device on the test Channel loading test file from the Master Device to the Client Device on the test Channel loading test file from the Master Device to the Client Device on the test Channel loading test file form the Master Device to the Client Device on the test Channel loading test file form the master and and the radar Burst on the Operating Channel and to the endire period of the test. 4. At time T0 the Radar Waveform generator sends a Burst of pulses for one of the Radar Type 0 in Table 5 a levels defined in Table 3 , on the Operating Channel for duration greater than 10 seconds. Measure and record the transmissions of the UUT at the end of the radar Burst on the Operating Channel for duration greater than 10 seconds. Measure and record the transmission Time. 5. Observe the transmissions of the UUT due to a nere resume any transm



### Test Setup Diagram



<u>Test Data</u> Not Applicable.

IEEE 802.11AC Channel 122 / 5610 MHz

Non-Occupancy Period	l (min)	Limit			
≥30min			≥30 min		
10 dB/div Ref 10.00 dBm					
0.00					
-10.0					
-20.0					
-30.0					
-40.0					
-50.0					
-60.0	اليمار ولا يعالم المحمل والمرازي و و هذا أن اللومان. و هم ما الله معركة أنه را المحمل المعرف المحمل الم	y is his a section is a single provide a section of the	king dan katalan di sebagi sebagi Kanan katalan sebagi	lent (lint) i i handi i i Igenateri data (handi i	
-70.0					
-80.0					
Center 5.300000000 GHz				Span 0 Hz	
Res BW 3.0 MHz	#VBW 3.0 MHz		Sweep 1.85ks	(8001 pts)	
MSG			STATUS		





### 7. TEST SETUP PHOTOS





### 8. EXTERNAL AND INTERNAL PHOTOS

### 8.1. External Photos

Please Refer Report to CISRR25032219104

### 8.2. Internal photos

Please Refer Report to CISRR25032219104

-----End of the report-----