

MPE Calculations

Systems operating under the provision of 47 CFR 1.1307(b)(1) shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the FCC guidelines.

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user or nearby persons and can therefore be considered a mobile transmitter per 47 CFR 2.1091(b). The MPE calculation for this exposure is shown below.

Using the Foxconn Antennas:

The peak radiated output power (EIRP) is calculated as follows:

$$\text{EIRP} = P + G$$

$$\text{EIRP} = 17.39 \text{ dBm} + (2.51) \text{ dBi}$$

$$\text{EIRP} = 19.90 \text{ dBm} (97.72 \text{ mW})$$

Where

P = Power input to the antenna (mW).

G = Power gain of the antenna (dBm)

Power density at the specific separation:

$$S = PG / (4R^2\pi)$$

$$S = (54.83 \times 1.78) / (4 \times 20^2 \times \pi)$$

$$S = 0.019 \text{ mW/cm}^2$$

Where

S = Maximum power density (mW/cm^2)

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)

The maximum permissible exposure (MPE) for the general population is 1 mW/cm^2 .

The power density at 20cm does not exceed the 1 mW/cm^2 limit. Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

$$R = \sqrt{PG / 4\pi}$$

$$R = \sqrt{(54.83 \times 1.78) / 4\pi}$$

$$R = 2.79 \text{ cm}$$

Where

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = The safe estimated separation that the user must maintain from the antenna (cm)

The numeric gain (G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log}^{-1} (2.51 \text{ dBi} / 10)$$

$$G = 1.78$$

Using the Wistron NeWeb Corp. Antennas:

The peak radiated output power (EIRP) is calculated as follows:

$$\text{EIRP} = P + G$$

$$\text{EIRP} = 17.39 \text{ dBm} + (5.00) \text{ dBi}$$

$$\text{EIRP} = 22.39 \text{ dBm} (173.38\text{mW})$$

Where

P = Power input to the antenna (mW).

G = Power gain of the antenna (dBm)

Power density at the specific separation:

$$S = PG/(4R^2\pi)$$

$$S = (54.83 \times 3.16) / (4 \times 20^2 \times \pi)$$

$$S = 0.034 \text{ mW/cm}^2$$

Where

S = Maximum power density (mW/cm^2)

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)

The maximum permissible exposure (MPE) for the general population is 1mW/cm^2 .

The power density at 20cm does not exceed the 1mW/cm^2 limit. Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

$$R = \sqrt{PG/4\pi}$$

$$R = \sqrt{(54.83 \times 3.16) / 4\pi}$$

$$R = 3.71 \text{ cm}$$

Where

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = The safe estimated separation that the user must maintain from the antenna (cm)

The numeric gain (G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain}/10)$$

$$G = \text{Log}^{-1} (5.00 \text{ dBi}/10)$$

$$G = 3.16$$

Using the Amphenol Antennas:

The peak radiated output power (EIRP) is calculated as follows:

$$\text{EIRP} = P + G$$

$$\text{EIRP} = 17.39 \text{ dBm} + (2.85) \text{ dBi}$$

$$\text{EIRP} = 20.24 \text{ dBm} (105.68\text{mW})$$

Where

P = Power input to the antenna (mW).

G = Power gain of the antenna (dBm)

Power density at the specific separation:

$$S = PG/(4R^2\pi)$$

$$S = (54.83 \times 1.93) / (4 \times 20^2 \times \pi)$$

$$S = 0.021 \text{ mW/cm}^2$$

Where

S = Maximum power density (mW/cm^2)

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)

The maximum permissible exposure (MPE) for the general population is 1mW/cm^2 .

The power density at 20cm does not exceed the 1mW/cm^2 limit. Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

$$R = \sqrt{PG/4\pi}$$

$$R = \sqrt{(54.83 \times 1.93) / 4\pi}$$

$$R = 2.90 \text{ cm}$$

Where

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = The safe estimated separation that the user must maintain from the antenna (cm)

The numeric gain (G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain}/10)$$

$$G = \text{Log}^{-1} (2.85 \text{ dBi}/10)$$

$$G = 1.93$$