


Case No. : <u>CTA24081600603</u>	
Ambient Condition: <u>22</u> °C, <u>53</u> %RH, According Standard: ■PART 15C	
Test Date: <u>2024.8.13</u>	Test Engineer: <u>Lushan Kong</u>


Appendix C.1: DTS Bandwidth

Test Result

TestMode	Antenna	Frequency[MHz]	DTS BW [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
11B	Ant2	2412	10.080	2406.960	2417.040	0.5	PASS
		2437	10.040	2432.000	2442.040	0.5	PASS
		2462	10.080	2456.920	2467.000	0.5	PASS
11G	Ant2	2412	16.320	2403.840	2420.160	0.5	PASS
		2437	16.320	2428.840	2445.160	0.5	PASS
		2462	16.320	2453.840	2470.160	0.5	PASS
11N20SISO	Ant2	2412	17.600	2403.200	2420.800	0.5	PASS
		2437	17.600	2428.200	2445.800	0.5	PASS
		2462	17.600	2453.200	2470.800	0.5	PASS
11N40SISO	Ant2	2422	36.320	2403.840	2440.160	0.5	PASS
		2437	36.320	2418.840	2455.160	0.5	PASS
		2452	36.320	2433.840	2470.160	0.5	PASS

Test Graphs





11G_Ant2_2412



11G_Ant2_2437



11G_Ant2_2462



11N20SISO_Ant2_2412




11N20SISO_Ant2_2437




11N20SISO_Ant2_2462




11N40SISO_Ant2_2422



11N40SISO_Ant2_2437



11N40SISO_Ant2_2452




Appendix C.2: Occupied Channel Bandwidth

Test Result


TestMode	Antenna	Channel Frequency[MHz]	OCB [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
11B	Ant2	2412	13.411	2405.3380	2418.7490	---	---
		2437	13.422	2430.3343	2443.7563	---	---
		2462	13.414	2455.2883	2468.7023	---	---
11G	Ant2	2412	17.128	2403.4579	2420.5859	---	---
		2437	17.232	2428.4038	2445.6358	---	---
		2462	17.147	2453.4221	2470.5691	---	---
11N20SISO	Ant2	2412	18.221	2402.8966	2421.1176	---	---
		2437	18.238	2427.9059	2446.1439	---	---
		2462	18.200	2452.8994	2471.0994	---	---
11N40SISO	Ant2	2422	36.642	2403.7330	2440.3750	---	---
		2437	36.546	2418.7811	2455.3271	---	---
		2452	36.530	2433.7959	2470.3259	---	---

Test Graphs

11B_Ant2_2412




11B_Ant2_2437



11B_Ant2_2462



11G_Ant2_2412




11G_Ant2_2437



11G_Ant2_2462




11N20SISO_Ant2_2412




11N20SISO_Ant2_2437




11N20SISO_Ant2_2462



11N40SISO_Ant2_2422





Appendix C.3: Maximum conducted output power


Test Mode	Antenna	Frequency[MHz]	Peak power [dBm]	Limit [dBm]	Verdict
11B	Ant2	2412	17.71	≤30.00	PASS
		2437	17.85	≤30.00	PASS
		2462	18.58	≤30.00	PASS
11G	Ant2	2412	21.93	≤30.00	PASS
		2437	22.22	≤30.00	PASS
		2462	22.88	≤30.00	PASS
11N20SISO	Ant2	2412	21.89	≤30.00	PASS
		2437	22.16	≤30.00	PASS
		2462	22.82	≤30.00	PASS
11N40SISO	Ant2	2422	22.06	≤30.00	PASS
		2437	22.42	≤30.00	PASS
		2452	22.59	≤30.00	PASS

Appendix C.4: Maximum power spectral density

Test Result


TestMode	Antenna	Frequency[MHz]	Result[dBm/3-100kHz]	Limit[dBm/3kHz]	Verdict
11B	Ant2	2412	-8.65	≤8.00	PASS
		2437	-8.69	≤8.00	PASS
		2462	-6.85	≤8.00	PASS
11G	Ant2	2412	-10.92	≤8.00	PASS
		2437	-10.25	≤8.00	PASS
		2462	-8.52	≤8.00	PASS
11N20SISO	Ant2	2412	-10.44	≤8.00	PASS
		2437	-10.34	≤8.00	PASS
		2462	-9.42	≤8.00	PASS
11N40SISO	Ant2	2422	-13.22	≤8.00	PASS
		2437	-13.37	≤8.00	PASS
		2452	-12.48	≤8.00	PASS

Test Graphs







11G_Ant2_2412




11G_Ant2_2437




11G_Ant2_2462



11N20SISO_Ant2_2412




11N20SISO_Ant2_2437




11N20SISO_Ant2_2462




11N40SISO_Ant2_2422



11N40SISO_Ant2_2437



11N40SISO_Ant2_2452




Appendix C.5: Band edge measurements

Test Result


TestMode	Antenna	ChName	Frequency[MHz]	RefLevel[dBm]	Result[dBm]	Limit[dBm]	Verdict
11B	Ant2	Low	2412	5.36	-42.73	≤ -14.65	PASS
		High	2462	6.63	-49.36	≤ -13.37	PASS
11G	Ant2	Low	2412	4.15	-27.3	≤ -15.85	PASS
		High	2462	4.82	-48.13	≤ -15.18	PASS
11N20SISO	Ant2	Low	2412	4.29	-24.88	≤ -15.71	PASS
		High	2462	4.97	-47.71	≤ -15.03	PASS
11N40SISO	Ant2	Low	2422	0.81	-28.07	≤ -19.19	PASS
		High	2452	1.79	-39.58	≤ -18.22	PASS

Test Graphs







11G_Ant2_High_2462




11N20SISO_Ant2_Low_2412




11N20SISO_Ant2_High_2462



11N40SISO_Ant2_Low_2422



11N40SISO_Ant2_High_2452





Appendix C.6: Conducted Spurious Emission

Test Result

TestMode	Antenna	Frequency[MHz]	FreqRange [Mhz]	RefLevel [dBm]	Result [dBm]	Limit [dBm]	Verdict
11B	Ant2	2412	Reference	3.42	3.42	---	PASS
			30~1000	3.42	-60.12	≤ -16.58	PASS
			1000~26500	3.42	-48.37	≤ -16.58	PASS
		2437	Reference	4.70	4.70	---	PASS
			30~1000	4.70	-60.22	≤ -15.3	PASS
			1000~26500	4.70	-47.61	≤ -15.3	PASS
		2462	Reference	5.27	5.27	---	PASS
			30~1000	5.27	-59.54	≤ -14.73	PASS
			1000~26500	5.27	-47.63	≤ -14.73	PASS
11G	Ant2	2412	Reference	0.23	0.23	---	PASS
			30~1000	0.23	-61.04	≤ -19.77	PASS
			1000~26500	0.23	-47.57	≤ -19.77	PASS
		2437	Reference	2.57	2.57	---	PASS
			30~1000	2.57	-60.36	≤ -17.43	PASS
			1000~26500	2.57	-47.77	≤ -17.43	PASS
		2462	Reference	3.19	3.19	---	PASS
			30~1000	3.19	-60.79	≤ -16.81	PASS
			1000~26500	3.19	-47.65	≤ -16.81	PASS
11N20SISO	Ant2	2412	Reference	3.76	3.76	---	PASS
			30~1000	3.76	-60.31	≤ -16.24	PASS
			1000~26500	3.76	-47.59	≤ -16.24	PASS
		2437	Reference	3.77	3.77	---	PASS
			30~1000	3.77	-60.26	≤ -16.23	PASS
			1000~26500	3.77	-47	≤ -16.23	PASS
		2462	Reference	2.29	2.29	---	PASS
			30~1000	2.29	-60.62	≤ -17.71	PASS
			1000~26500	2.29	-47.46	≤ -17.71	PASS
11N40SISO	Ant2	2422	Reference	0.87	0.87	---	PASS
			30~1000	0.87	-60.88	≤ -19.13	PASS
			1000~26500	0.87	-47.54	≤ -19.13	PASS
		2437	Reference	0.59	0.59	---	PASS
			30~1000	0.59	-60.45	≤ -19.41	PASS
			1000~26500	0.59	-46.86	≤ -19.41	PASS
		2452	Reference	1.44	1.44	---	PASS
			30~1000	1.44	-60.13	≤ -18.56	PASS
			1000~26500	1.44	-47.72	≤ -18.56	PASS

Test Graphs







11B_Ant2_2437_0~Reference



11B_Ant2_2437_30~1000




11B_Ant2_2437_1000~26500



11B_Ant2_2462_0~Reference




11B_Ant2_2462_30~1000




11B_Ant2_2462_1000~26500




11G_Ant2_2412_0~Reference







11G_Ant2_2437_30~1000




11G_Ant2_2437_1000~26500




11G_Ant2_2462_0~Reference




11G_Ant2_2462_30~1000




11G_Ant2_2462_1000~26500




11N20SISO_Ant2_2412_0~Reference



11N20SISO_Ant2_2412_30~1000




11N20SISO_Ant2_2412_1000~26500



11N20SISO_Ant2_2437_0~Reference



11N20SISO_Ant2_2437_30~1000





11N20SISO_Ant2_2437_1000~26500




11N20SISO_Ant2_2462_0~Reference







11N40SISO_Ant2_2422_30~1000




11N40SISO_Ant2_2422_1000~26500




11N40SISO_Ant2_2437_0~Reference




11N40SISO_Ant2_2437_30~1000



11N40SISO_Ant2_2437_1000~26500



11N40SISO_Ant2_2452_0~Reference



11N40SISO_Ant2_2452_30~1000

