

### RF Exposure / MPE Calculation

No.	:	12079942H
Applicant	:	Sony Interactive Entertainment Inc.
Type of Equipment	:	Wireless communication module
Model No.	:	J20H096
		*Bluetooth part
FCC ID	:	AK8M18DFT1

Sony Interactive Entertainment Inc. declares that Model: J20H096 complies with FCC radiation exposure requirement specified in the FCC Rule 2.1091 (for mobile).

### RF Exposure Calculations:

The following information provides the minimum separation distance for the highest gain antenna provided with the “J20H096” as calculated from (B) Limits for General Population / Uncontrolled Exposure of TABLE 1- LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE) of §1.1310 Radiofrequency radiation exposure limits.

**[Bluetooth part]**

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a  $1\text{ mW/cm}^2$  uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$  1.40 mW (Maximum average output power)

☒ Time average was used for the above value in consideration of 6-minutes time-averaging

☐ Burst power average was used for the above value in consideration of worst condition.

$G =$  4.365 Numerical Antenna gain; equal to 6.4 dBi

$$r = 20 \text{ cm (Separation distance)}$$

**Power Density Result**  $S = 0.00122 \text{ mW/cm}^2$

**UL Japan, Inc.**

**Ise EMC Lab.**

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124

**Reference:****[WLAN (2.4 GHz) part]**

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm<sup>2</sup> uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$  13.19 mW (Maximum average output power)

☐ Time average was used for the above value in consideration of 6-minutes time-averaging

☒ Burst power average was used for the above value in consideration of worst condition.

$G =$  5.140 Numerical Antenna gain; equal to 7.11dBi

$r =$  20 cm (Separation distance)

$$\text{Power Density Result } S = 0.01349 \text{ mW/cm}^2$$

**Reference:****[WLAN (5 GHz) part]**

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm<sup>2</sup> uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$  15.28 mW (Maximum average output power)

☐ Time average was used for the above value in consideration of 6-minutes time-averaging

☒ Burst power average was used for the above value in consideration of worst condition.

$G =$  5.358 Numerical Antenna gain; equal to 7.29 dBi

$r =$  20 cm (Separation distance)

$$\text{Power Density Result } S = 0.01629 \text{ mW/cm}^2$$

Therefore, if Bluetooth and WLAN 2.4GHz transmit simultaneously,

$$\begin{aligned} S &= 0.00122 \text{ mW/cm}^2 + 0.01349 \text{ mW/cm}^2 \\ &= 0.01471 \text{ mW/cm}^2 \end{aligned}$$

Therefore, if Bluetooth and WLAN 5GHz transmit simultaneously,

$$\begin{aligned} S &= 0.00122 \text{ mW/cm}^2 + 0.01629 \text{ mW/cm}^2 \\ &= 0.01751 \text{ mW/cm}^2 \end{aligned}$$

Even taking into account the tolerance, this device can be satisfied with the limits.

---

**UL Japan, Inc.**

**Ise EMC Lab.**

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124