Safety Precautions Specifications What's in the Box **Overview Buttons & Indicators** Connections **Portable Wireless Speaker** • Avoid dropping the speaker on the floor. • Bluetooth version: V4.2 • Bluetooth profile: A2DP, AVRCP, HFP, HSP • Do not try to disassemble or repair the speaker • Driver: 2 x Φ45mm, 2 x Passive radiator Wireless Audio to Amplify Your Life! unless you are a technician. Output power: 2 x 12W Do not submerge the speaker in water. Micro USB Cable Never expose the speaker to extreme high or low Signal-to-noise ratio ≥ 80dB Power Button & Indicator Volume + Button temperatures. • Frequency response: 70-20KHz Battery level Indicator **Bluetooth Pairing** Battery: 3.7V/5200mAh • Stop use immediately if thunderstorm happens. Tribit MFB Button --Bluetooth Button WIRELESS SPEAKER XBOOM • Do not clean its surface with any corrosive cleanser • Music play time: Up to 20 hours (varies by volume XBASS Button & Indicator Volume - Button or other chemical solutions. level and music files) **AUX-IN Port** Charging time: 4 hours @ 5V/2A **Charging Port** Tritoit • Dimensions (H x W x D): 68 x 180 x 68 mm /2.68 x 7.09 x 2.68 in **USER MANUAL** User Manual XBoom Weight: 545g /19.2oz Step2: Pair/Connect the Speaker A Step3: Enjoy music with two XBooms **Wireless Daisy Chain with Two XBooms Indicators** Reset Function **Button** Operation Pair a Bluetooth Bluetooth Press the button to manually Indicator Status If this speaker has any problem, you can try to press and Step 1: Connect the Speaker A and B Button Device enter pairing mode Blue indicator flashes slowly Reconnection mode hold Volume + and Volume - buttons simultaneously for Press the button to increase ⊚ ··· ⊗ ⑧ [1] Volume Up Volume + ⊚ … ⊛ ⑧ 【 ▮ ▮ ▮ the volume level Blue indicator flashes quickly | Bluetooth pairing mode | 5s to reset this speaker and remove the old pairing in indicator Press the button to decrease |Volume Down | Volume -Blue indicator keeps sturdily on Connected your Bluetooth device, and then pair again. the volume level XBASS White indicator lights up Bass mode is activated Play/pause MFB Press once the button **Customer Service** indicator MFB Next track Double press the button Four white indicators light up | Remaining battery Previous track MFB • 18-month limited warranty Press the button for 3 times power: 71% ~ 100% answer/end the MFB Press once the button • For FAQS and more information, please visit: Battery Three white indicators light up | Remaining battery incoming call indicator Email: support@tribitaudio.com Reject an Press and hold the button for Two white indicators light up | Remaining battery Speaker B Speaker A incoming call www.tribitaudio.com **Buttons** power: 26% ~ 50% Speaker A Voice dial Press and hold the button for Keep Speaker A and B power on One white indicator lights up | Remaining battery function 2s to activate (your device must Function Button Operation • Press the Bluetooth button on Speaker A at least 5s till the power: 10% ~ 25% support this function) Note: Same as normal Bluetooth pairing Power ON/OFF | Power Button | Press the button to turn A red indicator lights up Low battery power tone comes up XBASS on/off the speaker Press the button to switch (<10%), Please recharge • Wait for the Speaker A and B connecting success with tone Bass and normal mode the speaker. try to correct the interference by one or more of the following **FCC Statement** measures: Changes or modifications not expressly approved by the party Reorient or relocate the receiving antenna. responsible for compliance could void the user's authority to • Increase the separation between the equipment and receiver. operate the equipment. • Connect the equipment into an outlet on a circuit different This equipment has been tested and found to comply with the from that to which the receiver is connected. limits for a Class B digital device, pursuant to Part 15 of the • Consult the dealer or an experienced radio/TV technician for FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential This device complies with part 15 of the FCC rules. Operation installation. This equipment generates uses and can radiate is subject to the following two conditions: radio frequency energy and, if not installed and used in (1) This device may not cause harmful interference. accordance with the instructions, may cause harmful (2) This device must accept any interference received, interference to radio communications. However, there is no including interference that may cause undesired operation. guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to