

6. Allow the trace to stabilize.

7. Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB relative to the maximum level measured in the fundamental emission.

9.4 EUT Operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.

9.5 Test Result

Temperature:	26 ℃	Relative Humidity:	54%	
Pressure:	101kPa	Test Voltage:	DC 3.8V	
Test Mode:	TX Frequency U-NII-1 (5180-5240MHz)			

Condition	Mode	Frequency (MHz)	99% bandwidth (MHz)	-26dB bandwidth (MHz)	Result
NVNT	а	5180	16.627	23.169	Pass
NVNT	а	5200	16.687	23.598	Pass
NVNT	а	5240	16.655	23.182	Pass
NVNT	n20	5180	17.845	24.179	Pass
NVNT	n20	5200	17.86	24.708	Pass
NVNT	n20	5240	17.815	24.402	Pass
NVNT	n40	5190	36.36	44.736	Pass
NVNT	n40	5230	36.348	44.255	Pass
NVNT	ac20	5180	17.838	24.96	Pass
NVNT	ac20	5200	17.842	24.435	Pass
NVNT	ac20	5240	17.837	24.146	Pass
NVNT	ac40	5190	36.331	44.52	Pass
NVNT	ac40	5230	36.363	44.922	Pass
NVNT	ax20	5180	19.011	24.583	Pass
NVNT	ax20	5200	19.043	24.706	Pass
NVNT	ax20	5240	19.01	23.775	Pass
NVNT	ax40	5190	37.839	44.069	Pass
NVNT	ax40	5230	37.791	43.413	Pass

Page: 59 of 156

Edition: B.2













































































Temperature:	26 ℃	Relative Humidity:	54%		
Pressure:	101kPa	Test Voltage:	DC 3.8V		
Test Mode :	TX Frequency U-NII-3(5745-5825MHz)				

Condition	Mode	Frequency (MHz)	99% bandwidth (MHz)	-6dB bandwidth (MHz)	Limit -6dB bandwidth (MHz)	Result
NVNT	а	5745	16.773	16.379	0.5	Pass
NVNT	а	5785	16.757	16.379	0.5	Pass
NVNT	а	5825	16.769	16.367	0.5	Pass
NVNT	n20	5745	17.932	17.605	0.5	Pass
NVNT	n20	5785	17.945	17.596	0.5	Pass
NVNT	n20	5825	17.924	17.63	0.5	Pass
NVNT	n40	5755	36.579	36.343	0.5	Pass
NVNT	n40	5795	36.509	36.349	0.5	Pass
NVNT	ac20	5745	17.963	17.607	0.5	Pass
NVNT	ac20	5785	17.936	17.638	0.5	Pass
NVNT	ac20	5825	17.942	17.603	0.5	Pass
NVNT	ac40	5755	36.557	36.336	0.5	Pass
NVNT	ac40	5795	36.517	36.329	0.5	Pass
NVNT	ax20	5745	19.124	18.929	0.5	Pass
NVNT	ax20	5785	19.164	18.918	0.5	Pass
NVNT	ax20	5825	19.078	18.926	0.5	Pass
NVNT	ax40	5755	37.993	37.861	0.5	Pass
NVNT	ax40	5795	37.963	37.925	0.5	Pass



Test Graphs -6dB Bandwidth NV/NT a 5745MHz					
Agilent Spectrum Analyzer - Occupied BW RL RF 50 Ω AC Center Freq 5.745000000	GHz Center File Center Trig: F #IFGain:Low #Atter	SENSE:INT Freq: 5.745000000 GHz Free Run Avg Hold: 1: 30 dB	ALIGN AUTO 09:59:46 AM Nov 14, 2024 Radio Std: None 100/100 Radio Device: BTS	Frequency	
Ref Offset 3.72 dE 10 dB/div Ref 23.72 dBm	3		Mkr1 5.74746 GHz -4.2510 dBm		
13.7				Center Freq 5.74500000 GHz	
-6.28	annan marina	n menonskinger	same and the second sec		
-16.3			The sector		
-36.3			and the second sec		
-56.3				CF Step	
Center 5.745 GHz #Res BW 100 kHz	#	VBW 300 kHz	Span 30 MHz Sweep 3.333 ms	3.000000 MHz <u>Auto</u> Man	
Occupied Bandwidt	h			Freq Offset 0 Hz	
16 Transmit Freq Error	-63.022 kHz	OBW Power	99.00 %		
x dB Bandwidth	16.38 MHz	x dB	-6.00 dB		
MSG					
Agilent Spectrum Analyzer - Occupied BW	-60B Band				
Center Freq 5.785000000	GHz Center Trig: F #IFGain:Low #Atten	r Freq: 5.785000000 GHz Free Run Avg Hold: 1: 30 dB	Radio Std: None 100/100 Radio Device: BTS	Frequency	
Ref Offset 3.72 de 10 dB/div Ref 23.72 dBm	3		Mkr1 5.785 GHz -17.952 dBm		
13.7				Center Freq 5.785000000 GHz	
-6.28	mantenation	ากา 1 าร์หาระกับหมายคาม	wontry		
-16.3 -26.3			WWWWWWWWWW		
-36.3			and the second s		
-66.3				CF Step	
Center 5.785 GHz #Res BW 100 kHz	#	VBW 300 kHz	Span 30 MHz Sweep 3.333 ms	3.000000 MHz <u>Auto</u> Man	
Occupied Bandwidt	Freq Offset 0 Hz				
Transmit Freq Error	-69.164 kHz	OBW Power	99.00 %		
x dB Bandwidth	16.38 MHz	x dB	-6.00 dB		
MSG			STATUS		









































































10. Maximum Conducted Output Power

10.1 Block Diagram Of Test Setup



10.2 Limit

According to FCC §15.407

The maximum conduced output power should not exceed:

Frequency Band(MHz)	Limit
5150~5250	250mW
5725~5850	1W

10.3 Test Procedure

Maximum conducted output power may be measured using a spectrum analyzer/EMI receiver or an RF power meter.

1. Device Configuration

If possible, configure or modify the operation of the EUT so that it transmits continuously at its maximum power control level (see section II.B.).

a) The intent is to test at 100 percent duty cycle; however a small reduction in duty cycle (to no lower than 98 percent) is permitted if required by the EUT for amplitude control purposes. Manufacturers are expected to provide software to the test lab to permit such continuous operation.

b) If continuous transmission (or at least 98 percent duty cycle) cannot be achieved due to hardware limitations (e.g., overheating), the EUT shall be operated at its maximum power control level with the transmit duration as long as possible and the duty cycle as high as possible.

2. Measurement using a Spectrum Analyzer or EMI Receiver (SA)

Measurement of maximum conducted output power using a spectrum analyzer requires integrating the spectrum across a frequency span that encompasses, at a minimum, either the EBW or the 99-percent occupied bandwidth of the signal.1 However, the EBW must be used to determine bandwidth dependent limits on maximum conducted output power in accordance with § 15.407(a).

a) The test method shall be selected as follows: (i) Method SA-1 or SA-1 Alternative (averaging with the EUT transmitting at full power throughout each sweep) shall be applied if either of the following conditions can be satisfied:

• The EUT transmits continuously (or with a duty cycle ≥ 98 percent).

• Sweep triggering or gating can be implemented in a way that the device transmits at the maximum power control level throughout the duration of each of the instrument sweeps to be averaged. This condition can generally be achieved by triggering the instrument's sweep if the duration of the sweep (with the analyzer configured as in Method SA-1, below) is equal to or shorter than the duration T of each transmission from the EUT and if those transmissions exhibit full power throughout their durations.



(ii) Method SA-2 or SA-2 Alternative (averaging across on and off times of the EUT transmissions, followed by duty cycle correction) shall be applied if the conditions of (i) cannot be achieved and the transmissions exhibit a constant duty cycle during the measurement duration. Duty cycle will be considered to be constant if variations are less than ± 2 percent.

(iii) Method SA-3 (RMS detection with max hold) or SA-3 Alternative (reduced VBW with max hold) shall be applied if the conditions of (i) and (ii) cannot be achieved.

b) Method SA-1 (trace averaging with the EUT transmitting at full power throughout each sweep): (i) Set span to encompass the entire emission bandwidth (EBW) (or, alternatively, the entire 99% occupied bandwidth) of the signal.

(ii) Set RBW = 1 MHz.

(iii) Set VBW ≥ 3 MHz.

(iv) Number of points in sweep \geq 2 Span / RBW. (This ensures that bin-to-bin spacing is \leq RBW/2, so that narrowband signals are not lost between frequency bins.)

(v) Sweep time = auto.

(vi) Detector = RMS (i.e., power averaging), if available. Otherwise, use sample detector mode. (vii) If transmit duty cycle < 98 percent, use a video trigger with the trigger level set to enable triggering only on full power pulses. Transmitter must operate at maximum power control level for the entire duration of every sweep. If the EUT transmits continuously (i.e., with no off intervals) or at duty cycle \ge 98 percent, and if each transmission is entirely at the maximum power control level, then the trigger shall be set to "free run".

(viii) Trace average at least 100 traces in power averaging (i.e., RMS) mode.

(ix) Compute power by integrating the spectrum across the EBW (or, alternatively, the entire 99% occupied bandwidth) of the signal using the instrument's band power measurement function with band limits set equal to the EBW (or occupied bandwidth) band edges. If the instrument does not have a band power function, sum the spectrum

10.4 EUT Operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.



10.5 Test Result

Temperature:	26 ℃	Relative Humidity:	54%		
Pressure:	101kPa	Test Voltage :	DC 3.8V		
Test Mode :	TX (5.1G) Mode Frequency U-NII-1 (5180-5240MHz) & TX (5.8G) Mode Frequency U-NII-3 (5745-5825MHz)				

Condition	Mode	Frequency (MHz)	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	а	5180	13.04	24	Pass
NVNT	а	5200	13.99	24	Pass
NVNT	а	5240	14.31	24	Pass
NVNT	n20	5180	11.83	24	Pass
NVNT	n20	5200	12.36	24	Pass
NVNT	n20	5240	12.66	24	Pass
NVNT	n40	5190	9.73	24	Pass
NVNT	n40	5230	9.91	24	Pass
NVNT	ac20	5180	11.7	24	Pass
NVNT	ac20	5200	12.36	24	Pass
NVNT	ac20	5240	12.99	24	Pass
NVNT	ac40	5190	9.87	24	Pass
NVNT	ac40	5230	9.33	24	Pass
NVNT	ax20	5180	11.52	24	Pass
NVNT	ax20	5200	12.33	24	Pass
NVNT	ax20	5240	12.72	24	Pass
NVNT	ax40	5190	9.82	24	Pass
NVNT	ax40	5230	9.71	24	Pass



Condition	Mode	Frequency (MHz)	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	а	5745	9.92	30	Pass
NVNT	а	5785	9.79	30	Pass
NVNT	а	5825	9.24	30	Pass
NVNT	n20	5745	9.16	30	Pass
NVNT	n20	5785	8.85	30	Pass
NVNT	n20	5825	8.31	30	Pass
NVNT	n40	5755	8.05	30	Pass
NVNT	n40	5795	7.4	30	Pass
NVNT	ac20	5745	9.13	30	Pass
NVNT	ac20	5785	8.74	30	Pass
NVNT	ac20	5825	8.21	30	Pass
NVNT	ac40	5755	7.7	30	Pass
NVNT	ac40	5795	7.57	30	Pass
NVNT	ax20	5745	9.21	30	Pass
NVNT	ax20	5785	8.82	30	Pass
NVNT	ax20	5825	7.42	30	Pass
NVNT	ax40	5755	7.85	30	Pass
NVNT	ax40	5795	7.27	30	Pass

Page: 100 of 156



11. Out Of Band Emissions

11.1 Block Diagram Of Test Setup



11.2 Limit

According to FCC §15.407(b)

Undesirable emission limits. Except as shown in paragraph (b)(7) of this section, the maximum emissions outside of the frequency bands of operation shall be attenuated in accordance with the following limits: (1) For transmitters operating in the 5.15-5.25 GHz band: All emissions outside of the 5.15-5.35 GHz band shall not exceed an e.i.r.p. of -27 dBm/MHz.

(2) All emissions shall be limited to a level of -27 dBm/MHz at 75 MHz or more above or below the band edge increasing linearly to 10 dBm/MHz at 25 MHz above or below the band edge, and from 25 MHz above or below the band edge increasing linearly to a level of 15.6 dBm/MHz at 5 MHz above or below the band edge, and from 5 MHz above or below the band edge increasing linearly to a level of 27 dBm/MHz at the band edge.

11.3 Test Procedure

1. Check the calibration of the measuring instrument using either an internal calibrator or a known signal from an external generator.

Position the EUT without connection to measurement instrument. Turn on the EUT and connect its antenna terminal to measurement instrument via a low loss cable. Then set it to any one measured frequency within its operating range, and make sure the instrument is operated in its linear range.

3. Set RBW of spectrum analyzer to 1 MHz with a convenient frequency span.

4. Measure the highest amplitude appearing on spectral display and set it as a reference level. Plot the graph with marking the highest point and edge frequency.

5. Repeat above procedures until all measured frequencies were complete.

11.4 EUT Operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data