R Gaming Tools

The router provides a variety of gaming tools to bring you the most immersive gaming experience.

* Log in to the web management page of the router to use these gaming tools.

Game Panel

View real-time device status on an exclusive gaming dashboard, including RGB effects, network traffic, performance, and connected USB devices, Also, your boosting games and devices are displayed.

Game Detector

Users can see the real-time ping of their game server.

Game Port Forwarding

Game Port Forwarding includes built-in rules for popular online games. Simply select your game from the list and configure basic settings for it. An optimized gaming experience is just around the corner.

duration of every game played.

Game Statistics

Displays your gaming record, including data traffic and the

TP-Link HomeShield premium security services keep your home network safe with cutting-edge features. Tap the HomeShield tab to enjoy.

TP-Link HomeShield —————

Network Protection

Detects cyber threats to keep your privacy and connected devices well protected.

Quality of Service (QoS)

Prioritize your bandwidth needs for a better networking experience.

For more details, visit https://www.tp-link.com/homeshield.

Parental Controls

Manage online time and block inappropriate content to maintain healthy online habits.

Comprehensive Reports

Gain full statistics and insight to help you understand vour home network better.

You can experience strong, stable, and seamless wireless connections throughout your home with EasyMesh.

Seamless Roaming

Connects mobile devices to your routers or extenders that provide the best coverage. Devices compatible with EasyMesh also share a single Wi-Fi name so you stay connected in every room.

One-Click Settings

Press the WPS button on the main router and the satellite device within 2 minutes of each other, then the EasyMesh network will set up.

Flexible Scalability

Flexibly scale your home networking with different vendors*, different topologies, different Protocols and different product categories.

*Failure may be due to firmware conflicts of different vendors. A better network connection can be established between all APs from TP-Link.

For more information, visit https://www.tp-link.com/easymesh/ Scan for Setup Video

S USB Applications

With the USB port, it's easy to share files and media with multiple devices.

Visit https://www.tp-link.com/app/usb to learn more about the USB applications.

Remote Access

Access the USB drive when you are away from home

Local Storage Sharing

Share files from the USB drive with devices on your home network

Media Server

Play media from the USB drive on your computer and smart devices

Keep the device away from water, fire, humidity or hot environments.

Do not attempt to disassemble, repair, or modify the device. If you need service, please contact us.

Do not use any other chargers than those recommended.

Do not use damaged charger or USB cable to charge the device.

Do not use the device where wireless devices are not allowed.

Adapter shall be installed near the equipment and shall be easily accessible.

TP-Link hereby declares that the device is in compliance with the essential requirements and other relevant provisions of directives 2014/53/EU. 2009/125/EC. 2011 /65/EU and (EU) 2015/863.

The original EU declaration of conformity may be found at https://www.tp-link.com/en/support/ce/

TP-Link hereby declares that the device is in compliance with the essential requirements and other relevant provisions of the Radio Equipment Regulations 2017. The original UK declaration of conformity may be found at https://www.tp-link.com/support/ukca/

Need Help?

Q1. What should I do if I want to change the Internet (WAN) port for internet service?

Connect to your desired Internet (WAN) port with an Ethernet cable. During the quick network setup, select the corresponding port as the internet port. Alternatively, go to More > Internet Connection > Internet Port (Tether app) or Internet > Internet Port (web management page) to

Q2. What should I do if I can't access the web management page? Reboot your router and try again.

- If the computer is set to a static IP, change its settings to obtain an IP address automatically.
- Verify that http://tplinkwifi.net is correctly entered in the web browser. Alternatively, enter http://192.168.0.1 or http://192.168.1.1 in the web browser.
- Use another web browser and try again.
- Disable and enable the network adapter in use.

Q3. What should I do if I can't access the internet?

- Log in to the web management page of the router, go to Internet > Internet Port, and check if you selected the port that you've already plugged your Ethernet cable into.
- Power off your modem for about 5 minutes, then power it on and check the internet. If your modem has more than one Ethernet port, keep the other ports unconnected.
- Check if the internet is working normally by connecting a computer directly to the modem via an Ethernet cable. If it is not, contact your internet service provider.
- Log in to the web management page, and go to the Network Map page to check whether the internet IP address is valid or not. If it's valid, go to Advanced > Network > Internet, click Advanced Settings, select Use the Following DNS Addresses, set the primary DNS to 8.8.8.8, and set the secondary DNS to 8.8.4.4. If it is not, check the hardware connection or contact your internet service provider.
- For cable modem users, log in to the web management page of the router and go to Advanced > Network > Internet > MAC Clone. Select Clone Current Device MAC and click SAVE. Then reboot both the modem and the router.

Q4. What should I do if I forget my wireless password?


- If you have not changed the default wireless password, it can be found on the label at the bottom of the router.
- Connect a computer directly to the router using an Ethernet cable. Log in to the router's web management page at http://tplinkwifi.net and go to the Wireless page to retrieve or reset your wireless password.


Q5. What should I do if I forget my web management page password? If you are using a TP-Link ID to log in, click Forgot Password? on the

- login page and then follow the instructions to reset it.
- Alternatively, press and hold the Reset button until the LED blinks blue. Then visit http://tplinkwifi.net to create a new login password.

Q6. How should I position my router for optimal Wi-Fi performance?

- Keep the router vertical while working.
- Don't place your router in a corner or in a closet.
- Avoid obstacles and high-powered appliances.
- Keep your router in a central location at a certain height.





Quick Installation Guide

AXE5400 Tri-Band Wi-Fi 6E Gaming Router

