

VX-600/900U Component Applications

Address	Parts Type	Description	Application
Q 1001	Dual Transister	XP1501-(TX)	TX5V AVR
Q 1002	Transister	CPH6102-TL	TX5V AVR
Q 1003	Dual Transister	UMZ2N TR	PTT
Q 1004	Dual Transister	UMG2N TR	TX/RX SW
Q 1005	Transister	2SD1767 T100 Q	LAMP DRIVER
Q 1006	Transister	PDTC114TE	LAMP SW
Q 1007	IC	TDA2822D013TR	EXT AF AMP
Q 1008	Transister	CPH6102-TL	AF AMP SW
Q 1009	IC	TK71650SCL	5V AVR
Q 1010	Transister	PDTC114TE	LAMP SW
Q 1011	IC	TDA2822D013TR	INT AF AMP
Q 1012	IC	BIC702CBZ	RF AMP
Q 1013	Transister	UN911F-(TX)	RX 5V SW
Q 1014	Dual Transister	UMG2N TR	TRX LED SW
Q 1015	Transister	2SA1774 TL R	CURRENT SENS
Q 1016	Hybird RF Module	M68732LA (typ AS1)	PA
Q 1016	Hybird RF Module	M68732HA (typ CS,D)	PA
Q 1016	Hybird RF Module	M68732SHA (typ F)	PA
Q 1017	Dual Transister	UMC5N TR	AF AMP SEL
Q 1018	Quadruple OP-AMP	NJM2902V	APC/RX TUNE/AF AMP
Q 1019	Transister	PDTC144EE	AF AMP SEL
Q 1020	Dual Transister	UMC5N TR	AF AMP SEL
Q 1021	IC	M62364FP 600D	D/A Converter
Q 1022	Quadruple OP-AMP	NJM2902V	MIC AMP/AF FILTER
Q 1023	Transister	PDTC144EE	TRX SW
Q 1024	Transister	PDTC144EE	PO OFF SW
Q 1025	Transister	UN911F-(TX)	SAVE SW
Q 1026	Transister	2SC3356-R25	Pre DRIVE
Q 1027	IC	AK2345-T4	AUDIO PROSSESSOR
Q 1028	Transister	PDTC114TE	TRX SW
Q 1029	Transister	2SC5226-4-TL	Buff AMP
Q 1030	Transister	PDTC114TE	NARROW ATT SW
Q 1031	Transister	PDTC114TE	Buff AMP SW
Q 1032	Transister	2SC5226-4-TL	Buff
Q 1033	Transister	PDTC144EE	RX VCO SW
Q 1034	ID	S-80735SN-DZ-T1	RESET
Q 1035	Dual Transister	XN1501-(TX)	3.5V AVR
Q 1036	IC	TK71635SCL	3.5V AVR
Q 1037	Transister	CPH6102-TL	3.5V AVR
Q 1038	FET	2SK508-T2B K52	RX VCO
Q 1039	Transister	PDTC114TE	TX VCO SW
Q 1040	IC	S-93C56AMFN-TB	EEPROM
Q 1041	Transister	2SC4227-T2 R34	TX VCO
Q 1042	Transister	2SC4617 TL	RESET
Q 1043	Transister	2SC4617 TL	Ripple Filter
Q 1044	Transister	2SC5226-4-TL	IF AMP
Q 1045	Transister	PDTC144EE	Buff AMP SW
Q 1046	Transister	2SC5226-4-TL	Buff AMP
Q 1047	Transister	2SC4617 TL	Clock Shift
Q 1048	Transister	UN911F-(TX)	WIDE/NARROW SW
Q 1049	IC	TA31136FN(EL)	FM Sub-System IC
Q 1050	IC	LC87F72C8A	Main Microprocessor
Q 1051	Transister	2SC4617 TL	2ND LOCAL OSC

Q 1052	IC	BU2090FS-E1	BEEP CNTL/PORT CNTL
Q 1053	IC	SA7025DK	PLL IC
Q 1054	Transister	2SC4617 TL	FILTER AMP
Q 1055	Transister	2SC4617 TL	Reference OSC
Q 1056	Transister	PDTC144EE	Wide/Narrow SW
Q 1057	Transister	PDTC144EE	Wide/Narrow SW
Q 1058	IC	NJM2902V1	CTCSS DEC2
Q 1059	Transister	UN911F-(TX)	LAMP SW

D 1001	Dual Diode	DA221 TL	Protector
D 1002	Diode	MA2S111-(TX)	Protector
D 1003	Diode	MA2S111-(TX)	Protector
D 1004	Diode	MA2S111-(TX)	Protector
D 1005	Diode	HVU131	ANT SW
D 1006	Diode	MA2S111-(TX)	Protector
D 1007	Diode	MA2S111-(TX)	Protector
D 1008	Diode	MA2S111-(TX)	Protector
D 1009	Diode	MA2S111-(TX)	Protector
D 1010	Dual Diode	DA221 TL	Protector
D 1011	Zener Diode	PTZ TE25 15A	Protector
D 1012	Dual Diode	DA221 TL	Protector
D 1013	Dual Diode	DA221 TL	Protector
D 1014	Dual Diode	DA221 TL	Protector
D 1015	Diode	MA2S111-(TX)	TX/RX SW
D 1016	Diode	HVU131	ANT SW
D 1017	LED	LNJ808K8SRA	KEY LAMP
D 1018	LED	LNJ808K8SRA	KEY LAMP
D 1019	LED	LNJ808K8SRA	KEY LAMP
D 1020	LED	LNJ808K8SRA	KEY LAMP
D 1021	Dual Diode	RB715F T106	Power DET
D 1022	LED	LNJ808K8SRA	KEY LAMP
D 1023	LED	LNJ808K8SRA	KEY LAMP
D 1025	Diode	MA2S111-(TX)	Protector
D 1026	Zener Diode	UDZ TE17 3.9B	Protector
D 1027	Varactor Diode	HVC350B-TRF	RX tune
D 1028	Varactor Diode	HVC350B-TRF	RX tune
D 1029	Dual Diode	DA221 TL	TEMP DET
D 1030	Varactor Diode	HVC350B-TRF	RX tune
D 1031	Varactor Diode	HVC350B-TRF	RX tune
D 1032	Varactor Diode	HVC350B-TRF	RX tune
D 1033	Varactor Diode	HVC350B-TRF	RX tune
D 1034	Dual Diode	DA221 TL	LIMITTER
D 1035	Dual Diode	MA132WK-(TX)	TX/RX SW
D 1036	Diode	MA2S111-(TX)	Protector
D 1037	FET	GN2011-Q(TX)	MIXER
D 1038	Dual Diode	DA221 TL	LIMITTER
D 1039	Diode	MA2S111-(TX)	Protector
D 1040	Diode	MA2S111-(TX)	Protector
D 1041	Diode	MA2S111-(TX)	Protector
D 1042	Diode	MA2S111-(TX)	Protector
D 1043	Varactor Diode	HVC350B-TRF	MOD

D 1044	Diode	MA2S111-(TX)	Protector
D 1045	Dual Diode	DA221 TL	RESET
D 1046	Zener Diode	HZU4ALL-TR	Protector
D 1047	Diode	MA2S111-(TX)	Protector
D 1048	Varactor Diode	HVC350B-TRF	RX VCO Freq Cont
D 1049	Varactor Diode	HVC350B-TRF	RX VCO Freq Cont
D 1050	Varactor Diode	HVC350B-TRF	TX VCO Freq Cont
D 1051	Varactor Diode	HVC350B-TRF	RX VCO Freq Cont
D 1052	Varactor Diode	HVC350B-TRF	RX VCO Freq Cont
D 1053	Varactor Diode	HVC350B-TRF	TX VCO Freq Cont
D 1054	Dual Diode	DA221 TL	Limiter
D 1055	Diode	MA2S111-(TX)	Protector
D 1056	Dual Diode	DAN222 TL	Wide/Narrow SW
D 1057	Varactor Diode	HVC350B-TRF	FREQ TEMP CNTL
D 1058	Dual Diode	DA221 TL	NOISE DET
D 1059	Dual Diode	DA221 TL	NOISE DET
D 1060	Dual Diode	DAN222 TL	Wide/Narrow SW
D 1061	Varactor Diode	HVC350B-TRF	DEC MOD
D 1062	Varactor Diode	HVC350B-TRF	FREQ ADJ
D 1063	NOT USED	-	
D 1064	NOT USED	-	