

Thank you for purchasing the TOZO authentic product.
For more latest products, parts and accessories,
please visit: www.tozostore.com
For any assistance please contact Email: info@tozostore.com



TOZO®

7.0 Specification

Support Bluetooth profile	A2DP, AVRCP, HFP, HSP
Transmission Distance	≥12m
Bluetooth working frequency	2.402GHz-2.480GHz
Speaker type	Φ6mm+2
Impedance	16Ω±15%
Standby time	70 hours
Call time	5 hours
Music playback time	8 hours
Earbuds battery capacity	55mAh
Charging time of earbuds	1.7 hours
The battery capacity of charging case	600mAh
Charging time of the charging case	1.8 hours
Weight	4.5g


8.0 Waterproof

Waterproof for daily use (sweating, rain, washing face, showering, having a bath, etc, but not for swimming under water.)
• Please note that the phone's Bluetooth signal can not be transmitted underwater.

Not for swimming under water



Notes for signal transmission distance
(as show below)



EN

Warning!

1. Do not dismantle or refit the product to avoid malfunction or fire hazards.
2. Keep away from corrosive liquids.
3. Keep away from extreme ambient temperatures below -10°C or above 60°C.
4. Keep away from children and pets.
5. Do not touch the earbuds with sharp objects.
6. Do not use the product in thunderstorm weather.
7. If it has not been used for more than a month, please charge and maintain it in time to ensure that it is safe.
8. Since the Bluetooth signal cannot be transmitted underwater, swimming, diving will caused the signal disconnected or intermittent.

SPECIAL REMINDER:

Wipe the hardware contacts of the headset and charging box when the headset is not charging.



Note:

If your problem is not answered above,
please contact us via email,
we will respond within 24 hours.




Email: info@tozostore.com



Battery Warning!

This product has built-in lithium battery.
Do not expose the product to strong sunlight,
fire or throw it into the fire to avoid explosion.


TOZO®
www.tozostore.com




T6 TRUE WIRELESS STEREO
User Manual

TOZO®

1.0 Product diagrammatic sketch




2.0 Wearing diagrammatic sketch



NOTE: The M ear tips have been pre-attached on the earbuds.

3.0 Wearing steps



4.0 Operation of earbuds

4.1 How to pair

1. Take out the two earbuds from charging case, they will turn on automatically and will connect each other within 10 seconds.
2. The two earbuds flash alternately in red and blue (pairing mode).
3. Search for pairing name [TOZO-T6] and select it in your mobile.

4.2 Another method of turning on & Turning off

- Turn on:
Tap and hold the Touch Control on both earbuds for over 3 seconds.
- Turn off:
1.Touch the Control button 5 seconds will turn off when earbuds in playless status.
2.The earbuds will turn off automatically after it is disconnected for more than 6 minutes.

EN

TOZO®

4.3 Reset

If you accidentally get only one earbud work, or fails to pair each other, please reset it:

- 1.Delete all [TOZO-T6] Bluetooth records on the phone, then turn off the Bluetooth.
- 2.Pick up two earbuds from charging case, then holding both earbuds pannel for 5 seconds untill red lights on to turn off earbuds.
- 3.Pressing the both earbuds for another 5 seconds till red and blue light blinking alternately, and then clicking the both earbuds twice quickly.
- 4.The reset will be done when the blue light flashes rapidly, and then red and blue light blinking alternately.

NOTE: In case there is [Connection Unsuccessful] in your devices, please delete all historical records of [TOZO-T6] and try the paring process again.

5.0 Charging

5.1 Charging the earbuds

1. Put the earbuds into the charging case, they will power off & be charged automatically. When the red LED lights up, it means that the earbuds are being charged from charging case.
2. The red light will turn off when the earbuds are fully charged.

5.2 Charging the charging case

Please use the 5V/1A adapter to charge the charging case, which can be charged with a computer USB or other USB interface charger.


5.3 Box wireless charging

Designed for the modern life, never be strangled by headphone cables. Enjoy the convenience of wireless charging and free charging devices provided by airports, hotels, and cafe shops around the world.

NOTE: The battery indicator—white indicator light is above the wireless charger.

5.4 Charging warning

Don't tap the earbuds touch button while in charge, otherwise it will be fail to pair.
Then you should follow the reset to factory settings.



EN


6.0 Button operation

6.1 Earbuds LED Indicator


Turn on	Blue light flash for one seconds
Turn off	Red light flash for one seconds
Pairing status	The two earbuds flash red and blue alternately
Paired with the phone	Non-flashing light
Charging process	Red lights on
Fully charged	Red light goes out

6.2 Music Operation

(Operation in wearing of double earbuds)



6.3 Calling Control



NOTE: If you accidentally get only one earbud paired with phone, please make sure both earbuds have been turn on. (Tap and hold the unpaired earbud for 3 seconds to turn on). If necessary, please try "Reset" options to restore to factory settings.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

.....

- English:

This device complies with Industry Canada licence-exempt RSS standard(s).

Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

.....

- French:

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.