

BTE008 SPORT BLUETOOTH EARBUDS



User Manual

Get started

Congratulations! Thank you for choosing BTE008 Bluetooth stereo headphone. Before using BTE008, users should read this manual to familiarize themselves with the Bluetooth functions of your mobile phone or other devices.

Safety Rules

- 1, Please follow the rules depicted in this manual carefully to ensure your safety. Before using this BTE008, we would strongly encourage you to read through this user manual.
- 2, Be more care of any edges, uneven surfaces, metal parts, accessories and packaging to avoid any possibility of injury.
- 3, Do not dismantle, repair and modify product to avoid fire breaking, electric shocking and product damaging completely, which are not covered under warranty.
- 4, Do not use any diluents or volatile liquid to clean the BTE008.
- 5, Do not use the BTE008 in a hazardous location.

Kit Contents

- 1, 1 X Stereo Bluetooth headphone BTE008
- 2, 1 X Charging Micro USB Cable
- 3, 3 X Eartips (L/M/S)
- 4, 1 X User Manual

Features:

- *Stable & Mature AIROHA Chipset
- *Bluetooth 5.0
- *IPX5 rated (sweatproof)
- *Charging Voltage: 5V
- *Battery: 140mAh Lithium battery
- *Lightweight and comfortable earbuds
- *180 hours standby time
- *Easy to pair



How to use

1, L&R orientation

Note eartips angle inwards(forwards)
following direction of your ear canal.

This means that L&R orientation is
reversed for over-ear, as explained later.



2. Great sound performance is in selecting the right size eartip

We love great sound. Make sure you hear it.

Because everyone's ears are different, be sure to try all sizes of eartips. Only with the right size eartips will you enjoy snug fit & premium sound quality.

Back it up with secure fit ear cushions.

The earbuds may slip out of your ear a little. You will lose bass when this happens so use the secure fit ear cushions to hold them in place for best sound.

3. General Function

Operation	LED Status
Power on	Blue LED flashes 1 second
Power off	Red LED flashes 1 second
Pairing	Red LED & Blue LED flashes alternately
Standby	Blue LED flashes 1 time in 5 seconds
Incoming call	Blue LED flashes continuous
Low battery	Red LED flashes
Charging	Red LED flash when in charging Blue LED flash when charging finished

4, Basic Buttons Operation

Power on: Press multifunction button for 2-3 seconds. Blue LED flashes 1 time.

Headphone turn on. (ps:no power on under charging condition)

Power off: Press multifunction button for 3-4 seconds. Red LED went out after 1 second.

Headphone turn off.

Volume up: Short press the “+” button for volume up. When volume reaches to Max, "Tick" reminding voice occurs.

Volume down: Short press the “—” button for volume down.

Play/Pause: Short press multifunction button, music pause. Press it again, music continues.

Previous: Long press 2 seconds 'volume down' button, music turns to previous song.

Next: Long press 2 seconds 'Volume up' button, music turns to next song.

Answer Call: Short press multifunction button to answer the phone call.

End call: Short press multifunction button, phone call ended.

Reject call: Press multifunction button for 1-2 seconds to reject a call.

Last number redial: in standby status, press multifunction button twice to redial the last number.

Charging: New headphone has enough power for pairing and dialing out for several times. When in low battery, please charging via USB cable for 2 hours. Red LED keep lighting during charging, blue LED keep lighting when charging finished.

Reset Mode: When charging, long press “+” button for 3-4 seconds at the same time to release pairing list, when red LED flashes once, headphone reset finished.

Keep current calls and accept new ones: Double press MFB button to put ongoing call on hold, answer a new call (ps: need mobile phone to support call waiting function)

Switch between phone calls: Double press MFB button

Low power alert: Red LED flashes

Specification

Bluetooth version:	5.0
Talk time:	7h
Stand-by time:	180h
Music play time:	7h
Wireless range:	≥10m
Bluetooth profiles:	A2DP、HFP、HSP、AVRCP
Impedance:	16Ω
Sound pressure level:	94±3dB
Frequency Response:	20Hz---20 KHz
Weight:	20g

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance

could void the user's authority to operate the equipment.

This device complies with Part

15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.