

ITEM NO. 99/05

## CAUTION:

- Your Transceiver Set has been fully adjusted prior to shipment from the factory. Be sure not to touch the internal components other than replacing the battery.
- 2. When the sound becomes weak, it is time to change the Battery.
- After use, always return the "ON-OFF" Switch to the "OFF" position.
- 4. Keep your set in a dry and clean place.

## **HOW TO OPERATE YOUR TRANSCEIVER:**

- 1. Open battery cover and snap in a 9-volt battery.
- Turn the "ON-OFF" switch to "ON" position. Your transceiver is now ready to operate.
- 3. Press the "PUSH-TO-TALK" switch for transmitting.
- 4. Release the "PUSH-TO-TALK" switch for receiving.
- When transmitting, speak clearly in a normal voice, holding the set about 3" from your mouth.
- Best transmission and reception are obtained when the antenna is held in a vertical position.

## HOW TO USE MORSE CODE FUNCTION:

- For transmitting a signal, turn the "ON-OFF" switch to "ON" position.
- While pushing the "PUSH-TO-TALK" button, press in the morse code button momentarily and release for desired signals.
- For receiving a signal, adjust valume control for normal listening level.
- When back to voice communications again, use normal "PUSH-TO-TALK" operation.

## **REMARK:**

Modifications not authorized by the manufacturer may void users authority to operate this device.