



Vision 650

User Manual V1.0



Please read the User Manual

PACKING INVOLVED



Introduction

Thank you very much for purchasing Vision 650, our bone-conduction headphone.

Vision 650 is a wireless bone conduction headphone-free Bluetooth communication system. They can communicate wirelessly via Bluetooth with all smart phones and other electronic devices, such as MP3 players, PCs and Apple systems, allowing you to easily and safely listen to music and phone calls without being constrained by wires.

While you are skiing, cycling, driving, jogging, or walking, you will do so with an improved level of personal safety, because Vision 650 is based on the bone-conduction system which allows you to hear good and clear sound through your bones directly to your internal ear while still being able to safely hear the sounds around you.

Vision650

USER MANUAL

Safety instructions

For safe and correct usage, please read these Safety Instructions before using.

All of the following points contain important safety instructions and must be strictly followed.

- ⚠ If the environment is noisy, use soft ear plugs.
- ⚠ The greater the volume of the headset, the corresponding power consumption will increase, the vibration will be greater, the use of time will be shortened.

SPECIFICATIONS

Speaker Type	Bone-Conduction Speaker
Bluetooth Version	Version 4.0, Class 2
Operation Frequency	20HZ-20KHZ
Playback Time	6h
Charging Time	2h
Standby Time	20day
Effective Distance	10 m
Weight	30g
Size	130*115*48 mm
Battery	Li-ion Battery (200MAh 3.7V)

Vision650

USER MANUAL

PRODUCT & BUTTONS



How To use

Charge the headphones with the included micro-USB cable. The LED light will turn from Red to green when charging is complete.

Pairing Procedures

Your new Vision 650 can be connected only to mobile phones, music readers, GPS navigators and other devices that are equipped with Bluetooth communication system.

To achieve wireless connection with your Bluetooth mobile phone, it is necessary to make an initial setting operation called "Pairing".

The Pairing process is required only when the product is used for the first time. From the second time on, when you push the power switch, "ON", some phones will reconnect automatically while others will show the message, "Do you want to connect with Vision 650?" If you see this message, you must push "OK".

Bluetooth Connecting Operation

To avoid mis-pairing with other devices, please locate your Vision 650 and the device that you wish to pair it with as close as possible (best within 1 meter).

Press and hold the Power ON button for 5 seconds, until the green and red LED flashes alternately. Vision 650 is in pairing mode now.

Search for Vision 650 using your phone or other device.

Select "Vision 650" from the list of devices discovered from your phone or music reader.

Follow the onscreen steps to confirm the selection.

Please Note:

Some models of phones or music devices also may require you to insert a password. In this case, please enter the passkey "0000" (four zero). When pairing is successful, the green LED will flash slowly. In the future, you will not need to pair again. You will only have to follow the normal power on procedure.

Remove Bluetooth connection:

Power off your Vision 650.

Place your Vision 650 out of the Bluetooth sensing distance of the paired device, select the disconnection function on the paired device, and follow the procedure.

● Answer the phone

The Vision650 has an answering phone feature. When there is an incoming call, press the answer button to answer the call.

● Volume down/Power button (B); Volume up Button (C)

Function	Action	Prompt/Audrey says"
Power on	Press and hold volume- for 3 seconds.	"Welcome to the voice world"
Power off	Press and hold volume- for 3 seconds.	"Goodbye"
Mute	Press and hold both buttons for 2 seconds while on a call	"Mute on"/or"Mute off"
Check battery status	Click the volume up or down button while music is paused	"Battery high, Battery medium Battery low, charge me"
Adjust volume	Click the volume up or down button to adjust volume	One beep

● Disposal device cannot be turned on

1. If the device cannot be turned on, please plug in the USB twice, the red light will be bright and the device will return to normal.
2. If the device is still unable to start up, please consult the after-sales service.

LED Indicator

Solid red	Charging
Solid green	Charging complete
Flashes red and green	Pairing mode
Flashes green	Incoming call
Flashes red every 2 minutes	Low battery

Multifunction Button(A)

Function	Action	Prompt/Audrey says"
Play/pause music	Click one	One beep
Skip to next song	Double-click while music is playing	One beep
Answer/end call	Click one	Two\ One beep
Answer call waiting and put the current caller on hold	Click one to switch between callers	One beep
Answer call waiting and hang up on current caller	Press and hold for 2 seconds	One beep
Reject a call	Press and hold for 2 seconds	Two beep
Prompt device assistant	Press and hold for 2 seconds	Device beep
Redial last number	Double-click	"Last number redial"

Multipoint Pairing

Multipoint pairing allows Vision 650 to be connected to two devices at once, allowing user to Seamlessly transition between the two.

1. Start with your headphones off.
2. Press and hold volume- until Audrey says "Pairing" and the LED light flashes red and green.
3. Press and hold the multifunction button and volume- button for 3 seconds. Audrey says "Multipoint Enabled".
4. Open your first device's Bluetooth menu and select "Vision 650", Audrey says "Connected".
5. Turn off your headphones.
6. Re-enter Pairing mode by pressing and holding volume- until Audrey says "Pairing" and The LED light flashes red and green.
7. Open your second device's Bluetooth menu and select "Vision 650", Audrey says "Connected".
8. Turn off your headphones.
9. Turn on your headphones, Your headphones are now connected to both devices.

How to reset your headphones

1. Start with your headphones off
2. Enter pairing mode by pressing and holding volume- until Audrey says "Pairing" and the LED light flashes red and green.
3. Press and hold the multifunction button , volume- button and volume+ button (all three buttons) simultaneously for 3-5 seconds, until you hear two beeps or fee vibrations.
4. Turn off your headphones . Vision 650 is now reset and can be re-paired to your device.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To assure continued compliance, any changes or modifications not expressly approved by the party.

Responsible for compliance could void the user's authority to operate this equipment. (Example- use only shielded interface cables when connecting to computer or peripheral devices).

This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement.
The device can be used in portable exposure condition without restriction.