

# User Manual

# Introduction

Mic 2 is a dual channel wireless microphone system, including two transmitters and one receiver, which is able to record two sound sources simultaneously. The transmitter has a built-in omnidirectional microphone, supports the use of an external microphone, and can be clipped to clothing or any place close to a sound source. The charging case provided is able to charge the transmitters and receiver simultaneously and link them automatically.

## Overview

### DJI Mic 2 Transmitter

1. Recording Status LED

Indicates the record status of the transmitter.

Blinking Pattern	Descriptions
Solid red	Recording
Pulses red	Mute
Off	Not recording

2. Data Port (USB-C)

For copying audio or updating firmware after connecting to a computer. Can also be used for charging.

3. Record Button

Press once to start or stop recording.

4. 3.5 mm TRS Input

For connecting external microphone. DO NOT connect a microphone with a power supply of 24 V or 48 V.

5. System Status Indicator

Blinking Pattern	Descriptions
<b>Battery Level Descriptions</b>	
Solid red	Battery Level $\leq 20\%$
<b>Noise Reduction</b>	
Solid yellow	Noise reduction is enabled
<b>Connection Status to the Receiver</b>	
Solid green	Connected with the receiver
Blinks green slowly	Disconnected from the receiver

Blinks green quickly	Linking
<b>Bluetooth Connection Status</b>	
Solid blue	Connected with the Bluetooth device
Blinks blue slowly	Disconnected from the Bluetooth device
Blinks blue quickly	Linking
<b>Battery Level During Charging</b>	
Blinks green slowly	Battery level: 0~25%
Blinks green twice	Battery level: 26~50%
Blinks green three times	Battery level: 51~75%
Blinks green four times	Battery level: 76~100%
Off	Fully charged

## 6. Linking Button

Press and hold for 2 seconds to start linking to the receiver. Once the receiver is attached to a mobile phone and the receiver and transmitter are linked, press once to take a photo or start or stop recording on the mobile phone (only supports mobile phones where the volume button can be used to take a photo or start or stop a video).

## 7. Power Button

Press and hold for 2 seconds to power on or off. Press twice to mute.

## 8. Charging Pad

Charging will begin after connecting the transmitter to the charging pad of the charging case and the transmitter will automatically link with the receiver in the charging case.

# Specifications

Name	DJI Mic 2 Transmitter
Model	DMT02
Dimensions	30×50×25 mm
Weight	25.2 g
Wireless Mode	GFSK 1 Mbps and 2 Mbps
Operating Frequency	2.4000-2.4835 GHz

Transmitter Power (EIRP)	< 20 dBm
Bluetooth Protocol	BR/EDR
Bluetooth Operating Frequency	2.4000-2.4835 GHz
Bluetooth Transmitter Power (EIRP)	< 20 dBm
Battery Type	LiPo 1S
Battery Capacity	360 mAh
Charging Temperature	5° to 45° C (41° to 113° F)
Operating Temperature	-10° to 45° C (14° to 113° F)