

  Please scan here to download user manual Mechanical Gaming Keyboard Operating Instructions	US UK Dear user Thank you for choosing REDRAGON product. To protect your rights and for better customer service, please read the following warranty rules carefully. 1. Within 18 months of purchase date, repair is guaranteed for failure due to electrical circuit problems. Other damages, such as disassembly, hard impacts, submersion into water, plugging into improper current or voltage, and damage caused by natural disasters such as fire, flood, or earthquake are not included. 2. Consumable parts (such as foot pads) and spare parts replacement are not included in our warranty. 1	OS Support WinXP/Vista/Win7/Win8/Win10 /Win11/Mac OS How to connect the keyboard with multi-ple devices Wired Connection 1. Slide the ON/OFF switch on left side of the keyboard to OFF. 2. Take out the USB A to USB Type C cable in the package and connect the keyboard with your computer, the computer will recognize and configure the keyboard automatically. 3. Once the keyboard is powered up, charging begins. The LED marked with “M” lights on red. It will turn to white when keyboard is fully recharged. 2.4G Wireless Connection 1. Slide the ON/OFF switch on left side of keyboard to ON. 2. press [FN]+[4] for about 3 seconds, the LED marked with “M” flashes quickly in green, plug the USB receiver into any available USB port on your computer within 20 seconds. The computer will recognize and configure the keyboard automatically. 3. The indicator will flash on Red when the battery is low. Please recharge the keyboard in time by plug type C cable into computer or it will turn off automatically soon, Please note LED marked with “M” will be light on Red while charging, it turn to Green when charging completed(In 2.4g connecting mode) Bluetooth Connection 1. Slide the ON/OFF/BT switch on left side of keyboard to ON. 2. Press [FN]+[1](or [2]/[3] for other Bluetooth devices), the LED marked with “M” flashes in blue (or cyan/magenta for the others) 3. Turn on Bluetooth and scan for available devices on your computer or smart phone. It will find “3.0 Keyboard or 5.0 Keyboard” device. Select one of them to get connected with it automatically. 2	4. The indicator will flash in Red when the battery is low. Please recharge the keyboard in time by plug type C cable into computer or it will turn off automatically soon, Please note LED marked with “M” will be light on Red while charging, it turn to cyan/magenta when charging completed(In Bluetooth connecting mode). Function Introduction 1. With standard USB and 2.4G/BT connections, the keyboard can be used on computer without any software or driver installation. 2. There are 20 backlight effects. 3. Commands of key combinations with [FN] key [FN]+[N]: Change backlight mode. There are 20 backlight effects. [FN]+[M]: Change back light color. [FN] + [←]: Slow down the running speed of backlight . [FN] + [→]: Add up the running speed of backlight. [FN] + [Win]: Disable or enable the [Win] key. [FN] + [1]: Select Bluetooth device one (for Bluetooth connection). [FN] + [2]: Select Bluetooth device two (for Bluetooth connection). [FN] + [3]: Select Bluetooth device three (for Bluetooth connection). [FN] + [4]: Change to 2.4G wireless connection. Press and hold the [FN]+[4] for 3 seconds to pair the keyboard with its receiver. [FN] + [ESC]: Set the keyboard to default setting. [FN]+[PrtSC]: Turn ON/OFF backlight [FN]+O: ScrLK [FN]+P: Pause [FN]+[{ }]: INSERT [FN]+[]]: DELETE [FN]+[;]: HOME [FN]+[' "]: END [FN]+[. >]: PAGE UP [FN]+[/ ?]: PAGE DN 3
---	---	---	--

Multi-Media function FN+F1: My computer FN+F2: Open browser FN+F3: Calculator FN+F4: Media player FN+F5: Previous track FN+F6: Next track FN+F7: Play/Pause FN+F8: Stop FN+F9: Mute FN+F10: Volume- FN+F11: Volume+ FN+F12: My Email

How to recharge the keyboard

Find the USB A to USB type C cable in the packaging ,plug the keyboard and connect it with computer for charging, the LED indicator(M) of keyboard will be turn to red.

Remark: The LED indicator (M) will turn to red when keyboard is out of battery.

4

型号	K643WGC-RGB-PRO/8886		备注：尺寸：100x100mm (折页) 材质：80g书写纸 印刷：单黑色双面印刷				Eastertimes Tech 	
名称	说明书							
日期	2023-8-9(修改)							
页码	1 OF 1		文件编号					
绘图	雷国建	审核			核准		版本	A.2