

User Manual



I . Production Description:

The Bluetooth earphone of IQ-130BT is a high quality stereo Bluetooth headphone which possesses wireless music and calling function. Appearance vogue, beautifully designed, easy to carry, suitable for household, outdoor travel and other places, enjoy music anytime and anywhere. Provide super perfect sound quality for you're your computer, digital music players, and mobile phones and so on audio-visual products.

II .Function Features:

【Bluetooth Play】 Support pairing Bluetooth devices to play music such as mobile phone, tablet, TV.

【Hands-free calls】 Support for hands-free calls function, built-in high sensitive microphones, making phone calls have carefree to enjoy.

【Voice Prompt Coming Calls】 It will prompt the phone number when

you have a coming call, it is more convenient.

【IOS Battery Display】 IOS mobile phone real-time display the earphone battery, let you know the earphone battery.

【MP3 Play】 Play the TF card MP3 files directly.

【FM Radio】 FM digital stereo radio, Automatic search and memory radio, save time and effort.

【Audio Input】 stereo audio input ports ,easy to connect the computer, digital music player, mobile phone and other audio-visual products so on all kinds of audio source.

【Rechargeable Lithium Electricity】 The built-in rechargeable lithium battery, environmental protection, economical and practical.

【Intelligent Charging】 The voice prompt please charge when the battery is low, when full charge it will automatically cut off power to avoid battery charging too much to damage to the battery.

III. Operation of Play music:

Microcomputer system of the native can automatically detect recognition peripherals, enter the Bluetooth mode after power on, automatic identification play when insert TF card. Insert audio signal will automatic power off and turn to ordinary headphone for use. Detailed functional operation, please read the fourth "Function Definition of Product Buttons and Slot"

IV.Function Definition Of Product Buttons And Slot:

①  ②  /V+ ③  /V- ④ FM/MP3 ⑤  ⑥ Micro
USB Charging Ports ⑦ Audio Input Ports ⑧ TF Card Slot ⑨
Built-in Mic ⑩ Status indicator lamp

① : Long press about 3 second, it was default to the Bluetooth mode after power on, the blue light and green light alternately flashes, now the Bluetooth enter match mode. Again long press about 3 second to power off, indicator light will be off. In listening to TF card music or mobile phone music via Bluetooth, short press this button the music was suspended, short press the music will be suspended, short press again music from the new play. In listening to the radio, short press for all automatic channel search platform, and store the search to radio down (for the first time to use this headphones listening to the radio, please make a full channel searching operation), it will take about 1 minute to complete the whole channel searching time.

② /V+: In listening to TF card music or mobile phone music via Bluetooth, Short press for play the next song. Listening to the radio, short press to select radio stations that broadcast the next stored. long press for turn up the volume in any mode.

③ /V-: In listening to TF card music or mobile phone music via Bluetooth, Short press for play the previous song. Listening to the radio, short press to select radio stations that broadcast the previous stored. long

press for turn down the volume in any mode.

④FM/MP3: Long press can switch to radio, Bluetooth, TF card mode (only insert TF card can switch to the TF card mode) in turn. Listen to mobile phone music via Bluetooth or TF card music, short press can choose natural, pop, rock, jazz, country, heavy bass six kinds of sound in turn

⑤📞: After the success connection of the Bluetooth and phone, when short press for answering the phone call, long press can refuse to answer the phone. After the call short press for hang up, continue press two times will redial the last time phone number.

⑥【Micro USB Charging Port】: Power input jack, can use the native USB cable connect to the computer USB interface for charging, or use a mobile phone charger to charge.

⑦ 【Audio Input】 stereo audio input ports ,easy to connect the computer, digital music player, mobile phone and other audio-visual products so on all kinds of audio source.

⑧ 【TF CARD Slot】 : Insert the TF Card to play the music.

V. Bluetooth Pairing Operation Method:

In the Bluetooth mode, the blue light and green light alternately flashes, it is the state of the Bluetooth pairing, At this time search the corresponding Bluetooth device name on the phone, click the device name on the mobile phone for the Bluetooth pairing, hear "Connect successfully" means the

pairing is successful, the Status indicator lamp lights blue color.

VI. The Radio Function Using Method:

Volume control, long press the “◀◀/V-” key to turn down the volume, long press the “▶▶/V+” key to turn up the volume.

1. Automatic searching

In FM radio mode, press “⏻/▶” key to start searching automatically. Indicator lights flashing when searching, automatic memory and save the stored after the completion searching.

2. Memory channel selection

After automatically searching, press the “◀◀/V-” or “▶▶/V+” key can select the radio has been saved.

VII. Method of turn to ordinary headphone:

Insert the 3,5mm audio line jack into the audio input ports, the Bluetooth headphone will automatically power off, can use the Bluetooth headphone as ordinary headphone now, at the same time the function of the Bluetooth headphone are useless(power off status) to save the electricity.

VIII.Method Of Charging :

Insert the end of the charging cable to native MINI USB socket, the other end of the USB plug into the PC USB port, or connect to the standard 5 v charger interface, the indicator light turns red when charging, the red light will extinguish when full of.

IX. Low Battery:

When there was a low voltage power, the machine will prompt "Low battery, please charge", and then will automatically shut down, please recharge in time at this time. If it is not to be used for a long time, charging one time every month at least, it can protect the battery and extend battery life.

X. Technical specifications:

- | | |
|-----------------------------|----------------|
| 1. Charging voltage: | Micro USB 5V |
| 2. Working current: | 30-50mA |
| 3. Bluetooth Working range: | 10M |
| 4. Output power: | 2×20mW |
| 5. Frequency range: | 2.402-2.480GHz |
| 6. Distortion factor: | ≤1% |
| 7. SNR: | ≥95dB |
| 8. Support TF Card: | 128M-32G |
| 9. Radio frequency: | 87.5-108MHz |
| 10. Frequency response: | 20Hz-20KHz |

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.