

On My God, **教学视频**太好用了吧!



认识耳机

双耳机配对

首次配对方法: 1、取出两只耳机,再将两只耳机放回充电盒中。(此步骤为

新机激活) 2、再次取出两只耳机

3、刷新手机蓝牙设备列表,点击配对QCY-T6,完成配对 *耳机取出会自动开机,若未自动开机,请充电后重新尝试

切换设备配对方法:

1. 关闭A手机蓝子,耳机自动断开进入配对模式 2. 刷新B手机蓝牙设备列表,点击配对QCY-T6,完成配对 *不支持同时连接两台手机,下次开机默认回连上次配对的




恢复出厂设置

清除配对记录(此方法用干无法正常连接时)

1. 已有连接过手机,在手机蓝牙设备列表中,找到QCY-T6,点击进入设置,选择忽略或取消配对。 2. 取出两只耳机,同时长按8秒,直至红灯长亮2秒后熄灭,表示调为关机状态。 3. 重新同时长按两只耳机大约10秒,直至红绿灯同时闪3次,

红灯闪1次,表示耳机重置成功。 *恢复出厂后用首次配对的方法连接即可正常使用

「東京の一川市国の成功3077/ACES (1997年) 手動配対 (此方法領用予封直手失链接的情況) 关机状态下,触摸触控板5秒,直至红绿灯交替闪,再次触摸 兩次触控板、操作成功后,紅绿灯会同时闪烁(双耳同时操作) 如果出現主耳紅绿交替闪烁,副耳灭灯的情况,则为两只耳 机组队成功。



佩戴耳机

1.将耳帽斜向下轻轻塞入耳道,以轻摆头部耳机不晃动 75 a.。 2.通话时,将耳机麦克风朝向嘴部可使通话更清晰。

三方通话接听与切换通话

当手机来电时,双击触控板接听电话进行通话;当手机有新来电时,双击触控板保持上一个通话,进行第 二个来电的通话。 长按触控板2秒可以随意切换两个通话。

拒接第二个来电

当手机来电时,双击触控板接听电话进行通话;当手机有新来电时,长按触控板2秒拒接新来电,继续保持当前通话。

单耳机使用模式

1. 耳机在关机状态下,任一耳机长按触控板约5秒,进入配对 状态 (红绿灯交替闪烁)

2. 打开手机蓝牙搜索配对名,选择QCY-T6点击连接。 3. 连接完成

给耳机充电

耳机放入充电盒中,即关机进入充电状态,充电时红灯常亮, 充满电后绿灯常亮1分钟后熄灭

给充电盒充电

当电量小于60%时,充电盒亮红灯;当电量在60%~95%时,充电盒亮绿灯;当电量在95%以上,充电盒亮蓝灯。

型 号: In1947 配对名: QCY-T6 蓝牙版本: V5.0 待机时间: 约100小时 充电时间: 约2小时 音乐时间: 约6小时 通话时间: 555-小时 通信距离: 10米 (无障碍环境下) 电池类型: 聚合物锂离子电池

耳机电池容量: 3.7V 60mAh 充电盒电池容量: 3.7V 600mAh 充电盒输入参数: 5V==600mA 支持协议: HSP/HFP/A2DP/AVRCP

Th能会细

QCY-T6

TWS真无线蓝牙耳机

使用场景	状态	操作/现象	LED	语音提示	
	关机状态下,且未有配对记录前提下(首次使用)	长按触控板1秒开机自动进入配对状态	红绿灯交替闪	TONE音	
TWS相互配对	关机状态下长按5秒进蓝牙 配对模式	双击触控板1次进入TWS配对搜索	红绿灯同时双闪,连 上左耳进入配对状 态,右耳灭灯	TONE音	
TT-40	关机状态下	长按触控板1秒	绿灯常亮1秒	TOUE	
开机	充电状态下	从充电盒拿起,耳机开机	绿灯常亮1秒	TONE音	
关机	开机状态下	长按触控板8秒(未连接设备是可联动关机)	红灯常亮2秒	TO115 TO	
		放入充电盒,关机	红灯常亮	TONE音	
接听电话/结束电话	来电响铃中/通话中	双击触控板	\	TONE音	
拒接来电	来电响铃中	长按触控板约2秒松手	\	TONE音	
唤醒语音助手	在已连接状态	三击触控板	\	TONE音	
来电	耳机连接手机	耳机有铃声提醒	\	来电响针	
音乐暂停/播放	音乐状态下	双击触控板	\	\	
切换上下曲	音乐状态下	左耳机长按2秒上一曲,右耳机长按2秒下一曲	\	\	

QCY蓝牙耳机售后服务

- QCY蓝牙耳机售后服务承诺:严格按照(中华人民共和国消费者权益保护法)、《中华人民共和国产品质量法)实行售后三包服务,服务内容如下: 在三包有效期内,您可凭购物凭证依照本规定享受免费的修理,更换,退货

- 产品质量问题。可享受修理的服务。 售品服务与支持 传修那,又口起12个月(请变着保管购买凭证) 在一品保修期内,用产品本身质量引起的故障。请用户凭购买凭证与经销商取 对部任何户品格等现在,是一品本身质量引起的故障。请用户凭购买凭证与经销商取 对部任何产品需求或验验申可归贵于产品质量本身,则不在保修范围内。有下列 情形者不属于保修范围内。 1.因天灾、地震、雷击、异常电压、环境因素而发生之故障或短期的。 2.自行或委托未经规厂按规维修之厂商拆卸、改装或更换非原厂零件。 3.未按使用于解处维修之厂商拆卸、改装或更换非原厂零件。 3.未按使用于解除作或因人为使用不当而造成损坏者,如产品潜水、腐蚀、掉落、 矫正或属在异常温湿度环境下。

P广信息: 户姓名 系电话
订单编号 用户信息: 用户姓名 联系电话
用户姓名 联系电话
联系电话
用户地址
退換货原因
销售单位

FAQ

1.Q:怎么只能听一个?A:将两只耳机放回充电舱,重新取出查看是否恢复双耳模式,如未恢复重置耳机即可解决。

2.Q:手机提示无法连接怎么解决? A:将手机上的配对记录删除,删除后重新进行搜索信号连接

3.0:怎么听歌/通话没声音?

(人)、公司助人四公汉户目: A:安卓在手机连接记录的右边有个设置图标,点击进入,将两个音频选项取消勾选重新选择,苹果在设置通用辅助功能进入音频通话方式,选择自动,如未就是自动,就换其他选项,然后选择自动,如未恢复,删除配对记录重新尝试。

4.Q:怎么视频/游戏有延迟?A:受使用环境、网络、手机编解码速度的影响,会造成手机传送音频数据到耳机时造成不同程度的延迟。

5.Q:怎么卡頓/斷续? A:亲,如果使用时有大量的 Wi-Fi 连接、4G 信号、大功率电器等等产生干扰,可能会出现卡顿、断续的情况,换个环境或者重新配对连接下就可以解决了。

若有售后服务需求,请联系客服

网址:www.qcy.com 制造商:东莞市和乐电子有限公司 地址:广东省东莞市道滘镇大岭丫工业区(粤晖路大岭丫段5号)

产品中有害物质的名称及含量

		有書物质									
1	部件名称	铅的	汞 Hg	顎 Cd	六价铬 Cr (M)	多溴 联苯 PBB	多溴 二苯醚 PBDE	邻苯二 甲酸二 异丁酯 DIBP	邻苯二 甲酸 (2-乙酯) DEHP	邻苯二 甲酸二 丁酯 DBP	邻苯二甲酸丁 干酯 BBP
i	耳机主体	Χ	0	0	0	0	0	0	0	0	0
1	电 池	0	0	0	0	0	0	0	0	0	0
1	耳 套	0	0	0	0	0	0	0	0	0	0
	配 件	0	0	0	0	0	0	0	0	0	0
	奈 由 线	Х	0	0	0	0	0	0	0	0	0

本表格依据SJ / T 11364的规定编制

O:表示该有害物质在部件所有均匀材质中的含量均在 (EU)2015/863规定的限量要求以下。 X:表示该有害物质至少在该部件的某一均质材料中的含量超出 (EU)2015/863规定的限量要求,但目前行业无成熟的替代方案,

在豁免范围仍符合欧盟ROHS指令的环保要求。



如本手册所述,在正常使用条件下,本产品的环保使用期限为10年 在此期间,产品不会泄露任何危险物质,本产品可以回收,必须按 照当地法规处理。







- 1. 使用产品前请仔细阅读本使用说明书并请妥善保管;
- 2. 首次使用时,请先将本产品充满电;
- 3. 如果产品长期(超过2个星期)不用,请对其充电; 4. 必须选择正规厂家生产且经过国家CCC认证的充电器;
- 5. 若手机无法搜索蓝牙耳机,请确认蓝牙耳机是否处于"配对模式",若长时间未进行配对或连接,蓝牙耳机配对功能将关闭, 请重新开启蓝牙耳机至"配对模式";若手机程序出错,请重启 手机;若蓝牙耳机程序出错,请重启蓝牙耳机或者恢复出厂

- 请勿以任何理由拆除或维修改装耳机,否则可能会导致起火,
- 电子击穿甚至彻底损坏本产品; 请勿将产品置于温度过低或过高(0℃以下或45℃以上的环
- 元,, 请避免靠近儿童或动物的眼睛使用产品指示灯; 请勿在雷暴天气下使用该产品,雷暴可导致本产品工作不正常,
- 请勿用油及其他挥发性液体擦拭本产品;

注意:长时间使用耳机可能会造成听力损害,请合理安排使用

时间。 本耳机不支持输出超过2A的充电座给耳机充电,否则会 损害耳机本体。

330 mm

折页线

CCA



55 mm




QCY-T6

Overview

Choose Your Eartips







How to Pair

1. Pick up both earbuds, pop both earbuds into the case

to activate them. 2. On cellphone, search for QCY-T6 and tap to conr *Once paired earbuds will auto power on upon picking up from the case. If earbuds fail to auto power on, please charge them and try again.

1. Turn off phoneA's Bluetooth faculty and earbuds will auto disconnect and enter into pairing mode. 2. On phoneB, search for QCY-T6 and tap to connect.

auto reconnect to phoneB upon powering up again.



Factory Setting

(Try the following steps to fix connectivity issue)


On cellphone, search for QCY-T6, tap and choose ignore

or cancel pairing.
2. Pick up two earbuds, keep touching both bars for 8s or until LEDs glow red for 2s to power off.

3. Keep touching both bars for 10s or until LEDs blink red and green 3 times then blink red to set earbuds to factory. *Please refer "First Time Pairing" to connect after factory

Manual Pairing (please refer the following steps in case two

earbuds lose connection) Power off earbuds then keep touching panels for 5s or until LEDs blink red and green. After then, double touch panels and LEDs will blink red and green. Two earbuds will then



How to Wear



1.Rotate earbud and pop it into your ear then shake head to check wearing stability.

2.Please adjust mic towards your mouth to gain better

Three-way Calling & Switch

calling experience.

Double touch the bar to answer incoming call. If another call is coming in sync, double touch again to put the first call on hold while activating the second one or keep touching the bar

for 2s to ignore the second call. Keep touching the bar for 2s to switch between active call and held call.

Mono Mode

L. Power off earbuds, hold Touch Panel on either earbud for 5s to enter pairing mode(LED blinks red and green)

2. On cellphone, search for QCY-T6 and tap to connect

3. Connected

Charging Earbud Push earbud into the case to charge. LED will glow solid red

when charging and turn to green for 1 minute once top up.

Charging the Case LED on the case will glow solid red when battery level is under 60%; LED will turn green when battery level is between 60% and 95 and become solid blue when the battery level is

Product Parameters

Model:ln1947 Pairing name: QCY-T6
Bluetooth version: V5.0 Stand time: approx. 100hr Charging time: approx. 2hr
Talking time: approx. 5.5hr

Stand time: approx. 100hr
Music time: approx. 6 hr

Operation range: 10m(with no obstacle) Battery type: li-ion Battery capacity(earbud):3.7V 60mAh

Battery capacity(charging case):3.7V 600mAh Input parameter(charging case):5V === 600mA Bluetooth profiles: HSP/HFP/A2DP/AVRCP

Function Introduction

TWS Bluetooth Earbuds

Functions	Current status	Operation/result	LED	Prompt	
	Power-off with no connectivity record	Keep touching the bar for 1s to power on and earbud will auto enter pairing mode	LED blinks red and green	TONE	
Entering TWS Mode	Power off then keep touching the bar for 5s to enter pairing mode	Double touch the bar to enter TWS mode	LED blink red and green then right LED turns off	TONE	
Dawer en	Power-off	Keep touching the bar for 1s	LED glows green for 1s	TONE	
Power-on	Charging	Pick up earbuds from the case	LED glows green for 1s	TONE	
Power-off	Power-on	Keep touching the bar for 8s(only two unpaired earbuds will be powered off together)	LED glows red for 2s	TONE	
	Power-on	Pop earbud into the case to power off	LED glows red	TONE	
Answer/end call	Incoming call/calling	Double touch the bar	\	TONE	
Ignore call	Incoming call	Keep touching the bar for 2s	\	TONE	
Voice assistant	Connected	Triple touch bar	\	TONE	
Incoming call	Connected to phone	Incoming call ring	\	call ring	
Music pause/play	Music playing	Double touch the bar to pause,double touch again to resume playing	\	\	
Skip track	Music playing	Keep touching right/left bar to skip track forward/backward	\		

Warranty Card

Warranty Period
12 months after you purchase this item.(or you may inquire your local shopper for more details.)
Free Service:
Supposing any defects caused by quality issues occur within the warranty period, please take this warranty card and purchase receipts to your distributor for free exchance service

exchange service.
Model Number:
Date of Purchasing:
User's Name:
User's Phone:
User's Address:
Shop's Name:
Shop's Address:
Comments:

Free exchange service will not be accessed under following circumstances:

1. Damages caused unauthorized disassembly.

2. Defects or physical damages caused by leaking or dropping off.

3. Damages by act of God.Supposing your item is within any damages or defects except the above circumstances, please return to us or your distributor for free repairing.

FCC Statement

in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.


This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

EMIT (D. SCOODS)

Made In China

RoHS FCC ID:RDR-IN11947R

10) Hazardous substances and their contents in the item



This form is made by SJ/T 11364 regulation.

2: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU) 2015/863 regulation.

: means that hazardous substance content in ,at least

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time. Address: Daojiao Town, Dongguan City, Guangdong, China

Before using the headset, please read the manual carefully and keep it for future references.

2. The headset need to be fully charged prior to first-time use. If the headset is left unused for over two weeks, please recharge it periodically.

4. Please use the chargers made by qualified manufacturer 4. Please use the chargers made by qualified manufacturer. S. If the headset cannot be found by your phone, please check whether it is in pairing mode; if left unconnected for a long while, the headset will exit pairing mode, please re-enter the mode; if a procedure error of your phone occurs, reboot it; if a procedure error of the headsetoccurs, reboot or reset it.

Caveats
1. Never disassemble or modify your headset for any

reasons to avoid any damages and danger.

2. Do not store the headset in extreme temperatures (under 0°C or over 45°C). Avoid using the indicator close to the eves of children or Do not use this headset during a thunderstorm to avoid

irregular function and increased risk of electricshock.

5. Do not use harsh chemicals or strong detergents to

6. Keep the headset dry.

