

688mm									
86mm									
172mm	<div><div><div>canjice</div><div>Product name: True wireless earphones Model: A801-65 Manufacturer: Shenzhen CANNICE Technology Co., Ltd Place of origin: 4th Floor, New Office Building, Caiqiao Printing Factory, Xitou New Village, Tangxia, Dongguan Guangdong. Service Hotline: 400-662-3664</div></div></div>		<div><div>Start</div><div>Packing list</div><div><div><div></div><div>Earphonesx1</div><div></div><div>Charging box X1</div></div><div><div></div><div>Ear cushionsx1</div><div></div><div>USB cablex1</div><div></div><div>Manual/Warranty cardx1</div></div></div></div>	<div><div>Product overview</div><div><div><div>1.Charging box LED light (white light)</div><div>2.USB charging interface</div><div>3.Headphone LED light/Talk noise-cancelling hole</div><div>4. Multifunction button</div><div>5. Talking mic</div><div>6. Breathable hole</div><div>7. L/R logo</div><div>8.Magnetic charge point</div></div><div></div><div></div></div></div>	<div><div>Specs</div><div><div>1. Bluetooth Version : Bluetooth V5.0</div><div>2. Input Power: 5.0V== 500mA</div><div>3. Frequency Response: 20Hz-20KHz</div><div>4. Distance: 10m</div><div>5. Charging time: 2h</div><div>6. Impedence: 32Ω± 15%</div><div>7. IPX Standard Test: IPX5</div><div>8. Speaker Diameter: 5.8mm</div><div>9. Sensitivity(S.P.L) dB: 106± 3dB at 1KHz</div></div></div>	<div><div>Power on</div><div>Method1</div><div>Open the charging box cover and the earphone will start up automatically.</div><div></div><div>Method2</div><div>Press and hold the multifunction button for about 4 seconds in off state.</div><div></div></div>	<div><div>Pairing</div><div>After earphone burning and recording, TWS pairing for the first time: Turn off your phone's bluetooth (the earphone will automatically turn off after 5 minutes) R earphone red and white lights flash alternately, It lights up every 4s</div><div><div>1. If there is a phone pairing record in the headset, it will fail to connect back to the recently used phone and 10s. It will enter the pairing mode again.</div><div>2. Automatically enter the pairing state after manually disconnecting the phone connection.</div><div>3. Long press the touch button for 6 seconds when the L or R earphone is turned off.</div></div><div>Note: Random master and slave of left and right earphones.</div><div></div></div>	<div><div>Connection lost</div><div>Situation 1: Bluetooth off Turn off your phone's bluetooth (the earphone will automatically turn off after 5 minutes) R earphone red and white lights flash alternately, It lights up every 4s</div><div>Situation2: Out of connection distance If the connection between the phone and the earphones exceeds the effective range, the earphone will power off automatically after 5 minutes of reconnection timeout.</div><div></div></div>	<div><div>canjice</div><div>TRUE WIRELESS STEREO HEADPHONES</div><div>A801-65 INSTRUCTION</div></div>
	<div><div>Incoming call</div><div>Answer/End calls</div><div>Click the L/R function button to answer a new call and hang up the phone.</div><div></div><div>Reject calls</div><div>pressing the R/L function button 2 secs,</div><div></div><div>Note: This function is supported when earphone is used alone.</div></div>	<div><div>Voice assistant</div><div>TWS connection status, three taps L/R earphone function button.</div><div></div><div><div>Music</div><div>Pause/Play</div><div>Single click the L/R earphone to play/pause music.</div><div></div></div></div>	<div><div>Music</div><div>Track backward</div><div>Double click the R earphone function button.</div><div></div><div>Track forward</div><div>Double click the L earphone function button.</div><div></div><div>Volume increase</div><div>Long press R function button, every 1 second volume will go up by 1 level, 5 levels totally.</div><div>Volume down</div><div>Long press L function button, every 1 second volume will go down by 1 level, 5 levels totally.</div><div></div><div>Note: This function is not supported when earphone is used alone.</div></div>	<div><div>Power off</div><div>Method1</div><div>Put the earphone into the charging box for automatic shut down and the red indicator is on.</div><div></div><div>Method2</div><div>In the power on state, press and hold the multifunction button for 6 seconds. The red indicator light will be on for 2 seconds.</div><div></div></div>	<div><div>Charging</div><div>Earphone charging</div><div>The charging box does not close the cover, and the charging box charges the earphone;</div><div>Put the earphones into the charging box. The charging box closes the cover and the earphones disconnects the phone to enter the charging state.</div><div></div><div>Note: The charging case lamp effects current status. There is no indicator light during earphone charging</div></div>	<div><div>Charging box charging</div><div>LED status when charging the charging box</div><div>When the power is below 33%, the first light flashes; <33%</div><div>When the power is 33%~67%, the first light is always on, and the second light is blinking; 33%~67%</div><div>When the power is greater than 67%, the front 2 lights are always on, and the 3rd light is flashing; >67%</div><div>100% </div><div>Charging box charge LED status when not charging</div><div>When the power is below 10%, the first light flashes; <10%</div><div>When the electricity is 10%~33%, the first light is on; 10%~33%</div><div>When the power is 33%~67%, the front 2 lights are on; 33%~67%</div><div>When power is 67%~100%, 3 lights are always on. 67%~100%</div><div></div></div>	<div><div>Safety and care</div><div>Using earphone at high to moderate volumes for extended periods of time will result in permanent hearing damage. It is advised you keep volume levels moderate to low at all times for your safety.</div><div>Do not use while driving a car, cycling, operating machinery, or performing other activities that require hearing surrounding sounds.</div><div>Do not use earphone in thunderstorm weather, the earphone may not work properly in the condition, and increase the risk of being hit by lightning .</div><div>Earphone may not work properly under high temperature or high humidity conditions. Do not use any corrosive cleaner/oil to clean the earphone.</div><div>If the earphone comes in contact with liquids, quickly wipe away .If submersed in water, do not turn the earphone on until completely dried. Tips: liquid submersion voids the warranty.</div><div>Keep the earphone and packaging out of reach of children .</div><div><div>Battery warning!</div><div>Improper battery replacement can result in explosion hazard and can only be replaced with batteries of the same type or equivalent type.</div><div>* For batteries with removable batteries, batteries must be recycled or handled properly. Disassembly is not allowed for products that cannot be removed.</div><div>* Do not disassemble, strike, crush or put the battery into fire. Do not expose the battery to conductive materials, liquids, fire, or high temperatures.</div><div>* Do not allow metal objects to touch the two poles of the battery. Do not continue to use the battery if it has bulges, leaks, discoloration, odors, or any other abnormality.</div><div>* Do not use the battery after it has been immersed in water.</div><div>* If the battery is used improperly, it may explode or leak, causing burns and other personal injuries. If the battery leaks, it should be carefully disposed of according to the local laws and regulations concerning battery disposal.</div></div></div>	<div><div>FCC Warning</div><div>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</div><div>NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.</div><div>If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</div><div>-- Reorient or relocate the receiving antenna.</div><div>-- Increase the separation between the equipment and receiver.</div><div>-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.</div><div>-- Consult the dealer or an experienced radio/TV technician for help. The device has been evaluated to meet general RF exposure statement.</div><div>The device can be used in portable exposure condition without restriction</div><div>FCC ID: 2ADTV-A801-65</div><div>Warning: Changes or modifications to this unit not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment</div></div>	

128g铜版纸，688*172mm风琴折

