

Bluetooth version	4.2
Hardware	Ver 1.0
Range	10 meters (equal to 33 feet)
Frequency range	2.402-2.48GHz
Charging input power	DC 5V/1.0A
Max. output power	2W
RF max. output power	3.58dBm
Battery	3.7v, 300mAh lithium
Charging time	Approx. 3 hours
Working time	Approx. 4 hours
Unit weight	Approx. 129g
IP grade	IPX4
Bluetooth firmware	Ver 3.2
Bluetooth software	Ver 4.0

Model number BTS-06 Batch number PPI019393



FCC ID: 2ALSKBTS-06

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

However, there is no guarantee that interference will not occur in a particular installation.

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.



Wireless Shower Speaker

50mm

70mm

Read this manual carefully before putting the appliance into operation and keep this manual for future reference.

- Keep the device away from heat, direct sunlight and sharp edges.
 - Keep the device away from naked flames.
 - Do not insert any metal object into the device.
- Risk of short circuit.
- To avoid a static charge, do not use the device in an extremely dry climate.
 - Do not repair the unit yourself but contact an authorised specialist (danger of explosion if the battery is incorrectly replaced). The authorised specialist should replace only with the same or equivalent battery type.
 - Do not immerse product in any liquid to avoid short circuits.
 - Avoid placing the speaker in direct contact with flowing water.
 - For best results apply suction cup to a smooth, flat surface.

- ⏻ On/off, to switch on or off.
- ⏮ Short press for the previous song, long press for turning down the volume.
- ⏭ Short press for the next song, long press for turning up the volume.
- 📞 Phone, to pick up or hang up a phone call.
- ⏸ Play /Pause the music.

- You can press phone button twice quickly to redial the last phone call.

USB charging cable

This Wireless speaker is powered by integrated rechargeable lithium battery.

- Insert the charging cable into the DC 5V socket on the unit, connect the USB plug into a PC or AC/DC adaptor. The LED indicator turns red when the battery is being charged.
- When the battery is fully charged, the red LED indicator goes out.

Activate the Wireless Speaker's pairing mode in power off mode, press and hold the on/off button for about 6 seconds until the blue LED is flashing. Now the speaker is ready for pairing.

Tips:

- Please make sure the speaker is in power off mode when trying to activate the pairing mode.
- Turn on your mobile phone and activate the bluetooth function.
- Search for Bluetooth devices BTS-06 will show.
- Pair your device with BTS-06. If password is needed, type in "0000". After BTS-06 is paired with your device, connect it to your device.
- Fully charge speaker before first use

Once this speaker is paired and connected to your mobile device, next time when you switch on this speaker, it will connect to your mobile devices automatically as long as the bluetooth in your mobile device is on.

Symptoms	Causes	Solutions
Cannot switch the speaker on	Battery empty	Charge the battery
Unable to pair the speaker	Speaker is already switched on and it is not in pairing mode	Refer to the section "Pairing BTS-06 to mobile phone or other device"

LYNX
wireless speaker, manual, USA

author	Mafalda Goncalves
date	19.05.2017
version	1
scale	1:1
key	○ trim line ○ safe line ○ bleed line ○ fold line
colours	none
finishes	none
fonts	none
notes	none

If you need help or have any questions please contact us in the design studio via londondesign@brandaddition.com.

by **brand addition**