



PACKAGE CONTENT

- 2x SC01 Bluetooth earphones
- 1x SC01 charging case
- 1x Charging cable
- 1x User Manual
- 2x Large ear tip
- 2x Medium ear tip (in the charging case)
- 2x Small ear tip

PRODUCT OVERVIEW

- Charging case
- Earphones
- Charging case indicator light
- Charging port
- Earphone indicator light
- Earphone touch area
- Earphone charging contacts
- Ear tip

THE POP-UP WINDOW SUPPORTS THE FOLLOWING TECNO PHONES

CAMON	19	POVA	3
	19 5G		Nico 2
	19 Premier		9 Pro
	19 Pro	SPARK	9T

BASIC FEATURES OF PRODUCT

Product Name	TECNO Sonic 1 Pro
Model Name	SC01P
Charging Cable	Type-C
Earphone battery capacity	4. mAh*2
Charging box battery capacity	800mAh
Charging Voltage/Current	5V/100mA, 5V/1000mA
Music Playing Time	6.2H+45H†
Standby Time	Approx. 55H
Transmission range	1 km
Bluetooth Name	TECNO Sonic 1
Operating Temperature	0°C~45°C
Storage Temperature	-20°C ~ 60°C
Time for full Charging the Earbuds	1.5h
Time for full Charging the Case	Approx. 3h

EARPHONE INDICATOR LIGHT

Earphone Status	Indicator light status
Power On	White light on for 1S
Power Off	Blue light on for 1S

Charging box low battery: The white light of the charging case flashes quickly while put the earphones in it.

CHARGE

1 EARPONE, 2 WEARING STYLE

Software Function Description

Scan the code to download Weife App and use more functions.

Customization of EQ mode, noise cancellation mode, touch key function and power detection, as well as upgrade of earphone firmware, etc. are supported. (Only available on Android phones)

1 pair of earphones with multiple EQ modes

Various EQ modes: Bass Booster, Treble Booster, Vocal Booster, Default. Choose the style that suits you best.

Earphone Touch Key Customization

- With free customization of functions triggered by earphone touch keys, keep one step ahead of others in answering calls and controlling music.
- When wearing the earphones on both sides, tap and hold the touch area of earphones to switch in a cycle of "Off/Transparency/Noise Cancellation".
- A quick cycle switch between "Noise Cancellation/Transparency" can be set in Weife App, as shown in the right figure.

Create your own music EQ according to your audition.

WARRANTY TERMS&CONDITIONS

A limited 6-month warranty applies to TECNO SC01 purchased from the Tecno-Mobile-Official store. Please feel free to contact us if you run into any problems. This warranty covers only original TECNO products. It does not extend to normal wear and tear, or any effects or damage caused by misuse of the product. The warranty is for primary products only. Additional or free of cost products are not covered under warranty.

TECNO MOBILE LIMITED

TM and ©2022 TECNO Corporation. All rights reserved. Other product and company names mentioned herein may be trademarks or trade names of their respective owners. Specifications are subject to change without notice. Model names and the availability of particular products may vary by region.

www.tecno-mobile.com
serviceus@tecno-mobile.com

Bluetooth, CE, RoHS, Recycle, FCC ID: 2ADY1-SC01P, MADE IN CHINA

POWER ON/OFF

Power on
The earphones will be power on automatically while open the charging case.

Power off
Put the earphones into charging case and close it, the earphones will be power off automatically.

CONNECT SMART DEVICES

Connect smart devices in dual earphone mode

- When first using, open the case, the earphones will enter into TWS pairing mode (when power on, the white light flashes 1S and then white light flash quickly on both earphones).
- The L & R earphones will connect with each other successfully in 3S, then enter into pairing mode, the master earphone flashes blue and white light alternatively, and the slave earphone light goes off.
- Please search and connect with the "TECNO Sonic 1 Pro", and both of the earphones light will go off when pairing successfully.

TOUCH BUTTON OPERATION

- Long Press
- Tap

CALL MODE

- L/R earphone operation

VOLUME+/VOLUME-

- L/R earphone operation

MUSIC MODE

- L/R earphone operation

ACTIVATE THE VOICE ASSISTANT

- L/R earphone operation

FCC CAUTION

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Device types:SC01P (FCC ID: 2ADY1-SC01P)

IMPORTANT NOTE

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC RADIATION EXPOSURE STATEMENT

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

Hereby, TECNO MOBILE LIMITED, Declares that this True Wireless Earbuds is in compliance with the essential requirements and other relevant provisions of directive 2014/53/EU.

CE CAUTION

- Use carefully with the earphone maybe excessive sound pressure from earphones and headphones can cause hearing loss.
- Risk of explosion if battery is replaced by an incorrect type, dispose of used batteries according to the instructions.
- Dispose of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion;
 - leaving a battery in an extremely high temperature surrounding environment that can result in an explosion or the leakage of flammable liquid or gas;
 - a battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas.

The product shall only be connected to a USB interface of version USB 2.0.

4. EU Temperature: 0°C~+45°C (Standard), 0~+40°C (with adapter).

5. To prevent possible heating damage, do not listen at high volume levels for long periods.

6. USB cable is shielded.

OPERATING FREQUENCY
BT/BLE: 2402-2480MHz (TX/RX)

MODULATION MODE
GFSK, π/4-DQPSK, BPSK (BT)
GFSK(BLE)

RF OUTPUT POWER (Only for CE)
BT Left: 4.27dBm Right: 4.59dBm
BLE Left: 4.00dBm Right: 3.88dBm

EU DECLARATION OF CONFORMITY

In accordance with EU Directives and Regulations

Company name: TECNO MOBILE LIMITED
Address: FLAT N 14/F BLOCK B UNIVERSAL INDUSTRIAL CENTRE 19-25 SHAN MEI STREET FOYAN NT HONGKONG
as the manufacturer hereby declares under our sole responsibility that the Product(s): True Wireless Earbuds
Model name: SC01P

is in conformity with the essential requirements of the RE Directive 2014/53/EU:
Article 3.2 ETSI EN 300 328 V2.2.2 (2019-07)

EMC EN 301 489-1 V2.2.3(2019-11);
Article 3.1(b) Draft ETSI EN 301 489-17 V3.2.5 (2022-08)

Safety EN IEC 62368-1:2020+A11:2020
Article 3.1(a)

Health EN 62479-2010&EN 50663:2017
Article 3.1(a)

An EU Type Examination Certificate for this Product was issued in accordance with Annex II (Module B) of the 2014/53/EU Radio Equipment Directive by Bay Area Compliance Laboratories Corp. (2014/53/EU Radio Equipment Directive Notified Body Identification Number 1313)

Signed on behalf of TECNO MOBILE LIMITED (Signature of authorized person)
Sincerely Yours,
Signature

Nengyong Wu
Project Manager
Date: 2023-04-28

CUSTOMER SERVICE

Caricare provides service

WARRANTY CERTIFICATE

Name:	
Address:	
Telephone number:	
Date of purchase: (dd/mm/yy)	
Store name:	
S/N:	