# EH006 骨传导蓝牙耳机



使用指南

## 按键功能概述



# 控制说明

开机:耳机处于关机状态,长按开机键,保持3秒,LED蓝灯闪亮,提示音:

关机:耳机处于开机状态,长按开机键,保持3秒, LED红灯闪一下关机, 提示音: poweroff;

蓝牙连接: 关机状态, 长按开机键3秒, 进入配对状态, LED指示灯灯 蓝灯闪烁, 耳机提示音: Pairing; 设备(智能手机、平板电脑等) 搜 索到EH006或EH-006,点击连接;(备注: EH006为不 带MP3功能; EH-006为 带MP3功能)

连接成功:耳机成功连接至设备时, LED蓝灯3秒闪-下,耳机提示音: Connected:1

断开连接:提示Disconnected, 手机端主动关闭蓝牙, 10分钟后无 连接自动关机(10分内可以自动回连最后记录或者被其他设备搜索

暂停/播放:音乐播放状态下,单击多功能按键为暂停,再单击多功能

接听/挂断:来电状态下,单击多功能按键为接听,双击多功能按键 为拒接电话:

通话状态下:单击多功能按键为挂断;

音量增加:单击音量增加键:

音量减小:单击音量减小键;

下一曲:长按音量加键;

上一曲:长按音量减键;

语音助手:有滴滴提示音, 蓝牙链接状态, 双击多功能按键讲入语 音助手,再双击退出; MP3/蓝牙切按:在开机状态下三击开机切换 蓝牙模式或者MP3模式。


复位:插上充电线后,耳机将会复位并关机充电;(常按"+.-"" 键5秒 复位后开机并讲入配对模式)

恢复出厂设置:关机状态下音量加减键同时长按5秒清除配对信息

低电提示:电池电压低于3.3V时红灯快闪0.2S间隔(有语音提示),底 电关机。

充电:使用充电线时,将耳机插入USB电源,充电状态下,LED指示灯为 红灯长亮, 充电充满则红灯灭(蓝灯常亮)。

# 骨传导原理



我们听到的大部分声音,都是声波经过空气到达耳膜,然后声波 使耳膜发生震动进而将声音传至内耳道;

另一种方式是,声波通过骨头震动直接传至内耳而不经过耳膜, 这也是人们听到自己声音的-种方式,这种声音的传播方式就是骨

# 佩戴说明



将耳机挂在颈后,两侧的扬声器贴在面颊骨,调整佩戴的舒适度

# 产品规格

型号---- FHO06

音乐播放时间----标准状态: 6-8小时

充由时间\_\_\_2小时 蓝牙版 太一53 防水等级---- HP67 喇叭阻抗----8Ω 麦克风灵敏度——42 土2db 产品重量——24g 蓝牙连接距离--15-米 充电电压---5V. 充电电流——100毫安 协 议——A2DP .AVRCP.HSP.HFP

待机时间---20天

### 重要说明

本款耳机骨传导耳机的正确佩戴位置为耳朵前方的面颊骨 处,请勿将骨传导扬声器置于耳内;长时间听大音量的音乐可能 会带来不适感, 请尽可能使用中等左右的音量, 避免长时间使用

无论音量大小, 使用耳机都将影响您对周围环境声音的感 知,使用耳机时需多加注意;

切勿抛扔、坐压耳机;

耳机应远离火、水和高压设备;

不适合三岁以下儿童使用,包含小零件:请勿将其归类为生

活垃圾, 可将其送往当地相应的电器电子设备回收站。

### 产品中有责有事物质或元素的名称及含量

部件名称	有害物质					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
印刷线路板	х	0	0	0	0	0
金属部件	Х	0	0	0	0	0
电池	0	0	0	0	0	0
塑料部件	0	0	0	0	0	0
线缆	х	0	0	х	0	0
本表格依据SJ/T 11364的规 〇 表示该有毒有害物质在该部 X 表示该有毒有害物质至少在	件所有均					

# 产品型号:\_\_\_\_\_ 购买日期: 维修内容: 维修 人 答 夕 ·

产品服务保修卡

1、本公司提供 一年 免费保修期,时间从购买之 細計算. 2、人为破坏,外观件磨损,以及外部条件异常所造

- 3、如遇产品质量问题,请立即与本公司联系,切勿
- 4、保修时请携带此卡,到指定维修中心进行维修。



### EHOO6 BONE CONDUCTION HEADPHONE



User Manual

#### Includes:

Eh006, charge cable, and user guide

Please read and follow this user guide thoroughly before using the Eh006.





- Magnetic charging port
- ② -Volume down button / Previous track
- ③ Multi-function button Power ON/OFF, start/pause, accept/end phone calls)
- 4 + Volume up button / Next track
- (5) LED indicator
- 6 Microphone

### Controlling instructions

 $\ensuremath{\text{Pow}}\xspace \ensuremath{\text{er}}\xspace \ensuremath{\text{on}}\xspace : \ensuremath{\text{When}}\xspace \ensuremath{\text{the}}\xspace \ensuremath{\text{headset}}\xspace \ensuremath{\text{space}}\xspace \ensuremath{\text{on}}\xspace : \ensuremath{\text{space}}\xspace \ensuremath{\text{the}}\xspace \ensuremath{\text{the}}\xspace \ensuremath{\text{space}}\xspace \ensuremath{\text{the}}\xspace \ensuremath{\text{ensuremath}}\xspace \ensuremath{\text{the}}\xspace \ensuremath{\text{the}}\xspace$ 3 seconds, the LED blue light flashes, Prompt tone "bower on:" means

Pow er off: When the headset is power on, press and hold the power button for 3 seconds, the red LED flashes once to power off, Prompt tone "poweroff" means power off:

Blue tooth connection: When the headphone is Power off state, press and hold the power button for 3 seconds to enter the pairing state, the LED indicator flashes red and blue, and the headset prompts: Pairing: the device (smartphone, tablet, etc.) searches for EH006 or EH-006, click

Note: FH 006 is without M P3 function: FH-006 is with M P3 function) Successful connection: When the headset is successfully connected to the device, the blue LED light flashes for 3 seconds - down, and the headset prompts: Connected:

D isconnected: It prompts Disconnected, and the mobile phone automatically turns off the Bluetooth, and automatically shuts down after 10 minutes if there is no connection (it can automatically reconnect to the last record within 10 minutes or be searched for connection by other devices);

Pause/Play: When the music is playing, click the multi-function button to pause, and then click the multi-function button to play; Answer/hangup:

In incoming call status: click the multi-function button to answer, double-click the multi-function button to reject the call:

In the call state: click the multi-function button to hang up;

Volum e up: click the volume up key; Volum e down: click the volume down key;

Next song: long press the volume plus key; Previous song: long press the volume down key; Voiceassitant: there is a beep sound, the bluetooth link status, double-click the multi-function button to enter the voice assistant, and then double-click to exit:


Reset: After plugging in the charging cable, the headset will reset and shut down for charging; (press the "+. —" button for 5 seconds to reset and then power on and enter pairing mode)—DEL

Restore factory settingsPress and hold the volume plus and minus keys at the same time for 5 seconds to clear the pairing information in the Low battery prompt: When the battery voltage is lower than 3.3V, the

red light flashes quickly for 0.2S interval (with voice prompt), and the battery is turned off at the bottom

Charging When using the charging cable, plug the earphones into the USB power supply. In the charging state, the LFD indicator light will be on red, and when fully charged, the red light will be off (blue light will be on).

## Principles of bone conduction



Most of the sounds we hear is the result of sound waves passing through our eardrum to make the vibrate so that the sound waves can he conducted to the innernal auditory ear canal-

Another way is that sound waves are transmitted directly conducted to the innernal auditory ear canal through the vibration of the bone instead of eardrum. This is also a way for people to hear their own voice and this sound conduction is called bone conduction.

### How to wear



Hang the headphne behind your neck with both speaker clinging to your cheekbones, after that, adjust it until you feel comfortable.

Product Specifications

Model-----EH006 Music playing time ----- Standard state: 6-8 hours Standby time-----20 days

Charging time----2 hours Bluetooth version----5.3 Waterproof grade-----IP8

Speaker Impedance-----80 Microphone Sensitivity----42 ± 2db

Product weight-----24g Bluetooth connection distance----15 meters

Charging voltage----5v Charging current-----100mA

Protocol-----A2DP,AVRCP,HSP,HFP

### Safety warning

The correct wearing position of this earphone bone conduction earphone is the cheekbone in front of the ear. Do not put the bone conduction speaker in the ear; listening to loud music for a long time may cause discomfort, please use the medium or so as far as possible. volume, avoid using high volume for a long time:

Regardless of the volume, using headphones will affect your perception of ambient sound, so you need to pay more attention when using headphones:

Do not throw or sit on the earphones;

Headphones should be kept away from fire, water and high pressure equipment; Not suitable for children under three years old, contains small parts;

Do not classify it as household waste, but take it to the appropriate local recycling station for electrical and electronic equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions

(1) this device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measur

- Reorient or relocate the receiving antenna

crease the separation between the equipment and receiver. -Connect the equipment into an outlet on a circuit different from that to which the

-Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.