



## BASIC OPERATION


After powering up your video monitor, the parent unit streams live video in direct mode. We recommend you follow the instructions on screen to set up home Wi-Fi network with your monitor for functionality enhancements and mobile access. See **Auto software and firmware update** and **Download app for mobile access** in this quick start guide.

### Use the menu

Press **MENU** on the parent unit to enter the main menu, choose a menu item, or save a setting. You can use the parent unit menu for advanced settings or operations, such as to play or stop the baby unit lullaby, or adjust the baby unit sound sensitivity.


While in the menu:

- Press **◀|▲|▶|▼** to scroll among the menu options.
- Press **SELECT** to select an item.
- Press **TALK** to return to the live video.
- Press **Q** to go to the **Help & info** page.



### Adjust speaker volume


Press **VOL -|VOL +** to adjust the parent unit speaker volume level received from the baby unit.



### Zoom

Press **Q** to zoom in or out.

Zoom sequence:    




## MOUNT THE BABY UNIT (OPTIONAL)


### NOTES

- Check for reception strength and camera angle of the baby unit before drilling the holes.
- The types of screws and plugs you need depend on the composition of the wall. You may need to purchase the screws and plugs separately to mount your baby unit.


- Place the wall mount bracket on a wall and then use a pencil to mark two holes in parallel. Remove the wall mount bracket and drill two holes in the wall (7/32 inch drill bit).
- If you drill the holes into a stud, go to step 3.
- If you drill the holes into an object other than a stud, insert the wall plugs into the holes. Tap gently on the ends with a hammer until the wall plugs are flush with the wall.




- Align the wall mount bracket and screws with the holes in the wall as shown. Tighten the screw in the middle hole first, so that the wall mount bracket position is fixed. You can tighten the other screw in the top hole.



- Place the baby unit on the wall mount bracket, and then slide it forward until it locks into place. Connect the power adapter to the baby unit and a power supply not controlled by a wall switch.



- You can maximize your baby unit's viewing angles by tilting the wall mount bracket. Hold the baby unit, and then rotate the knob in anticlockwise direction. This will loosen the joint of the wall mount bracket. Tilt your baby unit up or down to adjust to your preferred angle. Then, rotate the knob in clockwise direction to tighten the joint and secure the angle.



## NIGHT LIGHT

You can control the night light remotely on the parent unit or directly on the baby unit.


### On the parent unit:

- Press **MENU**.
- Press **◀** or **▶** to scroll to  **Night Light** menu, then press **MENU** or **▼** to enter.
- Press **◀** or **▶** to choose below options:

-  Turn on/off night light
-  Change night light color
-  Adjust night light brightness
-  Set night light timer

### On the baby unit:

-  **Night Light Control Key**
- Single Tap: Turn on/off
- Tap and hold: Adjust night light brightness



## FOR RM7766-2HD ONLY

### Monitoring Modes

When more than one baby unit is paired to the parent unit, you can choose to view different baby units in three monitoring modes. Learn more about each below:

|                    |                                                                                     |                                                                                                   |
|--------------------|-------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|
| <b>Single Mode</b> |  | The screen displays images only from the selected baby unit in full screen.                       |
| <b>Split Mode</b>  |  | The screen displays images from all paired baby units at the same time in split view.             |
| <b>Patrol Mode</b> |  | The screen displays a single cam view that transitions to a different baby unit every 10 seconds. |

### Change the monitoring mode:

- Press **MENU** when the parent unit is idle.
- Press **MENU** or **▼** to enter  **Monitoring Mode menu**.
- Press **◀** or **▶** to choose between **Single** , **Split** , and **Patrol**  monitoring mode options. Press **SELECT** to confirm.



## TEST THE SOUND LEVEL AND POSITION THE BABY MONITOR

### Testing the sound level of the baby monitor

#### NOTE


This baby monitor is intended as an aid. It is not a substitute for proper adult supervision, and should not be used as such.

#### CAUTION

- For hearing protection, make sure the parent unit is more than 3 feet away from the baby unit. If you hear any high-pitched noise from the parent unit, move the parent unit further until the noise stops. You can also press **VOL -** on the parent unit to lower or mute the noise.

#### TIP

- Increase the parent unit speaker volume if you cannot hear the sounds transmitted from the baby unit.




### Positioning the baby monitor

#### CAUTION

- Keep the baby unit out of the reach of your baby. Never place or mount the baby unit inside the baby's crib or playpen.

- Place the baby unit more than 3 feet away from your baby.
- Adjust the angle of the baby unit to aim at your baby.




## TEST THE LOCATION FOR THE BABY UNIT

If you plan to install your baby unit in a designated location, and use your home Wi-Fi network to connect your video monitor, you need to test which of your selected monitoring areas within the house have good Wi-Fi signal strength. After you have powered on your parent unit, you can use your parent unit's Wi-Fi signal strength indicator to assist in checking. Once you have identified the suitable location, you can install your baby unit. Adjust the distance between your baby unit and the Wi-Fi router if needed.

#### TIP

- Depending on surroundings and obstructing factors, such as the effect distance and internal walls have on signal strength, you may experience reduced Wi-Fi signal. To improve the Wi-Fi signal strength, adjust the distance or direction of your parent unit. Check with your parent unit again.



## AUTO SOFTWARE AND FIRMWARE UPDATE

To ensure that your baby monitor is always at its best performance, the parent unit will prompt you to update its software and the baby unit firmware when there are new versions available.

- Follow the instructions on the parent unit screen to update your baby monitor. If you skip the updates, the parent unit and baby unit will be updated automatically when the parent unit is powered off, and then powered on again.

- To check if your device is running on the latest software or to update your device software, go to:

 **> Software Update**

### Connect your baby monitor to Wi-Fi

- You must connect your video monitor to your secured home Wi-Fi network in order to receive the latest software and firmware updates. To set it up, go to:

 **> Configure Wi-Fi**



## NEED HELP?

For instructions and guides to make the best use of your baby monitor, and for the latest information and support, check out our online help topics and FAQs. The online help page will also be updated periodically to reflect product system updates.

Use your smartphone or mobile device to access our online help.

- Go to <https://help.vtechphones.com/RM7766HD> or <https://help.vtechphones.com/RM7766-2HD>; OR

- Scan the QR code on the right. Launch the camera app or QR code scanner app on your smartphone or tablet. Hold the device's camera up to the QR code and frame it. Tap the notification to be redirected to the online help page.

- If the QR code is not clearly displayed, adjust your camera's focus by moving your device closer or further away until the image is clear.

If you would like to contact us, visit

<https://help.vtechphones.com/cs>.

You can also call our Customer Support at 1-844-848-8324 (1-844-84-VTECH) [in US] or 1-888-211-2005 [in Canada] for help.



RM7766HD online help



RM7766-2HD online help



## GENERAL PRODUCT CARE

To keep this product working well and looking good, follow these guidelines:

- Avoid placing it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps).
- DO NOT expose it to direct sunlight or moisture.
- Avoid dropping the product or treating it roughly.
- Clean with a soft damp cloth.
- DO NOT immerse the parent unit and the baby unit in water and do not clean them under the tap.
- DO NOT use cleaning spray or liquid cleaners.
- Make sure the parent unit and the baby unit are dry before you connect them to the mains again.
- Clean the USB charging port of dust, dirt, and lint regularly.

## STORAGE

When you are not going to use the video monitor for some time, store the parent unit, the baby unit and the adapters in a cool and dry place.



## FREQUENTLY ASKED QUESTIONS

Below are the questions most frequently asked about the video monitor.

- Can I turn the parent unit display screen off but keep hearing sounds from the baby unit?
- Yes, press **ON/OFF** on the parent unit to turn off the screen. The parent unit display will also dim automatically after being inactive for some time. In both instances, you will still be able to hear all sounds from the baby unit. Press any key to turn the screen back on.
- Why is the baby unit not responding normally?
- Try the following (in the order listed) for a common cure:
1. Disconnect the power to the baby unit.
  2. Wait a few minutes before connecting power back to the baby unit.
  3. Reboot the parent unit.

- Why is my screen in black and white?
- The baby unit has a light sensor that measures ambient light. When the ambient light is dim, such as during night time or in a dark room, the baby unit activates its infrared LEDs, and displays the camera images in black and white night vision.

- Why does my baby unit show offline? Why is the connection lost every now and then?
- The baby unit may have lost connection to the Wi-Fi router. Check your network and router settings.
- Other electronic products may cause interference with your baby unit. Try installing your baby unit as far away from these electronic devices as possible.

- Why can't I hear a sound/Why can't I hear my baby crying?
- The parent unit speaker volume may be too low. Press **VOL +** on the parent unit to increase the volume.
- You may have set a low sound sensitivity level. Set the sound sensitivity to a higher level. For details, go to [www.vtechphones.com](https://www.vtechphones.com) for online help topics.

## THE RBRC SEAL

The RBRC seal on the lithium-ion battery indicates that Vtech Communications, Inc. is voluntarily participating in an industry program to collect and recycle these batteries at the end of their useful lives, when taken out of service within the United States and Canada. The program provides a convenient alternative to placing used lithium-ion batteries into the trash or municipal waste, which may be illegal in your area.

Vtech's participation makes it easy for you to drop off the spent product at local retailers participating in the program or at authorized Vtech product service centers. Please call 1 (800) 8 BATTERY for information on Li-ion battery recycling and disposal bans/restrictions in your area. Vtech's involvement in this program is part of its commitment to protecting our environment and conserving natural resources.

The RBRC Seal and 1 (800) 8 BATTERY are registered trademarks of Call2recycle, Inc.

## FCC AND IC REGULATIONS

### FCC Part 15

NOTE: This equipment has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Recent or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

To ensure safety of users, the FCC has established criteria for the amount of radio frequency energy that can be safely absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC criteria. The baby unit shall be installed and used such that parts of all persons' body are maintained at a distance of approximately 8 in (20 cm) or more. The transmitter and antenna of the parent unit shall be held at least 1 in (2.5 cm) from your face.

This Class B digital apparatus complies with Canadian requirements.

Can ICES-3 (B)/NMB-3(B)

**Industry Canada**

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) This device may not cause interference. (2) This device must accept any interference that may cause undesired operation of the device.

The term "IC" before the certification/registration number only signifies that the Industry Canada technical specifications were met. This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.

### RF radiation exposure statement

The product complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. The baby unit should be installed and operated with a minimum distance of 8 in (20 cm) between the baby unit and all persons' body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. This equipment complies also with Industry Canada RSS-312 with respect to Canada's Health Code 6 for Exposure of Humans to RF Fields.

## CALIFORNIA ENERGY COMMISSION BATTERY CHARGING TESTING METHOD

This video monitor meets the California Energy Commission (CEC) regulations for energy consumption. Your video monitor is set up to comply with the energy-conserving standards right out of the box.

Follow the instructions to install and charge the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to camera units, the CEC battery charging testing mode is activated while it is powered off and charging.

## FOR CETL COMPLIANCE ONLY

Lorsque vous utilisez votre appareil, vous devriez toujours suivre certaines mesures de précaution de base afin de réduire les risques d'incendie, d'électrocution et de blessures corporelles, dont ceux qui suivent:

1. Observez toutes les instructions et mises en garde inscrites sur l'appareil.
2. L'installation par un adulte est requise.
3. **MISE EN GARDE:** N'installez pas l'unité où elle pourrait être exposée à un risque d'incendie, d'électrocution ou de blessures corporelles. Ne renversez jamais de liquide dans cet appareil.
4. Afin de réduire les risques d'électrocution, ne démontez pas cet appareil, mais apportez-le dans un centre de service autorisé.
5. L'ouverture du boîtier ou le retrait de toutes pièces qui contiennent des composants électroniques (autres écouteurs, batteries, etc.) peut entraîner des dommages à l'appareil. Un montage incorrect peut par la suite présenter des risques d'électrocution.
6. Vous devez tester la réception chaque fois que vous mettez l'appareil en fonction.
7. Examinez les composants afin de vérifier si celles-ci ne sont pas endommagées.
8. Il existe un très faible risque de perte de confidentialité avec certains appareils électroniques (autres écouteurs, téléphones sans fil, etc.). Pour éviter, assurez-vous que le produit n'a jamais été utilisé avant d'être remis en fonction.
9. Le produit n'est pas conçu pour être utilisé en tant que moniteur médical.
10. Les enfants ne doivent être supervisés afin de vous assurer qu'ils ne jouent pas avec l'appareil.
11. Les petites pièces de ce moniteur peuvent être avalées par les bébés ou les petits enfants. Veuillez tenir ces pièces hors de portée des enfants.
12. Le produit n'est pas conçu pour être utilisé par des personnes souffrant de troubles cardiaques ou d'autres conditions médicales. Consultez votre médecin si vous avez des questions.
13. L'adaptateur dont la polarité ou la tension serait inadéquate conformément aux informations du **Scéau RBRC**.
14. N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur non autorisé peut entraîner des dommages à l'appareil.
15. N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur non autorisé peut entraîner des dommages à l'appareil.

### CONSERVEZ CES INSTRUCTIONS

- Mises en garde**
- Utilisez et entreposez le produit à une température entre 0 °C (32 °F) et 40 °C (104 °F).
  - Risque de brûlure, risque d'incendie, risque d'explosion associé à l'utilisation de la batterie.
  - N'exposez pas cet appareil à des frottements ou des chocs excessifs, et ne le laissez pas à l'extérieur.
  - Ne l'installez pas à proximité d'une source de chaleur.
  - Ne l'installez pas à proximité d'une source de chaleur.

- Avertissement:** Risque de strangulation.
- Les enfants se sont étouffés dans des cordons.
  - Gardez ce cordon hors de portée des enfants à l'âge de 12 mois.
  - N'enlevez pas cette étiquette.
  - Ne jamais placer le moniteur à l'intérieur du berceau ou du parc de bébé.
  - Ne jamais couvrir le moniteur ou l'unité (s) portative avec un article tel qu'une serviette ou une couverture.
  - D'autres produits électroniques peuvent causer des interférences avec votre caméra IP. Essayez d'installer votre caméra IP le plus loin possible de ces dispositifs électroniques: téléphones sans fil, radios, téléphones cellulaires, interphones, moniteurs de pièces, téléviseurs, ordinateurs personnels, appareils électroniques de cuisine et téléphones sans fil.

**Stimulateurs cardiaques implantés dans l'organisme**

Les stimulateurs cardiaques ne s'appliquent qu'aux dispositifs numériques sans fil.

**Consignes de sécurité:** Wireless Technology Research, LLC (WTR), une firme de recherche indépendante, a mené une évaluation pluridisciplinaire des interférences entre les téléphones sans fil portatifs et les stimulateurs cardiaques implantés dans l'organisme. Appuyée par l'Administration des aliments et drogues (FDA) des États-Unis, la firme WTR recommande de prendre les mesures suivantes:

- Avant d'utiliser des stimulateurs cardiaques:**
- Vous devriez maintenir les dispositifs sans fil à au moins six pouces du stimulateur cardiaque.
  - Ne placez pas cet appareil sur un chariot, meuble, trépied, ou autre support.
  - Ne placez pas cet appareil sur une surface plane, telle qu'une table ou un lit.
  - Ne placez pas cet appareil sur une surface plane, telle qu'une table ou un lit.
  - Ne placez pas cet appareil sur une surface plane, telle qu'une table ou un lit.

Le produit de Vtech est conforme à toutes les normes se rapportant aux champs électromagnétiques (EMF) standard. Si vous le utilisez dans un environnement où il y a une exposition à des champs électromagnétiques, veuillez consulter les instructions de l'appareil pour en savoir plus sur la façon de minimiser l'exposition. Si vous utilisez le produit dans un environnement où il y a une exposition à des champs électromagnétiques, veuillez consulter les instructions de l'appareil pour en savoir plus sur la façon de minimiser l'exposition.

**Please retain your original sales receipt as proof of purchase.**