3

III. GENERAL TEST CONDITIONS AND PROCEDURES

Measurement procedures were used as outlined in MP-1, as specified in Part 15.31, except as noted herein. The open field tests were performed on a three-meter range maintained by Carl T. Jones Corporation at the Springfield facility. Complete description and measurement data for the site have been placed on file with the Commission. Carl T. Jones Corporation is listed by the FCC as a facility available to do measurement work for others on a contract basis. Prior to open-field testing, the equipment was placed in a shielded enclosure and scanned at a distance of 1 meter to determine its emission characteristics.

4

IV. RADIATED EMISSION MEASUREMENTS

The receiver was assembled on a rotatable wooden test stand approximately one meter in height. The receiver's antenna was fully extended. Because of the superregenerative nature of the receiver, an unmodulated RFf signal was transmitted to it during testing in order to insure proper functionality. The emission spectrum was examined from 30 MHz to 1000 MHz using a Hewlett-Packard 8568B spectrum analyzer and Compliance Design "Roberts" tuned dipole antennas.

At each emission frequency, the EUT was rotated 360 degrees, and the antenna was raised and lowered from one to four meters to determine the maximum emission levels. Measurements were taken using both horizontal and vertical antenna polarizations. The spectrum analyzer's 6 dB bandwidth was set to 100 kHz. The analyzer was operated in the CISPR quasi-peak detection mode for measurements of all emissions less than 1000 MHz. No post-detector video filters were used. The EUT was investigated in three orthogonal planes. There were no detectable emissions observed during the EUT's initial scan.

Test Results: Because there were no detectable emissions observed during the 1-meter initial scan, the EUT was not taken to the open-area-test-site. The EUT complied with the FCC Limits.

Note: SEE ENCLOSED INITIAL FREQUENCY SCAN SPECTRAL PLOTS.

Five spectral plots are included. The spectral plots are:

- 1. CW carrier on, EUT on (RBW = 10kHz)
- CW carrier on, EUT on (RBW = 300Hz)
- 3. Spectrum at 2 f_a, CW carrier on, EUT on (RBW = 100kHz)
- 4. Spectrum at 3 f_o, CW carrier on, EUT on (RBW = 100kHz)
- 5. Spectrum through 10 f_o, CW carrier on, EUT on (RBW = 100kHz)

The actual field intensity in decibels above one microvolt per meter (dBµV/m) is determine by algebraically adding the measured level in dBµV, the antenna factor (dB), and the cable loss (dB) at the appropriate frequency.

$$FI_a (dB\mu V/m) = FI_m (dB\mu V) + AF (dB) + CL (dB)$$

Fl_a = Actual Field Intensity

Fl_m = Measured Field Intensity

AF = Antenna Factor

CL = Cable Loss

As a sample calculation, assume a particular device emits a signal with a frequency of 49.96 MHz. The received signal level is measured as 4.0 dBµV. The total attenuation factor (antenna factor plus cable loss) for 49.96 MHz is 4.7 dB. The actual radiated field is calculated as follows:

$$4 dB\mu V + 4.6 = 8.6 dB\mu V/m$$

In no case did the radiated emissions exceed the limits specified in Paragraph 15.109(a) of the Commission's Rules.

V. POWER LINE CONDUCTED EMISSIONS MEASUREMENTS

Measurements of the power line conducted emissions were not performed since the EUT has no means for connection to the public utility power grid.

TABLE 1 FIELD STRENGTH RADIATED EMISSIONS DATA SHEET

ANTENNA FACTOR FCC EMISSION ANTENNA EMISSION LIMIT AND **EMISSION** FREQUENCY **POLARITY** LEVEL **CABLE LOSS** (3 METERS) LEVEL (H,V) (MHZ) (dBuV) (dB) (dBuV/m) (dBuV/m)

Note: No detectable emissions were observed during the 1 meter scan, therefore the EUT was not taken to the open-area-test-site. See attached spectral plots.

CLIENT: TAIYO KOGYO
FCC ID: AEK971949R
MODEL: Hot Rocker
TEST DATE: 08/28/98

TEST ENGINEER: Michael A. Nicolay

SIGNATURE: Tichn Thrus

EXHIBIT 2 Photographs - Including Label Placement

EXHIBIT 5 Spectral Plots

EXHIBIT 6 TEST EQUIPMENT USED FOR FCC COMPLIANCE TESTING BY CARL T. JONES CORPORATION

<u>MANUFACTURER</u>	DEVICE	MODEL NUMBER	QUANTITY
Hewlett Packard	Spectrum Analyzer	8568B	1
Hewlett Packard	Quasi-Peak Adapter	8565OA	1
Hewlett Packard	Spectrum Analyzer	141 T	1
Hewlett Packard	RF Section	8555A	1
Hewlett Packard	RF Section	8553B	1
Hewlett Packard	IF Section	8552A	1
Tektronix	Spectrum Analyzer	7L13	1
Electro-Metrics	Spectrum Analyzer	ESA-1000	2
Hewlett Packard	Frequency Counter	5245L	1
Hewlett Packard	Frequency Converter	5253B	1
Hewlett Packard	Pre-Amplifier	8447E	2
Hewlett Packard	Signal Generator	8656B	2
Hewlett Packard	Signal Generator	606B	1
Boonton Electronics	Signal Generator	102B	1
Boonton Electronics	Power Meter	42B	1
Tektronix	Oscilloscope	475	1
Marconi Instruments	AM/FM Modulation Mete	r TF2300	1
Compliance Design	20 MHz-1000 MHz Ante	ennasRoberts	tm1 Set
Solar Electronics	50 Microhenry LISN	8028-50-TS-24-BNC	1
Solar Electronics	50 Microhenry LISN	8012-50-R-24-BNC	2











