LOW-PROFILE BLUETOOTH FM TRANSMITTER

USER MANUAL
MODEL: VM-201
VERSION: V01-24-8

1

Features

-Hands-free calling with built-in microphone

-Bluetooth connection to mobile device (A2DP)

-Comes with USB-A charging port

-Supports Bluetooth, Aux in, Micro SD card and flash drive

-Display FM station

-Car battery voltage display

2

Overview

Microphone

Display

FM Setting
Previous

Flash Drive

USB

Function Switch

Answer/Volume +/-

Next

Micro SD Card

Aux In

Audio cable

3

Controls

Buttons	Action	Behaviors
"CH"	Press	Enter FM Station Setting
	Press for 3 seconds	Change playlist
"M"	Long press	Enter EQ Mode
	Press	Change source
"((·))"	Rotation	Setting FM frequency; Adjust volume during playback
	Press	Answer/End the call; Pause/Play Music
	Press Twice	Call Back
	Press for 3 seconds	Reject the call
	Press for 5 seconds	Screen off/on
"⏮"	Press	Previous Track; Frequency adjustment 0.1MHz
"⏭"	Press	Next Track; Frequency adjustment 0.1MHz

4

Operation

1. Insert device into 12/24V DC port. Display shows FM station, Bluetooth indicator flash.

FM 107.9

2. Turn on vehicle radio. Select unused FM station (FM 88.1 to 107.9).

(Note: If sound quality is poor try another unused FM station.)

FM 88.1

5

Press

- "((·))" to enter FM station setting

- "⏮" / "⏭" -/+ by 0.1MHz

- "M" for confirmation

FM 88.2

6

SELECT SOURCE (BLUETOOTH, AUX INPUT, FLASH DRIVE, MICRO SD CARD)

Pair Device

First-time setup:

- Power On

- Bluetooth indicator flashes in "Pairing Mode"

- Connected to "VM-201" on smartphone

- Voice confirmation of successful connection

7

CONTROLS

"⏮" / "⏭" Go back/ Skip song

"((·))" Pause / Play

"M" =Change source

MP3/WMA/WAV/FLAC Supported

When playing songs from Micro SD card or USB flash drive, long press "⏮" / "⏭" to change folder.

Note: It will automatically enter Micro SD card or Flash drive mode when connecting, and automatically return to Bluetooth mode after it is removed.

Important: Use source device for AUX input track controls.

8

HANDS-FREE CALLS

Press

- "((·))" to answer call

- "((·))" to end or reject call

- "((·))" 2x to redial last call out number

Incoming Call   Talking   End the Call

Example

Note: May also use the Bluetooth connected device to disconnect the call.

9

Specifications

DC Input: 12V-24V

Output: 5V-2.1A Max

Bluetooth Version: V5.3

Audio Frequency: 20Hz~20kHz

Working Current: 60mA(Max)

Stand-by Current: 25mA(Max)

Bluetooth Working Frequency: 2.402~2.480Ghz

Bluetooth Effective Distance: 32ft

FM Emission Effective Distance: 6ft

Sensitivity: -89dBm

RF Output: -1.681dBm

FM Frequency: 88.1MHz-107.9MHz

10

Legal

FCC Compliance Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

⚠ **Warning:** Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if notinstalled and used in accordance with the instructions, may cause harmful interference to

11

radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

– Reorient or relocate the receiving antenna.

– Increase the separation between the equipment and receiver.

– Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

– Consult the dealer or an experienced radio/TV technician for help.

12

Walmart,Inc., Bentonville, AR72716

https://www.walmart.com

CUSTOMER SERVICE: support@meiditech.com

Bluetooth Trademark Statement

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Artsun Enterprise Company Limited is under license. Other trademarks and trade names are those of their respective owners.

13

Safety Precautions

⚠ CAUTION

Do not disassemble   Warning Spray   Keep Dry   Warning Flammable

No harsh cleaning chemicals. Clean with dry soft cloth.

⚠ WARNING

⚠ WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov

RF Exposure Information

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

14

Troubleshooting

Issue	Problem	Prevention/Solution
Poor sound quality	The selected FM station is the same as a broadcast FM station	Change to another FM station
No audio transmitted	Incorrect FM station selected	Adjust the device FM station to match the vehicle FM station
The car stereo is very noisy in radio mode	High volume level selected on the car stereo	Turn up the volume of Bluetooth connected device and turn down the volume of the car stereo to reduce noise
Can't recognize the MicroSD card or flash drive	The slot only support up to 128 GB	Replace the memory card with a capacity less than 128 GB

15

What is in the Package

1. Low-profile Bluetooth FM Transmitter

2. Audio cable

3. User Manual

★ Please note product features will be upgraded without any notice.

16

型号：VM-201

材质：120g双铜纸

印刷：四色双面印刷

成品尺寸：72*105MM

展开尺寸：576*105MM

折页方法：风琴折