


 <h3>使用说明书</h3>	<p>产品示意图</p>  <p>包装清单</p> <p>G9S真无线耳机主机 G9S真无线耳机充电盒 Micro 5pin 充电线 备用大、小耳帽 使用说明书</p>	<p>产品规格</p> <p>产品型号: G9S 无线版本: V5.3 电池规格: 耳机3.7V 支持模式: HFP/HSP/A2DP/AVRCP 灵敏度: 105dB ± 3dB S.P.L at 1KHz 信号距离: 1 0 米 (无任何较大障碍物的理想环境中) 播放时间: 约2.5 小时 通话时间: 约3 小时 待机时间: 约8 0 小时 充电时间: 给充电仓充电约1.5 小时, 充电仓给耳机充电约1 小时 充电仓给耳机充电次数: 约3 次</p> <p>功能操作说明</p> <p>1. 开机 将耳机从充电仓拿出自动开机或长按左右耳机多功能键3秒开机。</p> <p>2. 关机 将耳机放入充电仓自动关机长按左右耳机多功能键7秒关机。</p> <p>3. 开机回连 当配对成功后, 第二次开机时蓝牙耳机优先进入回连状态自动回连已连接过的手机。</p>	<p>4. 播放/暂停 在待机状态下, 单击左右耳机多功能键均可直接播放音乐, 播放时单击左右耳机多功能键均可暂停播放。</p> <p>5. 切换歌曲 播放音乐时长按左耳机多功能键2秒同时响“嘀”一声切换到上一曲, 长按右耳机多功能键2秒同时响“嘀”一声切换到下一曲。</p> <p>6. 音量加减 双击左耳机多功能键逐级加大音量, 双击右耳机多功能键逐级减小音量</p> <p>7. 来电接听 手机来电时, 单击左右耳机多功能键均可接听电话。</p> <p>8. 来电挂断 手机通话时, 单击左右耳机多功能键均可挂断电话。</p> <p>9. 来电拒接 手机来电时, 长按左右耳机多功能键2秒可拒接来电。</p> <p>10. 末号重拨 在待机或者播放音乐时, 三击左耳机多功能键即可拨打您通话记录中最后一个拨打过的电话。</p> <p>11. 启动语音助手 三击右耳机多功能键即可启动苹果Siri或谷歌语音助手进行语音控制手机操作。</p> <p>12. 低电量提示 当耳机电池电量不足时, 间隔30秒播放一次电量不足提示音, 直至耳机低电关机。</p>	<p>配对方式</p> <p>普通配对方式</p> <p>1 .从充电仓取出或者同时长按左、右耳机多功能键3秒开机, 直至红绿灯交替闪烁, 进入对耳搜索配对状态, 进入对耳自动配对, 配对成功后主耳(右耳)持续红绿灯交替闪烁, 副耳为蓝灯慢闪, 同时播放对耳配对成功提示音。</p> <p>2 . 启动手机或者其它设备的无线功能, 如果是安卓系统手机或者设备请点击手机“搜寻无线设备”选项, 如果是IOS 系统的手机或者设备则会自动搜索设备; 当搜寻到该无线耳机的型号后, 点击进入配对; 当配对成功后, 主(右)耳机会发出连接成功的提示音, 左右耳机指示灯变为蓝灯慢闪, 进入连接待机状态, 配对成功后主耳为右声道, 副耳为左声道。</p> <p>3 . 两只耳机也可单独与手机进行配对使用, 操作方法可按上步骤2 操作手法进行操作。</p> <p>充电操作</p> <p>1 .将Micro USB充电线一头插上充电仓的USB口一头插上充电器即可给充电仓充电, 4 灯会显示最新的电量。</p> <p>2 .给耳机充电: 将耳机放入充电仓即可自动充电, 充电时耳机指示灯为红色, 充满电后熄灭; 充电仓的灯会显示剩余电量, 当耳机充满电后, 耳机灯会熄灭。</p>	<p>注意事项</p> <p>1. 请在安全的环境下充电。在给充电仓充电时当充电指示灯熄灭后请尽快将充电仓与USB充电线分开, 以免在长时间插着充电对充电仓造成损伤。</p> <p>2. 在音乐播放时, 请将音乐调至合适音量大小, 以免长期在大音量状态下对听力造成损伤。</p> <p>3. 尽量避免在有干扰源的地方使用本耳机, 否则有可能对耳机信号产生影响。</p> <p>4. 尽量避免在有腐蚀的环境中使用本耳机, 以免对耳机的功能产生影响。</p> <p>温馨提示:在您使用本无线耳机听音乐或者通话时, 请注意适当调节音量大小, 以免过大的音量对您的听力造成影响!</p>
--	---	---	---	--	---

 <h3>user manual</h3>	<p>Product diagram</p>  <p>Packing list</p> <p>G9S true wireless headset host G9S real wireless headset charging box Micro 5pin charging cable Spare large and small earcaps an instruction manual</p>	<p>Product specification</p> <p>Product model:G9S True wireless version: V5.3 Battery specification: earphone 3.7v ; Charging bin 3.7v Supported mode: HFP/HSP/A2DP/AVRCP Sensitivity: 105dB 3dB S.P.L at 1KHz Signal distance: 10 m (in an ideal environment without any large obstacles) Playing time: about 2.5 hours Talk time: approximately 3 hours Standby time: about 80 hours Charging time: charge the charging warehouse for about 1.5 hours, and charge the headset for about 1 hour Charging times for the headset: about 3 times</p> <p>Functional instructions</p> <p>1.Boot Take the headset out of the charging bin and start it automatically or long press the left and right multi-function button of the headset for 3 seconds.</p> <p>2.Shut down Put the earphone into the charging chamber and turn it off automatically. Long press the left and right earphone multifunction keys for 7 seconds to turn it off.</p> <p>3. Boot back When the pairing is successful, the bluetooth headset will first enter the state of reconnect when the second time is started and automatically reconnect the connected phone.</p> <p>4.Play/pause Press the left earphone multi function button for 2 seconds to play music, and then press the right earphone multi function button for2 seconds to play music.</p> <p>6.Volume up and down Double-click the left earphone multifunction button to increase the volume step by step, and double-click the right earphone multifunction button to decrease the volume step by step.</p> <p>7.Answer incoming calls</p>	<p>When the mobile phone calls, click the left or right earphone multifunction button can answer the phone.</p> <p>8.Call hang up When talking on the mobile phone, you can hang up the phone by clicking the left or right earphone multifunction button.</p> <p>9.Call rejection When the phone calls, long press the left and right earphone multifunction button for 2 seconds to reject the call.</p> <p>10.Redial When you are on standby or playing music, you can make the last call in your phone record by three clicks of the left earphone multifunction button.</p> <p>11. Start voice assistant Three clicks on the right earphone multifunction button can activate apple's Siri or Google voice assistant for voice control of the phone operation.</p> <p>12. Low battery alert When the battery of bluetooth headset is low, play the warning sound of low battery at an interval of 30 seconds until the headset is low battery and turns off.</p> <p>pairing method</p> <p>1.Take out from the charging warehouse or press the left and right earphone multifunction button for 3 seconds to start up the headset until the red and blue lights flicker alternately, enter the state of search and pairing for the ear, enter the state of automatic pairing for the ear. After the pairing is successful, the red and blue lights of the main ear (right ear) continue to flicker alternately, while the blue lights of the secondary ear slowly flash, and play the prompt sound of successful pairing for the ear.</p> <p>2. Start the bluetooth function of mobile phone or other devices. If it is an android phone or device, please click the "search bluetooth device" option. When the model of the bluetooth headset is found, click to enter pairing. After the pairing is successful, the main (right) ear will send out a signal that the connection is successful, and the indicator lights of the left and right earphones will turn to blue light and enter the standby state of connection. After the pairing is successful, the main ear will be the right channel, and the second ear will be the left channel.</p> <p>3. The two earphones can also be paired with the mobile phone independently. The lamp operation method can be operated according to the operation method in step 2 above.</p>	<p>Charging operation</p> <p>1. Plug one end of the Micro USB charging cable into the USB port of the charging warehouse and plug one end of the charger to charge the charging warehouse.The will display the latest power.</p> <p>2. Charge the earphone: put the earphone into the charging bin to charge it automatically. The lamp earphone indicator is red when charging, and it will be off after being fully charged. The lamp of the charging cabin will display the remaining power. When the headset is fully charged, the lamp of the charging cabin will go out.</p> <p>Precautions</p> <p>1. Please charge in a safe environment. When charging the charging warehouse, please separate the charging warehouse from the USB charging cable as soon as possible after the charging indicator is off, so as to avoid damage to the charging warehouse caused by the long time of charging.</p> <p>2. When the music is playing, please adjust the music to the appropriate volume to avoid long-term damage to the hearing under the condition of high volume.</p> <p>3. Try to avoid using the earphone where there is interference source, otherwise it may affect the earphone signal.</p> <p>4. Try to avoid using the earphone in a corrosive environment, so as not to affect the function of the earphone.</p> <p>Tips: when you use this bluetooth headset to listen to music or talk, please pay attention to adjust the volume, so as not to affect your listening too much!</p>	<p>FCC Statement</p> <p>Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p> <p>-- Reorient or relocate the receiving antenna.</p> <p>-- Increase the separation between the equipment and receiver.</p> <p>-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.</p> <p>-- Consult the dealer or an experienced radio/TV technician for help</p> <p>This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions</p> <p>(1) this device may not cause harmful interference, and</p> <p>(2) this device must accept any interference received, including interference that may cause undesired operation.</p>
---	--	---	--	--	--