



- 1 x Wireless Keyboard
- 1 x Charging Cable
- 1 x USB Receiver

Specifications	Indicator Lights Description
Keycode size: 304.30x179.0x58mm(Qwerty) Touchpad size: 54.8x44.8mm Weight: 197.3g Working distance: 10m Lithium battery capacity: 140mAh	Charge time: 2-3 hours Uninterrupted work time: 48 hours Stand-by time: 500 hours Sleep time: 100 minutes Awaken way: Arbitrary key to awaken

Indicator Lights Description

- ③ **Power Indicator:** Displays blue when turned on; stay in red when charging; flash red quickly when low power.
- ④ **Bluetooth Indicator:** Displays blue and then goes out when switching channels; flashes blue when it enters the pairing state.
- ⑤ **Caps Lock Indicator:** Displays blue when caps is locked.

Bluetooth® 182 Pairing Instructions

1. Turn on the power switch located on the side of the keyboard. The power indicator lights up in blue and then goes out.
2. Press **F1** to select Bluetooth channel 1 or **F2** to select Bluetooth channel 2 channel.
3. Press the Bluetooth connection button. The power indicator enters the pairing state. The Bluetooth indicator light starts to flash blue.
4. Turn on the Bluetooth settings on the device to enter search/pairing state.
5. Find "Wireless Keyboard" and click it. After the connection is successful, you can use the keyboard.

- Turn on the Bluetooth settings on the device to enter search/pairing state.
- Find "Bluetooth Keyboard" and click on it. After the connection is successful you can use the keyboard.
- Press **IN** to select your system to ensure that the function keys and touchpad functions are used normally.

[illegible]

- When switching the operating system, please remember to press the corresponding button ($\text{fn} + \text{Q/W/E/R}$) to switch, so as not to affect normal use.
If it fails to connect properly, it is recommended to turn off the Bluetooth keyboard power supply, restart and connect again.

NOTE: If multiple devices are used at the same time, press $m = 0/n/d/3$ to switch to the connected devices freely.

If you want to change the device connected to the 2.4G / Bluetooth1 / Bluetooth 2 channel, just follow the above connection method to re-configure and connect to the 2.4G / Bluetooth1 / Bluetooth 2 channel.

Auto-reconnect function: when you turn on the keyboard, it will connect with the last-used device automatically. (After the connection, don't press the connect button again, or it will disconnect and you have to reconnect the connect button again, please click the pairing records from your device if the connection fails, please delete all the pairing records from your device if you don't want to connect with this device.)

Turn off your device Bluetooth function and turn it on again and then follow the above instructions again.

Touchpad Gesture		OS (Support List)	Android	Windows 10	Mac OS
Swirl Shortcut		Win + Q	Win + W	Win + E	Win + R
Two-finger Tap		Mouse Left	Mouse Left	Mouse Left	Mouse Left
Two-finger Drag		Mouse Right	Mouse Right	Mouse Right	Mouse Right
Three-finger Tap		Mouse Wheel	Mouse Wheel	Mouse Wheel	Mouse Wheel

Keyboard Language Switching

- iOS 8 or below: command + space
- iOS 9 or above: ctrl + space
- Android: ctrl + space / shift + space / others
- Windows 10: ctrl / command + space or alt + shift / caps lock

Note:

Due to different system versions, the above may not work in all Android devices.

Important

As this is a multilingual keyboard, set the language of the device to your desired language before use.

For iOS devices only:
Settings > General > Keyboard > Keyboards > Add new keyboard

For Samsung Android devices only:
 Settings > Controls > Language and Input > Samsung Keyboard
 > Select input languages > Select desired language

For Android devices only:
 Settings > Language & input > Physical/Keyboard > Set up keyboard layouts > Select desired language

Control Panel > Clock, Language and Region > Select desired language

System Requirements

iOS 6.0 and above
Mac OS X v10.6 or Mac OS X v10.12 and above
Min. CPU: x86 v1.0 / PC computer with a Bluetooth host
Windows XP / Vista / 7 / 8 / 10
Android 3.0 and above with Bluetooth HID profile
(Smartphones and Tablets)

This keyboard is not compatible with Samsung Smart TV, Xbox and Nokia phones.

How to Charge it

Use the included USB cable for charging. Connect one end to a USB charger, and the other to the keyboard. **(USB charger is not included)**
In charging, the power indicator will turn red. Generally, it takes approximately 2-3 hours for a full charge. **(Output: DC 5V/500mA)**

FAQ

Q2. Fail to connect

A2. 1. Before to connect, please set as below.

Change Samers Bluetooth keyboard for 30 minutes.

On your device, delete/remove/forget the previous connection record with "Bluetooth keyboard".

Once the connection is removed, turn Bluetooth on again.

Make sure that your Samers device and your device are within close proximity of each other.

Step 2. Follow the Pairing Instruction to connect it again.

Q3. My Samers Bluetooth keyboard frequently gets disconnected or laggy.

FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates noise and can radiate radio frequency energy, and it may interfere with radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off or on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

1. Test your **Bluetooth** product.
 2. Charge your **Bluetooth** keyboard for 30 minutes. Low battery power can adversely affect connectivity and overall functionality.
 3. Make sure that your **Samsung Bluetooth** keyboard and computer are within close proximity of each other.
 4. Try moving away from:
 - * Any device that could emit wireless waves: Microwave, cordless phone, baby monitor, wireless speaker, garage door opener.
 - * Wi-Fi router.
 - * Computer power supplies.
 - * USB cables or metal wiring in the wall.
 5. Make sure that your **OS** is up to date.
 6. Check if there are any updates running in the background that may cause the delay.
 7. Try on a different computer/smartphone/tablet.
- If the problem **OS** (Windows/Mac/OS) Please email us.

More questions about using under Android devices.

Android operating system is still not unified, and different manufacturer make different rule. For standard keyboard, because of rule change, the standard function may not work any more. If you are using under Android device and suffering some problems, please contact us.

Contact Us

If you have any use problems with our keyboard, please do not hesitate to contact us! Please rest assured that we will definitely help you solve them!

Please contact us for a 24-month worry-free warranty. Samsums@126.com