103 mm

70 mm

USER MANUAL

CS300/CS500

User Manual
Manual del usuario
Benutzerhandbuch
Manuale Utente
Manuel d'utilisation
取扱説明書

SCAN for more

COOSPO

All About Passion

CS300-MTN-2-EN13

Product Accessories

Charging

⚠ Using a fast power adapter to charge the bike computer is not advisable as it may cause damage to the battery. After charging, please ensure to cover the USB rubber plug to keep water out.

How to Install



Common wheel size and circumference(Wheel Size L (mm))

12 × 1.75 935mm	24 × 2.00 1925mm	26 × 1.40 2005mm	700 × 18C 2070mm
14 × 1.5 1020mm	24 × 2.125 1965mm	26 × 1.50 2010mm	700 × 19C 2080mm
14 × 1.75 1055mm	26 × 1.75 2023mm	27 × 1 2145mm	700 × 20C 2086mm
16 × 1.5 1185mm	26 × 1.95 2050mm	27 × 1-1/8 2155mm	700 × 23C 2096mm
16 × 1.75 1195mm	26 × 2.00 2055mm	27 × 1-1/4 2161mm	700 × 25C 2105mm
18 × 1.5 1340mm	26 × 2.10 2068mm	27 × 1-3/8 2169mm	700 × 28C 2136mm
18 × 1.75 1350mm	26 × 2.125 2070mm	27.5×1.75 2114mm	700 × 30C 2170mm
20 × 1.75 1515mm	26 × 2.35 2083mm	27.5×2.125 2174mm	700 × 32C 2155mm
20 × 1-3/8 1615mm	26 × 3.00 2170mm	27.5×1.5 2074mm	700C Tubular 2130mm
22 × 1-3/8 1770mm	26 × 7/8 1920mm	27.5×1.95 2146mm	700 × 35C 2168mm
22 × 1-1/2 1785mm	26 × 1(59) 1913mm	29×2.1 2288mm	700 × 38C 2180mm
24 × 1 1753mm	26 × 1(65) 1952mm	29×2.2 2298mm	700 × 40C 2200mm
24× 3/4 Tubular 1785mm	26 × 1.25 1953mm	29×2.3 2326mm	700 × 42C 2224mm
24 × 1-1/8 1795mm	26 × 1-1/8 1970mm	650 X 35A 2090mm	700 × 44C 2235mm
24 × 1-1/4 1905mm	26 × 1-3/8 2068mm	650 × 38A 2125mm	700 × 45C 2242mm
24 × 1.75 1890mm	26 × 1-1/2 2100mm	650 × 38B 2105mm	700 × 47C 2268mm

Button Function

ⓘ For the first time use, please charge the device.

Button	Function
①	Power on/off: Short Press - On Long Press - Off Riding: Short Press - Lap Settings: Short Press – Save and return
②	Short Press - Start/Stop Long Press - Save Settings: Short Press - Confirm
③	Short Press - Page Switch Long Press – Enter Settings

Icons

	GPS Off		Speed sensor connected
	GPS Signal		Heart Rate Monitor
	Battery		Speed Sensor
	Start/Ride		Cadence Sensor
	Stop		Power
AUTO	Auto-Pause	ODO	Odometer
	Indoor Ride	DST	Distance
	Bluetooth Connection with App	AST	Ascent
AVG	Average	GAR	Gradient
MAX	Max	CAL	Calorie
%MAX	Percentage of max	LAP	Lap
mph	Miles per hour		Power Meter
km/h	Kilometers per hour	UTC	Time zone
	Speed above average	ALT	Altitude
	Speed below average	°C°F	Temperature: may vary from actual environment.

Data Page

Dynamic Zone Chart

The Dynamic Zone Chart shows the current zone of data, For example, if the current speed is 25.6km/h, then you are in zone 3 of speed.
Speed zone, cadence zone, heart rate zone, and power zone can be set in CoospoRide » Devices » My Profile.



Customize Pages

Page ①: Speed, Time, Distance, Gradient, Altitude
Page ②: Speed, Power, Cadence, Heart Rate, Ascent
Page ③: Average Speed, Time, Average Altitude, Average Gradient, Distance
Page ④: Max Speed, Time, Max Altitude, Max Gradient, Total Distance
Page ⑤: Speed, Time, Distance, Gradient, Odometer

Note: Page ⑤ is closed by default; please enable in CoospoRide > Devices > Page Settings;
Page data can be customized in CoospoRide APP.



Device Settings

Long press > for 2 seconds to access settings, short press > to switch between P1~P5, and short press ▶|| to enter current settings.

Note: Settings will be automatically saved and exited after 10 seconds of no button operation.

Setting ① : Add Sensor

The device automatically identifies and adds sensors.
Searching: icons and data flash;
Connected: icons and data are always on;
Short press ○ to save and return.

ⓘ Check sensor compatibility: www.coospo.com/faq

Add sensors in the app:
Open CoospoRide » Devices » CS300 » Add Sensor.



Setting ② : Time Zone

Short press > to add time zones;
Short press ▶|| to confirm current digit and set the next digit;
Short press ○ to save and return.

Setting ③ : Wheel Size

Short press > to add values;
Short press ▶|| to confirm the current digit and set the next digit;
Short press ○ to save and return.
Please refer to the page 4 for wheel size settings.



Setting ④ : Unit Settings

Short press > to switch between metric/ imperial units.
Short press ○ to save and return.

Setting ⑤ : Power Calibration

Short press > to calibrate the power sensor.
Short press ○ to save and return.



Connect to CoospoRide APP

ⓘ Please do not pair the bike computer at your phone's Bluetooth settings,
Please download CoospoRide APP in Apple Store or Google Play;
Enable the Bluetooth and location permissions on your phone;
CoospoRide APP > Bike Computer > Add Device > CS300 > Click on Device ID to connect the bike computer.

ⓘ Please ensure that Bluetooth and location permissions are enabled for the app before connecting, Some phone models may not be able to search for Bluetooth devices without authorization.

Ride

GPS Positioning

⚠ 1. For the initial satellite positioning, please wait 30~90 seconds in an open outdoor area, The date and time of the device will be set automatically after the initial positioning is successful.
2. To get the best satellite signal, please ensure that the bike computer remains stationary while it acquires the GPS signal.

Start:
Short press ▶|| for a 3~2~1 countdown on the data page, begin your ride with the start icon displayed.

Lap:
Short press ○ to mark a lap after starting ride, Lap displays for 10 seconds; any key press cancels the lap.

Pause/Auto-Pause:
Short press ▶|| to pause the ride. Press ▶|| again to resume the ride ,

If you enable the auto-pause, the ride pauses when you stop moving or when the speed falls below the value you set. This feature prevents undesired data recording during stops, rests, or while walking the bike.

Save:
Long press ▶|| to save the ride,

Check Data:
Press > to switch pages and review the data from your last ride,
More Data: Check more detailed activity data on CoospoRide APP.

Contact us

Website: www.coospo.com E-mail: support@coospo.com

Attentions

The information contained in this manual is for reference only. The product described above may be subject to alteration owing to the manufacturer's continuing research and development plans without prior notice,

Disclaimer

The information contained in this manual just for reference. The product described above may be subject to alteration owing to the manufacturer's continuing research and development plans, without making an announcement in advance,

We shall not bare any legal responsibility for any direct or indirect, accidental or special damages, losses and expenses arising from or in connection with this manual or the contained product.

FCC statement

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

IC WARNING

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:
(1) This device may not cause interference,
(2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

(1) L' appareil ne doit pas produire de brouillage;

(2) L' appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d' en compromettre le fonctionnement.

Waste electrical products should not be disposed of with household waste. Please recycle where facilities exist. Contact your local government or a retailer for additional information.

- Do not open or modify the product.
- Do not disassemble or attempt to service this product.
- This product is safe under normal and reasonably foreseeable operating conditions.
- If product is operating improperly, call COOSPO support.
- Product must be returned to the manufacturer for any service or repair.