

Feature

- ※ High gain
- ※ Omani-directional
- ※ Wide bandwidth

Application

- ※GSM850/900/DCS/PCS/WCDMA B1/B2/B4/B5/B8
- LTE B1/B2/B3/B4/B5/B7/B8/B12/B17/B20/B28/B38/B40/B41/B66/B42
- NR Mode N1/N3/N5/N7/N8/N12/N20/N28/N38/N40/N41/N66/N71/N77/N78

别漏掉下表面的表格


Name and address of the antenna manufacturer	Model number of the antenna
Dongguan Demen Electronics Co., Ltd 6th Floor, Building D, Dongguan Demen Co., Ltd., Fenghuanggang Industrial Park, No. 1 Fengtai Road, Tangxia Town, Dongguan City, Guangdong Province ##供应商名称和地址，要求全英文##	金属框项目蜂窝天线无丝印 NFC 丝印: X6870-NFC-DM-XX-XX

TYPE		
Transmitter Frequency		GSM 850/WCDMA B5/LTE B5 NR n5: 824 – 849 MHz
		GSM 900/WCDMA B8/LTE B8 NR n8: 880 – 915 MHz
		DCS /WCDMA B4/LTE B3/B4/B66 NR n3/n66: 1710 – 1785 MHz
		PCS/WCDMA B2/LTE B2:1850-1910MHz
		WCDMA B1/LTE B1 NR n1: 1920 – 1980MHz
		LTE B7 NR n7:2496-2565MHz
		LTE B40 NR n40:2300-2400MHz
		LTE B38/B41 NR n38/n41:2565-2645MHz
		LTE B20 NR n20:832-862MHz
		LTE B12/B17/B28 NR n12/n28:710-755MHz
		LTEB42 NR n77/n78:3300-4200MHz
Receiver Frequency		GSM 850/WCDMA B5/LTE B5 NR n5: 869 – 894 MHz
		GSM 900/WCDMA B8/LTE B8 NR n8: 925 – 960 MHz
		DCS/LTE B3/B66 NR n3/n66: 1805 – 1880 MHz
		WCDMA 4/LTE B4 NR n4: 2110-2155 MHz
		PCS/WCDMA B2/LTE B2:1930-1990MHz
		WCDMA B1/LTE B1 NR n1: 2110 – 2170MHz
		LTE B7 NR n7:2620-2690MHz
		LTE B40 NR n40:2300-2400MHz
		LTE B38/41 NR n38/n41:2565-2645MHz
		LTE B20 NR n20:791-821MHz
		LTE B12/B17/B28 NR n12/n28:758-803MHz
		LTEB42 NR n77/n78:3300-4200MHz
RF-Output Power (E.I.R.P)		GSM850/900: 32+/-2dBm
		DCS/PCS: 30+/-2dBm
		LTE B1/B2/B3/ B4/B5 /B7/B8/B17/B20/B28/B38/B40/B41/B66: 23+/-2dBm
		WCDMA B1/B2/B4/B5/ B8: 23+/-2dBm
	ANT0	LTEB42 NR n77/n78: -6.69
		WiFi5G:-3
	ANT2	GSM 850/WCDMA B5/LTE B5 NR n5:-6.2
		GSM 900/WCDMA B8/LTE B8 NR n8:-7.77
		LTE B12/B17 NR n12:-14.28


Antenna Gain		LTE B28NR n28:-6.09
		LTE B20 NR n20:-6.6
		LTE B7 NR n7:-5.06
		LTE B40 NR n40:-4.57
		LTE B38/41 NR n38/n41:-4.97
		NR n71:-8.56
	ANT3	WCDMA B1/LTE B1 NR n1: -2.08
		PCS/WCDMA B2/LTE B2:-1.87
		DCS /WCDMA B4/LTE B3/B4/B66 NR n3/n66:-3.04
		LTE B7 NR n7:-1.90
		LTE B40 NR n40:-2.25
		LTE B41/B38 NR n41/n38:-2.01
	ANT4	GSM 850/WCDMA B5/LTE B5 NR n5: -6.02
		GSM 900/WCDMA B8/LTE B8 NR n8: -11.49
		LTE B12/B17/B28 NR n12/n28:-5.8
		LTE B20 NR n20:-7.94
	ANT5(ENDC)	WCDMA B1/LTE B1 NR n1: -6.16
		PCS/WCDMA B2/LTE B2:-6.68
		DCS /LTE B3/B66 NR n3/n66:-8.4
		WCDMA B4/LTEB4 :-10.2
		LTE B7 NR n7:-10.61
		LTE B40 NR n40:-9.71
		LTE B41/B38 NR n41/n38:-11.07
	ANT6	LTEB42 NR n77/n78:-6.31
	ANT7	WCDMA B1/B4LTE B1/B4/B66 NR n1/n4/n66 : -5.87
		PCS/WCDMA B2/LTE B2:-4.95
		DCS /LTE B3/NR n3:-3.9
		LTE B7 NR n7:-1.17
		LTE B40 NR n40:-3.38
		LTE B41/B38 NR n41/n38:-2
		LTEB42 NR n77/n78:-3.56
	ANT8	LTEB42 NR n77/n78:-4.2
	ANT12	GPS(L1):-5.35
		BT/WIFI2.4:-2.67
	ANT13	WIFI2.4:-4.82
Type of Modulation		

※ Antenna Gain


ANT0



LTEB42 NRN77/78 & WIFI5G Phi=0deg




LTEB42 NRN77/78 & WIFI5G Phi=90deg




LTEB42 NRn77/78 & WIFI5G Theta=90deg

※ Antenna Gain


ANT2




GSM 850/WCDMA B5/LTE B5 NR n5 Phi=0deg




GSM 850/WCDMA B5/LTE B5 NR n5 Phi=90deg




GSM 850/WCDMA B5/B20 LTE B5 NR n5/n20 Theta=90deg




GSM 900/WCDMA B8/LTE B8 NR n8 Phi=0deg




GSM 900/WCDMA B8/LTE B8 NR n8 Phi=90deg




GSM 900/WCDMA B8/LTE B8 NR n8 Theta=90deg




LTE B12/B17 NR n12:-14.28 Phi=0deg




LTE B12/B17 NR n12:-14.28 Phi=90deg




LTE B12/B17 NR n12:-14.28 Theta=90deg




LTE B28NR n28 Phi=0deg




LTE B28NR n28 Phi=90deg




LTE B28NR n28 Theta=90deg




NR n71 Phi=0deg




NR n71 Phi=90deg




NR n71 Theta=90deg




LTE B7/NR n7 Phi=0deg




LTE B7/NR n7 Phi=90deg




LTE B7/NR n7 Theta=90deg



LTE B40/B38/B41NR n40/n38/n41 Phi=0deg




LTE B40/B38/B41NR n40/n38/n41 Phi=90deg




LTE B40/B38/B41NR n40/n38/n41 Theta=90deg

※ Antenna Gain


ANT3




WCDMA B1/LTE B1 NR n1 Phi=0deg




WCDMA B1/LTE B1 NR n1 Phi=90deg




WCDMA B1/LTE B1 NR n1 Theta=90deg




PCS/WCDMA B2/LTE B2 Phi=0deg




PCS/WCDMA B2/LTE B2 Phi=90deg




PCS/WCDMA B2/LTE B2 Theta=90deg




DCS /WCDMA B4/LTE B3/B4/B38/B41/B66/B7 NR n3/n7/n38/n41/n66 Phi=0deg




DCS /WCDMA B4/LTE B3/B4/B38/B41/B66/B7 NR n3/n7/n38/n41/n66 Phi=90deg




DCS /WCDMA B4/LTE B3/B4/B38/B41/B66/B7 NR n3/n7/n38/n41/n66 Theta=90deg



LTE B40 NR n40 Phi=0deg




LTE B40 NR n40 Phi=90deg




LTE B40 NR n40 Theta=90deg

※ Antenna Gain


ANT4:




GSM 850/WCDMA B5/LTE B5 NR n5 Phi=0deg




GSM 850/WCDMA B5/LTE B5 NR n5 Phi=90deg




GSM 850/WCDMA B5/LTE B5 NR n5 Theta=90deg




GSM 900/WCDMA B8/LTE B8 NR n8 Phi=0deg




GSM 900/WCDMA B8/LTE B8 NR n8 Phi=90deg




GSM 900/WCDMA B8/LTE B8 NR n8 Theta=90deg




LTE B12/B17/B28 NR n12/n28 Phi=0deg




LTE B12/B17/B28 NR n12/n28 Phi=90deg




LTE B12/B17/B28 NR n12/n28 Theta=90deg



LTE B20 NR n20 Phi=0deg




LTE B20 NR n20 Phi=90deg




LTE B20 NR n20 Theta=90deg

※ Antenna Gain


ANT5




WCDMA B1/B4/LTE B1/B4/B7/B38/B41NR n1/n7/n38/n41/n42 Phi=0deg




WCDMA B1/B4/LTE B1/B4/B7/B38/B41NR n1/n7/n38/n41/n42 Phi=90deg




WCDMA B1/B4/LTE B1/B4/B7/B38/B41 NR n1/n7/n38/n41/n42 Theta=90deg




PCS/WCDMA B2/LTE B2/B3 Phi=0deg




PCS/WCDMA B2/LTE B2/B3 Phi=90deg




PCS/WCDMA B2/LTE B2/B3 Theta=90deg



LTE B40 NR n40 Phi=0deg




LTE B40 NR n40 Phi=90deg




LTE B40 NR n40 Theta=90deg

※ Antenna Gain


ANT6



LTEB42 NRn77/78 Phi=0deg




LTEB42 NRN77/78 Phi=90deg




LTEB42 NRN77/78 Theta=90deg

※ Antenna Gain


ANT7:




WCDMA B1/B4LTE B1/B4/B66 NR n1/n4/n66 Phi=0deg




WCDMA B1/B4LTE B1/B4/B66 NR n1/n4/n66 Phi=90deg




WCDMA B1/B4/LTE B1/B4/B66 NR n1/n4/n66 Theta=90deg




PCS/WCDMA B2/LTE B2 Phi=0deg




PCS/WCDMA B2/LTE B2 Phi=90deg




PCS/WCDMA B2/LTE B2 Theta=90deg




DCS /LTE B3/NR n3 Phi=0deg




DCS /LTE B3/NR n3 Phi=90deg




DCS /LTE B3/NR n3 Theta=90deg




LTE B7/ B41/B38 NR n7/n41/n38 Phi=0deg




LTE B7/ B41/B38 NR n7/n41/n38 Phi=90deg




LTE B7/ B41/B38 NR n7/n41/n38 Theta=90deg




LTE B40 NRn40 Phi=0deg




LTE B40 NR n40 Phi=90deg




LTE B40 NR n40 Theta=90deg



LTEB42 NRn77/78 Phi=0deg




LTEB42 NRN77/78 Phi=90deg




LTEB42 NRN77/78 Theta=90deg

※ Antenna Gain


Ant8



LTEB42NRn77/78Phi=0deg




LTEB42 NRn77/78 Phi=90deg




LTEB42 NRn77/78 Theta=90deg

※ Antenna Gain


Ant12



GPS(L1)/WIFI2.4 Phi=0deg




GPS(L1)/WIFI2.4Phi=90deg




GPS(L1)/WIFI2.4 Theta=90deg

※ Antenna Gain


Ant13



WiFi2.4 Phi=0deg



WiFi2.4 Phi=90deg



WIFI2.4 Theta=90deg

PREPARED BY	CHECKEDBY	APPROVAL BY	S.R.NO	
			DATE:	2024/12/18