microlab



Вluetooth[®]

Important Safety Instructions

- e cart, stand, tripod,

FCC and Canada EMC Compliance Information

Getting started

Congratulations! Thank you for choosing MOGUL headphones . Before using MOGUL, users should read this manual to familiarize themselves with the functions of your mobile phone or other devices.

Safety Rules

Please follow the rules depicted in this manual carefully to ensure your safety. Before using MOGUL, we would strongly encourage you to read through this user manual. Be more care of any edges, uneven surfaces, metal parts, accessories and packaging to avoid any possibility of injury. Do not dismantle, repair and modify product to avoid fire breaking, electric shocking and product damaging completely, which are not covered under warranty. Do not use any diluents or volatile liquid to clean MOGUL. Do not use the MOGUL in a hazardous location.

Specifications

Talk time:	≥23H		
Stand-by time:	700H		
Music play time:	≥21H		
Wireless range:	≥10m		
Bluetooth profiles:	HSP, HFP, A2DP, AVRCP		
Impedance:	64 Ω		
Sound pressure level:	100±3dB		
Frequency Response:	20Hz – 20KHz		
Weight:	200g		

Features

P, AVRCP	1, 3 2, S 3, T
	LE
	Or

.5mm audio jack music line-in function Support connecting with 2 phone devices The headphone battery power status showed on iOS

ED Indicator

Operation	LED Status	
Power on	Blue LED flashes 2 times	
Power off	Red LED flashes 2 times	
Pairing	Red LED & Blue LED flashes alternately	
Standby	Blue LED flashes 3 times in 5 seconds	
Low battery	Red LED flashes 2 times every 2 seconds	
Charging	Red LED keeplighting during charging Red LED off when finished.	

Power On

Press multifunction button for 2 seconds, Headphone turned on Blue LED flashes 2 times.



Power off

Press multifunction button for 3 seconds. Red LED turn off after flashes 2 times, Headphone turned off.



Pairing

Press multifunction button for 5 seconds Red LED & Blue LED will flash alternately



Activate phone BT function and then search for MOGUL to connect



Volume up



Volume down

Short press "-" button

long press "-"

long Press "+" button





Previous


" button



Next

Play & Pause

Short press multifunction button, music pauses. Press it again, music continues.



Incoming Call

Short press multifunction button to answer the incoming call. Blue LED will quickly flash



Reject Call

Press "+" button for 2 seconds to reject a call. Blue LED flashes 2 times.




Last number redial

In standby status, continuously press headphone multifunction button twice to redial the last number.



Call Mute function

Press "-" button for 2 seconds, call mute. Press "-" button for 2 seconds again, call mute function cancelled.






Short press multifunction button to end phone call.

Transfer call:

End call:

During the phonecall press "+" button for 2 seconds, call switched to mobile phone. Press "+" button for 2 seconds again, call switched to headphone.



Share Me

After finish pairing for headphone&cell phone, short press Share me button, LED Indicator light flash alternately white&blue. Turn on second headphone under pairing mode, second headphone will connecting with first phone automatic. Share me connecting finished! Two headphones can share same music from same cell phone. Long press Share me button can disconnect the second headphone's connecting with voice prompt.



Voice control


Quickly press multi function button 3 times to activate Siri. *Your cell phone needs support this function.

Battery Capacity status:

When headphone is connected to iOS devices, he battery power status will show in the upper riaht corner.



3.5mm audio jack music line-in function Connect 3.5mm audio jack line for wired music. (Phone call function cannot be used in this mode.)



Pairing (One headphone supports \ connecting 2 phone devices)

Pairing with the phone A successfuly, then turn off







Do the same procedure with phone B. Then power off the headphone again



Power on the headphone, it will automatically connect to the Phone B of Last connected, and short press the two key of "volume +" and "volume -" simultaneously ,can enable the multipoint Connect function, select the headphone in Phone A



Charging

When in low battery, please charge via USB cable. Red LED keeps lighting during charging, Red LED turns off when charging finished.



Kit Contents

- 1.1 X MOGUL 2.1 X Charging Micro USB Cable
- 3.1 X User Manual
- 4.1 X 3.5mm jack audio cable

Warning

- 1, You must choose a qualified charger from a regular
- manufacturer to charge the headphone.

 2, You must charge the headphone if it has not been used for more than 12 months.



www.microlab-global.com Microlab Electronics Co., Ltd Made in China