

All product and product specifications are subject to change without notice to improve reliability, function, design or otherwise.

purosound.com


# JuniorJams-PLUS

### **User Manual**

Congratulations on your purchase of a pair of Puro Sound Labs JuniorJams-PLUS Headphones! Hearing health is a lifelong endeavor and we're dedicated to building products that promote Healthy Ears, while delivering incredible sound and value. Thank you for your purchase! Please read our usual manual to get the most out of your headphones.

If you ever have a problem, please contact us at support@purosound.com

From our family to yours, enjoy!



- A . Power on/Off
- B. Volume Up
- C. Volume Down
- D. Multifunction Button (MFB)
- E Bluetooth LED
- F. Charging Interface
- G . MIC
- H . AUX Interface

#### ACCESSORIES

#### JuniorJams-PLUS

3.5mm Limiter Audio Cable **USB-C Charging Cable** Daisy Chain Sharing Cable Drawstring Travel Bag User Manual

#### SPECIFICATIONS

Bluetooth Version: V5.1 Dimension: 197\*155\*65.9 mm Bluetooth Profile: HSPv1.2 HFPv1.6 A2DP v1.3 AVRCP v Frequency: 2.402GHz-2.480GHz Built-in lithium battery voltage: 3.7V Battery capacity: 400mAh Driver Dimension: Φ40mm Headset power: 20mW\*2 THD≤10% Weight: 220g

SNR: ≥90dB Charging voltage: 5V DC 100-240V AC adapter Charging Time: 2H Charging current: ≥300MA Standby Time: 300H Talking Time: 22H Support dual connection: Support connecting with two mobile Work Temperature : -10—55°C

#### QUICK START (PAIRING)

- 1. Charge the headphones until the blue light remains on (indicating full charge). Charging cable is a USB-C - USB cable found in the headphone packaging.
- 2. Turn the headphones on by sliding the power button from "off" to "or Headphones will automatically enter "discoverable" mode, indicated by blue and red alternating flashes.
- 3. Bring the headphones within 1 meter (3 ft.) of the source device and follow the source device instructions for pairing a Bluetooth device. You will hear a voice prompt indicating that the headphones are paired.
  - a. For Apple source devices Go into "settings" -> Bluetooth, Make sure Bluetooth functionality is on. JuniorJams-PLUS will show up as a discovered device, select JuniorJams-PLUS.

### JUNIORJAMS-PLUS FUNCTIONALITY

- Power On: Slide power button from "OFF" to "ON."Automatic power off: Power will automatically shutoff if there is no connection
- for 10 minutes or if battery is below 5%. Charging: Plug in charging cable. LED will show red when charging and blue
- when fully charged. Play/Pause: When music is playing, press"MFB" once to pause/play.
- Next Song: When music is playing, press "MFB" twice to skip to next song.
  Previous Song: When music is playing, press "MFB" three times to skip to
- previous song. Volume up : When playing music, press "+"for volume up.
- $\,$  MIC  $\,$  Mute : When calling, double press "-"for Mic mute, double press again
- to cancel Answer a call/hang up: For incoming call, click "MFB" to answer a call, and
- to hangup. Reject Call : Hold "MFB" to reject call and send to voicemail. · Limiter Cable: The 3.5mm Limiter Cable can be used to connect Junior Jams-PLUS
- to device either when headphones are charged or not charged. Make sure to check that Limiter Cable is used in proper direction. · Daisv-chain: Daisv-chain cord can be used to connect two JuniorJams headphones together.
- o Pair headphone A with device via Bluetooth or Limiter Cable, o Connect headphone B to headphone A using the daisy-chain cord.

#### LED STATUS INDICATOR

1. Power ON: Blue LED flashes twice

2.Power OFF: Red LED flashes twice 3. Pairing mode: Alternating Blue and Red LED flashes

 Connected status: Blue LED flashes once every 10 seconds
 Unconnected standby status: Blue LED flashes twice every 5 seconds 6. Charging status: Red LED steady

7. Full charged: Blue LED steady 8. Low Power: Red LED flashes

### **BATTERY INFORMATION**

Your device is powered by a rechargeable battery. The full performance of a new battery is achieved only after two of three complete charge and discharge cycles. The battery can be charged and discharged hundreds of times, but it will eventually wear out. Do not leave a fully charged battery connected to a charger since overcharging may shorten battery lifetime. Leaving the device in hot or cold places, such as in closed car in summer or winter conditions, will reduce the capacity and lifetime of the battery. Battery performance is particularly limited in temperatures well below freezing. Battery should be charged once per month to extend the life of the battery. Do not dispose of batteries in a fire as they may explode.

#### WARRANTY Puro Sound Labs, LLC warrants the original owner of this product against

manufacturing and material defects under normal use for a period of one (1) year from the date of retail purchase from Puro Sound Labs or a Puro Sound Labs authorized reseller. The warranty does not cover damages resulting from misuse, abuse, water damage, normal wear and tear, or modification. For warranty claims, please visit http://purosound.com/support or email us at support@purosound.com

Puro Sound Labs, at its sole discretion will repair or replace the product, or refund

the original owner the purchase price

## FCC&IC Statement

The user is cautioned that changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with Part 15 of the FCC Rules and Industry Canada licence-

exempt RSS standard(s).

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular

nums equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

— Reorient or relocate the receiving antenna.

-- Consult the dealer or an experienced radio/TV technician for help

Reorient or relocate the receiving antenna.
 Increase the separation between the equipment and receiver.
 Connect the equipment into an outlet on a circuit different from that to which

pareils radio exempts de licence

FCC ID: 2AWFS-JAMSPLUS IC: 23211-JAMSPLUS

#### SAFETY INFORMATION Warning! Continued exposure to loud noise (more than 85 decibels) (85 dBA) may cause gradual but permanent damage to hearing.

Always turn the level of your Puro product down to a low level before placing the headphones on your (or your child's) head. Gradually turn up the volume until you achieve a comfortable level. Never listen at high volumes for long periods. Always verify maximum achievable volume levels before the headphones are given to a child for use.

The JuniorJams model features a volume governor that limits output for hearing safety. The rating uses an A-weighted scale with several genre of popular music to safety, the rating loss an American test of the wint several gettied in popular industrial achieve a max of approximately 85 dBA. The levels have been tested on popular portable iOS and Android phones and tablets while streaming via the wireless Bluetooth connection. Further, the in-line cable allowing use when the battery is

depleted has been designed to limit to the same approximately 85 dBA value on most portable iOS and Android phones and tablets. When using the wired connection, a home stereo or other high-powered source may exceed 85 dB. Because we cannot test every device in the market, please verify that the maximum level that can be achieved with your source device is within the "comfortable" guideline. Do not use the headphones with products that can achieve levels above the "comfortable" guideline.

headphones fit many adults.) Do not use the headphones any time it would be dangerous to not be aware of noises around you. If using while on an airplane, please follow the instructions of the crew for permitted use of a Bluetooth product.

Do not use the headphones while operating a motor vehicle. (Our kids

Do not use or store the headphones in a wet environment. If the headphones are submerged or become wet, do not use.

### CARE AND MAINTENANCE

- · Do not hit or beat the produc. · Do not forcibly rotating the earpiece as internal circuitry can be damaged.
  - · Keep the product away from water and high temperature; do not use this product in extreme weather.
  - · Do no put the product into fire.
  - · Do not block the mesh of the speaker.