

Important information:

1. Keep the charging case and earbuds away from Wifi routers and other bluetooth devices to avoid potential signal interference.
2. Operate the earbuds within a 10 metre range (barrier free environment) of the phone they are connected to.
3. Do not expose the earbuds to temperatures below 32°F or above 100°F.
4. Both the charging case and individual earbuds contain lithium batteries. Do not expose the lithium batteries to strong sunlight or intense heat or throw them into a fire due to the potential risk of an explosion occurring.
5. To prevent the risk of electric shock, do not use the earbuds during thunderstorm weather conditions in your vicinity.
6. Do not pull apart or attempt to open the earbud casings or charging case for any reason. The potential exists for risk of damage, burns or electric shock. The manufacturer's warranty is void if this is attempted.

QUICK START GUIDE

Wireless Earbuds with Charging Case- Black

MANUAL



Pairing your Bluetooth® Earbuds to your Phone

For both Single and Double Ear Connection: Long press the multi-function button on earbud(s), then release the button after tone. The red and blue lights will alternately flash. Open your phone, go to the Bluetooth settings and search for connection (**#09472**). After the connection is successful, you can listen to music or make a phone call.

Note: Phone calls only support unilateral bluetooth headset. Shutdown, play and pause can be made on any one of the connected headphones multifunction button controls (another headset will synchronous control). If only using one earbud, and wanting to connect the second earbud, long press the multifunction button to auto connect.



Wireless Verion	Bluetooth V5.3, Ultra low power consumption
Wireless Profile	A2DP1.3/HFP16/HSP1.2/AVRCP1.6/D11.3
Frequency	2.4GHZ
Working Range	About 10M
Battery Capacity	Internal 50mAh rechargeable Li-ion battery
Standby Time	About 100hrs if one earbud on About 60hrs if both earbuds on
Continuous Working Time	Using one earbud, approx. 4-5hrs Using both earbuds, approx. 3-4hrs <small>(Support incoming call number IOS system power display)</small>

Answering Phone calls

To answer a call, a short press of the multi-function button will answer the call. If you do not want to answer a call, you can quickly press the multi-function button (call blocking function).

Double Tapping the multi-function button will dial the last outgoing call (last number redial).

Listen to Music

Open your music player and press the button once, to play/pause playlist music. Triple tap on the left multi-function button will skip back to the last song. Triple tap on the right multi-function button will skip ahead to the next song.

Charging Earbuds

Place earbuds in charging case. When charging, you will see a red light. Red light will turn to blue light when charging is complete.

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

FCC ID: 2ATF5-E09472