


1. Description

BDE-ANT-LE2340RA is an integrated PCB trace antenna designed for BDE-LE2340RA module series, including but not limited to the below part numbers:

- BDE-LE2340R53KPA
- BDE-LE2340R52KPA
- BDE-LE2340R22KPA
- BDE-LE2340R52GEA
- BDE-LE2340R21GEA

The dimension of the antenna area is 11.5mm x 3.8mm.




2. Specifications

Electrical				
Frequency (MHz)	2400 - 2500			
Efficiency	35.08% @ 2.4G band			
Peak Gain	0.96dBi @ 2.4G band			
Impedance	50 ohm			
Polarization	Linear			
Radiation	Omni-directional			
Mechanical				
Dimension	11.5mm x 3.8mm x 0.6mm			
PCB Substrate	FR4			
Environmental				
Temperature Range	-40°C to 85°C			

3. Antenna Characteristics

The antenna characteristics data are measured with the module sitting on the evaluation board as the picture on the right shows.


The dimension of the evaluation board is 58.5mm x 59mm x1.6mm.




Integrated PCB Trace Antenna for BDE-BW33PA Module Series

Datasheet

3.1 Return Loss




3.2 Radiation Pattern





Integrated PCB Trace Antenna for BDE-BW33PA Module Series

Datasheet



3.3 Efficiency and Gain

Frequency (MHz)	Efficiency (%)	Gain (dBi)			
2.4G Band					
2400	24.86	-0.92			
2410	27.25	-0.51			
2420	30.05	-0.01			
2430	33.18	0.70			
2440	34.58	0.85			
2450	34.50	0.64			
2460	35.08	0.78			
2470	34.89	0.92			
2480	32.68	0.95			
2490	32.42	0.96			
2500	30.63	0.60			

4. Revision History

Revision	Remark	Date
V1.0	Initial release	2024/8/21



Important Notice and Disclaimer

The information contained herein is believed to be reliable. BDE makes no warranties regarding the information contain herein. BDE assumes no responsibility or liability whatsoever for any of the information contained herein. BDE assumes no responsibility or liability whatsoever for the use of the information contained herein. The information contained herein is provided "AS IS, WHERE IS" and with all faults, and the entire risk associated with such information is entirely with the user. All information contained herein is subject to change without notice. Customers should obtain and verify the latest relevant information before placing orders for BDE products. The information contained herein or any use of such information does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other intellectual property rights, whether with regard to such information itself or anything described by such information.

Contact

BDE Technology Inc.

USA: 67 E Madison St, # 1603A, Chicago, IL 60603, US

Tel: +1-312-379-9589

China: B2-403, 162 Science Avenue, Huangpu District, Guangzhou 510663, China

Tel: +86-20-28065335

Website: www.bdecomm.com Email: info@bdecomm.com