印刷说明

材质: 250g双铜版纸


对折尺寸: 105x150mm

装订方式: 风琴折页,黑白印刷

注意: 此页不做印刷



User Manual



Contents

1. Important Safety Instructions 1	 Make sure to stop the main unit from operating and unplug power adapter before moving.
2. Package Contents 4	Assembly
3. Specification4	 Place the air purifier on a stable surface to avoid vibration a noise.
4. Introduction 5	 The air inlet of the main unit should be at least 3.94in (10cm from walls or other obstructions to avoid blocking the air inlet.
5. Assembly Instructions 8	Cleaning and Storage
6. Controls & Indicators	 Frequently clean the dust, hair, and impurities from the surfethe filters to reduce bacterial growth.
7. App Download Instructions14	 Clean the dust and impurities blocking the air inlet to prever decrease in air intake.
8. Maintenance & Care	 If the air purifier will not be used for an extended period of t cover the air outlet on the top of the air purifier to prevent dusettling on the grille and fan blades, and to keep them clean.
9. Troubleshooting 16	Power Supply
10. Notice19	Follow the instructions below when using the power adapter coutlet to avoid fire, electric shock, or damage.
11. Warranty 20	 The air purifier is directly powered by the power adapter and not support charging or battery storage.
12. Contact Us	• Do not excessively pull, twist, or bend the power cord, as thi expose the wire core or cause the core to break.

Not Use Replacement Parts The Manufacturer (e.g. Parts

1. Important Safety Instructions

To Reduce The Risk Of Fire, Electric shock Or Injury To Persons, Do Not Use Replacement Parts That Have Not Been Recommended By The Manufacturer (e.g. Parts Made At Home Using A 3D Printer).	 Use the provided power power adapters.
Movement	 Disconnect the power be the air purifier.
 Make sure to stop the main unit from operating and unplug the 	• If the nower adapter is

power adapter for replacement from the manufacturer.

- urifier on a stable surface to avoid vibration and
- ne main unit should be at least 3.94in (10cm) away • Do not insert fingers or foreign objects into the air inlet, air er obstructions to avoid blocking the air inlet. outlet, or detection port to avoid accidents.

- avoid being pulled in or blocking the air inlet and the air outlet. in the dust, hair, and impurities from the surface of • Do not sit on, lean on, or tilt the main unit to avoid malfunction
- of the air purifier. and impurities blocking the air inlet to prevent a • Do not use the air purifier simultaneously with household gas

During Use

100-240V, two-prong flat power outlet).

• Do not pour liquids, powders, or small particles from the air outlet into the main unit to avoid malfunction or safety accidents.

appliances, such as gas stoves, gas water heaters, etc. to avoid er will not be used for an extended period of time. igniting the air purifier. et on the top of the air purifier to prevent dust from

igniters, fire pits, etc.

Use Restrictions ctions below when using the power adapter and e, electric shock, or damage. Do not use the air purifier in the following situations, as it may

- result in electric shock, fire, or other damage. is directly powered by the power adapter and does ing or battery storage. Keep the main unit, especially the air inlet, away from open flame
- devices, such as candles, incense burners, stoves, fireplaces, ely pull, twist, or bend the power cord, as this may cigarettes, firecrackers, lighters, electronic ignition spray guns, expose the wire core or cause the core to break.

Connect the power adapter to a suitable power outlet (AC Keep the main unit away from high-temperature heating devices

stoves, irons, etc. Keep flammable materials away from the main er adapter only. Do not use other brands of

- Do not place the air purifier on an uneven, sloping, or small before performing maintenance or moving tabletop where it may easily tip over.
- Do not place the air purifier in bathrooms, basements, or other If the power adapter is damaged, you must purchase a dedicated damp locations where it may get wet.

- If abnormalities such as unusual noise, odor, high temperature, or who lack of experience and knowledge, unless they have been irregular fan rotation occur, stop using the air purifier immediately. given supervision or instruction regarding the use of the air purifier
 - by a person responsible for their safety. • Keep away from children to prevent them from playing with the
- air purifier. Do not allow hair or other fabrics to come near the main unit. to

• This air purifier is not intended for use by persons (including

children) with reduced physical, sensory, or mental capabilities, or

2. Package Contents

such as electric heaters, space heaters, foot warmers, electric



Power

Adapter x1

AP-02

24V == 2.75A

100-240V~ 50/60Hz







Manual x1

Model No.

Dimensions

Adaptor Input

Appliance Input

Rated Power

3. Specification

Smart Air

4. Introduction

About the Air Purifier







Filter x1




ClearBreathe Neo Smart Air Purifier

23.5*11.8*11.8in/600*300*300mm

About the Filter

Captures long strip-shaped objects such as cotton lint, fibers, hair, and pet fur. Equipped with a hook&loop strip. After a period of use, the filter



b-Activated Carbon Filter

a-Hair Pre-filter

 Adsorbs gaseous pollutants from pets, kitchens, secondhand smoke, indoor mold, etc., and reduces odors in the environment.

c. Air Quality Indicator	 Deeply filters small particles such as tiny dust, smoke particles,
f. Air Outlet	pollen, and pet dander.

—— c

е е

b. Main Unit

e. Base Cover

a. PM2.5 Detection Port | h. Filter Compartment | i. Power Port

Physically adsorbs smoke, odors, allergens, and other ultra-fine

Filters compounds such as formaldehyde, benzene, ammonia.

e-Nylon Pre-filter

- Captures fine foreign objects and large particles, such as cotton fluff and small hair.
- Performs pre-filtration of large airborne particles, blocking them before they reach the main filter, making it easier to clean and

About the Air Quality Indicator

About the Control Panel

Orange

a. WiFi Indicator

b. Child Lock

c. Auto Mode

d. Speed Level

Red

PM 2.5 Value Blue Verv Good 36-75ug/m³ Green

Moderate

c-Main Filter

5-Stage deep filtration system

 Deeply filters small particles such as tiny dust, smoke particles,
pollen, and pet dander.


d-HEPA High-efficiency Filter

- hydrogen sulfide, and volatile organic compounds (VOCs).

5. Assembly Instructions

a. Take out the filter.

For initial use, place the air purifier upside down on a flat surface. Rotate the base cover to open the filter compartment as shown in the illustration. Take out the 4-in-1 filter and remove the packaging.




b. Install the filter. Secure the hair pre-filter to the outside of the 4-in-1 filter. Place the

entire filter into the filter compartment (Handle facing up). Rotate the base cover to assemble the air purifier properly.




c. Place properly. Place the air purifier with the front facing up on a flat and stable

surface. Make sure the air inlet is at least 3.94in (10cm) away from walls or other obstructions.



d. Connect to power. Connect the provided power adapter to the power port on the air

purifier, then plug it in.





Hair Pre-filter



e. Filter Replacement Indicator

d — +

116ug/m³+

f. Value Display Screen

g. Child Lock Indicator

6. Controls & Indicators





Press to turn on/off the air purifier. It defaults to the speed used the last time when it was turned off.

Network pairing:

flashing. The air purifier will reset and enter the state of network pairing (the state of network pairing will last for



Slide left or right to adjust the speed (1-10 levels). The air

purifier has a memory function, when you turn on the air

purifier, it will run at the mode and speed used the last

Press to turn on/off the Auto mode. In Auto mode, the gir

automatically run at the speed used the last time it was

When the filter life is < 10%, will light up. To ensure

Auto Mode

- -----+

Speed Level

time it was turned off.

purifier will automatically adjust the speed level based on the air auglity (PM2.5 concentration). When the air auglity is moderate or poor, the air purifier will automatically run WiFi Indicator at a higher speed. When the air quality is good or very good, the gir purifier will automatically run at a lower

Sleep Mode

turned off.

Press to turn on/off the Sleep mode. In Sleep mode, the gir purifier will run at a lower speed. At this time, you can adjust the speed based on your personal tolerance for noise during sleep. If there is no operation for 3s, the Indicator Status screen display will be off (any touch will turn on the screen display). The air purifier can remember the speed setting, and the next time it enters Sleep mode, it will

Child Lock

Filter Reset

Press and hold for 3s to turn on/off the child lock. When \bigoplus lights up, the buttons on the screen are locked. When \bigcap is off, the child lock is turned off.

Statement

WiFi is connected.

optimal purification performance, please purchase a new filter for replacement. After replacing the filter, press Θ for 3s to reset the filter life to 100%. After reset, M will off. ו"וו"ו Humidity Value

WiFi is not connected. Wait to connect to WiF

Displays real-time temperature values, ranging from 14.2°F

Temperature Value

Filter Replacement Indicator

WiFi Indicator Status

Always on

Statement Filter life is <10%, indicating the filter needs to be replaced Filter life is ≥10%, indicating the filter is functioning normally

QQQ Value Display Screen

time, PM2.5 will light up.

to 140°F (10°C~60°C).

When you are operating the air purifier, the value display

screen will show the current operation information, such Once connected to the Prodiavtec app, the air purifier can as speed level (1-10), timer duration (00H, 01H......12H), etc. supports voice control through Alexa or Google Home. At this time, PM2.5 will not light up.

When you are not operating the air purifier, the value Google Play (Android device). Register your account via email. display screen will show the PM2.5 value (001-999). At this

Displays real-time humidity values, ranging from 5% to 99%.

to add the air purifier.

Filter cleaning

8. Maintenance & Care

mended to clean them once a month.

refer to the actual usage time.

interconnect with other devices added to the app. The air purifier

Open the Prodigytec app, and allow the app to access the location





4-in-1 filter replacement b. Turn on the air purifier and press (1) for 3s. Then the air purifier will enter the state of network pairing, and \approx will flash. The 4-in-1 filter has a life expectancy of 8-12 months. When the


> filter life is <10% (remaining life of approximately 1 month), M will light up in red to remind the user to replace the filter. Note: The actual filter life may vary depending on the frequency of use of the air purifier in each household, and the actual situation should



PM2.5 detection port

continuous purification, it may be due to dust accumulation caused by long-term use. In this case, you can use a hair dryer (on the cold air settina) and blow air diagonally toward the PM2.5 detection port to blow out the dust inside the detection port, so that the PM2.5 sensor can resume normal operation.

If the PM2.5 value remains high and does not decrease even after



Try to power off the air purifier, and restart it.

9. Troubleshooting

The air purifier cannot be powered on.

• Make sure there are no foreign objects in the air outlet, air inlet. Make sure you are using the provided power adapter to power on

The air purifier cannot connect to the Prodiavted

• Make sure your phone's BT is turned on and the air purifier is not currently connected to another phone.

PM2.5 cannot be detected or PM2.5 is displayed

Check whether the PM2.5 detection port has not been cleaned.

for a long time. You can use an air dryer (cold air) to remove the

• Make sure to remove the 4-in-1 filter packaging, and that the

During setting, you need to use a secure 2.4GHz WiFi network

Make sure there are no obstructions within 3.94in (10cm) ground

Check whether the PM2.5 detection port is blocked by any

Poor air purification effect

Clean or replace the filter.

Abnormal noise.

filter is installed properly.

the air purifier.

Make sure to remove the filter packaging.

• Adjust the air purifier to a higher speed.

- and ensure the network is working properly.

Make sure the WiFi password you enter is correct, and that there are no spaces at the beginning or end of the password.

• Try moving the gir purifier closer to the router, with your phone

Your router may need to be moved higher and away from

Make sure the air purifier and router are kept away from

- **FCC Statement** • Test the WiFi password by connecting other electronic devices to
- subject to the following two conditions: • If you are manually entering the SSID and password, make sure they are both correct.

10. Notice

- interference that may cause undesired operation.
- Warning: Changes or modification not expressly approved by the party responsible for compliance could void the user's authority to
- **Note:** This equipment has been tested and found to comply with the electrical appliances, such as microwaves, fridges, electronics, etc. to avoid signal interference. • If you are using a VPN, make sure to turn it off when setting the
- Disable any portal authentication on your WiFi network. If portal
- authentication is enabled, the air purifier will not be able to access your WiFi network and the setting will fail.

The air purifier is offline.

• Make sure the air purifier is plugged in and powered on, and the network condition is good.

as close to the air purifier as possible.

- Try to delete the offline air purifier from the app, and reconfigure
- (3) Connect the equipment into an outlet on a circuit different from the air purifier.
- Note: Power outgges, network disconnections, or changes to the WiFi router can all potentially cause the air purifier to go offline.

that to which the receiver is connected. (4) Consult the dealer or an experienced radio/ TV technician for help.

(1) Regrient or relocate the receiving antenna.

To maintain compliance with FCC's RF Exposure guidelines, this equipment should be installed and operated with minimum 20cm distance between the radiator and your body: Use only the supplied

IC Statement This device complies with Innovation, Science and Economic

Development Canada licence-exempt RSS standard(s). This device complies with Part 15 of the FCC Rules. Operation is Operation is subject to the following two conditions: (1) This device may not cause interference, and

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including
- operate the equipment.
- limits for a class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provided reasonable protection against harmful interference in a residential installation.
- energy and, if not installed and used in accordance with the instructions, any cause harmful interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

This equipment generates, uses and can radiate radio frequency

11. Warranty

12-month warranty for the product. **60-day** money-back guarantee for quality issues.

le fonctionnement.

(2) Increase the separation between the equipment and receiver. Note: Damages caused by the disregard of this user manual are

not subject to warranty.

12. Contact Us

At Provirted, we value your experience. If you have any questions about our product, please contact us through our store or app.

Our dedicated team will respond promptly to provide you with the support you need. Thank you for choosing Provirtec, and we look forward to serving you.

(2) This device must accept any interference, including interference

To maintain compliance with RSS-102 RF Exposure guidelines, this

equipment should be installed and operated with minimum 20cm

Cet appareil est conforme aux normes RSS exemptées de licence

(2) l'utilisateur de l'appareildoit accepter tout brouillageradioé

lectriquesubi, mêmesi le brouillageest susceptible d'encompromettr

Pour être conforme aux lignes directrices d'exposition RF RSS-102.

cet équipement doit être installé et exploité à une distance minimale

de 20cm entre le radiateur et votre corps: n'utilisez que l'antenne fournie

d'innovation, sciences et développement économique Canada.

L'exploitationestautorisée aux deux conditions suivantes


(1) l'appareil ne doit pas produire de brouillage, et

distance between the radiator and your body: Use only the supplied antenn

that may cause undesired operation of the device











Press to set a timer (0-12h) to turn off the air purifier.

7. App Download Instructions

App Store | Google Pla

c. Turn on BT on your phone, and enter "Home" in the Prodiayted

app. Select "+" -"Add device"- "Home appliance" - "ClearBreathe

Neo Smart Air Purifier". Then, follow the on-screen instructions

Use a vacuum cleaner to clean the dust from the hair pre-filter.

replacement interval of 2 to 4 months. The actual life of the hair

pre-filter depends on the frequency of use of the air purifier. Please

the 4-in-1 filter surface and the filter compartment. It is recom-

• Regularly replace the hair pre-filter with a recommended

a Download the **Prodiaytec** app from App Store (IOS device) or



