確認用です。印刷には使用しないでください

English

1 Opening

Thank you for purchasing the Bluetooth Keyboard with Tablet Stand.

2 Precautions

●Since this device is operated by electricity, there is a chance that it may ignite. In the unlikely event that the device emits smoke or a strange smell, turn off the power on the device and connected PC or other items; contact the store where purchased or our offices.
●Do not allow liquids, metals, or any foreign objects inside the device.
▲This device may cause electric shock, fire, or malfunction.
●Refrain from subjecting the device to strong vibration or impact.
▲This device may cause breakage or damage.
●Loss of data and programs that may occur while using this device are not under warranty.
▲Please take measures to protect data such as backing up data on a periodic basis.
●When cleaning this device, refrain from using products that contain volatile organic solvents such as benzamine or thinner.
▲To avoid damage to the surface or malfunction, wipe with a slightly damp cloth.
●This device is not intended for use as medical equipment, nuclear equipment, aerospace equipment, transportation equipment, etc. in which people's lives are in danger or when a high degree of reliability is required. The company will not assume responsibility for damage incurred involving personal injury, social issues, etc. that may result even when the device is used properly.
●This device used a 2.4GHz frequency bank.
Bluetooth is the same frequency band as 2.4 GHz radio equipment and wireless LAN equipment and may affect other equipment that uses the same frequency band.

3 Warnings Regarding Health

Operating the mouse, trackball, and keyboard for long periods of time can lead to pain or numbness in hands, arms, neck, shoulders, etc. Serious damage may be incurred if such use is repeated.
If you feel pain or numbness while operating the mouse or keyboard, stop use immediately and consult a doctor if necessary.
Take regular breaks from daily computer work to avoid strain on hands, arms, neck, shoulders, etc.

4 Specifications

Compatible Models	iPhone/iPad、Apple Mac※1、Android smartphones, tablets ※2、Windows PCs and tablets powered by (DOS/V) ※3
Compatible Systems	iOS、Mac OS、Android、Windows
Accessories	User's Manual

※1：Models to which the Bluetooth adaptor is connected / installed.
※2：Models compatible with the Bluetooth keyboard; check specifications of your model.
※3：Models with built-in Bluetooth modules.

<Keyboard Specifications>

key number, key pitch	78keys, 19mm
Battery life	Approx. 125 hours (continuous use)
Size	W286×D128×H17mm
Weight	410g (excluding batteries)

<Bluetooth Specifications>

Compliance standard	Bluetooth Ver.3.0
Transmission Distance	Up to approx. 10m (depending on usage environment)
Transmission output	Class 2

※Operation contents may differ depending iOS version.

5 Name of each part /Table of Shortcut Keys



	Android	iOS	Windows
①	darken screen	darken screen	darken screen
②	brighten screen	brighten screen	brighten screen
③	search	search	search
④	home	home	open page
⑤	right mouse click	N/A	right mouse click
⑥	right click	N/A	back
⑦	previous song	previous song	right click
⑧	pause/play	pause/play	pause/play
⑨	next song	next song	next song
⑩	mute	mute	mute
⑪	volume down	volume down	volume down
⑫	volume up	volume up	volume up
⑬fn+	pairing mode	pairing mode	pairing mode
⑭fn+	pairing channel1	pairing channel1	pairing channel1
⑮fn+	pairing channel2	pairing channel2	pairing channel2
⑯fn+	pairing channel3	pairing channel3	pairing channel3

6 How to use the stand



(1) Pull out the stand.

(2)Slide forward until it clicks into place.

(3)Put the keyboard as shown in the following picture, then it can be used as a stand.

To store the stand, follow the procedure in reverse order.
※Be careful when handling the stand. Handling the stand roughly and with strength may result in damage.

7 Pairing Method

(1)Turn on the Bluetooth functiong on the PC, tablet or smartphone.
(2)Turn the power switch on the side of the device to "on".
(3)Press the function key and pairing switch button simultaneously, then you can choose the pairing channel. When you chose one of the pairing channel, the pairing LED 1–3 will blink into blue slowly.

(4)Press the function key and pairing buttonl(Bin ⑤) at the same time, one of the pairing LED 1–3 will blink into blue quickly. Then the pairing channel you selected will enter pairing mode.
(5)Select "SANWA KBD BT28" as it is displayed on the Bluetooth setting screen.
(6)Pairing is completed.
(7)When registering multiple devices or switching devices to be used, you can switch easily by pressing the function key and the pairing switch button at the same time.
※Each time the code is set, a different number is displayed.
※When pressing number keys on this device, the numbers are not displayed on the screen.
Please be careful that no mistakes are made when entering numbers. If numbers are entered incorrectly or the allotted time passes, connection will fail.

8 Q&A

Q.I can't enter using the keys.
A.Even if the power switch is "on", the keyboard will enter sleep mode unless it is manipulated regularly. The keyboard can be returned from sleep mode by clicking any key. Operation may be unstable immediately after returning from sleep mode.

Q.When using this device, the Bluetooth audio is interrupted.
A.When using Bluetooth-compatible headphones, headsets, or speakers with this device, music and voices may be interrupted.

Q.Pairing failed.
A.In rare cases, pairing may fail. If this occurs, turn the power to "off" on this device and perform pairing operations again.

Q. The keyboard won't connect to a Mac.
A.Try the following method:
1.On the menu bar, delete SANWA BT KEYBOARD: Bluetooth icon → Bluetooth settings window → SANWA KBD BT28.
2.Turn the power to "off" on the Bluetooth keyboard.
3.On the Apple menu, click: System preferred settings → Energy Conservation.
4.Choose the battery tab, then uncheck all the checkboxes.
5.Choose the "Power adaptor" tab, then check the box for "Do not allow the computer to sleep automatically when display is off"; uncheck the other checkboxes.
6.Reperform pairing operations for the keyboard.

Chinese

1 敬礼

尊敬的客户，感谢您选购我司商品，在此致以最诚挚的谢意。

2 安全注意事项

●本商品使用电源运作、有自燃的可能性。若有冒烟、感觉到异味时，请立即切断商品及已链接的电脑或其他设备的电源。并联系所购买的门店或本公司。
●请避免液体、金属等异物进入商品内部。
▲有可能造成触电、火灾、故障。
●请勿剧烈振晃及施加强压。
▲有可能造成故障・破损。
●商品使用时产生的数据及程序丢失、烧同怒不负责。
▲建议您采取定期备份等方式以防丢失。
●清洁本品时，请勿使用含有苯精或稀料等挥发性有机溶剂的清洁剂。
▲有可能损失表面，造成故障。请将湿水抹布拧干后轻轻擦拭。
●本商品并非为医疗器械、核能设备及机器、宇宙飞船、运输设备及机器等于生命健康等关联的设备及机器，又或需要高端可靠性的设备及机器所使用而开发设计的。上诉情况使用商品造成的人身意外、公共危害等，我司概不负责。
●本商品采用2.4GHz无线技术。
蓝牙频段与2.4GHz无线机器与无线LAN机器相同，若同时使用可能会造成互相干扰。

3 健康须知

长时间使用鼠标、轨迹球以及键盘会给手臂、头部和肩颈等增加负担进而产生疼痛或酸麻。长此以往可能给身体造成严重损伤，倘若您使用鼠标和键盘过程中感觉到疼痛或酸麻，请立刻停止使用，并根据自身情况咨询医生。此外，请您注意日常使用电脑时要多休息多活动，不要给身体增加过多负担。

4 规格参数

适用设备	iPhone/iPad、Apple Mac※1、Android智能手机・平板电脑※2、搭载Windows（DOS/V）个人电脑・平板电脑※3
适用系统	iOS、Mac OS、Android、Windows
包装清单	使用说明书

※1：已安装或搭载蓝牙适配器。
※2：请检查您所使用设备的规格参数，以确定是否与蓝牙鼠标兼容。
※3：仅支持已搭载Bluetooth蓝牙模块的机型

<键盘参数>

键数・键距	78键・19mm
电池性能	约125小时(连续使用)
尺寸	W286×D128×H17mm
重量	410g(不含电池)

<Bluetooth参数>

蓝牙版本	Bluetooth Ver.3.0
传输范围	最大约10m(根据使用环境会有所不同)
输出电平	Class 2

※根据iOS版本不同，功能可能会有些许不同。

5 键位名称・快捷键对应表

	Android	iOS	Windows
①	亮度减	亮度减	亮度减
②	亮度加	亮度加	亮度加
③	搜索	搜索	搜索
④	主页面	主页面	F1
⑤	鼠标右键	N/A	鼠标右键
⑥	返回	N/A	返回
⑦	上一曲	上一曲	上一曲
⑧	暂停/播放	暂停/播放	暂停/播放
⑨	下一曲	下一曲	下一曲
⑩	静音	静音	静音
⑪	音量减	音量减	音量减
⑫	音量加	音量加	音量加
⑬fn+	配对模式	配对模式	配对模式
⑭fn+	配对通道1	配对通道1	配对通道1
⑮fn+	配对通道2	配对通道2	配对通道2
⑯fn+	配对通道3	配对通道3	配对通道3

6 支架的拿取方法



(1)先将支架轻轻拿出。

(2)将固定支架滑到顶部，直到听到“咔嚓”卡进凹槽的声音。

(3)将键盘正面朝上，将设备放置在支架上使用。

收纳支架时，请按拿取方式的反向操作。
※拿取收纳支架时请轻拿轻放。
若使用蛮力可能会损坏支架。

7 蓝牙配对方法

(1)请打开电脑、平板或手机的「蓝牙」功能。
(2)将打开位于侧面的电源开关。
(3)同时按下fn键和配对切换键，即可选择对应配对通道。
通过频慢闪烁蓝光的配对LED灯1–3即可得知所在通道。

(4)然后同时按下fn键和配对键（ ⑤ →⑬），对应通道的配对LED灯会快速闪烁蓝光。此时表明已进入配对模式。
(5)在配对设备中的蓝牙设定界面中选择「SANWA KBD BT28」。
(6)蓝牙配对已经完成。
(7)已经配对了多台设备，需要切换设备时，请同时按下fn键和与之对应的配对切换键，即可轻松进行切换。

※每次进行配对时，配对密码均会改变。
※在按下「数字键」输入配对密码时，输入的文字将不会显示在设备上。
请仔细确认设备上的密码，准确无误输入。未正确输入密码，或者操作时间过长将导致配对失败。

8 Q&A

Q.按键没有反应。
A.即使电源开关处于开启状态，若一段时间未使用键盘的话，键盘将进入休眠状态。
按下键盘按键，便会恢复至工作状态。
恢复初期键盘可能有些许延迟。

Q.使用本商品，蓝牙设备的声音中断。
A.本商品和蓝牙对应的耳机・耳麦・音箱等音乐、音响设备同时使用时，可能会造成音乐、音响中断。

Q.配对失败。
A.极少数情况下可能会有配对失败的情况。请将本商品的电源关闭后，重新开启电源再次进行配对。

Q.键盘无法与Mac进行配对。
A.请按下列步骤进行操作。
1.打开Mac的蓝牙设置 → 移除“SANWA KBD BT28”。
2.关闭键盘电源开关。
3.点击 系统偏好设置 → 节能器。
4.选择 电池 选项卡，取消所有勾选。
5.选择 电源适配器 选项卡，仅勾选“当显示器关闭时，防止电脑进入睡眠”。
6.再次重新配对键盘。

Japanese

1 はじめに

この度は、タブレットスタンド機能付きBluetoothキーボードをお買い上げいただき、誠にありがとうございます。

2 ご注意

●本製品は電気で動作しておりますので、発火する恐れがあります。万一煙が出たり変な臭いがした場合は、本製品及び接続しているパソコンや機器の電源を切り、お買い上げの販売店又は、弊社までご連絡ください。
●本製品内部に液体、金属などの異物が入らないようにしてください。
▲感電や火災、故障の原因となることがあります。
●本製品に強い振動や衝撃を与えないでください。
▲故障・破損などの原因となることがあります。
●本製品を使用中に発生したデータやプログラムの消失については保証はいたしかねます。
▲定期的にバックアップを取るなどの対策をあらかじめ行ってください。
●本製品のお手入れをする場合には、ベンジンやシンナーなどの揮発性有機溶剤が含まれているものは使用しないでください。
▲表面を傷めたり、故障の原因になることがあります。固くしぼった布などで水拭きしてください。
●本製品は医療機器、原子力設備や機器、航空宇宙機器、輸送設備や機器などの人命に関わる設備や機器、及び高度な信頼性を必要とする設備や機器やシステムなどへの組込みや使用は意図されておりません。これらの用途に本製品を使用された、人身事故、社会的損害などが生じても弊社はいかなる責任も負いかねます。
●本製品は2.4GHz周波数帯域を使用しています。
Bluetoothは2.4GHz無線機器や無線LAN機器と同じ周波数帯域であり、同じ周波数帯域を使用する他の機器に影響を与えることがあります。

3 健康に関する注意

マウスやトラックボール、キーボードを長時間操作すると、手や腕や首、肩などに負担が掛かり痛みや痺れを感じることがあります。そのまま操作を続け返していると、場合によっては深刻な障害を引き起こす恐れがあります。マウスやキーボードを操作中に身体に痛みや痺れを感じたら、直ちに操作を中止し、場合によっては医師に相談してください。また日常的にパソコン操作では定期的に休憩を取り、手や腕や首、肩など身体に負担が掛からないように心がけてください。

4 仕様

対応機種	iPhone/iPad、Apple Mac※1、Androidスマートフォン・タブレット※2、Windows搭載（DOS/V）パソコン・タブレット※3
対応システム	iOS、Mac OS、Android、Windows
付属品	取扱説明書

※1：Bluetoothアダプタを接続・インストールしている機種。
※2：Bluetoothキーボードに対応している機種。対応機種はご使用機器の仕様をご確認ください。
※3：Bluetoothモジュールが内蔵されている機種。

<キーボード仕様>

キー数・キーピッチ	78キー・19mm
バッテリー寿命	約125時間(連続使用)
サイズ	W286×D128×H17mm
重量	410g(電池含まず)

<Bluetooth仕様>

適合規格	Bluetooth Ver.3.0
通信距離	最大約10m(使用環境により異なります)
送信出力	Class 2

※iOSのバージョンにより、動作内容が変更される場合があります。

5 各部の名称・ショートカットキー対応表

	Android	iOS	Windows
①	画面を暗く	画面を暗く	画面を暗く
②	画面を明るく	画面を明るく	画面を明るく
③	検索	検索	検索
④	ホーム	ホーム	ページを開く
⑤	マウス右クリック	N/A	マウス右クリック
⑥	戻る	N/A	戻る
⑦	前の曲	前の曲	前の曲
⑧	一時停止/再生	一時停止/再生	一時停止/再生
⑨	次の曲	次の曲	次の曲
⑩	静音(ミュート)	静音(ミュート)	静音(ミュート)
⑪	音量を下げる	音量を下げる	音量を下げる
⑫	音量を上げる	音量を上げる	音量を上げる
⑬fn+	ペアリングモード	ペアリングモード	ペアリングモード
⑭fn+	ペアリングチャンネル1	ペアリングチャンネル1	ペアリングチャンネル1
⑮fn+	ペアリングチャンネル2	ペアリングチャンネル2	ペアリングチャンネル2
⑯fn+	ペアリングチャンネル3	ペアリングチャンネル3	ペアリングチャンネル3

6 スタンドの出し方

(1)スタンドを引き出します。

(2)手前をカチッと音がするまでスライドさせます。

(3)キー面を上にして置くことでスタンドとして使用できます。

スタンドを収納する際は逆の手順で行ってください。
※スタンドは丁寧に取り扱ってください。
無理に力を入れると破損する可能性があります。

7 ペアリング方法

(1)パソコン・タブレット・スマートフォンの「Bluetooth」機能を「オン」にしてください。
(2)本製品の側面にある電源スイッチをONにします。
(3)fnキーとペアリング切替えボタンを同時に押して、ペアリングする番号を選択・決定します。選択できるとペアリングLED1–3のいずれかが点滅します。

(4)次に、fnキーとペアリングボタン（ ⑤ の③）を同時に押すと、ペアリングLED1～3のいずれかが青色に点滅し、ペアリングチャンネルに入ります。
(5)接続機器のBluetooth設定画面に「SANWA KBD BT28」と表示されるので選択してください。
(6)ペアリングが完了します。
(7)機器を複数台登録して、使用機器を切替える場合はfnキーと該当のペアリング切替えボタンを同時に押すだけで簡単に切替えます。

※コードは設定するごとに異なった数字が表示されます。
※本製品の「数字キー」を押している際、画面に入力されている文字は表示されません。
画面の数字をよく確認し、間違えないように押してください。数字を間違えたり、時間が経過しすぎると接続に失敗します。

8 Q&A

Q.キー入力ができない。
A.電源スイッチがONの場合でも一定時間キーボードを操作しないとキーボードがスリープモードに移行します。
キーボードはキーを押すことで、スリープモードから復帰します。
復帰直後は動作が不安定になることがあります。

Q.本製品を使用すると、Bluetooth機器の音声が途切れる。
A.本製品とBluetooth対応のヘッドホン・ヘッドセット・スピーカーなどの音楽、音声機器を同時に使用した場合、音楽や音声が途切れる場合があります。

Q.ペアリングが失敗する。
A.ごくまれにペアリングに失敗する場合があります。本製品の電源を一度OFFにして、再度ペアリング操作を行ってください。

Q. キーボードがMacに接続できない。
A. 以下の方法をお試しください。
1. メニューバーの「Bluetoothアイコン」→「Bluetooth設定」のウィンドウ→ “SANWA KBD BT28”を削除します。
2. Bluetoothキーボードの電源をOFFにします。
3. Appleメニュー→「システム環境設定」→「省エネルギー」をクリックします。
4. 「バッテリー」タブを選んで、全てのチェックボックスのチェックを外します。
5. 「電源アダプタ」タブを選んで、“ディスプレイが切のときはコンピュータを自動でスリープさせない”のみチェックボックスにチェックを付け、その他のチェックボックスのチェックは外します。
6. 再度キーボードのペアリング設定をやり直します。

Bluetooth Keyboard

Manual/取扱説明書/使用説明书

GSKBBT28BK

User' s Manual　YouTube

FCC ID: 2AMSUBT28BK
DID: D039338

保証規定 (Conditions of Warranty/保修条款)

1.This warranty is limited to use within the term of warranty in accordance with the conditions that the device is damaged within the term of warranty, repair will be carried out by the company.
2.Repair will be carried out under the following conditions.
(1)When the warranty period has expired.
(2)When the warranty period is not presented.
(3)When the warranty period has been altered, or it is difficult to know warranty expiration.
(4)When the warranty period has been altered, or it is difficult to know warranty expiration.
(5)When the warranty period has been altered, or it is difficult to know warranty expiration.